

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

**6.7. storePreset**

For registering current station to a preset

**Request Parameters**

name	type	required	description
num	integer	yes	Specifying a preset number Value: one in the range gotten via /system/getFeatures

URI	<BaseURL>/v1/tuner/storePreset?num=<num>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/tuner/storePreset?num=10

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

**6.8. clearPreset**

For clearing Tuner preset.

**Request Parameters**

name	type	required	description
band	string	yes	Specifies Band. Values depend on Preset Type gotten via /system/getFeatures Values: "common" (common), "am" / "fm" / "dab" (separate)
num	integer	yes	Specifies Preset number Values: one in the range gotten via /system/getFeatures

URI	<BaseURL>/v1/tuner/clearPreset?band=<band>&num=<num>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/tuner/clearPreset?band=fm&num=10