

			"search_artist" (Pandora) "search_track" (Pandora)
input	string	yes	Specifies target Input ID. Controls for setListControl are to work with the input specified here Values: Input IDs for Net/USB related sources
index	integer	no	Specifies the reference index (offset from the beginning of the list). Note that this index must be in multiple of 8. If nothing was specified, the reference index previously specified would be used Values: 0, 8, 16, 24, ..., 64984, 64992
target_index	integer	no	Reserved
size	integer	yes	Specifies max list size retrieved at a time Value Range: 1 - 8
lang	string	no	Specifies list language. But menu names or text info are not always necessarily pulled in a language specified here. If nothing specified, English ("en") is used implicitly Values: "en" (English)/ "ja" (Japanese)/ "fr" (French)/ "de" (German)/ "es" (Spanish)/ "ru" (Russian)/ "it" (Italy)/ "zh" (Chinese)

URI	<BaseURL>/v1/netusb/getListInfo?input=<input>&index=<index>&size=<size>&lang=<lang>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/getListInfo?input=usb&index=32&size=8&lang=en

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details If codes shown below is returned, display appropriate messages to the external application user interface depending on which input current one is. List info is initialized once an error happens. 100 : Access Error (common for all Net/USB sources) 112 : Access Denied (Server)
input	string	Specifies target Input ID. (Available on and after API Version 1.17)
menu_layer	integer	Returns menu layer Value Range: 0 - 15
max_line	integer	Returns max row number of the list Value Range: 0 - 65000
index	integer	Returns the reference index of the list
playing_index	integer	Returns the index number in a list that is currently in playback. If no list element has playback status, or playback status wasn't found, returns -1
menu_name	string	Returns menu name
list_info	array	Returns list info with the row number size specified by Request Parameter. Returns empty data if index or size wasn't specified. If the max row number is reached in the middle of this list info, the list ends at the max row.
- text	string	Returns text info to display