

	<pre> "preset":{ "num":40 } "vtuner_fver":"A", "pandora":{ "sort_option_list":["recent", "alphabet"] } "distribution":{ "version":3.10, "compatible_client":[2, 3], "client_max":9, "server_zone_list":["main"], } } </pre>
--	---

4.3. getNetworkStatus

For retrieving network related setup / information

Request Parameters

URI	<BaseURL>/v1/system/getNetworkStatus
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/system/getNetworkStatus

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " Response Code List " for details
network_name	string	Returns Network Name (Friendly Name)
connection	string	Returns setup status of Connection Values: "wired_lan" / "wireless_lan" / "wireless_direct" / "extend_1" / "extend_2" / "extend_3" / "unknown"
dhcp	boolean	Returns DHCP setup
ip_address	string	Returns IP Address
subnet_mask	string	Returns Subnet Mask
default_gateway	string	Returns Default Gateway
dns_server_1	string	Returns DNS Server 1
dns_server_2	string	Returns DNS Server 2
wireless_lan	object	Returns information related to wireless network (Wi-Fi)
- ssid	string	Returns SSID
- type	string	Returns encryption type