

		shown below;
		b[0] Selectable

Example Response	<pre>{ "response_code":0, "qobuz":{ "quality":{ "value":"hr_192_24", "value_list":[{ "value":"hr_192_24", "attribute":0 }, ... { "value":"mp3_320", "attribute":1 },] } } }</pre>
------------------	---

7.17.setQuality

For setting the reproduction quality of streaming. Refer to available Input/setting value via /system/getSetting.

Request Parameters

name	type	required	description
input	string	yes	Specifies target Input ID Values: "qobuz"
value	string	yes	Specifies reproduction quality. Refer to available value in each input via /netusb/getSettings Values: "hr_192_24" / "hr_96_24" / "cd_44_16" / "mp3_320"

URI	<BaseURL>/v1/netusb/setQuality?input=<input>&value=<value>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/setQuality?input=qobuz&value=hr_192_24

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " Response Code List " for details

Example Response	<pre>{ "response_code":0 }</pre>
------------------	------------------------------------