<u>Request Parameters</u>

URI	<BaseURL>/v1/dist/stopDistribution
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/dist/stopDistribution

<u>Response Parameters</u>

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	   "response_code":0
	}

5.6. setGroupName

For setting up Group Name. Note that Group Name is reserved in volatile memory

<u>Request Parameters</u>

name	type	required	description
name	string	yes	Specifies Group Name. Use UTF-8 within 128 bytes. Default name would be used if it's not setup or "" (empty text) is specified

URI	<BaseURL>/v1/dist/setGroupName
Method	POST
Example Request (URI)	http://{host}/YamahaExtendedControl/v1/dist/setGroupName

Example Request (json)	{
	   "name":"[Link] Living Room"
	}

<u>Response Parameters</u>

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	   "response_code":0
	}