

	}
--	---

## 7.7. toggleRepeat

For toggling repeat setting. No direct / discrete setting commands available

### Request Parameters

URI	<BaseURL>/v1/netusb/toggleRepeat
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/toggleRepeat

### Response Parameters

name	type	Description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

## 7.8. toggleShuffle

For toggling shuffle setting. No direct / discrete setting commands available

### Request Parameters

URI	<BaseURL>/v1/netusb/toggleShuffle
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/toggleShuffle

### Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

## 7.9. getListInfo

For retrieving list information. Basically this info is available to all relevant inputs, not limited to or independent from current input

### Request Parameters

name	type	required	description
list_id	string	no	Specifies list ID. If nothing specified, "main" is chosen implicitly Values: "main" (common for all Net/USB sources) "auto_complete" (Pandora)