

1. Create a random Group ID (16 byte).
* Note not set the same Group ID
2. Setup all clients with the Group ID and target Zone being used by “setClientInfo”.

Request (URI)

http://{Device E}/ YamahaExtendedControl/v1/dist/setClientInfo

Request (json)

```
{  
    "group_id":"7B335AE4C12345677251DAA466669B40",  
    "zone":[  
        "main"  
    ]  
}
```

Response

```
{  
    "response_code":0  
}
```

3. Setup the master with GroupID and client list by “setServerInfo (add)”.

Request (URI)

http://{Device D}/ YamahaExtendedControl/v1/dist/setServerInfo

Request (json)

```
{  
    "group_id":"7B335AE4C12345677251DAA466669B40",  
    "zone":"main",  
    "type":"add",  
    "client_list":[  
        "192.168.0.8" ← 

|          |            |
|----------|------------|
| Device E | IP address |
|----------|------------|

  
    ]  
}
```

Response

```
{  
    "response_code":0  
}
```

4. Start distribution with setting current all system distribution number to the master by “startDistribution”. Already establish a distribution network with Device B being a master, and with Device A and Device C being clients, need to set num = 2.

Request (URI)

http://{Device B}/ YamahaExtendedControl/v1/dist/startDistribution?num=2