

Response

```

{
  "response_code":0,
  "menu_layer":0,
  "max_line":5,
  "index":0,
  "playing_index":-1,
  "menu_name":"USB",
  "list_info":[
    {
      "text":"FolderA",
      "thumbnail":"",
      "attribute":2
    },
    {
      "text":"FolderB",
      "thumbnail":"",
      "attribute":2
    },
    {
      "text":"File r00",
      "thumbnail":"",
      "attribute":4
    },
    {
      "text":"File r01",
      "thumbnail":"",
      "attribute":4
    },
    {
      "text":"File r02",
      "thumbnail":"",
      "attribute":4
    }
  ]
}

```

← Capability bit[1]: Select bit equal to 1

13.1.3. Layer change

Use “setListControl” to move to Folder B layer. Confirm if the attribute of Response Parameter is selectable as described before.

Request

http://{host}/YamahaExtendedControl/v1/netusb/setListControl?list_id=main&type=select&index=1

Response

```

{
  "response_code":0
}

```