

4.28. setHdmiOut1

For setting HDMI OUT 1 terminal output status

Request Parameters

name	type	required	description
enable	boolean	yes	Specifies HDMI OUT 1 terminal output status

URI	<BaseURL>/v1/system/setHdmiOut1?enable=<enable>		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/system/setHdmiOut1?enable=true		

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " Response Code List " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

4.29. setHdmiOut2

For setting HDMI OUT 2 terminal output status

Request Parameters

name	type	required	description
enable	boolean	yes	Specifies HDMI OUT 2 terminal output status

URI	<BaseURL>/v1/system/setHdmiOut2?enable=<enable>		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/system/setHdmiOut2?enable=true		

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " Response Code List " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------