

Retrieve list information via getListInfo after send setListControl:select command. It's possible to occur error if send setListControl:select command continuously.

- : setListControl:select -> getListInfo -> setListControl:select -> getListInfo
- × : setListControl:select -> setListControl:select -> getListInfo

## 13.2. Device Search

Here explains procedures of how to search MusicCast Devices

1. Specify MediaRenderer and issue M-Search.
2. Access to the URL of device description read from the Location header in the response.
3. Confirm tags shown below.

**<manufacturer>Yamaha Corporation</manufacturer>**

See if manufacturer name is "Yamaha Corporation"

**<yamaha:X\_device>**

See if there is this Yamaha tag

**<yamaha:X\_URLBase>http://192.168.10.103:80/</yamaha:X\_URLBase>**

Confirm device's IP address

**<yamaha:X\_yxcControlURL>/YamahaExtendedControl/v1/</yamaha:X\_yxcControlURL>**

Check the URL of YXC control

[Example of device description of a MusicCast Device]

```
<?xml version="1.0" encoding="utf-8" ?>
<root xmlns="urn:schemas-upnp-org:device-1-0"
xmlns:yamaha="urn:schemas-yamaha-com:device-1-0">
<specVersion>
  <major>1</major>
  <minor>0</minor>
</specVersion>
<device>
  <dlna:X_DLNAID>
xmlns:dlna="urn:schemas-dlna-org:device-1-0">DMR-1.50</dlna:X_DLNAID>
  <deviceType>urn:schemas-upnp-org:device:MediaRenderer:1</deviceType>
  <friendlyName>Room A</friendlyName>
  <manufacturer>Yamaha Corporation</manufacturer>
  <manufacturerURL>http://www.yamaha.com/</manufacturerURL>
  <modelDescription>MusicCast</modelDescription>
  <modelName>WXC-50</modelName>
  <modelNumber>50</modelNumber>
  <modelURL>http://www.yamaha.com/</modelURL>
  <serialNumber>0DA27313</serialNumber>
  <UDN>uuid:9ab0c000-f668-11de-9976-00a0ded26c17</UDN>
  <iconList>
```