

8.5. setShuffle

For setting shuffle. Available on after API version 1.19.

Request Parameters

name	type	required	description
mode	string	yes	Specifies shuffle Values: "off" / "on" / "folder"

URI	<BaseURL>/v1/cd/setShuffle?mode=<mode>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/cd/setShuffle?mode=off

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " Response Code List " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

8.6. toggleRepeat

For toggling repeat setting. No direct / discrete setting commands available

Request Parameters

URI	<BaseURL>/v1/cd/toggleRepeat
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/cd/toggleRepeat

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " Response Code List " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

8.7. toggleShuffle

For toggling shuffle setting. No direct / discrete setting commands available

Request Parameters

URI	<BaseURL>/v1/cd/toggleShuffle
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/cd/toggleShuffle