		Refer to "Response Code List" for details

Example Response	{
	
	    "response_code":0
	
	}

7.5. setRepeat

For setting repeat. Available on after API version 1.19.

Request Parameters

name	Type	required	description
mode	string	yes	Specifies the repeat setting Value : "off" / "one" / "all"

URI	<BaseURL>/v1/netusb/setRepeat?mode=<mode>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/setRepeat?mode=off

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{
	
	    "response_code":0
	
	}

7.6. setShuffle

For setting shuffle. Available on after API version 1.19.

Request Parameters

name	type	required	description
mode	string	yes	Specifies the shuffle setting Value : "off" / "on" / "songs" / "albums"

URI	<BaseURL>/v1/netusb/setShuffle?mode=<mode>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/netusb/setShuffle?mode=off

Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to "Response Code List" for details

Example Response	{ "response_code":0