

**Request Parameters**

name	type	required	description
zone	string	yes	Specifies target Zone Values: "main" / "zone2" / "zone3" / "zone4"

URI	<BaseURL>/v1/<zone>/getSoundProgramList		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/main/getSoundProgramList		

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details
sound_program_list	string array	Returns a list of selectable sound program

Example Response	<pre>{   "response_code":0,   "sound_program_list":[     "munich",     "vienna",     ...     "straight"   ] }</pre>	
------------------	---	--

**5.3. setPower**

For setting power status of each Zone

**Request Parameters**

name	type	required	description
zone	string	yes	Specifies target zone. Available for zones with this function Values: "main" / "zone2" / "zone3" / "zone4"
power	string	yes	Specifies power status Values: "on" / "standby" / "toggle"

URI	<BaseURL>/v1/<zone>/setPower?power=<power>		
Method	GET		
Example Request	http://{host}/YamahaExtendedControl/v1/zone3/setPower?power=on		

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	<pre>{   "response_code":0 }</pre>	
------------------	------------------------------------	--