

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

**4.38. requestSystemReboot**

For requesting System reboot. Available only when " system\_reboot " exists in system - func\_list under /system/getFeatures.

**Request Parameters**

URI	<BaseURL>/v1/system/requestSystemReboot
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/system/requestSystemReboot

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

**4.39. getAdvancedFeatures**

Get additional information about the functions installed in the device.

**Request Parameters**

URI	<BaseURL>/v1/system/getAdvancedFeatures
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/system/getAdvancedFeatures

**Response Parameters**

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to " <a href="#">Response Code List</a> " for details
web_settings_list	string array	Returns the items displayed on the Web Settings screen. Items not to be displayed are not returned. Values : "network_name" / "network_settings" / "airplay" / "firmware_update" / "standby" / "mac_filter" / "licenses" / "backup_restore" / "advanced_settings"
advanced_settings_list	array	If web_settings_list has advanced_settings, it returns