

## 6.5. recallPreset

For recalling a Tuner preset

### Request Parameters

name	type	required	description
zone	string	yes	Specifies station recalling zone. This causes input change in specified zone Values: "main" / "zone2" / "zone3" / "zone4"
band	string	yes	Specifies Band type. Depending on Preset Type gotten via /system/getFeatures, specifying value is different Values: "common" (band common) / "am" / "fm" / "dab" (separate)
num	integer	yes	Specifies Preset number Value: one in the range gotten via /system/getFeatures

URI	<BaseURL>/v1/tuner/recallPreset?zone=<zone>&band=<band>&num=<num>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/tuner/recallPreset?zone=main&band=fm&num=13

### Response Parameters

name	type	description
response_code	integer	0: Successful request / Others: Error Refer to <a href="#">"Response Code List"</a> for details

Example Response	{ "response_code":0 }
------------------	-----------------------------

## 6.6. switchPreset

For selecting Tuner preset.

Call this API after change the target zone's input to Tuner. It is possible to change Band in case of preset type is "common". In case of preset type is "separate", need to change the target Band before calling this API.

This API is available on and after API Version 1.17.

### Request Parameters

name	type	required	description
dir	string	yes	Specifies change direction of preset Values: "next" / "previous"

URI	<BaseURL>/v1/tuner/switchPreset?dir=<dir>
Method	GET
Example Request	http://{host}/YamahaExtendedControl/v1/tuner/switchPreset?dir=next