Connectivity Information PrimeServ Assist

This document gives information about the technical requirements for the customer`s side of the connection to Everllence CEON.

Connection Devices (mGuard RS4000 + SIMATIC IPC427D)

Interface:
WAN, Ethernet IEE 802

Transmission physics:
Max. 100m per segment, twisted pair

Transmission speed:
10/100MBit/s

Power supply:
24 VDC

Interface:
Ethernet (RJ-45)

Transmission physics:
Max. 100m per segment, twisted pair

Transmission speed:
10/100/1000MBit/s

Power supply:
19,2 – 28,8 VDC

Network Availability of Customer Digital Infrastructure:

- A static or DHCP provided Internet Address with access to the Contractor Everllence CEON Cloud is required in order to provide Service Delivery.
- Continuous connectivity to communications gateway installed on customer network needs to be provided to the following destination domains/IP:

- For CEON Access **TCP Port 443** for
  - **assethub.mya.io**
  - **upgrades.mya.io**
  - **assethub.manceon.io**

  (35.156.61.78 / 35.156.77.222 / 35.157.233.80)

- For firewall (mGuard) firmware & configuration updates **TCP Port 443** for
  - **149.247.176.129**

- For time syncronization open **UDP Port 123** for
  - **ntp.manceon.io** **(35.156.61.78 / 35.156.77.222 / 35.157.233.80)**
  - (Optional) **ntp.ubuntu.com** **(91.189.91.157)**

- For remote access **UDP Port 500 and UDP Port 4500** for
  - **149.247.177.99**

We recommend to set firewall whitelist rules with the domain names listed above.
If not possible please use IPs.

Please forward this checklist to your IT Department / Internet provider.