Connectivity Information PrimeServ Assist

4-Stroke

This document gives information about the technical requirements for the customer`s side of the connection to Everllence CEON.

Connection Devices (mGuard RS4000 + SIMATIC IPC427…)

Interface:
WAN, Ethernet IEE 802

Transmission physics:
Max. 100m per segment, twisted pair

Transmission speed:
10/100MBit/s

Power supply:
24 VDC

Interface:
Ethernet (RJ-45)

Transmission physics:
Max. 100m per segment, pair

Transmission speed:
10/100/1000MBit/s

Power supply:
19,2 – 28,8 VDC

Network Availability of Customer Digital Infrastructure:

- A Static or DHCP provided Internet Address with access to the Contractor Everllence CEON Cloud is required in order to provide Service Delivery.
- Continuous connectivity to communications gateway installed on customer network needs to be provided to the following destination domains/IPs:

- For CEON Access/ data transmission: encypted TLS1.3 **TCP Port 443**:
  - **assethub.mya.io**
  - **upgrades.mya.io**
  - **assethub.manceon.io**

  (35.156.61.78 / 35.156.77.222 / 35.157.233.80)

- For (mGuard) firewall, firmware & configuration updates **TCP Port 443**:
  - **149.247.176.129**

- For time syncronization open **UDP Port 123**:
  - **ntp.manceon.io** **(35.156.61.78 / 35.156.77.222 / 35.157.233.80)**
  - (Optional) **ntp.ubuntu.com** **(91.189.91.157)**

- Remote access (**UDP Port 500 and UDP Port 4500)**:
  - **149.247.177.99**

  (Once setup completed it can be disabled, or utilized when help is required)

We recommend to set firewall whitelist rules with the domain names listed above.
If not possible please use IPs.
Only Outbound (One-way) direction need to be enabled.

Please forward this checklist to your IT Department / Internet provider.