CENTRAL MANUFACTURING TECHNOLOGY INSTITUTE

C – Smart Manufacturing Cell

User Guide

Troubleshooting – Machine Configuration

PROJECT: SPV Data Flow

Use this guide when you face issues adding, editing, deleting, viewing, or performing password actions on machines in the Machine Configure page. For issues with Machine Status (OFFLINE, FAILED, copy errors) refer to the M2M Connectivity Troubleshooting Guide.

1 Page Not Loading or Machine List Is Empty

Symptoms

You will see: Blank table, spinner keeps loading indefinitely, or the message: 'Could not load machines'.

Likely Causes

Backend / API unreachable	The application server is down
Session or auth token expired	Your login session has timed out. The fetch requires a valid authenticated session.
HTTPS / certificate error	The browser blocks API calls when the server TLS certificate is untrusted, self-signed, or expired.
Browser extension blocking fetch	Ad blockers, privacy extensions, or corporate content policies intercept the API request silently.

Resolution Steps — Follow in Order

1. Refresh the page once. If the spinner clears and data loads, it was a transient network blip.
2. Log out completely and log back in. A fresh session token resolves most auth-related list failures.
3. Check whether other modules in the portal load. If nothing loads, the backend service itself is down — escalate to your IT / backend team immediately.
4. Try a private/incognito window with all extensions disabled. If the list loads, a browser extension is the cause.
5. If the browser shows a certificate warning icon in the address bar, the TLS certificate issue must be resolved by IT before the portal will function correctly.

2 Cannot Add or Edit Machine — Save Fails

Symptoms

You will see: The Save button does nothing, an error popup appears, or an inline field validation message is shown after clicking Save.

Likely Causes & What to Check

Cause	What Triggers It	Fix
Invalid IP address	Value is not a valid IPv4 or IPv6 address (e.g. stray spaces, letters, wrong separators)	Re-enter with no extra characters
Missing required field	machine_name, network_path, or ip_address, pw , login name left blank	Fill all fields marked with an asterisk (*)
Duplicate machine name	A machine with the same name already exists in the same type tab	Choose a unique name. Names must be unique per machine type (EL/RFID/IVC)
Invalid UNC path	Network path does not follow \\server\share\folder format	Use double backslashes: \\10.10.12.50\ShareName\Folder
Bad optional field type	Configured Year entered as text instead of a 4-digit integer	Enter year as a number: 2026 (not '2026' with quotes or text)
Session expired mid-edit	Session token expired while the form was open	Save the form values, log out, log in again, and re-enter

Retry tip: If save fails and the error message is generic, try entering a known-good sample record first (e.g. a machine that already works but with a different name) to confirm the form itself is functional before debugging the specific values.

3 Authentication Failed — Delete or Reveal Password Blocked

Symptoms

You will see: The Delete confirmation modal rejects your password and shows 'Authentication failed. Please verify your admin credentials and try again.' OR the Reveal Password action fails with the same error.

Why This Happens

Delete and Reveal Password are protected actions. Before processing, the backend verifies the password entered in the form against the currently logged-in user account. This is a second-factor confirmation step — it is separate from the initial login.

Wrong admin password entered	The password typed in the confirmation modal does not match your account password. This is the most common cause.
Caps Lock or keyboard layout	Password fields are case-sensitive. Check your Caps Lock key and keyboard input language before retrying.
Expired or reset password	Your domain / application password was changed (by you or by IT) since you last logged in. Your active session still works but your stored password is now wrong.
Account suspended or disabled	Your user account exists but has been disabled.

Resolution Steps

1. Type the password very slowly in the form. Watch for Caps Lock indicator..
2. If your password was recently changed, log out, log back in with the new password, and retry the Delete or Reveal action.
3. Try a hard refresh (Ctrl + Shift + R) to clear cached session data, then log in again before retrying.
4. If you are the admin and your own account fails, request other active admin accounts to do the same.

Note: The password entered in the modal is your own current account password — not the machine's share password or any other credential.

4 Machine Added Successfully but Shows Wrong Behaviour in Status Page

Symptoms

You will see: Machine was saved without errors in Machine Configure, but the Machine Status page shows it as OFFLINE, FAILED, or the machine never copies files despite appearing in the list.

This Is Not a Configure Page Bug

The Machine Configure page successfully saved the record — the issue is in how the saved values interact with the network and copy engine. Use the table below to identify the specific cause.

Status Seen	Most Likely Configure Mistake	What to Fix in Machine Configure
OFFLINE	Wrong IP address saved	Correct the IP field. Verify by pinging the device from the server network before saving.
FAILED — copy	Wrong or typo in Network Path	Re-enter the UNC path carefully: \\<ip>\<share>\<folder>. No trailing spaces, correct backslashes.
FAILED — auth	Wrong login name or password	Update Login Name and Password fields. Re-enter the password even if it looks correct — the stored value may be stale.
FAILED — share	Share not accessible from server	Verify IT has permitted SMB (port 445) from the application server to the device IP. Configure cannot fix this.
INACTIVE label	is_active deliberately set false	Re-enable Active in Machine Configure if copies should run. This is a configuration choice, not an error.

Where to go next: Once you have corrected the configure record, go to Machine Status, click Refresh, and trigger a manual copy to confirm the fix. If it still fails, use the M2M Connectivity Troubleshooting Guide for deeper diagnosis.

6 Delete Succeeds but Machine Still Appears in List

Symptoms

You will see: The Delete confirmation went through without an error, but the deleted machine is still visible in the machine list immediately after.

Likely Causes

UI cache / stale view state	The list in memory has not yet been refreshed from the server after the delete operation. This is the most common cause.
Delayed API refresh	The delete API call succeeded but the call to reload the list has not completed yet.
Tab not re-fetching	Switching between EL / RFID / IVC tabs triggers a fresh fetch. The current tab view may be showing a cached snapshot.

Resolution Steps

1. Click the Refresh button on the Machine Configure page. In most cases this immediately removes the deleted record.
2. Switch to a different machine type tab (e.g. from EL to RFID) and switch back. Each tab change triggers a fresh list fetch.
3. Hard refresh the browser page (Ctrl + Shift + R or Cmd + Shift + R on Mac).
4. If the machine is still present after a hard refresh, this indicates the delete API call may have silently failed. Check the browser Network tab (F12) for the DELETE request status code. If it returned 200 or 204, the record was deleted and this is a display issue only. If it returned 4xx or 5xx, the delete failed and you should retry or escalate.

When to escalate: If the machine reappears after multiple refreshes and the DELETE request returned a success status code, report to application team with the machine name, the time of deletion, and the exact machine name.

Field Validation Quick Reference

Use this table as a quick sanity check before clicking Save on any Add or Edit form.

Field	Required?	Valid Format / Example	Common Mistake
Machine Name	Yes	`Jinchen_PreEL_Vega`	Duplicate name or special characters
Network Path	Yes	`\\10.10.12.224\ImagePath\ThinkEyes\`	Forward slashes or missing backslash prefix
IP Address	Yes	`10.10.12.224`	Spaces, letters, or wrong format
Login Name	Yes	`administrator`	Domain format mismatch
Password	Yes	`(enter new value to change)`	Leaving blank thinking it clears password
Configured Year	No	`2026`	Entering text or wrong year
Machine Type	EL only	`A , B , T , Z`	Wrong type changes folder logic
Machine Suffix	RFID/IVC	`I8R, I9F, JIN`	Wrong suffix reads from wrong subfolder
Destination Path	Optional	`F:\2026_FILE_REPO`	Missing if custom server dest needed
Status (Active)	No	`Toggle ON = active`	Left inactive = never copies

For connectivity and copy issues after a machine is saved, refer to the M2M Connectivity Troubleshooting Guide.