

Residential Electrical Service Inspection Punch List

Estimated Time: 45–60 minutes

Customer:

Date:

Technician:

Service Equipment

- Inspect meter enclosure for corrosion, damage, water intrusion, and secure mounting.
- Inspect service mast/riser, weatherhead, and service entrance conductors.
- Check service attachment point and clearances (visual).
- Inspect main load center enclosure condition.
- Inspect dead front and panel cover.
- Check for rust, corrosion, insect intrusion, or moisture.
- Verify panel labeling is present and reasonably accurate.
- Verify all panel openings are properly closed.

Interior of Load Center

- Remove dead front.
- Check for overheating, discoloration, or arcing.
- Inspect bus bars.
- Inspect main breaker condition.
- Inspect branch breaker condition.
- Check for incompatible breaker types.
- Check for double-lugged breakers where not permitted.
- Check neutral bar for multiple conductors where prohibited.
- Verify grounding conductor terminations.
- Verify bonding screw/strap where applicable.
- Inspect conductor insulation condition.
- Check conductor routing and workmanship.
- Verify cable connectors are secure.
- Tighten accessible lugs and terminals to manufacturer specifications where applicable.

Electrical Testing

- Verify service voltage.
- Verify voltage balance between legs.
- Measure main load under normal operating conditions.
- Scan panel for abnormal heating (infrared if available).
- Spot-check several branch circuits for proper voltage.

Grounding & Bonding

- Inspect grounding electrode conductor.
- Inspect ground rod connection (if visible).
- Inspect water pipe grounding connection (if applicable).
- Inspect bonding jumpers.

AFCI / GFCI Protection

- Test accessible GFCI devices.
- Kitchen GFCI protection
- Bathrooms GFCI protection
- Garage GFCI protection
- Exterior GFCI protection
- Laundry GFCI protection
- Crawl space/basement GFCI protection
- Identify missing GFCI protection.
- Identify missing AFCI protection where applicable.

Smoke & Safety Devices

- Test smoke alarms.
- Test combination smoke/CO alarms.
- Recommend replacement if over 10 years old.

Interior Electrical

- Test representative receptacles.
- Check polarity and grounding.
- Check for loose devices.
- Inspect switches.
- Inspect lighting fixtures.
- Check for damaged receptacles.
- Check for damaged switch plates.

Exterior Electrical

- Inspect exterior receptacles.
- Verify weather-resistant devices.
- Verify in-use covers.
- Inspect exterior lighting.
- Inspect exposed conduit and fittings.

Attic / Crawlspace

- Inspect exposed wiring.
- Look for damaged NM cable.
- Check for exposed splices.
- Check support of cables.
- Look for rodent damage.

Safety Hazards

- Evidence of overheating.
- Aluminum branch wiring.
- Federal Pacific equipment.
- Zinsco equipment.
- Challenger equipment.
- Open splices.
- Extension cords used as permanent wiring.
- Missing panel directory.
- Missing bonding.
- Water intrusion.
- Corrosion.

Inspection Summary

Overall Condition: Excellent Good Fair Poor

Immediate Safety Concerns

Maintenance Items

Recommended Upgrades

Recommended Timeframe: Immediate Within 6 months Within 1 year Monitor