

M0FXB HamTech Dashboard for ASL3

How to edit the selection tiles in buttons.ini

Overview

HamTech selection tiles can be customised from the **buttons.ini** configuration file. You can change the text displayed on a tile and the AllStar command that the tile sends.

1. Connect to the ASL3 node

Open PuTTY (or another SSH client), connect to your ASL3 node and log in.

2. Open buttons.ini

At the command prompt enter:

```
sudo nano /var/www/html/buttons.ini
```

3. Find the tile you want to change

Each tile is represented by a section in the INI file. A typical entry looks similar to:

```
[link_hubnet]
title = Link HubNET
cmds[] = *341522
color = green
```

Setting	What it controls
title	The wording displayed on the dashboard tile.
cmds[]	The AllStar command sent when the tile is selected.
color	The tile colour, where supported by the HamTech configuration.

4. Example change

For example, to change the displayed name from **Link HubNET** to **Link My Hub**, edit the section to:

```
[link_hubnet]
title = Link My Hub
cmds[] = *341522
color = green
```

If you also need to change the destination, replace the value after **cmds[] =** with the correct AllStar command for your intended node or function.

5. Save the changes

In nano, press **Ctrl+O** to write the file, press **Enter** to confirm the filename, then press **Ctrl+X** to exit.

6. Refresh HamTech

Return to the HamTech dashboard in your browser and refresh the page. If the old tile is still displayed, use **Ctrl+F5** to force a full browser refresh.

Important: Make a backup before making extensive changes. Be careful when changing **cmds[]**: an incorrect AllStar command can make the tile perform the wrong action.