28- ARP-RELAY Configuration Commands

28.1 ARP-RELAY Configuration Command Tree

Description

This chapter gives an overview of nodes that are handled by "ARP-RELAY Configuration Commands".

Command Tree

```
----configure
    ----arp-relay
        ----[no] statistics
            - (vlan-port)
```

28.2 Arp-Relay Statistics Configuration Command

Command Description

This command allows the operator to enable/disable the detailed arp-relay statistics.

User Level

The command can be accessed by operators with ip privileges, and executed by operators with ip privileges.

Command Syntax

The command has the following syntax:

> configure arp-relay (no statistics (vlan-port)) | (statistics (vlan-port))

Command Parameters

Table 28.2-1 "Arp-Relay Statistics Configuration Command" Resource Parameters

Resource Identifier	Type	Description
(vlan-port)	Format: (vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PortId> : <Eqpt::VpiId> : <Eqpt::VciId> : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PortId> : <Eqpt::VpiId> : <Eqpt::VciId> : <Eqpt::UnstackedVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PortId> : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PortId> : <Eqpt::UnstackedVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / <Eqpt::OntSlotId> / <Eqpt::OntPortId> : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / <Eqpt::OntSlotId> / <Eqpt::OntPortId> : <Eqpt::UnstackedVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / voip : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / vuni : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / voip : <Eqpt::UnstackedVlan>	The vlan-port interface

Resource Identifier	Type	Description
	| vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / vuni : <Eqpt::UnstackedVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / <Eqpt::LLId> : <Eqpt::UnstackedVlan> | vlan-port : <Eqpt::RackId> / <Eqpt::ShelfId> / <Eqpt::SlotId> / <Eqpt::PonId> / <Eqpt::OntId> / <Eqpt::LLId> : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port:ng2 : <Eqpt::ChannelGroupId> / <Eqpt::SubChannelGroupId> / <Eqpt::Ng2OntId> / <Eqpt::Ng2OntSlotId> / <Eqpt::Ng2OntPortId> : <Eqpt::UnstackedVlan> | vlan-port:ng2 : <Eqpt::ChannelGroupId> / <Eqpt::SubChannelGroupId> / <Eqpt::Ng2OntId> / <Eqpt::Ng2OntSlotId> / <Eqpt::Ng2OntPortId> : stacked : <Eqpt::SVlan> : <Eqpt::CVlan> | vlan-port:ng2 : <Eqpt::ChannelGroupId> / <Eqpt::SubChannelGroupId> / <Eqpt::Ng2OntId> / vuni) Possible values: - vlan-port : vlan port - vlan-port:ng2 : an NGPON2 vlan port Field type <Eqpt::RackId> - the rack number Field type <Eqpt::ShelfId> - the shelf number Field type <Eqpt::SlotId> - the LT slot number Field type <Eqpt::PortId> - the port number Field type <Eqpt::VpiId> - atm VPI Field type <Eqpt::VciId> - atm VCI Field type <Eqpt::ChannelGroupId> - the channel group identifier Field type <Eqpt::SubChannelGroupId> - the subchannel group identifier Field type <Eqpt::PonId> - the PON identifier Field type <Eqpt::OntId> - the ONT identifier Field type <Eqpt::Ng2OntId> - the NG2 ONT identifier Possible values: - voip : virtual uni identifier obsolete alternative replaced by vuni - vuni : virtual uni identifier Possible values: - vuni : virtual NGPON2 uni identifier Field type <Eqpt::OntSlotId> - the ONT SLOT identifier Field type <Eqpt::OntPortId> - the ONT PORT identifier Field type <Eqpt::Ng2OntSlotId> - the NGPON2 ONT SLOT identifier Field type <Eqpt::Ng2OntPortId>	

Resource Identifier	Type	Description
	- the NGPON2 ONT PORT identifier Field type <Eqpt::LLId> - the LLID identifier,range 1 for EPON,range 1-8 for DPOE Possible values: - stacked : stacked vlan identity Field type <Eqpt::UnstackedVlan> - unstacked vlan id Field type <Eqpt::SVlan> - service vlan id Field type <Eqpt::CVlan> - customer vlan id	