mini eTPC parameter scans

ELI-NP, 14–19 October 2026 (ELITPC DAQ, α source)

Soichiro Aogaki (compiled with Claude)

20 October 2026 — informal working document for discussion

(English version of the Japanese report v4.3; runs 78–176)

Abstract

From 14 to 19 October 2026 we ran 19 parameter scans (runs 78–176, about 100 runs) on the ELI-NP mini eTPC (GET electronics, one zCoBo, one AsAd = 272 channels), covering the electronics, the high voltage, the readout mode and the gas flow. The six conclusions are: (1) **Operating point B** — GEM 240 V × 3, peaking time 502 ns × gain 120 fC, full readout, 25 MHz, triggerDelay 1750 — is adopted for routine running (all metrics stable over a 9.6 h overnight run). (2) The summed charge is fully collected for every peaking time; the peaking time only changes the peak height and the time width (shown by deconvolution). (3) The gain follows $\ln G = \sum_i a_i \Delta V_i$ with $a \approx 0.014 \pm 0.0015$/V (the three foils agree within errors and the effects add up); up to −30 V in total on the GEMs can be compensated by the electronics. (4) A single hit is measured to $\sigma_z \approx 0.20$ mm in drift direction (one time bin; constant in mm, independent of the HV and of the drift field) and to $\sigma \approx 0.30$ mm per view in the strip plane (232–502 ns). (5) The rate limit is set by the zCoBo firmware readout time (2.94 ms for 272 channels, ≈ 340 Hz; triggers arriving during readout are lost), not by the network. Zero suppression with per-channel thresholds (pedestal $+5\sigma$) reduces the data by 1/9–1/12 without any loss of quality; **the default candidate for beam runs is hit-register partial readout + ZS (23 kB/event)**. (6) Halving the gas flow from 100 to 50 ml/min lowers the total charge by 3.5 %, settling within a few hours (the volume exchange time of the 54 L chamber); 150 ml/min gives the same as 100. This is explained by the S/Q term of the steady-state impurity concentration $c = c_{\mathrm{bottle}} + S/Q$; the HV is not involved.

Contents

1 Setup and method **2**
- 1.1 Apparatus and common conditions . . . 2
- 1.2 Definition of the metrics . . . 2
- 1.3 Terms and abbreviations . . . 3
- 1.4 List of scans . . . 4

2 Electronics parameters **4**
- 2.1 triggerDelay (S1) . . . 4
- 2.2 Peaking time (S2), response kernel (S4) and deconvolution (S8) . . . 5
- 2.3 Gain (S3) and the E rule . . . 5

3 Detector high voltage and gas **7**
- 3.1 GEM voltage margin (S10) . . . 7
- 3.2 Drift voltage (S12) . . . 7
- 3.3 Operating point B and overnight runs (S7, S16) . . . 8
- 3.4 Gas flow (S19) . . . 8

4 Hit precision **9**
- 4.1 Definition of hits and of the two residuals . . . 9
- 4.2 z residual (S11) . . . 10
- 4.3 2D centroid precision = U/V/W closure residual (S14) . . . 10

5 Readout mode, rate and zero suppression **11**
5.1 Readout and hit register (S9, S15) 11
5.2 Maximum rate (S17) 11
5.3 Zero suppression (S5, S13, S18) 12
5.4 Design for beam runs (≈ 100 Hz) 13

6 Open issues and next steps **14**

A Tools and records **15**

B Parameters of operating point B **15**

1 Setup and method

1.1 Apparatus and common conditions

- Detector: mini eTPC (ELI-NP). 20 cm drift, triple GEM, U/V/W strip readout. CO_2 at 91 mbar.
- Source: ^{228}Th α source (outside the entrance wall, $x = -370$ mm). External trigger ≈ 4.6 Hz.
- Electronics: GET (4 AGET = 272 channels, 16 of them FPN), one zCoBo (firmware 2018-10-31), 25 MHz sampling (1 cell = 40 ns), 512 cells.
- HV (CAEN DT1415ET, 8 channels in series, 200 MΩ resistor chain): ch0 TR1 (induction) 350 V, ch1/3/5 GEM1–3 (GEM1 = readout side), ch2/4 transfer 350 V, ch6/7 drift 600 V × 2. **GEMs at** 250×3 **for S1–S9 and at** 240×3 **from 15 Oct 12:50 (operating point B).**
- DAQ: tpcdaq-rs (Rust) + root_sink (C++) on the ELITPC host (repository in Appendix A). The electronics parameters are kept as JSON (template + knobs + exceptions); the settings and the HV of every run are logged automatically.
- One scan point = one run (1,500 events ≈ 5.5 min unless stated otherwise).

1.2 Definition of the metrics

All metrics are computed per run by `tools/scan/run_metrics.C`.

- Pedestal: mean of cells 1–20 of each channel (per-channel calibration table for ZS data); the mean FPN waveform is subtracted to remove common-mode noise. Hit threshold 35 ADC.
- **Hit channels**: median number of channels above threshold. **Total charge**: median over events of the sum of all samples.
- **Saturation**: fraction of events with a channel at 4095 ADC. **Clip**: fraction of events whose band touches the start or end of the time window.
- **ok / length / dEdx**: result of fitting one straight line per event with the analysis macros (`analyzeUVW.C` + `makeTracks.C`, S. Aogaki). ok = fraction of successful fits, length = median track length [mm], dEdx = median / IQR of the charge per unit length (ADC/mm).
- σ_z: robust σ of the hit z residuals with respect to the line (`hit_residuals.C`). σ_{2D}: robust σ of the U+V+W closure residual divided by $\sqrt{3}$ (`uvw_closure.C`, Sec. 4.3).

1.3 Terms and abbreviations

GET / AGET / AsAd / zCoBo GET = General Electronics for TPCs. AGET = ASIC with 64 signal + 4 FPN channels (preamplifier, shaper, switched-capacitor array). AsAd = board carrying 4 AGETs (272 channels). zCoBo = Zynq (ZC706) board that reads the AsAd and sends the data to the PC, and its firmware (FW).

FPN Fixed Pattern Noise channels: the 4 of the 68 AGET channels that are not connected to the detector (ch 11, 22, 45, 56). They carry only the noise common to the signal path, so their mean waveform is subtracted from the signals to remove common-mode noise.

cell / bucket One SCA sample. At 25 MHz one cell = 40 ns; one event = 512 cells.

peaking time / gain AGET shaper peaking time (70 / 232 / 502 / 1014 ns) and preamplifier full-scale charge (120 fC / 240 fC / 1 pC). A larger gain value means a lower amplification.

full / partial readout, hit register Full = read all channels. Partial = read only the channels flagged in the AGET hit register (above threshold). With `channel Reading = always`, partial readout still reads all channels.

frameType 1 / 2 zCoBo output formats. 1 = 4 B/sample with channel number (partial, ZS); 2 = compact 2 B/sample (full readout only).

ZS Zero suppression: the zCoBo FW does not send samples below a per-channel threshold.

ped Pedestal (ADC value without signal, ≈ 450 ADC per channel).

IQR Interquartile range (75 % minus 25 % quantile); a width that is robust against outliers.

robust σ $1.4826\times$ MAD (median absolute deviation). Equal to σ for a Gaussian, not pulled by heavy tails.

FWHM Full width at half maximum. **S/N**: signal-to-noise ratio. **GEM**: Gas Electron Multiplier, three foils here. **TR**: transfer gap between GEMs; **TR1**: induction gap between GEM1 and the readout plane.

U / V / W, view The three strip families of the readout plane (inclined by 60° to each other). "One view" = the one-dimensional image seen by one strip family.

1.4 List of scans

Table 1: Scan index (S numbers as in the scan ledger `docs/SCANS_ja.md`).

#	Date	Scan	Runs	Conclusion
S1	10-14	triggerDelay, 5 points	78–82	Band position linear, 508−delay/4; set to 1750
S2	10-14	peaking time, 4 points	83–86	70 ns loses tracks, 1014 ns saturates in 1/3 of events
S3	10-14	gain, 4+1 points	87–90, 112	E rule gives 502 ns × 240 fC; 1 pC unusable
S4	10-14	pulser response kernel, 8 points	102–110	Kernel has no ringing; α "wiggle" is not from the electronics
S5	10-14	pedestal, 2 points	99, 100	Per-channel tables (232 / 502 ns)
S6	10-14	drift end at 12.5 MHz	111, 113	Source position too far out to span z; retry with the source inside
S7	10-14/15	overnight α run (E)	114	Stable over 10 h, 166k events
S8	10-14	deconvolution	84–88	Sum of samples collects all charge at any peaking time
S9	10-15	readout / hit threshold / ZS	115–121	Old partial mode read all channels: twice the data of full
S10	10-15	GEM voltage margin	122–129	$\ln G \approx 0.014/\mathrm{V} \times \Delta V$, tracks intact down to −30 V
S11	10-15	hit z residual	(analysis)	$\sigma_z \approx 0.2$ mm = 1 cell
S12	10-15	drift voltage, 3 points	130–132	$v \propto E$; σ_z constant in mm
S13	10-15	ZS, per-channel threshold	133	31.8 kB/event (1/8.8); macros need an update
S14	10-15	U/V/W closure residual	(analysis)	$\sigma_{2D} = 0.30$ mm/view
S15	10-15	hit-register threshold, 6 points	135–140	Threshold works, but at most 14 % below full
S16	10-15/16	overnight α run (B)	141	Stable over 9.6 h; B adopted
S17	10-16	maximum rate	148–169	Limit = FW readout time 2.94 ms
S18	10-16	ZS validation	170–173	No quality loss, 1/9–1/12 of the data; suppress FPN
S19	10-16/19	gas flow 100 / 50 / 150 ml/min	174–176	−3.5 % charge at 50, settles in hours; 150 same as 100

2 Electronics parameters

2.1 triggerDelay (S1)

25 MHz, 232 ns, 120 fC, partial readout. The first cell of the band (median first hit) is strictly linear in the delay, first = 508 − delay/4 (delay in units of 10 ns). At a delay of 2000, 15 % of the events are cut at the start and ok drops to 0.86. The setting was changed from 1500 to **1750** (band starts $\approx 2.8\,\mu$sbefore the trigger). Rule: delay [10 ns] = (window [ns] − 2800 − 160)/10 (1750 at 25 MHz, 3800 at 12.5 MHz).

Table 2: S1 triggerDelay (runs 78–82).

delay	run	first (p10–p90)	last (p90)	clip at start	hit ch	ok	length [mm]
1000	78	258 (243–264)	282 (325)	0	121	0.997	84.4
1250	79	196 (182–201)	220 (263)	0	121	0.998	84.4
1500	80	134 (119–139)	157 (198)	0	119	0.993	83.9
1750	81	71 (55–76)	94 (142)	0.001	120	0.992	84.1
2000	82	12 (3–16)	31 (74)	**0.154**	75	**0.863**	**68.1**




Figure 1: S1: first cell of the band versus triggerDelay (runs 78–82).

2.2 Peaking time (S2), response kernel (S4) and deconvolution (S8)

Delay 1750, 120 fC, GEMs at 250 × 3. Longer shaping picks up weaker strips (hit channels 121 → 147) but saturates more: at 1014 ns one third of the events saturate. At 70 ns the S/N is too low and one third of the tracks is lost.

Table 3: S2 peaking time (runs 83–86).

peaking	run	width [cell]	hit ch	total charge	sat.	ok	length / IQR	dEdx / IQR	wiggle A0 [ADC]
70 ns	83	25	52	0.25 M	0.0 %	0.660	45.4 / 46.3	4,602 / 855	4.4
232 ns	84	39	121	1.40 M	0.3 %	0.998	85.2 / 58.4	12,493 / 6,438	12.4
502 ns	85	62	128	3.24 M	4.8 %	0.997	88.9 / 58.8	19,087 / 9,466	27.9
1014 ns	86	106	147	7.21 M	33.7 %	0.998	104.5 / 66.6	22,469 / 9,693	59.9

The total charge grows as 1 : 2.3 : 5.2 with the peaking time. We first read this as "short shaping integrates only part of the signal"; that was **wrong** — it is an area effect (S8). The **pulser response kernel** is the impulse response of the electronics (preamplifier + shaper + SCA). The AsAd has a built-in pulser that injects the same known charge (a voltage step of −300 / −100 mV on the test capacitor) into the test inputs of all AGET channels at once. The injected pulse is much shorter than a detector signal (effectively a δ function), so the kernel is obtained by aligning the output waveforms of all channels at their peak, averaging and normalising to the peak (one run averages $68 \times 4 \times 600 \approx 150{,}000$ waveforms, Fig. 2). A detector waveform is "arrival-time distribution of the charge $\otimes$ kernel", so knowing the kernel one can deconvolve back to the arrival-time distribution (S8). The measured kernels are identical for the four AGETs and show no ringing (1.8 µscomponent $\leq 0.03\,\%$); the peak gain ratio is $232 : 502 : 1014 = 1 : 1.05 : 1.17$. Deconvolving the α waveforms with these kernels (`deconv.C`, FFTW, $\lambda_{\mathrm{rel}} = 10^{-3}$) brings the charge ratio back to 1 : 1.05 : 1.21, matching the pulser gain ratio. In other words, **the sum of samples collects the full input charge at every peaking time**. After deconvolution the FWHM converges to 13.7 / 14.6 / 18.7 cells (0.55–0.75 µs), the intrinsic width on the detector side (Fig. 3). Because of the noise amplification (S/N × 0.4–0.5) we do not use it online; it stays as an offline option ($\lambda = 10^{-2}$).

The "wiggle" with a period of 1.6–1.8 µsseen on α waveforms (signal channels only, proportional to the charge) is absent from the kernel, so it is not a response of the AGET shaping (origin unknown, Sec. 6).

2.3 Gain (S3) and the E rule

502 ns, GEMs at 250 × 3. The "E rule" — take the longest peaking time, with its gain, that keeps the fraction of events with a saturated channel below 2 % — selects **502 ns × 240 fC** (0.7 % saturation) at 250 × 3. At 1 pC the tracks fall below the 35 ADC threshold (ok 0.009). The wiggle amplitude scales with the output amplitude (it rides on the gain).




Figure 2: S4: pulser response kernels (left: 502 ns, run 107; right: 1014 ns, run 109). Mean waveform of each AGET normalised to the peak. No ringing.




Figure 3: S8: one channel of run 87 (502 ns × 120 fC) before and after deconvolution. FWHM 24.5 → 14.6 cells; charge ratio 0.048 (normalised by the kernel sum).

Table 4: S3 gain (runs 87–90, 112).

peaking × gain	run	hit ch	total charge	sat.	clip start/end	ok	length / IQR	dEdx / IQR
502 × 120 fC	87	127	3.20 M	4.7 %	8.3 / 21.4 %	0.997	88.2 / 58.8	19,352 / 9,283
502 × 240 fC	88	119	1.71 M	**0.7 %**	2.7 / 8.9 %	0.991	84.0 / 59.3	11,946 / 5,896
502 × 1 pC	89	23	0.16 M	0 %	0 / 0.1 %	0.009	—	—
1014 × 1 pC	90	43	0.53 M	0 %	0 / 0.1 %	0.626	48.3 / 50.2	3,669 / 820
1014 × 240 fC	112	122	3.90 M	2.1 %	0.7 / 4.8 %	0.998	84.6 / 58.4	16,155 / 7,814

3 Detector high voltage and gas

3.1 GEM voltage margin (S10)

On site, the GEMs were lowered one at a time or all three together (HV set by hand with CAEN GECO, runs with `gem_point.sh`), and the total charge was compared with the same electronics (502 ns × 120 fC). As Fig. 4 shows, $\ln(Q/Q_0)$ is explained by the sum of the ΔV of the three foils. The individual slopes GEM1 / GEM2 / GEM3 = 0.0148 / 0.0130 / 0.0145 ± 0.0026/V agree within errors, and the sum of the three single-foil points (-0.423 ± 0.045) equals the all-three point (-0.425 ± 0.026), so the effects add. Mean slope $a = 0.0141 \pm 0.0015$/V (a factor 0.86 per −10 V in total). Down to −30 V in total (240 V each, the same value as the full-size HIGS detector), the electronics compensate and the track quality (ok, hit channels, length, relative dEdx width) does not change; no trips or current anomalies occurred. The currents are about 8.6–8.8 µAon all channels and follow the voltage ratio when the GEMs are lowered. The 200 MΩ resistor chain on the HV side, as Traian explained earlier from the circuit diagram, is also clearly confirmed by the present V–I data: the summed voltage of ch0–5, 1,770 V at 240 × 3, divided by 200 MΩ gives 8.85 µAagainst a measured 8.63–8.80 µA; at 250 × 3, 1,800 V gives 9.0 µAagainst 8.80 µA.




Figure 4: S10: gain law. Each point has an error of ±0.026 (median charge of 1,500 events).

Table 5: S10 GEM voltages (compared at 502 ns × 120 fC; point a = reference run 87).

point	GEM1 / GEM2 / GEM3 [V]	run	hit ch	total charge	sat.	ok	length	dEdx / IQR
a	250 / 250 / 250	87	127	3.20 M	4.7 %	0.997	88.2	19,352 / 9,283
b	240 / 250 / 250	122	124	2.76 M	2.6 %	0.999	85.9	17,645 / 8,645
c	230 / 250 / 250	123	122	2.38 M	1.1 %	0.997	84.7	15,258 / 7,697
d	240 / 240 / 240	126	121	2.09 M	1.0 %	1.000	84.3	13,637 / 6,617
e	250 / 240 / 250	128	125	2.81 M	2.0 %	0.996	86.3	17,553 / 8,318
f	250 / 250 / 240	129	123	2.76 M	2.3 %	0.999	84.9	17,726 / 8,566

3.2 Drift voltage (S12)

At operating point B the drift voltage was set to 1,000 / 1,200 / 1,400 V (500/600/700 V × 2). The time width of the band times V is constant (±6 %), so $v_{\text{drift}} \propto E$, consistent with the nominal $v = 0.7233 \times E/p$. The pulse width goes 61 → 57 → 54 cells (−11 % for +40 % in E: the $1/\sqrt{E}$ of diffusion plus the shaping width). Total charge and hit channels do not change (no loss in focusing into GEM3). σ_z scales as $1/v$ in cells but is **constant in mm (0.207 / 0.208 / 0.208)**. Routine running stays at 1,200 V.

Table 6: S12 drift voltage (runs 130–132, operating point B).

V_{drift}	run	time width [cell]	width × V	pulse width [cell]	hit ch	total charge	σ_z [cell]	σ_z [mm]
1,000	131	28	28,000	61	120	2.07 M	1.30	0.207
1,200	130	22	26,400	57	121.5	2.09 M	1.09	0.208
1,400	132	20	28,000	54	123	2.09 M	0.93	0.208

3.3 Operating point B and overnight runs (S7, S16)

Operating point B (GEM 240×3, 502 ns × 120 fC, full readout, 25 MHz, delay 1750, drift 600×2, transfer 350) was adopted on 15 October at 12:50. The GEMs run 10 V per foil lower, and full readout uses frameType 2 (2 B/sample), so the data size is half of that of setting A (partial, 557 kB/event): 278.8 kB/event. The metrics of the overnight run 141 (9.6 h, 149,795 events, 4.32 Hz, 104 GB) agree with the 5.5 min check run 130 and with the overnight run of setting A (run 114, 10 h, 166,386 events).

Table 7: Overnight runs (S7, S16).

run	setting	events	kB/ev	hit ch	charge	sat.	ok	length / IQR	σ_z	σ_{2D}
114	A overnight (250×3, 502×240 fC, partial)	166,386	557	119	1.71 M	0.62 %	0.995	83.4 / 59.6	0.20	0.325
130	B check (5.5 min)	1,500	278.8	121.5	2.09 M	0.60 %	0.998	84.4 / 58.5	0.21	0.314
141	**B overnight**	149,795	278.8	121	2.08 M	0.92 %	0.999	84.1 / 58.8	0.20	0.321

3.4 Gas flow (S19)

Keeping operating point B, only the CO_2 flow was changed, $100 \rightarrow 50 \rightarrow 150$ ml/min (54 L chamber, 91 mbar; run 174 at 100, run 175 at 50 for 67.7 h, run 176 at 150). `gas_trend.C` splits the raw tree into 1 h (run 175) or 10 min (runs 174, 176) bins and follows the median event charge and other quantities (Fig. 5).

Table 8: S19 gas flow (whole-run metrics; run 176 includes the first 1.5 h of rise, its equilibrium value is 2.087 M).

run	flow	events	hit ch	charge	sat.	ok	length / IQR	dEdx / IQR
174	100 ml/min	11,145	120	2.077 M	1.0 %	0.999	84.1 / 58.9	13,532 / 6,508
175	50 ml/min (67.7 h)	1,057,719	120	**2.002 M**	0.9 %	0.999	83.8 / 58.9	12,998 / 6,336
176	150 ml/min (4.7 h)	73,652	121	2.078 M	1.0 %	0.997	84.2 / 58.7	13,493 / 6,539

- At 50 ml/min the total charge drops from 2.08 to 2.00 M (−3.5 %) and dEdx by −4 %. The 16 % quantile drops by the same ratio: the whole distribution shrinks uniformly. Hit channels, track length, ok, band position (first 75 / last 98 cells) and pulse width (56 cells) are unchanged, so the drift velocity and diffusion are unchanged. The HV (1 h means from InfluxDB, 69 points) stayed within ±0.05 V and ±0.5 % in current: not involved.
- The new equilibrium is reached within a few hours, and the rise after returning to 150 ml/min takes about 0.5 h. This matches the time constant for flushing 54 L at the given flow (at 91 mbar the actual volume flow is 11 times the normal flow: 1.6 h at 50 ml/min, 0.54 h at 150 ml/min); no slow process such as wall outgassing is needed.
- Interpretation: the steady-state impurity concentration (mainly H_2O and air from leaks) is $c = c_{\text{bottle}} + S/Q$ (S = production inside the system, Q = flow). The bottle term does not depend on the flow and drops out of the difference. The values 2.002 / 2.077 / 2.087 ± 0.004 M at 50 / 100 / 150 ml/min (150: mean of twenty 10 min bins between 1.5 and 4.7 h) are consistent within 1 % with a dependence on S/Q; above 100 ml/min the gain hardly changes.




Figure 5: S19: total charge after each flow change. Dashed lines: equilibrium value for each flow (grey 100 ml/min 2.077 M, blue 50 ml/min 2.002 M, red 150 ml/min 2.087 M). Statistical precision ±0.5 % per 1 h bin, ±1 % per 10 min bin. Run 175 stays flat at 2.00 ± 0.01 M from 24 h to 68 h (no day–night cycle). Run 176 ended at 4.7 h on an external HV interlock (from the gas system; no precursor in voltages or currents).

Practical consequences: **do not let a calibration span the few hours after a flow change**, and record the flow as part of the calibration conditions.

- By-product: in the length × charge plane the α lines of the ^{228}Th chain separate (^{220}Rn 6.29 MeV stops at 85 mm, ^{212}Bi at 45 mm, ^{224}Ra at 25 mm; ^{216}Po and ^{212}Po cross the active volume at 105 mm). Because the source sits 315 mm outside, the charge FWHM of the stopping lines is poor (19–31 %). This is the starting point for the metrics of the coming pressure scan.

4 Hit precision

4.1 Definition of hits and of the two residuals

So that this section can be followed without doing track reconstruction, "precision" is defined in three steps.

1. Hit (one strip = one point). The analysis macro `analyzeUVW.C` makes exactly one point from the waveform of each strip channel (after pedestal subtraction). It takes the samples above threshold (35 ADC) within ±5 cells of the maximum cell t_{peak} and computes the charge $q = \sum v_t$ and the time $\bar{t} = \sum v_t\, t/q$ (charge-weighted). Then $z = \bar{t} \times 40\,\text{ns} \times v_{\text{drift}}$ (1 cell = 0.19 mm), and the strip position s [mm] comes from the channel map. A hit is therefore (view, s, z, q): a two-dimensional point "strip position × drift direction" in each view. Strips with $q < 2000$ (weak induction that appears on all strips at the time of the track, the "halo") are dropped.

2. z residual (Sec. 4.2) — distance from the fitted line. `makeTracks.C` fits one three-dimensional straight line to the hits of the three views (the direction in xy from the spread of U/V/W, and z as a straight line in the path length l). Projecting the strip position of a hit onto the xy direction of the track gives its l, where the line predicts $z(l)$. **z residual** $r = z_{\text{hit}} - z(l)$ (Fig. 6, left). The width (robust σ) of the distribution of r over all hits tells how precisely the z of a single hit is determined. Because the line is fitted to the same hits, σ comes out slightly small (by about 1 % with ≈ 50 hits per view).

3. Closure residual (Sec. 4.3) — 2D precision without a track model. The U, V and W strips are inclined by 60° to each other, and the unit vectors along which the strip coordinates are measured (the pitch directions) are 120° apart, so the three unit vectors sum to zero. Therefore, for

any point in the xy plane the sum of the three strip coordinates $s_U + s_V + s_W$ is the same constant c (Fig. 6, right). Taking the charge centroids s_U, s_V, s_W of the three views in the same time slice (1 cell = a thin layer at the same z), they must point at the same location, so **the closure residual** $r = s_U + s_V + s_W - c$ contains only the centroid errors. If the three views have independent errors of the same size σ_s, then $\sigma_r = \sqrt{3}\,\sigma_s$; we call $\sigma_s = \sigma_r/\sqrt{3}$ the 2D precision "per view". No straight line is assumed, so curved tracks or failed reconstructions do not affect it.

Both distributions have heavy tails (multiple tracks, noise, saturated outliers), so widths are given as **robust** σ = 1.4826× **MAD** (median of the absolute deviations from the median; equal to σ for a Gaussian) rather than RMS.




Figure 6: The two residuals. Left: z residual = z of each hit minus the z predicted by the fitted line at the position of that hit. Right: closure residual = deviation of the sum of the three view centroids at the same time from the geometric constant c (no line used).

4.2 z residual (S11)

The robust σ of the hit z residuals with respect to the line (Fig. 7) is **0.19–0.22 mm ≈ 1 cell** at 232–502 ns (1 cell = 40 ns × 4.77 mm/µs = 0.19 mm). It is 0.25–0.31 mm at 1014 ns (+30–60 %) and 0.27 mm at 70 ns (insufficient S/N). It does not depend on the HV (GEMs 250 → 230 V, voltage sharing): 0.20–0.22. Together with S12, σ_z **is set by a distance, not by the timing** (candidate: strip width × track inclination ≈ 0.18 mm). The degradation at 1014 ns is the electronics timing precision added in quadrature ($\sqrt{0.31^2 - 0.21^2} \approx 0.23$ mm). The RMS is 2–5 times the robust σ (heavy tails), so fits must be robust. Whether the pulse width can serve as the z error of a hit was an idea by S. Aogaki tested here (it is not an established method); the answer is that it **overestimates the error by more than a factor of 10** (intrinsic width 14.5 cells = 2.8 mm, raw width 7–20 mm, measured 0.2 mm).

4.3 2D centroid precision = U/V/W closure residual (S14)

Definition in Sec. 4.1, item 3. Only hit channels (strips that pass the condition of item 1) are used, and only their samples within ±15 cells of their own peak time (to remove late tails and halo). Only z slices where all three views form a single cluster are counted. **The best value is 0.30 mm per view at 232 ≈ 502 ns**; 0.39–0.43 at 1014 ns (wide pulses spill out of the window) and 1.1 mm at 70 ns. No dependence on the GEM HV (0.30–0.32); slightly worse at 1,000 V drift (0.34). The precision depends strongly on the charge (from 0.7–0.8 mm in the lowest to 0.40–0.45 mm in the highest charge quartile): the 2D precision is set by S/N.

Summary: at operating point B (502 ns) the error of a hit (z slab) is $\sigma_s \approx 0.30$ **mm (2D, per view) and** $\sigma_z \approx 0.20$ **mm**.




Figure 7: S11: hit z residuals of run 87 (502 ns). Left: U/V/W, robust σ 0.21–0.22 mm. Right: correlation with the strip charge.




Figure 8: S14: closure residual of run 87. Left: distribution, robust σ 0.53 mm, i.e. $0.53/\sqrt{3} = 0.31$ mm per view. Right: correlation with the slice charge.

5 Readout mode, rate and zero suppression

5.1 Readout and hit register (S9, S15)

The partial readout used until then read all channels because the template had `channel Reading = always`; the hit-register threshold had no effect. Moreover partial readout uses frameType 1 (4 B/sample), giving **twice** the data of full readout (frameType 2, 2 B/sample, 279 kB/event): 557 kB/event. With a template using `Reading = only_if_hit` (S15) the threshold works (raising global / lsb goes from 400 to 241 kB), but because of the 4 B/sample it saves at most 14 % compared with full. **Routine running therefore uses full readout**, and compression is left to ZS.

5.2 Maximum rate (S17)

The limits were measured with periodic triggers (no signal) and with the AsAd pulser (−300 mV on all 256 channels = 100 % occupancy).

- **The limit is the zCoBo FW readout time**: 2.94 ms for 272 channels ($\approx$ 340 Hz with one AsAd), the same with full readout and with ZS. The event spacing is a constant "period + 2.94 ms", with no disturbance from network back-pressure.

- **Triggers during readout are lost** (not queued): with a 2 ms pulser period every second pulse is recorded. Dead time = rate × readout time (29 % at 100 Hz with full readout).
- **Readout time ≈ 0.11 ms + 10.4 µs× number of channels read**: with hit-partial readout and no signal (16 FPN channels) it is 0.28 ms (779 Hz). For an α event (≈ 136 channels) it is ≈ 1.5 ms, i.e. 15 % at 100 Hz. **Hit-register partial readout is the only way to reduce the dead time.**
- **ZS only reduces the bytes** (the readout time is unchanged): 65 kB even with all channels hit. Partial readout and ZS work together (frameType 1 + ZS).
- 1 GbE has headroom up to 340 Hz with full readout (86 MB/s with a 1 ms pulser, at the edge). With partial readout and all channels hit (557 kB) it stops at 170 Hz. Fibre or 10 GbE does not help the zCoBo link (the FW Ethernet core is 1 GbE; see Sec. 5.4).

Table 9: S17 maximum rate (runs 148–169).

series	signal	rate [Hz]	min. spacing [ms]	kB/event	limit
B full (272 ch)	none / pulser all ch	254 / 310	period + 2.94	279	FW readout
hit partial g4	none (16 FPN ch)	779	period + 0.28	33	FW readout ($\propto$ ch)
hit partial g4	pulser all ch (frameType 1)	170	3.0 + stall	557	**1 GbE**
ZS per channel	pulser all ch	333	3.0	65	FW readout
hit partial + ZS	pulser all ch	333	3.0	65	FW readout

5.3 Zero suppression (S5, S13, S18)

From a pedestal run (periodic trigger, full readout, 150 events) a per-channel table of mean and σ was made (S5: median pedestal of the signal channels 456.5 ADC, median σ 7.6–8.0, FPN σ 3.3), and threshold = pedestal $+5\sigma$ was put into the parameters as per-channel exceptions (`zs_params.sh`). ZS data contain no samples below threshold, so the usual algorithms that take the pedestal from the waveform (TPCReco's `PedestalCalculatorGRAW` as well as our macros) break. On the DAQ side the same table is given as `[system] ped_table` and used in three places: root_sink (table mode of PEventTPC), the monitor (restoring the event display) and the analysis macros (`zs_restore.C` fills the suppressed cells with the table values and writes a raw file of the same name, so the macros run unchanged).

The validation runs (S18, 1,500 events each, electronics of operating point B) are listed in Table 10. **ZS does not degrade the quality** (hit channels, ok, length, dEdx IQR, σ_z, σ_{2D} equal to the reference; the total charge is −3 % from the sub-threshold tails). Keeping the FPN channels improves no metric and costs +32 kB/event, so **the FPN channels are suppressed**. The only processing ZS can affect in principle is waveform processing that uses the sub-threshold tails (deconvolution as in Sec. 2.2, or unfolding); hit, track and charge metrics are not affected. Hit-partial g4 + ZS is the smallest (23.1 kB, 1/12) at the small price of −4 hit channels and +12 % in σ_{2D}. Since it is the only option that also reduces the dead time, **the default candidate for beam runs is hit g4 + ZS (FPN suppressed)**; source runs use B full (current) or B + ZS.

Table 10: S18 ZS validation (runs 170–173, reference = run 130).

run	setting	kB/event	hit ch	total charge	ok	length	σ_z	σ_{2D}
130	B full (reference)	278.8	121.5	2.09 M	0.998	84.4	0.21	0.314
170	**B + ZS**	**30.9** (1/9)	121	2.02 M	0.998	83.9	0.20	0.320
171	B + ZS, FPN kept	63.1	120	2.03 M	0.997	83.2	0.20	0.319
172	**hit g4 + ZS**	**23.1** (1/12)	117	2.03 M	0.996	82.9	0.19	0.357
173	hit g4 + ZS, FPN kept	55.7	116	1.99 M	0.997	82.0	0.19	0.354




Figure 9: Data size per α event (S9, S15, S18).

5.4 Design for beam runs (≈ 100 Hz)

The beam runs will not have a periodic trigger: **the particles arrive at random**, at an expected rate of ≈ 100 Hz (more would be welcome). With random arrival the readout time τ acts as a non-paralysable dead time, and the accepted rate is $m = n/(1 + n\tau)$ (Table 11). Even at 100 Hz, full readout loses a quarter of the events, so hit-partial readout is worth more than with a periodic beam. The accepted rate saturates at $1/\tau$ (340 Hz full, ≈ 680 Hz partial). With ZS the bandwidth, 23 kB $\times$ 300 Hz $\approx$ 7 MB/s, is no issue.

Table 11: Accepted rate for random arrival, $m = n/(1 + n\tau)$.

true rate n	full ($\tau = 2.94$ ms)	hit partial ($\tau \approx 1.5$ ms, 136 ch as for α)
100 Hz	77 Hz (−23 %)	87 Hz (−13 %)
200 Hz	127 Hz (−37 %)	154 Hz (−23 %)
300 Hz	160 Hz (−47 %)	207 Hz (−31 %)
saturation	340 Hz	≈ 680 Hz

The dead time must be measured. The zCoBo does not assign an eventIdx to triggers that arrive during readout (only accepted triggers are numbered consecutively), so the number of lost triggers cannot be recovered from the data and the yields cannot be corrected. The raw external trigger pulses should be counted per run with a scaler (counting the zCoBo SMA OUT1, the latch pulse, in the same scaler gives the accepted number for comparison); on the DAQ side, τ can be estimated per run from "0.11 ms + 10.4 µs× channels read" and logged.

About 10 GbE. Neither of the two zCoBo (ZC706) ports can run at 10 GbE. The RJ45 port uses the fixed MAC of the Zynq PS (at most 1 Gb/s; used at 100 Mbit for management by the FW). The SFP+ port is connected to a GTX transceiver that could run at 10 Gb/s in hardware, but the FW places a 1G AXI Ethernet core (1000BASE-X, line rate 1.25 Gb/s) in the PL and sends the data with the TCP stack of Linux on the ARM (checked in the boot log and README of the FW package). Optical modules (1000BASE-SX/LX) therefore work just like the copper adapter, but the speed stays at 1 GbE; a 10G-only module does not make it 10G (a module without 1G support will not link). Going to 10G would require a new FW (a licensed 10G IP plus a TCP/UDP engine in the PL), and the 2.94 ms readout time would limit first anyway. This 2.94 ms is about twice what the AGET specification implies (512 cells × 68 channels at a 25 MHz readout clock $\approx$ 1.4 ms per AGET), so there may be room in the readout part of the FW. **Question for the Warsaw group: which AGET readout clock does the zCoBo FW use?**

Estimate for ELITPC (Warsaw, two zCoBo × two AsAd): 544 channels per board → readout $\approx$ 5.8 ms → saturation at 170 Hz with full readout and −37 % at 100 Hz random. With partial readout (25 % occupancy, $\approx$ 150 channels) $\approx$ 1.7 ms, i.e. −15 %. The bandwidth is at the edge of 1 GbE (95 MB/s) with full readout and comfortable with partial + ZS. **Design for 100 Hz beam: hit-register**

partial readout + ZS + one 1 GbE link per board (merged into 10 GbE on the PC) + a trigger scaler. Whether the FW readout time really doubles with two AsAd has to be measured in Warsaw. Note: ZS graw files break the pedestal calculation of the offline grawToEventTPC. If ZS is used in Warsaw, we need to agree either to analyse our PEventTPC output (pedestal already subtracted with the table) or to add a pedestal-table input to TPCReco.

6 Open issues and next steps

- **Drift end (S6)**: even at 12.5 MHz with a 41 µswindow, the α tracks lie within 2–4 µsof the trigger (Fig. 10). The source is currently outside the chamber (attached to the gas line), and for solid-angle reasons the tracks barely extend in z, so tracks reaching the cathode side (20 cm) cannot be obtained in this configuration. The absolute $v_{\mathrm{drift}} = L/t_{\mathrm{max}}$ will be measured once the source is back inside the chamber. The bump near cell 340 does not move with the window position and is not physical (not understood).

- **Source of the gas impurities**: whether the flow-dependent term S (S19) comes from leaks or from outgassing is not yet separated. Humidity also matters (water permeation through tubing and O-rings scales with the room humidity; water absorbed in PCBs, Kapton and GEM foils is released; air entering through leaks carries water). **The dew point of the chamber gas is already measured, and it is the direct indicator**: the water partial pressure is fixed by the dew point, and around −40 °C a rise of 5–6 K means twice the water. If the doubling of S/Q from 100 to 50 ml/min is due to water, the dew point must have risen by a few K at that time; if it did not move, the cause is something else (e.g. O_2 from a leak). To be checked by putting the dew-point record at the flow changes (16 Oct 12:08, 19 Oct 10:38) next to the charge trend (Fig. 5). Converting to ppm needs the total pressure at the sensor, and if water from the bottle dominates the change will be small. An environment sensor (room temperature, humidity, pressure) and, once the source is inside, charge versus drift time will also help.

- **Wiggle**: the 1.6–1.8 µscomponent on α waveforms (signal channels only, proportional to the charge) is absent from the AGET response kernel; it may originate on the detector side (GEM / induction).

- **Multiple tracks**: the present reconstruction fits one straight line per event. This is also behind the larger residual RMS at 502 ns than at 1014 ns (different outlier behaviour).

- **Per-run ZS counters**: the ZS counters of root_sink and the monitor are to be written into the run-stop record; the PEventTPC charge sum has not been cross-checked yet.




Figure 10: S6: first / last hit cell of run 111 (12.5 MHz, delay 3800). The last hits cluster at 50–100 cells (2–4 µsafter the trigger); the spike at cell 508 is a window-edge artefact.

A Tools and records

- Repository: https://github.com/aogaki/tpcdaq-rs. The DAQ source (Rust + C++), the specification, the operating procedures, the scan ledger and the tickets (design history and results) are all there. The developer documents are in Japanese. **English LLM translations of the documents listed below are in `docs/en/`** (index: `docs/en/README.md`); the Japanese originals are authoritative. For any other document, ask S. Aogaki and an LLM translation will be prepared.
- Scan ledger: `docs/SCANS_ja.md` (S1–S19, the reference for all numbers; English: `docs/en/SCANS_en.md`). History and decisions: `TODO/archive/135--161` (English: `docs/en/tickets/`).
- Tools: `tools/scan/` (`scan.py`, `run_metrics.C`, `metrics_for_run.sh`, `pulser_kernel.C`, `deconv.C`, `drift_end.C`, `hit_residuals.C`, `uvw_closure.C`, `gas_trend.C`, `zs_exceptions.py`, `zs_params.sh`, `zs_restore.C`, `ledger.py`); every macro has tests.
- Specification: `docs/SPEC_ja.md` v1.49 (ZS table mode, display restoration, ped_table, decoder counters; English: `docs/en/SPEC_en.md`). Operation: `docs/RUNBOOK_ja.md`, section on ZS operation (English: `docs/en/RUNBOOK_en.md`).

B Parameters of operating point B

`base_1750.json`. Knobs: `writingClockFrequency_MHz` 25, `triggerDelay` 1750, `triggerMode` external, `peakingTime_ns` 502, `gain` 120 fC, `readout` full, `fpnRead` true, `zeroSuppression.enabled` false. Beam candidate: template `configure-elinp-hit.xcfg` (`channel Reading only_if_hit`), global 4 / lsb 15, ZS on with exceptions from `pedestal_502ns.json` (FPN threshold 4095).