Simple Z80, redrawn from the z80.info test schematic. Symbols are stock KiCad 10.0.7.
U3 is a 27C256, not the drawing's 27C512. Pin 1 is VPP, tied to +5V. A15 only feeds the decoder.
U1 is the Z84C00 symbol (CMOS Z80). U2 is HM62256, value 62256.
No 74HCT14 or 74HCT32 in this library. U7 is a 74HC14 symbol, U8 is a 74LS32 symbol, values set to the HCT parts.
PIO answers any I/O cycle with A7 low (use 00–03). UART answers any with A7 high (use 80–87).
8255 RESET and 16550 MR are active high, after one inverter. Z80 /RESET is after the second.

U7D 74HCT14: A15 (9) → A15 (8)

U8D 74HCT32: MREQ (12), A15 (13) → RAMCS (11)

U8C 74HCT32: MREQ (9), A15 (10) → ROMCS (8)

U7C 74HCT14: A7 (5) → A7 (6)

U8A 74HCT32: IORQ (1), A7 (2) → PIOCS (3)

U8B 74HCT32: IORQ (4), A7 (5) → UARTCS (6)

C2–C11: 100nF, one per IC, drawn here rather than beside each chip.

C2 C3 C4 C5 C6 C7 C8 C9 C10 C11 100nF

U1 Z84C00
CLK (6) → CLK
M1 (27)
MREQ (19), IORQ (20), RD (21), WR (22)
RFSH (28)
BUSREQ (25), BUSACK (23)
INT (16), NMI (17)
HALT (18), WAIT (24)
RESET (26) ← RESET
A0–A15 (30–5)
D0–D7 (14–13)
Vcc (11), GND (29)

U2 62256
A0–A14 (10–1)
D0–D7 (11–19)
CS (20) ← RAMCS
OE (22) ← RD
WE (27) ← WR
Vcc (28), GND (14)

U3 27C256
A0–A14 (10–27)
D0–D7 (11–19)
VPP (1) ← +5V
CE (20) ← ROMCS
OE (22) ← RD
Vcc (28), GND (14)

U5 16C550
D0–D7 (1–8)
A0 (28), A1 (27), A2 (26)
CS0 (12) ← +5V
CS1 (13) ← +5V
CS2 (14) ← UARTCS
XIN (16) ← CLK_UART
XOUT (17)
WR (18, 19) ← WR
RD (22, 21) ← RD
ADS (25) ← GND
INTR (30)
MR (35) ← RESET_H
RI (39), DCD (38), DSR (37) → DSR_TTL
CTS (36)
OUT1 (34) → DTR_TTL
DTR (33)
RTS (32)
OUT2 (31)
SIN (10) → RX_TTL
SOUT (11) → TX_TTL
RXRDY (29), TXRDY (24), DDIS (23)
BAUDOUT (15) → BAUDOUT
RCLK (9) → BAUDOUT
Vcc (40), GND (20)

C22 1uF

C20 C1P 10F

C21 C2P 10F

U6 MAX232
C1+ (1) ← C1P
C1− (3) ← C1M
C2+ (4) ← C2P
C2− (5) ← C2M
V+ (2) → VS_PLUS
V− (6) → VS_MINUS
T1IN (11) ← TX_TTL
T2IN (10) ← DTR_TTL
R1OUT (12) → RX_TTL
R2OUT (9) → DSR_TTL
T1OUT (14) → TX_RS232
T2OUT (7) → DTR_RS232
R1IN (13) ← RX_RS232
R2IN (8) ← DSR_RS232
Vcc (16), GND (15)

C23 VS_PLUS 1uF
C24 VS_MINUS 10F

J1 DE9
DSR_RS232, RX_RS232, TX_RS232, DTR_RS232

U7G 74HCT14
U8E 74HCT32
Vcc (14), GND (7)

Y1 4MHz
EN (1), Vcc (14), GND (7), OUT (8) → CLK

Y2 1.8432MHz
EN (1), Vcc (8), GND (4), OUT (5) → CLK_UART

U4 82C55A
RESET (35) ← RESET_H
CS (6) ← PIOCS
RD (5) ← RD
WR (36) ← WR
A0 (9), A1 (8)
D0–D7 (34–27)
PA0–PA7 (4–37)
PB0–PB7 (18–25)
PC0–PC7 (14–10)
Vcc (26), GND (7)

U7A 74HCT14: RESET_RC (1) → RESET_H (2)

U7B 74HCT14: RESET_H (3) → RESET (4)

U7E 74HCT14: (11) → (10)

U7F 74HCT14: (13) → (12)

R1 10K: RESET_RC
C1 10uF: RESET_RC
R2 10: RESET_RC → SW_RESET
SW1 RESET: SW_RESET

J2 PA: PA0–PA7
J3 PB: PB0–PB7
J4 PC: PC0–PC7