COMP 3331/9331: Computer Networks and Applications

1. BER, SNR, Data Rate
2. Hidden/Exposed Terminals
3. Channel association
4. CSMA/CA: RTS-CTS
5. Addressing

Week 10
Wireless Networks

Reading Guide: Chapter 7, Sections 7.1 – 7.3

Wireless and Mobile Networks: context

- *more wireless (mobile) phone subscribers than fixed (wired) phone subscribers (10-to-1 in 2019)!*

- *more mobile-broadband-connected devices than fixed-broadband-connected devices devices (5-1 in 2019)!*
  - *4G/5G cellular networks now embracing Internet protocol stack, including SDN*

- *two important (but different) challenges*
  - *wireless: communication over wireless link*
  - *mobility: handling the mobile user who changes point of attachment to network*

We will only focus on wireless challenges

Outline

Wireless 101

- **Frequency/Wave-Length –**

C is the speed of light

f is frequency

λ (lambda) is wavelength

Wavelength

$$\lambda = \frac{C}{f}$$

Frequency

$$f = \frac{C}{\lambda}$$

Wave

Wavelength

Wavelength

Distance ⟶

Elements of a wireless network

wired network infrastructure

Elements of a wireless network

wired network infrastructure

wireless hosts
- laptop, smartphone, IoT
- run applications
- may be stationary (non-mobile) or mobile
  - wireless does not always mean mobility!

Elements of a wireless network

wired network
infrastructure

base station

- typically connected to wired network
- relay - responsible for sending packets between wired network and wireless host(s) in its "area"
  - e.g., cell towers, 802.11 access points

Elements of a wireless network

wireless link
- typically used to connect mobile(s) to base station, also used as backbone link
- multiple access protocol coordinates link access
- various transmission rates and distances, frequency bands

wired network infrastructure

Characteristics of selected wireless links

Chart axes:

Data rates (vertical axis): 14 Gbps, 10 Gbps, 3.5 Gbps, 600 Mbps, 54 Mbps, 11 Mbps, 2 Mbps

- 802.11ax — 14 Gbps
- 5G — 10 Gbps
- 802.11ac — 3.5 Gbps
- 802.11n — 600 Mbps
- 802.11 af,ah
- 4G LTE
- 802.11g — 54 Mbps
- 802.11b — 11 Mbps
- Bluetooth — 2 Mbps

Range (horizontal axis):

Indoor	Outdoor	Midrange outdoor	Long range outdoor
10-30m	50-200m	200m-4Km	4Km-15Km

Inside the radio wave spectrum

Almost every wireless technology – from cell phones to garage door openers – uses radio waves to communicate. Some services, such as TV and radio broadcasts, have exclusive use of their frequency within a geographic area. But many devices share frequencies, which can cause interference. Examples of radio waves used by everyday devices

Most of the white areas on this chart are reserved for military, federal government and industry use

Auctioned spectrum

Broadcast TV Channels 2-13

Garage door openers

Cell phones

Wireless medical telemetry

Cell phones

2.4 GHz band
Used by more than 300 consumer devices, including microwave ovens, cordless phones and wireless networks (Wi-Fi and Bluetooth)

Wi-Fi networks

Satellite TV

Security alarms

| 3 kHz | 500 MHz | 1 GHz | 1.5 GHz | 2 GHz | 3 GHz | 4 GHz | 5 GHz | 50 GHz | 300 GHz |

AM radio 535 kHz to 1,700 kHz

Remote-controlled toys

Broadcast TV UHF channels 14-83

GPS (Global positioning systems)

Satellite radio

Weather radar

Cable TV satellite transmissions

Highway toll tags

Police radar

Signals in this zone can only be sent short, unobstructed distances

PERMEABLE ZONE
Frequencies in this range are considered more valuable because they can penetrate dense objects, such as a building made out of concrete

SEMI-PERMEABLE ZONE
Difficult for signals to penetrate dense objects

LINE-OF-SIGHT ZONES

Signals in this zone can travel long distances, but could be blocked by trees and other objects

Visible

Microwaves   Infrared   light   Ultraviolet   X-rays   Gamma rays

Lowest frequencies

Highest frequencies

RADIO WAVE SPECTRUM

3 kHz wavelength

300 GHz wavelength

The electromagnetic spectrum
Radio waves occupy part of the electromagnetic spectrum, a range of electric and magnetic waves of different lengths that travel at the speed of light; other parts of the spectrum include visible light and x-rays; the shortest wavelengths have the highest frequency, measured in hertz

Lower frequency

Higher frequency

Wavelength
Distance from crest to crest

What is a hertz?
One hertz is one cycle per second. For radio waves, a cycle is the distance from wave crest to crest

1 kilohertz (kHz) = 1,000 hertz
1 megahertz (MHz) = 1 million hertz
1 gigahertz (GHz) = 1 billion hertz

Source: New America Foundation, MCT, Howstuffworks.com
Graphic: Nathaniel Levine, Sacramento Bee

© 2008 MCT

Elements of a wireless network

infrastructure mode

- base station connects mobiles into wired network
- handoff: mobile changes base station providing connection into wired network

wired network infrastructure

# Elements of a wireless network

ad hoc mode

- *no base stations*
- *nodes can only transmit to other nodes within link coverage*
- *nodes organize themselves into a network: route among themselves*

Wireless network taxonomy

	single hop	multiple hops
infrastructure (e.g., APs)	host connects to base station (WiFi, cellular) which connects to larger Internet	host may have to relay through several wireless nodes to connect to larger Internet: mesh net
no infrastructure	no base station, no connection to larger Internet (Bluetooth, ad hoc nets)	no base station, no connection to larger Internet. May have to relay to reach a given wireless node; MANET, VANET

Outline

7.1 Introduction

14

Wireless link characteristics (1)

important *differences from wired link ….*

- *decreased signal strength:* *radio signal attenuates as it propagates through matter (path loss)*

- *interference from other sources:* *wireless network frequencies (e.g., 2.4 GHz) shared by many devices (e.g., WiFi, cellular, motors): interference*

- *multipath propagation:* *radio signal reflects off objects ground, arriving at destination at slightly different times*

…. make communication across (even a point to point) wireless link much more "difficult"

Multipath Effects

- ❖ Signals bounce off surface and interfere (constructive or destructive) with one another
- ❖ Self-interference

Ideal Radios

(courtesy of Gilman Tolle and Jonathan Hui, ArchRock)

Real Radios

(courtesy of Gilman Tolle and Jonathan Hui, ArchRock)

Wireless link characteristics (2)

- **SNR: signal-to-noise ratio**
  - *larger SNR – easier to extract signal from noise (a "good thing")*
- **SNR versus BER tradeoffs**
  - *given physical layer: increase power -> increase SNR->decrease BER*
  - *given SNR: choose physical layer that meets BER requirement, giving highest throughput*
    - *SNR may change with mobility: dynamically adapt physical layer (modulation technique, transmission rate)*

BER: Bit Error Rate

.... QAM256 (8 Mbps)

– – – QAM16 (4 Mbps)

——— BPSK (1 Mbps)

802.11: advanced capabilities

Rate adaptation

- *base station, mobile dynamically change transmission rate (physical layer modulation technique) as mobile moves, SNR varies*

  1. SNR decreases, BER increase as node moves away from base station

 *2. When BER becomes too high, switch to lower transmission rate but with lower BER*

QAM256 (8 Mbps)
QAM16 (4 Mbps)
BPSK (1 Mbps)
operating point

Wireless link characteristics (3)

Multiple wireless senders, receivers create additional problems (beyond multiple access):

Hidden terminal problem
- B, A hear each other
- B, C hear each other
- A, C can not hear each other means A, C unaware of their interference at B

Signal attenuation:
- B, A hear each other
- B, C hear each other
- A, C can not hear each other interfering at B

Wireless network characteristics

❖ Exposed Terminals

❖ Node B sends a packet to A; C hears this and decides not to send a packet to D (despite the fact that this will not cause interference) !!

❖ Carrier sense would prevent a successful transmission

Outline

7.1 Introduction

Wireless

7.2 Wireless links, characteristics

7.3 IEEE 802.11 wireless LANs ("Wi-Fi")

IEEE 802.11 Wireless LAN

IEEE 802.11 standard	Year	Max data rate	Range	Frequency
802.11b	1999	11 Mbps	30 m	2.4 Ghz
802.11g	2003	54 Mbps	30m	2.4 Ghz
802.11n (WiFi 4)	2009	600	70m	2.4, 5 Ghz
802.11ac (WiFi 5)	2013	3.47Gpbs	70m	5 Ghz
802.11ax (WiFi 6)	2021	14 Gbps	70m	2.4, 5 Ghz
802.11af	2014	35 – 560 Mbps	1 Km	unused TV bands (54-790 MHz)
802.11ah (WiFi Halow)	2017	347Mbps	1 Km	900 Mhz

- *all use CSMA/CA for multiple access, and have base-station and ad-hoc network versions*

# 802.11 LAN architecture

Internet

switch or router

BSS 1

BSS 2

- wireless host communicates with base station
  - base station = access point (AP)
- Basic Service Set (BSS) (aka "cell") in infrastructure mode contains:
  - wireless hosts
  - access point (AP): base station
  - ad hoc mode: hosts only

802.11: Channels, association

- *spectrum divided into channels at different frequencies*
  - *AP admin chooses frequency for AP*
  - *interference possible: channel can be same as that chosen by neighboring AP!*

- *arriving host: must associate with an AP*
  - *scans channels, listening for beacon frames containing AP's name (SSID) and MAC address*
  - *selects AP to associate with*
  - *then may perform authentication [Security]*
 - *then typically run DHCP to get IP address in AP's subnet*

BSS

802.11: passive/active scanning

passive scanning:
(1) beacon frames sent from APs
(2) association Request frame sent: H1 to selected AP
(3) association Response frame sent from selected AP to H1

active scanning:
(1) Probe Request frame broadcast from H1
(2) Probe Response frames sent from APs
(3) Association Request frame sent: H1 to selected AP
(4) Association Response frame sent from selected AP to H1

IEEE 802.11: multiple access

- *avoid collisions: 2^+ nodes transmitting at same time*
- *802.11: CSMA - sense before transmitting*
  - *don't collide with detected ongoing transmission by another node*
- *802.11: no collision detection!*
  - *difficult to sense collisions: high transmitting signal, weak received signal due to fading*
  - *can't sense all collisions in any case: hidden terminal, fading*
  - *goal: avoid collisions: CSMA/CollisionAvoidance*

A's signal strength

C's signal strength

space

Multiple access: Key Points

❖ No concept of a global collision
- Different receivers hear different signals
- Different senders reach different receivers

❖ Collisions are at receiver, not sender
- Only care if receiver can hear the sender clearly
- It does not matter if sender can hear someone else
- As long as that signal does not interfere with receiver

❖ Goal of protocol
- Detect if receiver can hear sender
- Tell senders who might interfere with receiver to shut up

IEEE 802.11 MAC Protocol: CSMA/CA

802.11 sender

1 if sense channel idle for **DIFS** then
   transmit entire frame (no CD)

2 if sense channel busy then
   start random backoff time
   timer counts down while channel idle
   transmit when timer expires
   if no ACK, double random backoff interval, repeat 2

802.11 receiver

 if frame received OK
 return ACK after **SIFS** (ACK needed due to hidden
   terminal problem)

sender   *receiver*

DIFS

data

SIFS

ACK

Avoiding collisions (more)

idea: sender "reserves" channel use for data frames using small reservation packets

- sender first transmits small request-to-send (RTS) packet to BS using CSMA
  - RTSs may still collide with each other (but they're short)
- BS broadcasts clear-to-send CTS in response to RTS
- CTS heard by all nodes
 - sender transmits data frame
  - other stations defer transmissions

Collision Avoidance: RTS-CTS exchange

Collision Avoidance: RTS-CTS exchange

802.11 frame: addressing

2	2	6	6	6	2	6	0 - 2312	4
frame control	duration	address 1	address 2	address 3	seq control	address 4	payload	CRC

Address 1: MAC address of wireless host or AP to receive this frame

Address 2: MAC address of wireless host or AP transmitting this frame

Address 3: MAC address of router interface to which AP is attached

Address 4: used only in ad hoc mode

Quiz

The following is the correct sequence of message exchanges as per the reservation process of 802.11 CSMA/CA

A. RTS->CTS->DATA->CTS

B. CTS->RTS->DATA->ACK

C. RTS->CTS->DATA->ACK

D. RTS->ACK->DATA->CTS

Quiz

❖ Which multiple access technique is used by IEEE 802.11?

    A. CSMA/CD

    B. Slotted ALOHA

    C. CSMA/CA

    D. TDMA

    E. FDMA

Summary

Wireless

❖ wireless links:
- capacity, distance
- channel impairments

❖ IEEE 802.11 ("Wi-Fi")
- CSMA/CA reflects wireless channel characteristics