EE200 Course Project

By :- Arjun Kori (250190) and Dheeraj Yadav(250344)

Q2 – The Midnight Episode: Catching the Arrhythmia

Introduction

Electrocardiography (ECG) is one of the most widely used diagnostic techniques for monitoring the electrical activity of the heart. Each heartbeat produces a characteristic waveform consisting of a P-wave, QRS complex and T-wave. In a healthy individual, these waveforms occur at regular intervals and therefore the ECG exhibits an approximately periodic structure. Any significant deviation from this regularity may indicate the presence of an arrhythmia, a condition in which the normal rhythm of the heart is disturbed.

In this project, the objective is to automatically detect the onset of arrhythmia from a recorded ECG signal. Instead of manually inspecting the entire signal, a template matching approach based on normalized correlation is employed. A healthy heartbeat template is extracted and compared against successive beats in the ECG recording. Whenever the similarity between the template and the current beat drops significantly, the detector identifies a possible arrhythmic event. In addition to time-domain analysis, frequency-domain analysis and spectrogram visualization are also used to study the behavior of the signal.

The ECG recording consists of 5000 samples recorded at a sampling frequency of 250 Hz. A healthy heartbeat repeats approximately every 0.8 seconds.

Part (a) Reading the Signal

(i) Duration of the ECG Recording

The duration of a discrete-time signal can be calculated using the relationship: $= N\,T\,/f_s$
where: N = total number of samples , f_s = sampling frequency Given:

$$N = 5000,\ f_s = 250Hz$$

Therefore, T = 5000/250 => $T = 20s$

Hence, the ECG recording is 20 seconds long.

Interpretation

This means that the entire cardiac activity captured by the Holter monitor spans a time interval of twenty seconds. Any arrhythmic event must therefore occur somewhere within this observation window.

(ii) Heart Rate and Samples per Beat

The heartbeat period is given as:

$$T_{beat} = 0.8s$$

Heart rate in beats per minute (BPM) is:

$$HR = 60/T_{beat}$$ Substituting

the values: $HR = 60/80 \Rightarrow HR = 75\ BPM$

Thus, the patient's heart rate during the healthy region is 75 beats per minute.

The number of samples occupied by one heartbeat is: $L = T_{beat} \times f_s \Rightarrow L = 0.8 \times 250 \Rightarrow L = 200 samples$
Therefore, each healthy heartbeat occupies approximately 200 samples.

Interpretation

The value of 200 samples is extremely important because it determines the size of the heartbeat template used later in the correlation detector.

(iii) Fundamental Frequency

Since the ECG is approximately periodic in the healthy region, its fundamental frequency is:

T_{beat} Substituting: $= 1/ f_0$

- $f_0 = 1.25Hz$

Therefore, the healthy ECG repeats at a fundamental frequency of approximately 1.25 Hz.

Interpretation

A periodic signal generates harmonics at integer multiples of its fundamental frequency. Therefore the healthy ECG spectrum is expected to contain harmonics located around: $1.25Hz, 2.5Hz, 3.75Hz, 5Hz, ...$

These harmonics provide useful information regarding the regularity of the heartbeat.

Part (b) Healthy Heart in Frequency Domain

(i) Nature of the Spectrum

A healthy ECG behaves approximately like a periodic signal. The Fourier Transform of a periodic signal does not produce a smooth continuous spectrum. Instead, it consists of discrete frequency components called harmonics. Therefore, the magnitude spectrum of the healthy ECG is expected to contain a series of discrete peaks occurring at integer multiples of the fundamental frequency. These harmonic peaks represent the repetitive nature of the heartbeat.

Interpretation

The presence of clearly defined harmonics indicates that the heart rhythm is regular. If the ECG becomes arrhythmic, the regularity of these harmonics decreases and additional frequency components may appear.

(ii) Frequency Contribution of ECG Components

An ECG waveform consists of three primary components:

P-Wave

The P-wave corresponds to atrial depolarization.

Characteristics: Smooth , Slowly varying ,Broad waveform

Therefore it mainly contributes low-frequency content.

T-Wave

The T-wave corresponds to ventricular repolarization.

Characteristics: Smooth ,Broad ,Slowly varying

Hence it also contributes primarily low-frequency components.

QRS Complex

The QRS complex corresponds to ventricular depolarization.

Characteristics: Sharp ,Narrow , Rapid transition

Rapid changes require high-frequency components for accurate representation.

Therefore the QRS complex contributes most of the high-frequency content of the ECG signal.

Interpretation

The high-frequency behavior of the ECG is largely governed by the QRS complex. If high-frequency components are distorted or removed, the QRS morphology changes significantly, making arrhythmia detection more difficult.

(iii) Effect of Increased Heart Rate

Suppose the heart rate increases to:

$$150 BPM$$

Converting to beats per second: $f_0 = 150/60 \; > f_0 = 2.5 Hz$

Therefore, the new fundamental frequency becomes 2.5 Hz.

As a result: Harmonic spacing doubles. ,Frequency components move farther apart , spectrum becomes more widely spread.

Interpretation

A faster heart rate shifts the harmonic structure toward higher frequencies while maintaining the same overall waveform shape.

Part (c) Cutting a Heartbeat (Windowing)

Introduction

Before Maya can compare the ECG recording against a healthy heartbeat, she must first obtain a clean template representing one complete normal cardiac cycle. This process is performed using a windowing operation.

A window is a mathematical function used to isolate a specific portion of a signal while suppressing all remaining samples. By applying an appropriate window to the healthy region of the ECG recording, one complete heartbeat can be extracted and used as the reference template for subsequent correlation analysis.

(i) Window Width and Placement

The heartbeat period is given as: $T_{beat} = 0.8s$

The sampling frequency is: $f_s = 250Hz$

Therefore, the number of samples occupied by one heartbeat is:

$$L = T_{beat} \times f_s \; > L = 0.8 \times 250 \; > L = 200 samples$$

Thus, a window width of 200 samples is required to capture exactly one complete heartbeat.

The healthy portion of the ECG occurs at the beginning of the recording. Therefore, the template should be extracted from the initial healthy segment where the heartbeat pattern is regular and free from arrhythmia.

Interpretation

Selecting a heartbeat from the healthy region ensures that the template accurately represents normal cardiac activity. Any later deviation from this template can then be attributed to abnormal behavior rather than template errors.

Mathematical Representation of the Window

A rectangular window can be represented as: $w[n] = \{1, \; n_1 \le n \le n_2 \, 0$, otherwise

where: n_1 is the start of the selected heartbeat , n_2 is the end of the selected heartbeat The extracted template is:

$t[n] = x[n]w[n]$ where: $x[n]$ is the ECG signal , $t[n]$ is the heartbeat template

(ii) Effect of Using an 80-Sample Window

Suppose Maya uses a window length of only 80 samples .Since one complete heartbeat occupies 200 samples, an 80-sample window captures only a portion of the cardiac cycle.

Possible consequences include: Missing P-wave , Missing T-wave ,Truncated QRS complex , Distorted waveform shape
As a result, the extracted template does not accurately represent a complete heartbeat.

Interpretation

A correlation detector built using an inc

omplete heartbeat template will produce unreliable similarity scores. Healthy beats may appear abnormal simply because the template itself is incomplete.

Effect of Using a 600-Sample Window

Suppose Maya uses a window length of 600 samples.

Since each heartbeat occupies approximately 200 samples, the window contains:

$$600/200 = 3 \text{ heartbeats.}$$

Consequently, the extracted signal contains multiple cardiac cycles instead of a single heartbeat.

This introduces several problems: Repeated waveform structures ,Increased computational complexity , Reduced specificity ,Ambiguous matching behavior

Interpretation

The purpose of the template is to represent one heartbeat. Including multiple beats makes it difficult to determine whether a mismatch arises from the current beat or from neighboring beats contained in the template.

(iii) Time-Frequency Tradeoff

Windowing introduces an important tradeoff between time resolution and frequency resolution.

Short Window

Advantages: Excellent time localization , Precise identification of signal changes

Disadvantages: Poor frequency resolution , Spectral leakage , Loss of waveform information **Long Window**

Advantages: Better frequency resolution , More spectral detail

Disadvantages: Poor time localization , Blurred temporal information

Why Not Use the Smallest Window Possible?

At first glance it may seem beneficial to use a very small window because it provides excellent time localization.

However, if the window becomes too short: Important waveform features disappear. The template no longer represents a complete heartbeat. Correlation performance deteriorates.

Therefore the shortest window is not automatically the best choice.

Final Choice

The optimum window length is: $L = 200 samples$

because it captures exactly one complete heartbeat while preserving the essential waveform structure.

Observation

A 200-sample window provides the best compromise between temporal localization and waveform completeness. It captures all major ECG components (P-wave, QRS complex and T-wave) while avoiding contamination from neighboring heartbeats. Therefore, the extracted 200-sample segment is selected as the healthy heartbeat template used throughout the remainder of the project.

Part (d) Match the Template (Correlation)

Introduction

Once a healthy heartbeat template has been extracted, Maya must compare it against every heartbeat present in the ECG recording. A suitable measure of similarity is normalized correlation. Correlation quantifies how closely two signals resemble one another. A large positive correlation indicates similar shapes, whereas a negative correlation indicates opposite behavior.

Normalized Correlation Formula

The normalized correlation coefficient is defined as:

$$\rho(m) = \frac{\sum_{k=0}^{L-1} t[k]x[m+k]}{\|t\|\|x_m\|}$$

where: $t[k]$ is the template , $x[m+k]$ is the ECG segment , L is the template length , m is the starting position of the segment The denominator contains:

$$\|t\| = \sqrt{\sum t^2[k]}$$

and

$$\|x_m\| = \sqrt{\sum x^2[m+k]}$$

which represent the energies of the template and ECG segment respectively.

(i) Range of Correlation Values

According to the Cauchy-Schwarz inequality:

$$\left|\sum t[k]x[k]\right| \le \|t\|\|x\|$$

Dividing both sides by:

$$\|t\|\|x\|$$

gives:

$$-1 \le \rho \le 1$$

Therefore the correlation coefficient always lies between -1 and +1.

Interpretation of Values

$\rho \approx 1$ indicates a near-perfect match.

$\rho \approx 0$ indicates little similarity.

$\rho \approx -1$ indicates an inverted match. Thus, healthy beats are expected to produce correlation values close to +1.

(ii) Importance of Normalization

Real ECG recordings often experience: Baseline wander , Electrode movement , Amplitude variation , Gain changes

Without normalization, a simple dot product would be: $S = \sum t[k]x[k]$

Suppose a perfectly healthy beat becomes twice as tall:

$x[k] = 2t[k]$ Then: $S = \sum t[k](2t[k])$ => $S = 2\sum t^2[k]$

The score doubles despite the waveform shape remaining unchanged.

This would incorrectly suggest that the second beat is more similar than the first.

Why Normalized Correlation Solves This Problem

Normalized correlation divides by the energies of both signals.

For:

$$x[k] = 2t[k]$$

the numerator doubles, but the denominator also doubles.

Consequently: $\rho = 1$ The similarity score remains unchanged.

Interpretation

Normalization ensures that the detector responds to waveform shape rather than signal amplitude. This is essential for ECG analysis because amplitude fluctuations frequently occur even during normal cardiac activity.

(iii) Inverted Beat Detection

Consider an abnormal beat that is inverted: $x[k] = -t[k]$

Substituting into the correlation formula:

$$\rho = \frac{\sum t[k](-t[k])}{\|t\|\|t\|}$$

$$\rho = -\frac{\sum t^2[k]}{\sum t^2[k]}$$

$$\rho = -1$$

Thus an inverted beat produces a correlation coefficient close to -1.

Interpretation

Inverted beats are extremely easy to detect because their correlation values move toward the lower limit of the allowable range. This makes correlation-based detectors particularly effective at identifying polarity reversals and severe waveform abnormalities.

Observation

The correlation coefficient provides a robust measure of heartbeat similarity. Healthy beats produce values close to +1, whereas abnormal beats produce substantially smaller values. Because the measure is normalized, it remains unaffected by amplitude changes and focuses exclusively on waveform shape. This property makes normalized correlation an excellent choice for automated arrhythmia detection.

Part (e) Onset Detection and Spectrogram Analysis

Introduction

After constructing a healthy heartbeat template and developing a correlation-based similarity measure, the next objective is to determine the exact moment at which the ECG recording begins to deviate from normal behavior . The fundamental idea is straightforward. As long as the ECG remains healthy, each heartbeat should closely resemble the template and therefore produce a correlation value close to 1. Once arrhythmia begins, the waveform shape changes and the correlation decreases significantly. By monitoring the correlation score over time, the onset of arrhythmia can be automatically detected.

(i) Arrhythmia Onset Detection

Correlation-Based Detection Rule

A simple detection rule is defined as follows: If $\rho(m) < T$ declare the corresponding beat abnormal. where: $\rho(m)$ = correlation score , T = threshold. In this project: $T = 0.5$ was selected. Thus, the first beat whose correlation falls below 0.5 is declared the onset of arrhythmia.

Threshold Selection

The choice of threshold directly affects detector performance.

Threshold Too High

Suppose: $T = 0.9$ Even small variations in healthy beats may cause:

$$\rho < 0.9$$

This results in: False alarms , Excessive sensitivity , Incorrect arrhythmia detection

Threshold Too Low

Suppose: $T = 0.1$

Many abnormal beats may still produce: $\rho > 0.1$

This causes: Missed detections , Delayed response , Reduced sensitivity

Balanced Threshold

- The value: $T = 0.5$
- provides a compromise between sensitivity and robustness. It allows normal variability while still identifying significant waveform distortions.

- **Actual Detector Result**

- Using the provided ECG dataset and healthy heartbeat template, the detector was executed beat-by-beat.
- The first correlation value below the threshold occurred at: $m = 2400$ samples.
- Converting to time: $t = 2400/250 \Rightarrow t = 9.6s$

Final Result

Arrhythmia onset was detected at: 9.6 *seconds*

after the start of the recording.

Interpretation

The ECG remains highly similar to the healthy template during the first 9.6 seconds. After this point, the heartbeat morphology changes sufficiently to reduce the correlation score below the chosen threshold.

Therefore: Arrhythmia begins at 9.6*s*

Spectrogram Analysis

Introduction

Although correlation provides a quantitative measure of similarity, it does not reveal how the frequency content evolves with time. To obtain a second independent view of the ECG signal, a spectrogram is used. A spectrogram is generated by:

1. Sliding a window across the signal.
2. Computing the Fourier Transform of each window.
3. Stacking the resulting spectra over time.

This process is known as the Short-Time Fourier Transform (STFT).

Mathematical Representation

The STFT of a signal is:

$$X(m,\omega) = \sum_{n=-\infty}^{\infty} x[n]w[n-m]e^{-}_{j\omega n}$$

where: $x[n]$ is the ECG signal , $w[n]$ is the window , m controls time position The spectrogram is:

$S(m,\omega) = |X(m,\omega)|^2$ which represents signal power as a function of both time and frequency.

Healthy Region

In the healthy region, the ECG behaves approximately as a periodic signal.

Therefore the spectrogram is expected to exhibit: Stable horizontal bands , Consistent harmonic structure , Nearly constant frequency content .These horizontal bands correspond to the fundamental frequency and its harmonics.

Interpretation :- A stable spectrogram indicates that successive heartbeats are highly similar and occur at regular intervals.

Arrhythmia Region

During arrhythmia: Beat intervals become irregular, Waveform morphology changes , Frequency content varies over time.

Consequently the spectrogram exhibits: Distorted harmonic bands , Energy redistribution , Irregular frequency patterns

Interpretation

The loss of stable horizontal structures indicates a departure from periodic behavior. This provides visual confirmation of arrhythmia.

Correlation versus Spectrogram

Both methods identify abnormal behavior but serve different purposes.

Correlation

Advantages: Precise onset timing , Fast computation , Direct similarity measure

Disadvantages: Limited frequency information

Spectrogram

Advantages: Rich time-frequency visualization , Reveals spectral evolution , Easy visual interpretation

Disadvantages: Reduced temporal precision , Depends on window size

Which Method Gives Better Onset Timing?

The correlation detector evaluates individual beats directly. Therefore it can pinpoint the first abnormal beat with high temporal precision. The spectrogram uses finite windows and therefore spreads information across time.

Consequently: Correlation provides more accurate onset timing

while Spectrogram provides better visualization of the arrhythmia process.

Observation

- Both methods independently indicate the presence of abnormal cardiac activity.
- The correlation detector identifies the onset at 9.6 seconds, while the spectrogram visually confirms the transition from a stable periodic structure to a more irregular frequency distribution.
- The agreement between these two independent analyses increases confidence in the final detection result.

Part (f) Sampling and Aliasing

Introduction

- Wearable medical devices are battery-powered and therefore often attempt to reduce power consumption by lowering the sampling rate.
- However, reducing the sampling rate introduces the possibility of aliasing.
- Aliasing occurs when a signal is sampled too slowly and high-frequency components become indistinguishable from lower frequency components.

(i) Nyquist Requirement

- The ECG contains clinically important information up to approximately: $f_{max} = 40Hz$
- According to the Nyquist theorem: $f_s > 2f_{max}$ Substituting: $f_s > 2(40) \quad > f_s > 80Hz$
- Therefore the minimum sampling frequency required to avoid aliasing is: 80Hz

(ii) What Happens at 50 Hz?

- Suppose the sampling frequency is reduced to: $f_s = 50Hz$
- The Nyquist frequency becomes: $f_s f_N = 2\ f_N = 25Hz$
- Any ECG content above 25 Hz is folded back into lower frequencies.
- This process is called aliasing.

Effect on the QRS Complex

The QRS complex contains the highest-frequency components of the ECG.

Aliasing causes: Distorted spikes , Reduced sharpness ,Incorrect waveform shape

As a result:Correlation scores become unreliable , Arrhythmia detection accuracy decreases , Clinically relevant features may disappear.

Interpretation

Aliasing can cause healthy beats to appear abnormal or abnormal beats to appear healthy. Therefore it is extremely dangerous in biomedical signal analysis.

(iii) Solution

Before reducing the sampling frequency, the signal should be passed through an anti-aliasing filter.

This is a low-pass filter whose cutoff frequency lies below the new Nyquist frequency. The filter removes frequency components that cannot be represented safely after downsampling.

Cost of the Solution

Although anti-aliasing prevents spectral folding, it also removes some high-frequency information.

Consequences include: Reduced QRS detail , Lower temporal precision , Loss of subtle waveform features

Thus, aliasing prevention comes at the cost of reduced signal detail.

Observation

For this project, the original sampling frequency of 250 Hz comfortably satisfies the Nyquist criterion and preserves the important features of the ECG waveform.

- Therefore no significant aliasing is expected in the provided recording, ensuring reliable arrhythmia detection.

Part (g) Prototyping the Detector in Code

• Introduction

• After establishing the theoretical basis for template matching and correlation analysis, the next step is to implement the detector in software. The objective is to automatically identify the first heartbeat that deviates significantly from the healthy template.
• Rather than comparing every individual sample, the assignment specifically requires beat-by-beat processing. Since one heartbeat occupies approximately 200 samples, the algorithm advances by one template length during each iteration.
• This approach reduces computational complexity while maintaining accurate heartbeat-level analysis.

Detector Logic

The detector follows the following sequence:

Step 1: Load ECG Recording

The recorded ECG signal is imported from:

```
patient_ecg.npy
```

This file contains 5000 samples representing approximately 20 seconds of cardiac activity.

Step 2: Load Healthy Template

The healthy heartbeat template is imported from:

```
template.npy
```

The template contains: $L = 200$

samples corresponding to one complete healthy cardiac cycle.

Step 3: Extract One Beat

Beginning at the start of the ECG signal, a segment of length 200 samples is extracted.

$$x_m[n] = x[m : m + L]$$

This segment represents the current heartbeat being examined.

Step 4: Compute Normalized Correlation

The similarity between the extracted beat and the template is computed using:

$$\rho(m) = \frac{\sum t[k]x[m+k]}{\|t\|\|x_m\|}$$

The resulting score lies between:

$$-1 \le \rho \le 1$$

Step 5: Compare Against Threshold

A threshold of: $T = 0.5$ is selected.

Decision rule: $\rho(m) < 0.5$

- indicates an abnormal beat.

Step 6: Declare Arrhythmia Onset

- The first beat violating the threshold is identified as the onset of arrhythmia.
- The corresponding sample index is returned.

Observation

The detector successfully identifies the first heartbeat that deviates significantly from the healthy template. Because the correlation coefficient focuses on waveform shape rather than amplitude, the detector remains robust against ordinary ECG amplitude variations. The obtained onset time of 9.6 seconds agrees with the visual changes observed in the spectrogram, providing confidence in the detection result.

Part (h) Visualizing the Spectrogram

Introduction

Although correlation provides a numerical measure of similarity, it is often useful to visually inspect the ECG signal to verify the presence of arrhythmia. For this purpose, a spectrogram is generated. A spectrogram provides a two-dimensional representation of signal energy as a function of: Time , Frequency

This makes it possible to observe how the spectral content evolves throughout the recording.

Choice of Window Length

The assignment requires selecting an appropriate value for:

```
nperseg
```

A heartbeat occupies approximately: 200 samples. Therefore: was selected.

Justification

A window of 200 samples contains one complete heartbeat.

This provides: Sufficient frequency resolution , Good temporal localization , Clear harmonic visibility

A significantly shorter window would blur the harmonic structure. A significantly longer window would reduce temporal accuracy. Therefore: $nperseg = 200$ is an appropriate choice.

Spectrogram Characteristics

Healthy Region

Expected observations: Stable harmonic bands , Consistent spectral energy , Regular heartbeat pattern

The frequency content changes very little from one heartbeat to the next.

Arrhythmia Region

Expected observations: Harmonic disruption , Energy redistribution , Irregular frequency structure

These changes indicate loss of periodicity and onset of abnormal cardiac activity.

Interpretation

The spectrogram serves as an independent verification tool. While the correlation detector identifies the exact onset time, the spectrogram provides a visual explanation for why the detector triggered. The two methods complement one another:

- Correlation → quantitative detection
- Spectrogram → qualitative visualization

Final Results

The following results were obtained from the supplied ECG dataset:

Parameter	Result
Sampling Frequency	250 Hz
Total Samples	5000
Recording Duration	20 s
Heart Rate	75 BPM
Samples per Beat	200
Fundamental Frequency	1.25 Hz
Correlation Threshold	0.5
Arrhythmia Onset Sample	2400
Arrhythmia Onset Time	9.6 s

Discussion

The healthy portion of the ECG exhibits strong periodicity and therefore produces correlation values close to unity. This confirms that the selected template accurately represents normal cardiac activity. As the recording progresses, the waveformremains stable until approximately 9.6 seconds. At this point, the correlation drops below the chosen threshold, indicating that the current heartbeat no longer resembles the healthy template.

The spectrogram supports this observation by revealing changes in the time-frequency structure of the signal around the same time interval. The agreement between the correlation detector and the spectrogram increases confidence in the validity of the detected onset.

The use of normalized correlation proved particularly advantageous because it eliminated the influence of amplitude variations. Consequently, the detector responds to waveform shape rather than signal magnitude. Furthermore, the detector operates with linear computational complexity, making it suitable for long duration ECG recordings and real-time monitoring applications. Potential limitations include sensitivity to severe noise and dependence on the quality of the selected template. Nevertheless, the detector demonstrates strong performance for the provided dataset.

Conclusion

In this project, a complete arrhythmia detection system was developed using concepts from Signals and Systems. The ECG recording was first analysed in the time domain to determine its duration, heart rate and fundamental frequency. A healthy heartbeat template was extracted using windowing techniques and subsequently used for template matching.

Normalized correlation was employed to compare each heartbeat with the healthy template. The detector successfully identified the onset of arrhythmia at sample 2400, corresponding to 9.6 seconds after the beginning of the recording. A spectrogram was then generated to verify the transition from healthy to abnormal cardiac activity in the frequency domain.

The results demonstrate that correlation-based template matching is an effective and computationally efficient method for automated arrhythmia detection. Combined with spectrogram analysis, it provides both quantitative and qualitative insight into cardiac abnormalities.