


```
# e2sm_rc_enabled: true          # Enable RC service module
# addr: 127.0.0.1                # RIC IP address
#bind_addr: 127.0.0.100          # A local IP that the E2 agent binds to for traffic from the RIC. ONLY required if
# port: 36421                    # RIC port

metrics:
layers:
    enable_rlc: true             # Enable RLC metrics
    enable_sched: true           # Enable DU scheduler metrics
periodicity:
    du_report_period: 1000       # Set DU statistics report period to 1s
```

=== CONFIGURACION UE (1779105403) ===

```
[rf]
freq_offset = 0
tx_gain = 50
rx_gain = 40
srate = 11.52e6
nof_antennas = 1

device_name = zmq
device_args = tx_port=tcp://127.0.0.1:2001,rx_port=tcp://127.0.0.1:2000,base_srate=11.52e6

[rat.eutra]
dl_eurfcn = 2850
nof_carriers = 0

[rat.nr]
bands = 3
nof_carriers = 1
dl_arfcn = 368500

[pcap]
enable = none
mac_filename = /tmp/ue_mac.pcap
mac_nr_filename = /tmp/ue_mac_nr.pcap
nas_filename = /tmp/ue_nas.pcap

[log]
all_level = warning
phy_lib_level = none
all_hex_limit = 32
filename = stdout
file_max_size = -1

[usim]
mode = soft
algo = milenage
opc = 63BFA50EE6523365FF14C1F45F88737D
k = 00112233445566778899aabbccddeeff
imsi = 208930000000001
imei = 353490069873319

[rrc]
release = 15
ue_category = 4

[nas]
apn = srsapn
apn_protocol = ipv4

[gw]
netns = ue1
ip_devname = tun_srsue
ip_netmask = 255.255.255.0

[gui]
enable = false
```

#

```
# Copyright 2021-2026 Software Radio Systems Limited
#
# This file is part of srsRAN
#
# srsRAN is free software: you can redistribute it and/or modify
# it under the terms of the GNU Affero General Public License as
# published by the Free Software Foundation, either version 3 of
# the License, or (at your option) any later version.
#
# srsRAN is distributed in the hope that it will be useful,
# but WITHOUT ANY WARRANTY; without even the implied warranty of
# MERCHANTABILITY or FITNESS FOR A PARTICULAR PURPOSE. See the
# GNU Affero General Public License for more details.
#
# A copy of the GNU Affero General Public License can be found in
# the LICENSE file in the top-level directory of this distribution
# and at http://www.gnu.org/licenses/.
#

services:
  5gc:
    container_name: open5gs_5gc
    build:
    context: open5gs
    target: open5gs
    args:
      OS_VERSION: "22.04"
      OPEN5GS_VERSION: "v2.7.0"
    env_file:
      # Ensure this file contains MCC=208, MNC=93, TAC=7 and IMSI range for 208930000000001
      - ${OPEN_5GS_ENV_FILE:-open5gs/open5gs.env}
    privileged: true
    ports:
      - "9898:9999/tcp"
      # Uncomment port to use the 5gc from outside the docker network
      # - "38412:38412/sctp"
      # - "2152:2152/udp"
    command: 5gc -c open5gs-5gc.yml
    healthcheck:
      test: [ "CMD-SHELL", "nc -z 127.0.0.20 7777" ]
      interval: 3s
      timeout: 1s
      retries: 60
    networks:
    ran:
      ipv4_address: ${OPEN5GS_IP:-10.53.1.2}

  gnb:
    container_name: srsran_gnb
    # Build info
    image: srsran/gnb
    build:
    context: ..
    dockerfile: docker/Dockerfile
    args:
      OS_VERSION: "24.04"
      # privileged mode is required only for accessing usb devices
      privileged: true
      # Extra capabilities always required
    cap_add:
      - SYS_NICE
      - CAP_SYS_PTRACE
    volumes:
```

```

# Access USB to use some SDRs
- /dev/bus/usb/:/dev/bus/usb/
# Sharing images between the host and the pod.
# It's also possible to download the images inside the pod
- /usr/share/uhd/images:/usr/share/uhd/images
# Save logs and more into gnb-storage
- gnb-storage:/tmp
# It creates a file/folder into /config_name inside the container
# Its content would be the value of the file used to create the config
configs:
- gnb_config.yml
- gnb_compose_config.yml
# Customize your desired network mode.
# current network configuration creates a private network with both containers attached
# An alternative would be `network: host`. That would expose your host network into the container. It
networks:
ran:
  ipv4_address: ${GNB_IP:-10.53.1.3}
metrics:
  ipv4_address: 172.19.1.3
# Start GNB container after 5gc is up and running
depends_on:
5gc:
  condition: service_healthy
# Command to run into the final container
command: gnb -c /gnb_config.yml -c /gnb_compose_config.yml

configs:
gnb_config.yml:
  # Path to your desired gNB config file (e.g., gnb_zmq.yaml generated above)
  file: ./gnb_zmq.yaml
gnb_compose_config.yml:
  content: |
  cu_cp:
    amf:
      addr: ${OPEN5GS_IP:-10.53.1.2}
      bind_addr: ${GNB_IP:-10.53.1.3}
  metrics:
    autostart_stdout_metrics: true
    enable_json: true
  remote_control:
    bind_addr: 0.0.0.0
    enabled: true

volumes:
gnb-storage:

networks:
ran:
  ipam:
    driver: default
    config:
      - subnet: 10.53.1.0/24
metrics:
  ipam:
    driver: default
    config:
      - subnet: 172.19.1.0/24

```