

11/12/19

Code:

```
org 0000h
mov a, #05h
mov r0, #05h
add a, r0
H: SJMP H
end
```

STEPS:-

- 1) Go to start.
- 2) 'Kill microvision' & select this option.
- 3) Go to project and close project.
- 4) Go to project and select 'new micro vision project'.
- 5) Go to documents.
- 6) Click 'new folder'.
- 7) Open the folder.
- 8) Give a file name and select 'save'.
- 9) Search for 'NXP' and expand 'NXP'.
- 10) Out of all the configuration, use 'P89V51RD2'.
- 11) Click 'OK'.
- 12) Click 'yes'.
- 13) Expand 'target 1' > source group.
- 14) Go to 'file' and click 'new'.
- 15) Write down code.
- 16) Go to 'file' > 'save as'.
- 17) File name must be given with '.ASM' extension.
- 18) Click 'save'.
- 19) Right click 'source group1'.
- 20) Click 'add existing files to group 'source group1'.
- 21) Folder name must be same and use '.asm' source file and under the 'file of type' drop down menu.
- 22) Select 'add' and then 'close'.
- 23) Click on 'translate' to compile program (check for error).
- 24) Go to debug > start / stop debug to run the code.
- 25) After step 23: built > rebuilt.

TASK-I

EXP-I

```
org 0000h
mov a, #0ah
mov r0, #05h
subb a, r0
H: SJMP H
end
```

```
org 0000h
mov a, #05h
mov b, #05h
mul ab
H: SJMP H
end
```

```
org 0000h
mov a, #020h
mov b, #05h
div ab
H: SJMP H
end.
```