SBL ENERGY LIMITED

NEO DET

STLD

TECHNICAL DATASHEET

Neo Det is a non-electric surface trunkline detonator system designed to control millisecond delays between blast holes or rows through reliable surface sequencing. It consists of a durable shock tube of specified lengths attached to a colour-coded plastic connector housing a low-strength precision delay detonator. The connector block is engineered to accept multiple shock tubes, ensuring secure retention and flexible routing across the blast field. The system enables accurate hole-to-hole or row-to-row delay timing and is compatible with standard in-hole detonators, providing versatility in complex surface initiation designs.

TECHNICAL DETAILS

Shell Material - Aluminium	
Dia of shell - 7.5mm	
Base charge - PETN	
Primary Charge - ASA	
Charge weight/det - 600mg PETN , 200mg ASA	
Detonator strength - No. 8 strength	

KEY FEATURES

- Colour-coded surface connector with a low-strength precision delay detonator.
- Accepts up to six shock tubes with secure retention.
- Durable, abrasion-resistant shock tube available in multiple lengths.
- Water-sealed tube end for field reliability.
- Suitable for surface delay sequencing between holes or rows.
- Works with standard non-electric in-hole detonators.

STORAGE & HANDLING

- Store Neo Det units in a cool, dry, and well-ventilated magazine approved for detonator storage (Class 6)
- Keep case stacks below 2 meters to prevent crushing or deformation.
- For optimal performance, use products within their recommended shelf life (around 24 months) and always follow FIFO (oldest stock first).
- Handle and transport detonators strictly according to applicable local and national regulations.
- Maintain storage conditions that protect the detonators from heat, moisture, and mechanical impact, as these can reduce reliability.

Office: 230, Hill Road, Da Rock Building, 2nd Floor, Shivaji Nagar, Nagpur - 440010 (MH) India.
+91-8308810133
info@sblenergy.com
www.sblenergy.com

SBL ENERGY LIMITED

RECOMMENDATIONS FOR USE

- Insert each shock tube into the connector block at a right angle, ensuring it locks firmly and sits without forming crossovers.
- Slide the connector block slightly down the tubes to confirm all tubes remain separated and properly engaged.
- The connector block holds six tubes securely without needing burial.
- Handle shock tubes and detonators carefully to avoid cuts, crushing, or damage.
- Neo Det can be initiated using a detonator of #8 strength or a detonating cord with a minimum PETN charge of 5 g/m.
- These connectors must not be used to directly initiate detonating cord.
- Never place detonating cord and shock tube together inside the same connector block, as this may lead to misfires.

STLD

Length(m)	Units/box	Tube Color
2	400	Orange
3	300	Orange
4	300	Orange
5	200	Orange
6	200	Orange

*Other lengths upon customer requirement.

Connector Color	Delay on Surface(ms)
yellow	17
red	25
orange	42
blue	67

*Other delays upon customer requirement.

Transport Classification	Class	UN Number
Standard Packaging	1.1B	UN 0360
Special Packaging	1.4S	UN 0500

PRODUCT DISCLAIMER

 The details presented in this document ("Information") are intended to provide general technical guidance regarding the referenced products ("Products"). While reasonable care has been taken in compiling this Information, SBL Energy Ltd does not guarantee its accuracy, consistency, or applicability to every operational environment, and the Information may be updated or amended without prior notice. Explosive Products must only be handled, transported, and used by personnel who are properly trained, certified, and authorized to work with such materials. Users are responsible for assessing site-specific conditions, verifying regulatory requirements, and ensuring that all procedures align with applicable safety standards and legal obligations. To the extent permitted by law, SBL Energy Ltd rejects any form of warranty—statutory, express, or implied—relating to the Information or the Products, including but not limited to performance guarantees or suitability for a particular use. The company shall not be held liable for any loss, damage, injury, or operational consequence arising from reliance on this Information or from misuse or improper handling of the Products.

This document is provided solely for reference and shall not be interpreted as a contractual commitment, product guarantee, or legally binding representation by SBL Energy Ltd.

Office: 230, Hill Road, Da Rock Building, 2nd Floor, Shivaji Nagar, Nagpur - 440010 (MH) India.
+91-8308810133
info@sblenergy.com
www.sblenergy.com