



NEO DET

COMBIDET

TECHNICAL DATASHEET

PRODUCT DESCRIPTION

Neo Det is a shock tube-based, dual-delay non-electric detonator system that integrates an in-hole delay detonator and a surface connector detonator into a single unit.

The system consists of an abrasion-resistant shock tube of specified lengths, with:

- An in-hole detonator crimped on one end, incorporating a long-delay element and a high-strength base charge suitable for initiating primers such as emulsion boosters, cast boosters, and other cap-sensitive explosives.
- A surface connector block on the other end, housing a low-strength, precision surface delay detonator. This connector is designed to accept up to six shock tubes, ensuring reliable surface-level sequencing.

The surface connector is colour-coded according to delay time, enabling clear identification and easy sequencing in the field. Its enclosed design provides secure shock-tube retention and minimizes risks of shrapnel or excessive noise during surface initiation.

TECHNICAL DETAILS

Shell Material - Aluminium

Dia of shell - 7.5mm

Base charge - PETN

Primary Charge - ASA

Charge weight/det - 600mg PETN , 200mg ASA

Detonator strength - No. 8 strength

KEY FEATURES

- Integrated in-hole + surface delay system for simplified blast layout.
- Abrasion-resistant shock tube for reliable signal transmission.
- High-strength in-hole detonator suitable for initiating cap-sensitive explosives and boosters.
- Low-strength, enclosed surface detonator for safer, low-noise surface initiation.
- The connector accepts up to six shock tubes with secure retention.
- Colour-coded delays for quick and error-free identification.
- Provides accurate and consistent delay timing for controlled blasting.
- Suitable for surface, construction, quarry, and underground blasting.





STORAGE & HANDLING

- Store Neo Det units in a cool, dry, and well-ventilated magazine approved for detonator storage (Class 6)
- Keep case stacks below 2 meters to prevent crushing or deformation.
- For optimal performance, use products within their recommended shelf life (around 24 months) and always follow FIFO (oldest stock first).
- Handle and transport detonators strictly according to applicable local and national regulations.
- Maintain storage conditions that protect the detonators from heat, moisture, and mechanical impact, as these can reduce reliability.

COMBIDET

Length(m)	Units/box	Tube Color
2 , 2.5	400	Orange
3 - 4	300	Orange
5 - 6	200	Orange
7 - 10	150	Orange
11 - 16	100	Orange
17 - 34	50	Orange
35 - 50	25	Orange

*Other lengths upon customer requirement.

Connector Color	Delay on Surface(ms)	Delay in-hole(ms)
yellow	17	250/450/500
red	25	250/450/500
orange	42	250/450/500

*Other delays upon customer requirement.

Transport
Classification

Class

UN
Number

Standard
Packaging

1.1B

UN 0360

Special
Packaging

1.4S

UN 0500



Office: 230, Hill Road, Da Rock Building, 2nd Floor,
Shivaji Nagar, Nagpur - 440010 (MH) India.



+91-8308810133



info@sblenergy.com



www.sblenergy.com

RECOMMENDATIONS FOR USE

- Choose a unit with adequate tube length so it comfortably reaches from the primer point to the next hole collar.
- Protect the connector block and all tube leads during loading, stemming, and mat placement to avoid impact or crushing damage.
- Keep tubes aligned side-by-side inside the channel; avoid crossing or overlapping during insertion.
- Neo Det units can connect up to six 3-mm shock tubes—never exceed this limit.
- Not designed to initiate detonating cord; using both in the same connector can cause misfires.
- Do not disassemble the delay detonator from the connector block or operate it separately.
- Avoid pulling, stretching, bending, or putting tension on the shock tube—it may split, allowing moisture to enter and cause initiation failure.
- Keep all Neo Det connectors disconnected until charging and stemming of all holes is fully complete and the area is clear.
- Ensure in-hole detonators are placed inside a proper primer that completely encloses and protects the detonator shell.
- Neo Det can be initiated with a detonator of #8 strength.



PRODUCT DISCLAIMER

© 2025 SBL Energy Ltd. All rights reserved. The details presented in this document ("Information") are intended to provide general technical guidance regarding the referenced products ("Products"). While reasonable care has been taken in compiling this Information, SBL Energy Ltd does not guarantee its accuracy, consistency, or applicability to every operational environment, and the Information may be updated or amended without prior notice. Explosive Products must only be handled, transported, and used by personnel who are properly trained, certified, and authorized to work with such materials. Users are responsible for assessing site-specific conditions, verifying regulatory requirements, and ensuring that all procedures align with applicable safety standards and legal obligations. To the extent permitted by law, SBL Energy Ltd rejects any form of warranty—statutory, express, or implied—relating to the Information or the Products, including but not limited to performance guarantees or suitability for a particular use. The company shall not be held liable for any loss, damage, injury, or operational consequence arising from reliance on this Information or from misuse or improper handling of the Products.

This document is provided solely for reference and shall not be interpreted as a contractual commitment, product guarantee, or legally binding representation by SBL Energy Ltd.

