



NEO PRIMEX

TECHNICAL DATASHEET

Neo Primex is a high-density cast booster made from a PETN-TNT explosive composition, moulded into a durable cylindrical shell. It is engineered to deliver high detonation pressure and a strong shock front needed to initiate bulk explosives, ANFO, watergels, emulsions, and other blasting agents that cannot be directly initiated by a detonator. The booster contains two longitudinal tunnels designed to accommodate a detonator or detonating cord. One tunnel is straight, while the other may incorporate a stepped or tapered detonator retention feature to ensure secure placement. Neo Primex boosters have a high density, and a high velocity of detonation (VOD) to maximize performance.

TECHNICAL DETAILS

PARAMETER		VALUE			
Shell Color		Red			
Nominal density, g/cm ³		1.65			
Nominal Velocity of detonation, m/s		7000			
Water resistance		Excellent			
Oil resistance		Excellent			
Nominal mass	100g +/- 5g	150g +/- 5g	250g +/- 10g	400g +/- 20g	
Nominal Diameter, mm	33 +/- 0.2	40 +/- 0.2	49 +/- 0.2	54 +/- 0.5	
Recommended Hole Diameter	Up to 115mm	Up to 135mm	Up to 160mm	above 102 mm	
Nominal Length, mm	93.5 +/- 1.0	98 +/- 1.0	88.5 +/- 1.0	114 +/- 2.0	

KEY FEATURES

- High-density PETN-TNT composition for strong initiation energy.
- Two longitudinal tunnels for detonator or detonating cord placement.
- Detonator retention feature for secure and safe positioning.
- Recessed base well protects cord, tube, or wires from damage.
- Compatible with No. 8 detonators and adequate PETN-loaded detonating cord.
- Excellent shelf life, highly resistant to water and oil.





RECOMMENDATIONS FOR USE

1 Initiation with Detonating Cord

- Use Neo Primex boosters only with a detonating cord that meets the minimum PETN coreload requirement specified for the product (typically 10 g/m).
- Attach the cord securely by threading it through one tunnel, looping it around the curved path, and bringing it back through the second tunnel. Form a firm loop and ensure the cord is snug before lowering the assembly into the hole.
- Cut the downline from the reel and secure it properly at the collar so that tension is maintained during charging.
- When adding additional boosters on the same downline, loosen the cord tail, thread the cord through the straight tunnel of the next booster, re-secure at the collar, and lower the unit to the correct depth.

2 Initiation with Delay Detonators

- Insert the delay detonator through the booster tunnel designed for in-hole initiation.
- For angled or rough holes, tape the top/bottom of the booster after assembly to prevent the detonator from slipping out.
- Lower the complete primer carefully, ensuring the lead wires or shock tube remain undamaged—avoid stepping on them or dragging them through sharp edges.

PRODUCT DISCLAIMER

© 2025 SBL Energy Ltd. All rights reserved. The details presented in this document ("Information") are intended to provide general technical guidance regarding the referenced products ("Products"). While reasonable care has been taken in compiling this Information, SBL Energy Ltd does not guarantee its accuracy, consistency, or applicability to every operational environment, and the Information may be updated or amended without prior notice. Explosive Products must only be handled, transported, and used by personnel who are properly trained, certified, and authorized to work with such materials. Users are responsible for assessing site-specific conditions, verifying regulatory requirements, and ensuring that all procedures align with applicable safety standards and legal obligations. To the extent permitted by law, SBL Energy Ltd rejects any form of warranty—statutory, express, or implied—relating to the Information or the Products, including but not limited to performance guarantees or suitability for a particular use. The company shall not be held liable for any loss, damage, injury, or operational consequence arising from reliance on this Information or from misuse or improper handling of the Products.

This document is provided solely for reference and shall not be interpreted as a contractual commitment, product guarantee, or legally binding representation by SBL Energy Ltd.

STORAGE & HANDLING

- Follow FIFO (First-In-First-Out) inventory rotation to use the oldest stock first.
- Cast boosters must be transported, stored and handled with care at all times.
- Avoid impact or collision with solid surfaces or other boosters, as this can cause damage leading to misfire or premature initiation.
- Use only detonators that can be fully fitted inside the booster. A partially exposed detonator may get damaged during charging and can cause untimely detonation.
- Suitable for use up to 60–65°C (depending on product specification). Seek technical advice for higher temperatures.
- Store in a cool, dry, licensed explosive magazine (Class 2).
- Shelf life is typically up to 5 years under proper storage conditions.

NEO PRIMEX

Nominal Mass (gm)	Box Dimension (mm*mm*mm)	Units/box
100	345 x 280 x 280	240
150	345 x 280 x 280	160
250	410 x 310 x 280	96
400	375 x 320 x 280	60

*Other sizes can be made available on request.

Transport Classification	Class	UN Number
Standard Packaging	1.1D	UN 0042



Office: 230, Hill Road, Da Rock Building, 2nd Floor,
Shivaji Nagar, Nagpur - 440010 (MH) India.



+91-8308810133



info@sblenergy.com



www.sblenergy.com