

Field-technician access · keep the robot in Hold and UVC physically disconnected

1 MAKE SAFE



Hold · wheels restrained
UVC supply disconnected

2 JOIN WI-FI AP

SSID: mars_XXXXXX
Password: alphaaggech



“No Internet” is normal.

3 USE LOCAL NAME

`mars.local`

Use the AP gateway IP only
if mDNS does not resolve.

4 CONNECT BY SSH

```
ssh mars@mars.local  
verify host fingerprint
```

Use the OS-account password,
not the Wi-Fi password.

5 INSPECT

```
hostname -I  
systemctl status camera  
ip -details link show can0
```

Record findings before any
approved service change.

6 EXIT + VERIFY

```
exit
```

Close the terminal, then verify:
Hold · zero motion · service healthy
web, video, RTK and CAN normal

XXXXXX is the unit-specific suffix. Never accept an unexpected SSH host-key change until the controller identity is verified.