

Bitnami Helm chart scan

Completed all 115 discovered charts with --filter, four workers, and a five-minute test budget per chart. No scan-wide deadline was imposed.

Recorded 19,846 test attempts across the 115 primary chart records in 41.0 minutes of wall time, including dependency preparation. Attempts include baseline checks and counterexample shrinking; they are not a count of unique inputs or bugs.

The kube-prometheus worker also recursively tested its nested CRD chart. That additional result is retained in supplemental-recursive-results.json; the 115-chart totals use each chart's dedicated job once.

Findings: 112 failed; 1 skipped-library; 2 time-limit.

Known-input phase: 112 failed; 2 time-limit.

Deferred robustness phase: 13 failed; 95 passed; 6 time-limit.

Known fields receive up to 90% of each chart budget; deferred original-contract cases run afterward using the remainder. A phase can finish early after finding and shrinking a counterexample. Dynamic and schema-defined maps remain open; the generation preference does not change the original validation contract or prove deferred inputs irrelevant.

Failure diagnostics across both phases: 13 explicit chart validation rejection; 6 manifest processing; 11 other; inspect diagnostic; 76 rendered YAML; 15 template evaluation; 4 values transport. These categories are based on diagnostic text and are not confirmed root causes.

Failures are observed render/manifest-check failures, including deliberate chart validation rejections and manifest-processing limitations. They need triage before being classified as chart defects. Charts without a values schema use inferred generation, not an authoritative input specification. A passed sample or completed scan does not establish exhaustive coverage.

Checks: dependency build in isolated copies, Helm lint, Helm template with values-schema checks, and built-in manifest checks. External kubeconform/kubesecc validation was not configured for this run.

Source: third_party/bitnami-charts at 6a8cccf3c29a1faabf0c34c8276a09ed14f3c5b3. The source checkout is retained.

A post-run serializer correction keeps ordinary Unicode keys literal instead of unnecessarily escaping every character. The original production findings remain unchanged; the four values-transport diagnostics are not evidence of chart-template defects. See transport-triage.json for the isolated reproduction.

Combined PDF (bitnami.pdf) · Aggregate data (bitnami-runs/bitnami-charts_1789251211/scan.json) · Raw logs and provenance (bitnami-runs/bitnami-charts_1789251211/README.md)

Directory: third_party/bitnami-charts

Started (Unix epoch): 1789251228

Elapsed: 2461.80 seconds

Charts discovered: 115

Scan status: completed

Discovery complete: True

Unstarted charts: 0

Results describe the tested sample; they do not prove chart correctness.

Baseline-only, skipped, blocked, and incomplete charts are not property-test passes.

Status counts

```
{
  "failed": 112,
  "skipped-library": 1,
  "time-limit": 2
}
```

Settings

```
{
  "max_examples": 100,
  "filter": true,
  "permutations": null,
  "chart_timeout_seconds": 300.0,
  "scan_timeout_seconds": null,
  "helm": "Helm 4.3.0",
  "seed": 0,
  "build_dependencies": true,
  "values": "values.yaml",
  "workers": 4,
  "max_examples_per_phase": 100,
  "known_input_budget_fraction": 0.9,
  "external_conformity": false
}
```

Errors

113 distinct diagnostics across 125 occurrences; 12 repeats grouped.
Matching diagnostics do not establish a shared root cause.

E001

Error: YAML parse error on apache/templates/svc.yaml: error converting YAML to JSON: yaml: line 13: mapping values are not allowed in this context

- bitnami/apache (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/apache_1789251228/0000>)

E002

Error: YAML parse error on apisix/templates/control-plane/api-token-secret.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/apixix (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/apixix_1789251228/0000>)

E003

Error: YAML parse error on appsmith/templates/backend/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/appsmith (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/appsmith_1789251228/0000>)

E004

Error: YAML parse error on argo-cd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/argo-cd (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/argo-cd_1789251295/0000>)

E005

Error: YAML parse error on argo-workflows/templates/controller/deployment.yaml: error converting YAML to JSON: yaml: line 30: mapping values are not allowed in this context

- bitnami/argo-workflows (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/argo-workflows_1789251302/0000>)

E006

Error: YAML parse error on cassandra/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/cassandra (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/cassandra_1789251382/0000>)

E007

Error: YAML parse error on cert-manager/templates/cainjector/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/cert-manager (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/cert-manager_1789251391/0000>)

E008

Error: YAML parse error on clickhouse/templates/statefulset.yaml: error converting YAML to JSON: yaml: line 178: mapping values are not allowed in this context

- bitnami/clickhouse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/clickhouse_1789251452/0000>)

E009

Error: YAML parse error on cloudnative-pg/templates/operator/clusterrolebinding.yaml: error converting YAML to JSON: yaml: line 4: did not find expected comment or line break

- bitnami/cloudnative-pg (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/cloudnative-pg_1789251513/0000>)

E010

Error: YAML parse error on consul/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/consul (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/consul_1789251533/0000>)

E011

Error: YAML parse error on contour/templates/certgen/serviceaccount.yaml: error converting YAML to JSON: yaml: line 15: did not find expected key

- bitnami/contour (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/contour_1789251558/0000>)

E012

Error: YAML parse error on deepspeed/templates/client/client-dep-job.yaml: error converting YAML to JSON: yaml: line 31: did not find expected key

- bitnami/deepspeed (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/deepspeed_1789251584/0000>)

E013

Error: YAML parse error on discourse/templates/service.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/discourse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/discourse_1789251597/0000>)

E014

Error: YAML parse error on dremio/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/dremio (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/dremio_1789251625/0000>)

E015

Error: YAML parse error on drupal/templates/svc.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/drupal (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/drupal_1789251652/0000>)

E016

Error: YAML parse error on ejbca/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/ejbca (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/ejbca_1789251723/0000>)

E017

Error: YAML parse error on elasticsearch/templates/coordinating/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/elasticsearch (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/elasticsearch_1789251725/0000>)

E018

Error: YAML parse error on envoy-gateway/templates/deployment.yaml: error converting YAML to JSON: yaml: line 37: did not find expected key

- bitnami/envoy-gateway (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/envoy-gateway_1789251751/0000>)

E019

Error: YAML parse error on external-dns/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/external-dns (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/external-dns_1789251819/0000>)

E020

Error: YAML parse error on flink/templates/jobmanager/deployment.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/flink (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/flink_1789251853/0000>)

E021

Error: YAML parse error on fluentd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/fluentd (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/fluentd_1789251891/0000>)

E022

Error: YAML parse error on flux/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/flux (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/flux_1789251919/0000>)

E023

Error: YAML parse error on ghost/templates/svc.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/ghost (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/ghost_1789251929/0000>)

E024

Error: YAML parse error on gitea/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/gitea (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/gitea_1789251952/0000>)

E025

Error: YAML parse error on gitlab-runner/templates/cluster-role.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/gitlab-runner (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/gitlab-runner_1789251987/0000>)

E026

Error: YAML parse error on grafana-alloy/templates/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/grafana-alloy (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana-alloy_1789252023/0000>)

E027

Error: YAML parse error on grafana-loki/templates/gateway/configmap-http.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/grafana-loki (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana-loki_1789252062/0000>)

E028

Error: YAML parse error on grafana-operator/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/grafana-operator (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana-operator_1789252073/0000>)

E029

Error: YAML parse error on grafana-tempo/templates/tempo-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/grafana-tempo (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana-tempo_1789252105/0000>)

E030

Error: YAML parse error on haproxy/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/haproxy (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/haproxy_1789252206/0000>)

E031

Error: YAML parse error on harbor/templates/core/core-dpl.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/harbor (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/harbor_1789252208/0000>)

E032

Error: YAML parse error on influxdb/templates/pdb.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/influxdb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/influxdb_1789252221/0000>)

E033

Error: YAML parse error on janusgraph/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/janusgraph (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/janusgraph_1789252257/0000>)

E034

Error: YAML parse error on kafka/templates/controller-eligible/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/kafka (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kafka_1789252297/0000>)

E035

Error: YAML parse error on kube-arangodb/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/kube-arangodb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kube-arangodb_1789252412/0000>)

E036

Error: YAML parse error on kuberay/templates/apiserver/clusterrolebinding.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/kuberay (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kuberay_1789252452/0000>)

E037

Error: YAML parse error on kubernetes-event-exporter/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/kubernetes-event-exporter (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kubernetes-event-exporter_1789252461/0000>)

E038

Error: YAML parse error on logstash/templates/sts.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/logstash (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/logstash_1789252473/0000>)

E039

Error: YAML parse error on mariadb-galera/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/mariadb-galera (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mariadb-galera_1789252506/0000>)

E040

Error: YAML parse error on mastodon/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/mastodon (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mastodon_1789252506/0000>)

E041

Error: YAML parse error on matomo/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/matomo (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/matomo_1789252549/0000>)

E042

Error: YAML parse error on metrics-server/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/metrics-server (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/metrics-server_1789252645/0000>)

E043

Error: YAML parse error on mlflow/templates/run/dep-job.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/mlflow (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mlflow_1789252697/0000>)

E044

Error: YAML parse error on mlflow/templates/run/dep-job.yaml: error converting YAML to JSON: yaml: line 29: did not find expected key

- bitnami/mlflow (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mlflow_1789252697/0000>)

E045

Error: YAML parse error on mongodb-sharded/templates/config-server/config-server-statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/mongodb-sharded (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mongodb-sharded_1789252809/0000>)

E046

Error: YAML parse error on mongodb/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/mongodb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mongodb_1789252761/0000>)

E047

Error: YAML parse error on moodle/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/moodle (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/moodle_1789252874/0000>)

E048

Error: YAML parse error on multus-cni/templates/daemonset.yaml: error converting YAML to JSON: yaml: line 73: did not find expected comment or line break

- bitnami/multus-cni (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/multus-cni_1789252902/0000>)

E049

Error: YAML parse error on mysql/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/mysql (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mysql_1789252935/0000>)

E050

Error: YAML parse error on nessie/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/nessie (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/nessie_1789252998/0000>)

E051

Error: YAML parse error on nginx/templates/context-includes-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/nginx (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/nginx_1789253009/0000>)

E052

Error: YAML parse error on nginx/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/nginx (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/nginx_1789253009/0000>)

E053

Error: YAML parse error on node-exporter/templates/daemonset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/node-exporter (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/node-exporter_1789253016/0000>)

E054

Error: YAML parse error on parse/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/parse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/parse_1789253081/0000>)

E055

Error: YAML parse error on phpmyadmin/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/phpmyadmin (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/phpmyadmin_1789253091/0000>)

E056

Error: YAML parse error on pinniped/templates/concierge/apiservice-identity.yaml: error converting YAML to JSON: yaml: line 23: found unexpected end of stream

- bitnami/pinniped (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/pinniped_1789253122/0000>)

E057

Error: YAML parse error on prometheus/templates/alertmanager/networkpolicy.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/prometheus (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/prometheus_1789253175/0000>)

E058

Error: YAML parse error on prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/prometheus (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/prometheus_1789253175/0000>)

E059

Error: YAML parse error on rabbitmq/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/rabbitmq (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/rabbitmq_1789253191/0000>)

E060

Error: YAML parse error on redmine/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/redmine (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/redmine_1789253293/0000>)

E061

Error: YAML parse error on seaweedfs/templates/filer/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/seaweedfs (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/seaweedfs_1789253341/0000>)

E062

Error: YAML parse error on solr/templates/statefulset.yaml: error converting YAML to JSON: yaml: line 180: did not find expected key

- bitnami/solr (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/solr_1789253352/0000>)

E063

Error: YAML parse error on sonarqube/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/sonarqube (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/sonarqube_1789253377/0000>)

E064

Error: YAML parse error on spark/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/spark (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/spark_1789253392/0000>)

E065

Error: YAML parse error on superset/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/superset (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/superset_1789253412/0000>)

E066

Error: YAML parse error on tensorflow-resnet/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/tensorflow-resnet (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/tensorflow-resnet_1789253441/0000>)

E067

Error: YAML parse error on thanos/templates/storegateway/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/thanos (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/thanos_1789253463/0000>)

E068

Error: YAML parse error on tomcat/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/tomcat (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/tomcat_1789253463/0000>)

E069

Error: YAML parse error on valkey-cluster/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/valkey-cluster (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/valkey-cluster_1789253483/0000>)

E070

Error: YAML parse error on valkey/templates/replicas/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/valkey (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/valkey_1789253482/0000>)

E071

Error: YAML parse error on vault/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/vault (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/vault_1789253486/0000>)

E072

Error: YAML parse error on victoriametrics/templates/vmagent/dep-ds.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/victoriametrics (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/victoriametrics_1789253519/0000>)

E073

Error: YAML parse error on wordpress/templates/httpd-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/wordpress (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/wordpress_1789253554/0000>)

E074

Error: execution error at (airflow/templates/NOTES.txt:129:3):
VALUES VALIDATION:

airflow: executors

You need to provide at least one value for the '.executor' parameter.

- bitnami/airflow (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/airflow_1789251228/0000>)

E075

Error: execution error at (aspnet-core/templates/NOTES.txt:58:4):
VALUES VALIDATION:

aspnet-core: missing-extra-volume-mounts

You specified extra volumes but not mount points for them.

Please also set the extraVolumeMounts parameter.

- bitnami/aspnet-core (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/aspnet-core_1789251350/0000>)

E076

Error: execution error at (cadvisor/templates/daemonset.yaml:155:25): ERROR: Preset key '' invalid.
Allowed values are xlarge,2xlarge,nano,micro,small,medium,large

- bitnami/cadvisor (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/cadvisor_1789251373/0000>)

E077

Error: execution error at (chainloop/templates/controlplane/secret-jwt-cas-private-key.yaml:14:22):
Authentication Private Key "casJWTPrivateKey" required

- bitnami/chainloop (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/chainloop_1789251406/0000>)

E078

Error: execution error at (drupal/charts/mariadb/templates/NOTES.txt:74:4):
VALUES VALIDATION:

mariadb: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/drupal (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/drupal_1789251652/0000>)

E079

Error: execution error at (fluent-bit/templates/NOTES.txt:30:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/fluent-bit:4.0.8-debian-12-r0

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true. Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- bitnami/fluent-bit (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/fluent-bit_1789251880/0000>)

E080

Error: execution error at (grafana-mimir/charts/memcachedchunks/templates/NOTES.txt:46:4):
VALUES VALIDATION:

memcached: architecture

Invalid architecture selected. Valid values are "standalone" and
"high-availability". Please set a valid architecture (--set architecture="xxxx")

- bitnami/grafana-mimir (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana-mimir_1789252066/0000>)

E081

Error: execution error at (jaeger/templates/collector/deployment.yaml:199:25): ERROR: Preset key '' invalid. Allowed values are xlarge,2xlarge,nano,micro,small,medium,large

- bitnami/jaeger (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/jaeger_1789252233/0000>)

E082

Error: execution error at (jenkins/templates/NOTES.txt:54:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/jenkins:2.516.2-debian-12-r0
- 00/bitnami/jenkins-agent:0.3327.0-debian-12-r1
- 00/bitnami/os-shell:12-debian-12-r51

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true. Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- bitnami/jenkins (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/jenkins_1789252283/0000>)

E083

Error: execution error at (jupyterhub/templates/proxy/deployment.yaml:32:32): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- bitnami/jupyterhub (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/jupyterhub_1789252291/0000>)

E084

Error: execution error at (kube-state-metrics/templates/deployment.yaml:205:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- bitnami/kube-state-metrics (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kube-state-metrics_1789252452/0000>)

E085

Error: execution error at (mariadb/templates/NOTES.txt:74:4):

VALUES VALIDATION:

mariadb: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/mariadb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mariadb_1789252495/0000>)

- bitnami/mariadb (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/mariadb_1789252495/0000>)

E086

Error: execution error at (memcached/templates/NOTES.txt:46:4):

VALUES VALIDATION:

memcached: architecture

Invalid architecture selected. Valid values are "standalone" and "high-availability". Please set a valid architecture (--set architecture="xxxx")

- bitnami/memcached (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/memcached_1789252601/0000>)

E087

Error: execution error at (nats/templates/NOTES.txt:176:4):

VALUES VALIDATION:

nats: resourceType

Invalid resourceType selected. Valid values are "deployment" and "statefulset". Please set a valid mode (--set resourceType="xxxx")

- bitnami/nats (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/nats_1789252944/0000>)

E088

Error: execution error at (oauth2-proxy/charts/redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/oauth2-proxy (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/oauth2-proxy_1789253043/0000>)

E089

Error: execution error at (odoo/templates/deployment.yaml:270:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- bitnami/odoo (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/odoo_1789253062/0000>)

E090

Error: execution error at (opensearch/templates/ingest/statefulset.yaml:90:12): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- bitnami/opensearch (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/opensearch_1789253064/0000>)

E091

Error: execution error at (postgresql/templates/NOTES.txt:118:4):
VALUES VALIDATION:

postgresql: psp.create, rbac.create

RBAC should be enabled if PSP is enabled in order for PSP to work.

More info at <https://kubernetes.io/docs/concepts/policy/pod-security-policy/#authorizing-policies>

- bitnami/postgresql (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/postgresql_1789253136/0000>)

E092

Error: execution error at (pytorch/templates/NOTES.txt:69:3):
VALUES VALIDATION:

pytorch: architecture

Invalid architecture selected. Valid values are "distributed" and "standalone". Please set a valid architecture (--set architecture="xxxx")

- bitnami/pytorch (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/pytorch_1789253187/0000>)

E093

Error: execution error at (redis/templates/NOTES.txt:202:4):
VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/redis (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/redis_1789253220/0000>)

- bitnami/redis (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/redis_1789253220/0000>)

E094

Error: execution error at (sealed-secrets/templates/deployment.yaml:172:25): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- bitnami/sealed-secrets (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/sealed-secrets_1789253315/0000>)

E095

Error: execution error at (whereabouts/templates/daemonset.yaml:164:25): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- bitnami/whereabouts (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/whereabouts_1789253539/0000>)

E096

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-aswf0y7m/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- bitnami/jenkins (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/jenkins_1789252283/0000>)

E097

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-i22elfg5/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- bitnami/redmine (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/redmine_1789253293/0000>)

E098

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-if0kaa5a/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- bitnami/ghost (robustness; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/ghost_1789251929/0000>)

E099

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-rtvpkvk8/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- bitnami/rabbitmq (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/rabbitmq_1789253191/0000>)

E100

Error: grafana/templates/application.yaml:225:72

executing "grafana/templates/application.yaml" at <.configMapName>:
nil pointer evaluating interface {}.configMapName

- bitnami/grafana (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana_1789252005/0000>)

E101

Error: kibana/templates/ingress.yaml:33:64

executing "kibana/templates/ingress.yaml" at <.name>:
nil pointer evaluating interface {}.name

- bitnami/kibana (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kibana_1789252366/0000>)

E102

Error: neo4j/templates/networkpolicy.yaml:47:19

executing "neo4j/templates/networkpolicy.yaml" at <.containerPort>:
nil pointer evaluating interface {}.containerPort

- bitnami/neo4j (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/neo4j_1789252975/0000>)

E103

Error: schema-registry/templates/http-route.yaml:7:13

executing "schema-registry/templates/http-route.yaml" at <\$route.enabled>:
nil pointer evaluating interface {}.enabled

- bitnami/schema-registry (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/schema-registry_1789253309/0000>)

E104

Error: template: cilium/templates/agent/daemonset.yaml:30:15: executing

"cilium/templates/agent/daemonset.yaml" at <semverCompare "<1.30-0" (include "common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- bitnami/cilium (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/cilium_1789251449/0000>)

E105

Error: template: concourse/templates/worker/rolebinding.yaml:27:22: executing

"concourse/templates/worker/rolebinding.yaml" at <semverCompare "<1.25-0" (include "common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- bitnami/concourse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/concourse_1789251532/0000>)

E106

```
Error: template: metallb/templates/speaker/rbac.yaml:44:14: executing
"metallb/templates/speaker/rbac.yaml" at <include "common.capabilities.psp.supported" .>: error
calling include: template: metallb/charts/common/templates/_capabilities.tpl:131:32: executing
"common.capabilities.psp.supported" at <semverCompare "<1.25-0" $kubeVersion>: error calling
semverCompare: invalid semantic version
```

```
- bitnami/metallb (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/metallb_1789252639/0000>)
```

E107

```
Error: template: rabbitmq-cluster-operator/templates/messaging-topology-operator/validating-webhook-
configuration.yaml:14:13: executing "rabbitmq-cluster-operator/templates/messaging-topology-
operator/validating-webhook-configuration.yaml" at <genSignedCert (include
"rmqco.msgTopologyOperator.fullname" .) nil (list (printf "%s.%s.svc" (include
"rmqco.msgTopologyOperator.webhook.fullname" .) (include "common.names.namespace" .)) (printf
"%s.%s.svc.%s" (include "rmqco.msgTopologyOperator.webhook.fullname" .) (include
"common.names.namespace" .) .Values.clusterDomain)) 365 $ca>: error calling genSignedCert: error
creating certificate: x509: "hypothesis-rabbitmq-messaging-topology-operator-
webhook.default.svc.\u0080" cannot be encoded as an IA5String
```

```
- bitnami/rabbitmq-cluster-operator (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/rabbitmq-cluster-operator_1789253208/0000>)
```

E108

```
chart rendered no resources (use allow_empty explicitly)
```

```
- bitnami/kube-prometheus/charts/kube-prometheus-crds (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/kube-prometheus-crds_1789252451/0000>)
- bitnami/kube-prometheus/charts/kube-prometheus-crds (robustness; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/kube-prometheus-crds_1789252451/0000>)
```

E109

```
duplicate resource: ('rbac.authorization.k8s.io/v1', 'Role', None, 'hypothesis-clickhouse-operator')
```

```
- bitnami/clickhouse-operator (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/clickhouse-operator_1789251497/0000>)
```

E110

```
invalid rendered YAML: more indented follow up line than first in a block scalar
  in "<unicode string>", line 474, column 15:
      set -o errexit
      ^ (line: 474)
```

```
- bitnami/zipkin (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/zipkin_1789253576/0000>)
- bitnami/zipkin (robustness; failed) (<bitnami-runs/bitnami-
charts_1789251211/runs/zipkin_1789253576/0000>)
```

E111

The test tool could not convert a YAML-tagged value to JSON. See this chart's reproducing values. This diagnostic alone does not establish a chart defect.

- bitnami/apache (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/apache_1789251228/0000>)
- bitnami/grafana-k6-operator (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/grafana-k6-operator_1789252042/0000>)
- bitnami/kong (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kong_1789252404/0000>)
- bitnami/redis-cluster (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/redis-cluster_1789253276/0000>)
- bitnami/scylladb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/scylladb_1789253311/0000>)
- bitnami/zookeeper (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/zookeeper_1789253580/0000>)

E112

level=INFO msg="warning: destination for kube-state-metrics.rbac.rules is a table. Ignoring non-table value ([])"

Error: YAML parse error on kube-prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/kube-prometheus (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/kube-prometheus_1789252419/0000>)

E113

resource has no metadata.name

- bitnami/keycloak (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/keycloak_1789252350/0000>)
- bitnami/keydb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/keydb_1789252362/0000>)
- bitnami/postgresql-ha (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/postgresql-ha_1789253152/0000>)
- bitnami/wildfly (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789251211/runs/wildfly_1789253553/0000>)

Charts

bitnami/airflow

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/airflow_1789251228/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: E074 (#e074)

Reproducing values (known-inputs):

```
{
  "executor": ""
}
```

bitnami/apache

Result: FAIL | Status: failed

Attempts: 411 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/apache_1789251228/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 119

Phase robustness: failed | Attempts: 292

Errors: E111 (#e111), E001 (#e001)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "="
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": ":"
  }
}
```

bitnami/apisix

Result: FAIL | Status: failed

Attempts: 83 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/apisix_1789251228/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 52

Phase robustness: time-limit | Attempts: 31

Errors: E002 (#e002)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/appsmith

Result: FAIL | Status: failed
Attempts: 136 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/appsmith_1789251228/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 35

Phase robustness: passed | Attempts: 101

Errors: E003 (#e003)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/argo-cd

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/argo-cd_1789251295/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: E004 (#e004)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/argo-workflows

Result: FAIL | Status: failed
Attempts: 130 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/argo-workflows_1789251302/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 29

Phase robustness: passed | Attempts: 101

Errors: E005 (#e005)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/aspnet-core

Result: FAIL | Status: failed

Attempts: 186 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/aspnet-core_1789251350/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 85

Phase robustness: passed | Attempts: 101

Errors: E075 (#e075)

Reproducing values (known-inputs):

```
{
  "extraVolumes": [
    null
  ]
}
```

bitnami/cadvisor

Result: FAIL | Status: failed

Attempts: 126 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/cadvisor_1789251373/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 25

Phase robustness: passed | Attempts: 101

Errors: E076 (#e076)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/cassandra

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/cassandra_1789251382/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: E006 (#e006)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/cert-manager

Result: FAIL | Status: failed
Attempts: 170 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/cert-manager_1789251391/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 69

Phase robustness: passed | Attempts: 101

Errors: E007 (#e007)

Reproducing values (known-inputs):

```
{  
  "leaderElection": {  
    "namespace": "\u001f"  
  }  
}
```

bitnami/chainloop

Result: FAIL | Status: failed
Attempts: 165 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/chainloop_1789251406/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 64

Phase robustness: passed | Attempts: 101

Errors: E077 (#e077)

Reproducing values (known-inputs):

```
{
  "development": false
}
```

bitnami/cilium

Result: FAIL | Status: failed

Attempts: 187 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/cilium_1789251449/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 86

Phase robustness: passed | Attempts: 101

Errors: E104 (#e104)

Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```

bitnami/clickhouse

Result: FAIL | Status: failed

Attempts: 193 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/clickhouse_1789251452/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 92

Phase robustness: passed | Attempts: 101

Errors: E008 (#e008)

Reproducing values (known-inputs):

```
{
  "startdbScriptsSecret": ":"
}
```

bitnami/clickhouse-operator

Result: FAIL | Status: failed
Attempts: 157 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/clickhouse-operator_1789251497/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 56

Phase robustness: passed | Attempts: 101

Errors: E109 (#e109)

Reproducing values (known-inputs):

```
{
  "watchNamespaces": [
    null,
    null
  ]
}
```

bitnami/cloudnative-pg

Result: FAIL | Status: failed
Attempts: 152 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/cloudnative-pg_1789251513/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: E009 (#e009)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ">"
}
```

bitnami/common

Result: N/A | Status: skipped-library
Attempts: N/A | Remaining iterations: unknown
Coverage: not a standalone application
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/common_1789251532/0000

Filtering applied: False
Chart did not enter finite permutation testing

bitnami/concourse

Result: FAIL | Status: failed
Attempts: 158 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/concourse_1789251532/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 57

Phase robustness: passed | Attempts: 101

Errors: E105 (#e105)

Reproducing values (known-inputs):

```
{  
  "kubeVersion": ":"  
}
```

bitnami/consul

Result: FAIL | Status: failed
Attempts: 140 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/consul_1789251533/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: E010 (#e010)

Reproducing values (known-inputs):

```
{  
  "existingConfigmap": "\u001f"  
}
```

bitnami/contour

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/contour_1789251558/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E011 (#e011)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/deepspeed

Result: FAIL | Status: failed

Attempts: 101 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/deepspeed_1789251584/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 12

Phase robustness: time-limit | Attempts: 89

Errors: E012 (#e012)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/discourse

Result: FAIL | Status: failed

Attempts: 162 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/discourse_1789251597/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: E013 (#e013)

Reproducing values (known-inputs):

```
{
  "service": {
    "annotations": {
      "": []
    }
  }
}
```

bitnami/dremio

Result: FAIL | Status: failed
Attempts: 133 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/dremio_1789251625/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 32

Phase robustness: passed | Attempts: 101

Errors: E014 (#e014)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/drupal

Result: FAIL | Status: failed
Attempts: 252 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/drupal_1789251652/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 29

Phase robustness: failed | Attempts: 223

Errors: E078 (#e078), E015 (#e015)

Reproducing values (known-inputs):

```
{
  "mariadb": {
    "architecture": ""
  }
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": "\u001f"
  }
}
```

bitnami/ejbca

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/ejbca_1789251723/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: E016 (#e016)

Reproducing values (known-inputs):

```
{  
  "ejbcaKeystoreExistingSecret": "\u001f"  
}
```

bitnami/elasticsearch

Result: FAIL | Status: failed
Attempts: 180 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/elasticsearch_1789251725/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 79

Phase robustness: passed | Attempts: 101

Errors: E017 (#e017)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/envoy-gateway

Result: FAIL | Status: failed
Attempts: 157 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/envoy-gateway_1789251751/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 56

Phase robustness: passed | Attempts: 101

Errors: E018 (#e018)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/etcd

Result: N/A | Status: time-limit
Attempts: 105 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/etcd_1789251756/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: time-limit | Attempts: 95

Phase robustness: time-limit | Attempts: 10

bitnami/external-dns

Result: FAIL | Status: failed
Attempts: 148 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/external-dns_1789251819/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 47

Phase robustness: passed | Attempts: 101

Errors: E019 (#e019)

Reproducing values (known-inputs):

```
{
  "interval": "\u001f"
}
```

bitnami/flink

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/flink_1789251853/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E020 (#e020)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": []
  }
}
```

bitnami/fluent-bit

Result: FAIL | Status: failed

Attempts: 245 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/fluent-bit_1789251880/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 144

Phase robustness: passed | Attempts: 101

Errors: E079 (#e079)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

bitnami/fluentd

Result: FAIL | Status: failed

Attempts: 129 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/fluentd_1789251891/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 28

Phase robustness: passed | Attempts: 101

Errors: E021 (#e021)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```


bitnami/flux

Result: FAIL | Status: failed
Attempts: 119 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/flux_1789251919/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 18

Phase robustness: passed | Attempts: 101

Errors: E022 (#e022)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/ghost

Result: FAIL | Status: failed
Attempts: 396 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/ghost_1789251929/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 154

Phase robustness: failed | Attempts: 242

Errors: E023 (#e023), E098 (#e098)

Reproducing values (known-inputs):

```
{
  "service": {
    "annotations": {
      "": []
    }
  }
}
```

Reproducing values (robustness):

```
{
  "": {
    "\u001e70\u0033a\u0033a\u00315o\u0035e \u00337i\u00332\u0032c\u00347\u0032a\u00359n\u0031d\u00317\u00355v\u0031f\n\u0031c\u00318\u00326\u0035fo\u00336\u00319\u00330\u00320k\u0000e8\u0035a\u0032e\u0033a\u0032a\u00339\u00331\u00324 \u00316t\u0031d\u00355\u00333\u00323\u0033b\u0032a\u0035eh\u0033c\u00353\u00332\u00326\u00333\u00318\u00332e\u00347\u00323\u00330\u00326\u0032c\u0034e \u00322\u0033c\u0033b\u00331\u00318h\u0035a\u0034e\u00359\u0031c\u00323\u00332\u00345i\u00326\u00332\u00323\u00330\u00324v\u0033b\u0034de\u0033a\u0032d\u00333\u0032a\u00330-
```

```
m\u00322i\u00345n\u00316\u0033a\u0031e\u00332\u0032f\u00330d\u00335\u0033c\u0031f\u00359\u00329\u0033c\u00318\u00333
\u0031e\u00325\u00331\u00333\u0032dr\u0031b\u00317\u00318e\u00359p\u00360r\u0033c\u0031e\u0033b\u0032d\u00317e\u0033
a\u00320\u00323\u0035fs\u00318\u00347\u00333\u0034d\u0031d\u00349e\u00349\u00325\u0032f\u0031e\u00332\u0035a\u0032c\u0035c\u0031f9\u0032c\u0034e\u0034e\u0031f\u00316\u00347\u00324t\u0034d\u0032c\u00324\u00353\u0033c\u0032d\u00358\u00345i\u0032a\u00331n\u00360g\u00334\u00349 \u0034f\u00349\u00345c\u0032c\u0031fh\u00361a\u0032b\u0033b\u0032f\u00358o
\u0032b\u0031f\u00316\u0034d\u00319\u0031d\u00349s\u00317": null
}
}
```

bitnami/gitea

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/gitea_1789251952/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: E024 (#e024)

Reproducing values (known-inputs):

```
{
  "smtpExistingSecret": "\u001f"
}
```

bitnami/gitlab-runner

Result: FAIL | Status: failed
Attempts: 213 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/gitlab-runner_1789251987/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 112

Phase robustness: passed | Attempts: 101

Errors: E025 (#e025)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/grafana

Result: FAIL | Status: failed
Attempts: 197 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana_1789252005/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 96

Phase robustness: passed | Attempts: 101

Errors: E100 (#e100)

Reproducing values (known-inputs):

```
{
  "dashboardsConfigMaps": [
    null
  ]
}
```

bitnami/grafana-alloy

Result: FAIL | Status: failed
Attempts: 239 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana-alloy_1789252023/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 138

Phase robustness: passed | Attempts: 101

Errors: E026 (#e026)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/grafana-k6-operator

Result: FAIL | Status: failed
Attempts: 187 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana-k6-operator_1789252042/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 86

Phase robustness: passed | Attempts: 101

Errors: E111 (#e111)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "="  
}
```

bitnami/grafana-loki

Result: FAIL | Status: failed

Attempts: 149 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana-loki_1789252062/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 48

Phase robustness: passed | Attempts: 101

Errors: E027 (#e027)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/grafana-mimir

Result: FAIL | Status: failed

Attempts: 125 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana-mimir_1789252066/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 24

Phase robustness: passed | Attempts: 101

Errors: E080 (#e080)

Reproducing values (known-inputs):

```
{  
  "memcachedchunks": {  
    "architecture": ""  
  }  
}
```

bitnami/grafana-operator

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana-operator_1789252073/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: E028 (#e028)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/grafana-tempo

Result: FAIL | Status: failed
Attempts: 138 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/grafana-tempo_1789252105/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 37

Phase robustness: passed | Attempts: 101

Errors: E029 (#e029)

Reproducing values (known-inputs):

```
{
  "tempo": {
    "configuration": "\u001f"
  }
}
```

bitnami/haproxy

Result: FAIL | Status: failed
Attempts: 193 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/haproxy_1789252206/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 92

Phase robustness: passed | Attempts: 101

Errors: E030 (#e030)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/harbor

Result: FAIL | Status: failed

Attempts: 137 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/harbor_1789252208/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: E031 (#e031)

Reproducing values (known-inputs):

```
{
  "existingSecret": "\u001f"
}
```

bitnami/influxdb

Result: FAIL | Status: failed

Attempts: 344 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/influxdb_1789252221/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 243

Phase robustness: passed | Attempts: 101

Errors: E032 (#e032)

Reproducing values (known-inputs):

```
{
  "pdb": {
    "maxUnavailable": "\u001f"
  }
}
```

bitnami/jaeger

Result: FAIL | Status: failed
Attempts: 207 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/jaeger_1789252233/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 106

Phase robustness: passed | Attempts: 101

Errors: E081 (#e081)

Reproducing values (known-inputs):

```
{
  "collector": {
    "resourcesPreset": ""
  }
}
```

bitnami/janusgraph

Result: FAIL | Status: failed
Attempts: 139 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/janusgraph_1789252257/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 38

Phase robustness: passed | Attempts: 101

Errors: E033 (#e033)

Reproducing values (known-inputs):

```
{
  "existingConfigmap": "\u001f"
}
```

bitnami/jenkins

Result: FAIL | Status: failed
Attempts: 405 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/jenkins_1789252283/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 136

Phase robustness: failed | Attempts: 269

Errors: E082 (#e082), E096 (#e096)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

Reproducing values (robustness):

```
{
  "": {
    "\u1e70\u033a\u033a\u0315o\u035e \u0337i\u0332\u032c\u0347\u032a\u0359n\u031d\u0317\u0355v\u031f
\u031c\u0318\u0326\u035fo\u0336\u0319\u0330\u0320k\u00e8\u035a\u032e\u033a\u032a\u0339\u0331\u0324 \
\u0316t\u031d\u0355\u0333\u0323\u033b\u032a\u035eh\u033c\u0353\u0332\u0326\u0333\u0318\u0332e\u0347\u
0323\u0330\u0326\u032c\u034e \u0322\u033c\u033b\u0331\u0318h\u035a\u034e\u0359\u031c\u0323\u0332\u03
45i\u0326\u0332\u0323\u0330\u0324v\u033b\u034de\u033a\u032d\u0333\u032a\u0330-
m\u0322i\u0345n\u0316\u033a\u031e\u0332\u032f\u0330d\u0335\u033c\u031f\u0359\u0329\u033c\u0318\u0333
\u031e\u0325\u0331\u0333\u032dr\u031b\u0317\u0318e\u0359p\u0360r\u033c\u031e\u033b\u032d\u0317e\u033
a\u0320\u0323\u035fs\u0318\u0347\u0333\u034d\u031d\u0349e\u0349\u0325\u032f\u031e\u0332\u035a\u032c\
\u035c\u01f9\u032c\u034e\u034e\u031f\u0316\u0347\u0324t\u034d\u032c\u0324\u0353\u033c\u032d\u0358\u03
45i\u032a\u0331n\u0360g\u0334\u0349 \u034f\u0349\u0345c\u032c\u031fh\u0361a\u032b\u033b\u032f\u0358o
\u032b\u031f\u0316\u034d\u0319\u031d\u0349s\u0317": null
  }
}
```

bitnami/jupyterhub

Result: FAIL | Status: failed

Attempts: 126 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/jupyterhub_1789252291/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 25

Phase robustness: passed | Attempts: 101

Errors: E083 (#e083)

Reproducing values (known-inputs):

```
{
  "singleuser": {
    "resourcesPreset": ""
  }
}
```


bitnami/kafka

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kafka_1789252297/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 40

Phase robustness: passed | Attempts: 101

Errors: E034 (#e034)

Reproducing values (known-inputs):

```
{  
  "dnsPolicy": "\u001f"  
}
```

bitnami/keycloak

Result: FAIL | Status: failed
Attempts: 240 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/keycloak_1789252350/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 139

Phase robustness: passed | Attempts: 101

Errors: E113 (#e113)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": "0"  
}
```

bitnami/keydb

Result: FAIL | Status: failed
Attempts: 127 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/keydb_1789252362/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 26

Phase robustness: passed | Attempts: 101

Errors: E113 (#e113)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": "0"
}
```

bitnami/kibana

Result: FAIL | Status: failed

Attempts: 317 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kibana_1789252366/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 216

Phase robustness: passed | Attempts: 101

Errors: E101 (#e101)

Reproducing values (known-inputs):

```
{
  "ingress": {
    "enabled": true,
    "extraHosts": [
      null
    ]
  }
}
```

bitnami/kong

Result: FAIL | Status: failed

Attempts: 142 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kong_1789252404/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 41

Phase robustness: passed | Attempts: 101

Errors: E111 (#e111)

Reproducing values (known-inputs):

```
{
  "terminationGracePeriodSeconds": "="
}
```

bitnami/kube-arangodb

Result: FAIL | Status: failed

Attempts: 163 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kube-arangodb_1789252412/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 62

Phase robustness: passed | Attempts: 101

Errors: E035 (#e035)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/kube-prometheus

Result: FAIL | Status: failed

Attempts: 119 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kube-prometheus_1789252419/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 18

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/kube-prometheus/charts/kube-prometheus-crds

Result: FAIL | Status: failed

Attempts: 2 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kube-prometheus-crds_1789252451/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 1

Phase robustness: failed | Attempts: 1

Errors: E108 (#e108)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```

bitnami/kube-state-metrics

Result: FAIL | Status: failed

Attempts: 118 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kube-state-metrics_1789252452/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 17

Phase robustness: passed | Attempts: 101

Errors: E084 (#e084)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/kuberay

Result: FAIL | Status: failed

Attempts: 132 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kuberay_1789252452/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 31

Phase robustness: passed | Attempts: 101

Errors: E036 (#e036)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": []
  }
}
```

bitnami/kubernetes-event-exporter

Result: FAIL | Status: failed
Attempts: 331 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/kubernetes-event-exporter_1789252461/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 230

Phase robustness: passed | Attempts: 101

Errors: E037 (#e037)

Reproducing values (known-inputs):

```
{
  "image": {
    "digest": "\u001f"
  }
}
```

bitnami/logstash

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/logstash_1789252473/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 40

Phase robustness: passed | Attempts: 101

Errors: E038 (#e038)

Reproducing values (known-inputs):

```
{
  "existingConfiguration": "\u001f"
}
```

bitnami/mariadb

Result: FAIL | Status: failed
Attempts: 127 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mariadb_1789252495/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 5

Phase robustness: failed | Attempts: 122

Errors: E085 (#e085)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

Reproducing values (robustness):

```
{
  "": [],
  "architecture": ""
}
```

bitnami/mariadb-galera

Result: FAIL | Status: failed

Attempts: 90 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mariadb-galera_1789252506/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 68

Phase robustness: time-limit | Attempts: 22

Errors: E039 (#e039)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/mastodon

Result: FAIL | Status: failed

Attempts: 200 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mastodon_1789252506/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 99

Phase robustness: passed | Attempts: 101

Errors: E040 (#e040)

Reproducing values (known-inputs):

```
{
```

```
"extraDeploy": [  
  [  
]  
]  
}
```

bitnami/matomo

Result: FAIL | Status: failed
Attempts: 134 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/matomo_1789252549/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: E041 (#e041)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/memcached

Result: FAIL | Status: failed
Attempts: 161 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/memcached_1789252601/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 60

Phase robustness: passed | Attempts: 101

Errors: E086 (#e086)

Reproducing values (known-inputs):

```
{  
  "architecture": ""  
}
```

bitnami/metallb

Result: FAIL | Status: failed
Attempts: 225 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/metallb_1789252639/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 124

Phase robustness: passed | Attempts: 101

Errors: E106 (#e106)

Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```

bitnami/metrics-server

Result: FAIL | Status: failed

Attempts: 248 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/metrics-server_1789252645/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 147

Phase robustness: passed | Attempts: 101

Errors: E042 (#e042)

Reproducing values (known-inputs):

```
{
  "terminationGracePeriodSeconds": "\u001f"
}
```

bitnami/milvus

Result: N/A | Status: time-limit

Attempts: 30 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/milvus_1789252691/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: time-limit | Attempts: 23

Phase robustness: time-limit | Attempts: 7

bitnami/mlflow

Result: FAIL | Status: failed

Attempts: 193 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mlflow_1789252697/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 66

Phase robustness: failed | Attempts: 127

Errors: E044 (#e044), E043 (#e043)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

Reproducing values (robustness):

```
{
  "nameOverride": "\u001f",
  "": []
}
```

bitnami/mongodb

Result: FAIL | Status: failed

Attempts: 87 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mongodb_1789252761/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 43

Phase robustness: time-limit | Attempts: 44

Errors: E046 (#e046)

Reproducing values (known-inputs):

```
{
  "configuration": "\u001f"
}
```

bitnami/mongodb-sharded

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mongodb-sharded_1789252809/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: E045 (#e045)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/moodle

Result: FAIL | Status: failed
Attempts: 184 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/moodle_1789252874/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 83

Phase robustness: passed | Attempts: 101

Errors: E047 (#e047)

Reproducing values (known-inputs):

```
{
  "existingSecret": "\u001f"
}
```

bitnami/multus-cni

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/multus-cni_1789252902/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: E048 (#e048)

Reproducing values (known-inputs):

```
{
  "CNIMountPath": ">"
}
```

bitnami/mysql

Result: FAIL | Status: failed
Attempts: 234 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/mysql_1789252935/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 133

Phase robustness: passed | Attempts: 101

Errors: E049 (#e049)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/nats

Result: FAIL | Status: failed

Attempts: 152 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/nats_1789252944/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: E087 (#e087)

Reproducing values (known-inputs):

```
{
  "resourceType": ""
}
```

bitnami/neo4j

Result: FAIL | Status: failed

Attempts: 188 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/neo4j_1789252975/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 87

Phase robustness: passed | Attempts: 101

Errors: E102 (#e102)

Reproducing values (known-inputs):

```
{
  "extraContainerPorts": [
    null
  ]
}
```

bitnami/nessie

Result: FAIL | Status: failed
Attempts: 252 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/nessie_1789252998/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 151

Phase robustness: passed | Attempts: 101

Errors: E050 (#e050)

Reproducing values (known-inputs):

```
{
  "existingConfigmap": "\u001f"
}
```

bitnami/nginx

Result: FAIL | Status: failed
Attempts: 325 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/nginx_1789253009/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 81

Phase robustness: failed | Attempts: 244

Errors: E052 (#e052), E051 (#e051)

Reproducing values (known-inputs):

```
{
  "existingContextEventsConfigmaps": [
    "\u001f"
  ]
}
```

Reproducing values (robustness):

```
{
  "contextIncludes": {
    "events": "\u001f",
    "": []
  }
}
```

bitnami/node-exporter

Result: FAIL | Status: failed
Attempts: 190 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/node-exporter_1789253016/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 89

Phase robustness: passed | Attempts: 101

Errors: E053 (#e053)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/oauth2-proxy

Result: FAIL | Status: failed
Attempts: 130 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/oauth2-proxy_1789253043/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 29

Phase robustness: passed | Attempts: 101

Errors: E088 (#e088)

Reproducing values (known-inputs):

```
{  
  "redis": {  
    "architecture": ""  
  }  
}
```

bitnami/odoo

Result: FAIL | Status: failed
Attempts: 128 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/odoo_1789253062/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 27

Phase robustness: passed | Attempts: 101

Errors: E089 (#e089)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/opensearch

Result: FAIL | Status: failed

Attempts: 183 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/opensearch_1789253064/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 82

Phase robustness: passed | Attempts: 101

Errors: E090 (#e090)

Reproducing values (known-inputs):

```
{  
  "ingest": {  
    "resourcesPreset": ""  
  }  
}
```

bitnami/parse

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/parse_1789253081/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E054 (#e054)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```

bitnami/phpmyadmin

Result: FAIL | Status: failed
Attempts: 301 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/phpmyadmin_1789253091/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 200

Phase robustness: passed | Attempts: 101

Errors: E055 (#e055)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/pinniped

Result: FAIL | Status: failed
Attempts: 160 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/pinniped_1789253122/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 59

Phase robustness: passed | Attempts: 101

Errors: E056 (#e056)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/postgresql

Result: FAIL | Status: failed
Attempts: 116 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/postgresql_1789253136/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 15

Phase robustness: passed | Attempts: 101

Errors: E091 (#e091)

Reproducing values (known-inputs):

```
{
  "psp": {
    "create": true
  }
}
```

bitnami/postgresql-ha

Result: FAIL | Status: failed

Attempts: 156 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/postgresql-ha_1789253152/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 55

Phase robustness: passed | Attempts: 101

Errors: E113 (#e113)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/prometheus

Result: FAIL | Status: failed

Attempts: 318 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/prometheus_1789253175/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 75

Phase robustness: failed | Attempts: 243

Errors: E057 (#e057), E058 (#e058)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "extraDeploy": [
    []
  ]
}
```



```
]
}
```

bitnami/pytorch

Result: FAIL | Status: failed
Attempts: 143 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/pytorch_1789253187/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 42

Phase robustness: passed | Attempts: 101

Errors: E092 (#e092)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

bitnami/rabbitmq

Result: FAIL | Status: failed
Attempts: 539 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/rabbitmq_1789253191/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 274

Phase robustness: failed | Attempts: 265

Errors: E099 (#e099), E059 (#e059)

Reproducing values (known-inputs):

```
{
  "args": [
    {
      "\u1e70\u033a\u033a\u0315\u035e \u0337i\u0332\u032c\u0347\u032a\u0359n\u031d\u0317\u0355v\u031f\u031c\u0318\u0326\u035fo\u0336\u0319\u0330\u0320k\u00e8\u035a\u032e\u033a\u032a\u0339\u0331\u0324\u0316t\u031d\u0355\u0333\u0323\u033b\u032a\u035eh\u033c\u0353\u0332\u0326\u0333\u0318\u0332e\u0347\u0323\u0330\u0326\u032c\u034e \u0322\u033c\u033b\u0331\u0318h\u035a\u034e\u0359\u031c\u0323\u0332\u0345i\u0326\u0332\u0323\u0330\u0324v\u033b\u034de\u033a\u032d\u0333\u032a\u0330-m\u0322i\u0345n\u0316\u033a\u031e\u0332\u032f\u0330d\u0335\u033c\u031f\u0359\u0329\u033c\u0318\u0333\u031e\u0325\u0331\u0333\u032dr\u031b\u0317\u0318e\u0359p\u0360r\u033c\u031e\u033b\u032d\u0317e\u033a\u0320\u0323\u035fs\u0318\u0347\u0333\u034d\u031d\u0349e\u0349\u0325\u032f\u031e\u0332\u035a\u032c\u035c\u031f9\u032c\u034e\u034e\u031f\u0316\u0347\u0324t\u034d\u032c\u0324\u0353\u033c\u032d\u0358\u0345i\u032a\u0331n\u0360g\u0334\u0349 \u034f\u0349\u0345c\u032c\u031fh\u0361a\u032b\u033b\u032f\u0358o\u032b\u031f\u0316\u034d\u0319\u031d\u0349s\u0317": null
    }
  ]
}
```

```
}
```

Reproducing values (robustness):

```
{
  "": [],
  "auth": {
    "username": "\u001f"
  }
}
```

bitnami/rabbitmq-cluster-operator

Result: FAIL | Status: failed

Attempts: 173 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/rabbitmq-cluster-operator_1789253208/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 72

Phase robustness: passed | Attempts: 101

Errors: E107 (#e107)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u0080"
}
```

bitnami/redis

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/redis_1789253220/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 5

Phase robustness: failed | Attempts: 140

Errors: E093 (#e093)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

Reproducing values (robustness):

```
{
  "": [],
```

```
"architecture": ""
}
```

bitnami/redis-cluster

Result: FAIL | Status: failed
Attempts: 150 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/redis-cluster_1789253276/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 49

Phase robustness: passed | Attempts: 101

Errors: E111 (#e111)

Reproducing values (known-inputs):

```
{
  "existingSecret": "="
}
```

bitnami/redmine

Result: FAIL | Status: failed
Attempts: 304 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/redmine_1789253293/0000](#)

```
Filtering applied: True
Generation order only; original-schema cases run last, not removed
```

Phase known-inputs: failed | Attempts: 62

Phase robustness: failed | Attempts: 242

Errors: E060 (#e060), E097 (#e097)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "\u007f\u003a\u003a\u00315o\u0035e \u0037i\u0032c\u0034\u0032a\u00359n\u0031d\u00317\u00355v\u0031f\u0031c\u00318\u00326\u0035fo\u0036\u00319\u00330\u00320k\u000e8\u0035a\u0032e\u0033a\u0032a\u00339\u00331\u00324 \u00316t\u0031d\u00355\u00333\u00323\u0033b\u0032a\u0035eh\u0033c\u00353\u00332\u00326\u00333\u00318\u00332e\u00347\u00323\u00330\u00326\u0032c\u0034e \u00322\u0033c\u0033b\u00331\u00318h\u0035a\u0034e\u00359\u0031c\u00323\u00332\u00345i\u00326\u00332\u00323\u00330\u00324v\u0033b\u0034de\u0033a\u0032d\u00333\u0032a\u00330-m\u00322i\u00345n\u00316\u0033a\u0031e\u00332\u0032f\u00330d\u00335\u0033c\u0031f\u00359\u00329\u0033c\u00318\u00333\u0031e\u00325\u00331\u00333\u0032dr\u0031b\u00317\u00318e\u00359p\u00360r\u0033c\u0031e\u0033b\u0032d\u00317e\u0033a\u00320\u00323\u0035fs\u00318\u00347\u00333\u0034d\u0031d\u00349e\u00349\u00325\u0032f\u0031e\u00332\u0035a\u0032c\u0032
```

```
u035c\u01f9\u032c\u034e\u034e\u031f\u0316\u0347\u0324t\u034d\u032c\u0324\u0353\u033c\u032d\u0358\u03
45i\u032a\u0331n\u0360g\u0334\u0349 \u034f\u0349\u0345c\u032c\u031fh\u0361a\u032b\u033b\u032f\u0358o
\u032b\u031f\u0316\u034d\u0319\u031d\u0349s\u0317": null
}
```

bitnami/schema-registry

Result: FAIL | Status: failed
Attempts: 172 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/schema-registry_1789253309/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 71

Phase robustness: passed | Attempts: 101

Errors: E103 (#e103)

Reproducing values (known-inputs):

```
{
  "httpRoutes": [
    null
  ]
}
```

bitnami/scylladb

Result: FAIL | Status: failed
Attempts: 247 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/scylladb_1789253311/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 146

Phase robustness: passed | Attempts: 101

Errors: E111 (#e111)

Reproducing values (known-inputs):

```
{
  "initDBConfigMap": "="
}
```

bitnami/sealed-secrets

Result: FAIL | Status: failed
Attempts: 164 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/sealed-secrets_1789253315/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 63

Phase robustness: passed | Attempts: 101

Errors: E094 (#e094)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/seaweedfs

Result: FAIL | Status: failed

Attempts: 135 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/seaweedfs_1789253341/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: E061 (#e061)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/solr

Result: FAIL | Status: failed

Attempts: 166 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/solr_1789253352/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 65

Phase robustness: passed | Attempts: 101

Errors: E062 (#e062)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": ""  
}
```

bitnami/sonarqube

Result: FAIL | Status: failed
Attempts: 128 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/sonarqube_1789253377/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 27

Phase robustness: passed | Attempts: 101

Errors: E063 (#e063)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/spark

Result: FAIL | Status: failed
Attempts: 220 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/spark_1789253392/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 119

Phase robustness: passed | Attempts: 101

Errors: E064 (#e064)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/superset

Result: FAIL | Status: failed
Attempts: 137 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/superset_1789253412/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: E065 (#e065)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/tensorflow-resnet

Result: FAIL | Status: failed

Attempts: 179 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/tensorflow-resnet_1789253441/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 78

Phase robustness: passed | Attempts: 101

Errors: E066 (#e066)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/thanos

Result: FAIL | Status: failed

Attempts: 132 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/thanos_1789253463/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 31

Phase robustness: passed | Attempts: 101

Errors: E067 (#e067)

Reproducing values (known-inputs):

```
{
  "bucketCacheConfig": "\u001f"
}
```

bitnami/tomcat

Result: FAIL | Status: failed
Attempts: 144 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/tomcat_1789253463/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 43

Phase robustness: passed | Attempts: 101

Errors: E068 (#e068)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/valkey

Result: FAIL | Status: failed
Attempts: 140 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/valkey_1789253482/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: E070 (#e070)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/valkey-cluster

Result: FAIL | Status: failed
Attempts: 134 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/valkey-cluster_1789253483/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: E069 (#e069)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/vault

Result: FAIL | Status: failed

Attempts: 167 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/vault_1789253486/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 66

Phase robustness: passed | Attempts: 101

Errors: E071 (#e071)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/victoriametrics

Result: FAIL | Status: failed

Attempts: 171 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/victoriametrics_1789253519/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 70

Phase robustness: passed | Attempts: 101

Errors: E072 (#e072)

Reproducing values (known-inputs):

```
{
  "loggerFormat": "\u001f"
}
```

bitnami/whereabouts

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/whereabouts_1789253539/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E095 (#e095)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/wildfly

Result: FAIL | Status: failed
Attempts: 145 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/wildfly_1789253553/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: E113 (#e113)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/wordpress

Result: FAIL | Status: failed
Attempts: 213 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/wordpress_1789253554/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 112

Phase robustness: passed | Attempts: 101

Errors: E073 (#e073)

Reproducing values (known-inputs):

```
{  
  "apacheConfiguration": "\u001f"  
}
```

bitnami/zipkin

Result: FAIL | Status: failed

Attempts: 2 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/zipkin_1789253576/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 1

Phase robustness: failed | Attempts: 1

Errors: E110 (#e110)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```

bitnami/zookeeper

Result: FAIL | Status: failed

Attempts: 133 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/zookeeper_1789253580/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 32

Phase robustness: passed | Attempts: 101

Errors: E111 (#e111)

Reproducing values (known-inputs):

```
{  
  "dataLogDir": "="  
}
```