

Bitnami Helm chart scan

Visited all 115 discovered charts with --filter, four workers, and a five-minute test budget per chart. No scan-wide deadline was imposed.

Recorded 19,612 test attempts in 42.3 minutes. Attempts include shrinking and repeated inputs; they are not counts of unique inputs or confirmed bugs.

Findings: 113 failed; 1 skipped-library; 1 time-limit.

known-inputs: 113 failed; 1 time-limit.

robustness: 12 failed; 96 passed; 6 time-limit.

Observed failures include chart validation rejections, rendering failures, and possible tooling limitations. Inferred inputs are not an authoritative chart contract. Findings need triage before being called chart defects; time-limited coverage remains incomplete.

Checks: dependency build in isolated copies, Helm lint, Helm template with values-schema checks, and built-in manifest checks. External kubeconform/kubesecc validation was not configured.

Source: third_party/bitnami-charts at 6a8cccf3c29a1faabf0c34c8276a09ed14f3c5b3; Helm 4.3.0. Per-worker dependency caches are isolated. Each primary chart has one dedicated job; nested results from parent jobs are retained separately and excluded from totals.

Combined PDF (bitnami.pdf) · Aggregate data (bitnami-runs/bitnami-charts_1789260948/scan.json.gz) · Raw logs and provenance (bitnami-runs/bitnami-charts_1789260948/README.md)

Directory: third_party/bitnami-charts
Started (Unix epoch): 1789260967
Elapsed: 2539.00 seconds
Charts discovered: 115
Scan status: completed
Discovery complete: True
Unstarted charts: 0

Results describe the tested sample; they do not prove chart correctness.
Baseline-only, skipped, blocked, and incomplete charts are not property-test passes.

Status counts

```
{
  "failed": 113,
  "skipped-library": 1,
  "time-limit": 1
}
```

Settings

```
{
  "max_examples": 100,
  "filter": true,
  "fail": false,
  "permutations": null,
  "chart_timeout_seconds": 300.0,
  "scan_timeout_seconds": null,
  "helm": "Helm 4.3.0",
  "seed": 0,
  "build_dependencies": true,
```

```
"values": "values.yaml",
"clone_timeout_seconds": 180,
"workers": 4,
"external_conformity": false
}
```

Errors

115 distinct diagnostics across 125 occurrences; 10 repeats grouped.
Matching diagnostics do not establish a shared root cause.

E001

Error: YAML parse error on apache/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/apache (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/apache_1789260968/0000>)

E002

Error: YAML parse error on apache/templates/svc.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/apache (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/apache_1789260968/0000>)

E003

Error: YAML parse error on apisix/templates/control-plane/api-token-secret.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/apixix (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/apixix_1789260968/0000>)

E004

Error: YAML parse error on appsmith/templates/backend/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/appsmith (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/appsmith_1789260968/0000>)

E005

Error: YAML parse error on argo-cd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/argo-cd (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/argo-cd_1789261025/0000>)

E006

Error: YAML parse error on argo-workflows/templates/controller/deployment.yaml: error converting YAML to JSON: yaml: line 30: mapping values are not allowed in this context

- bitnami/argo-workflows (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/argo-workflows_1789261054/0000>)

E007

Error: YAML parse error on cassandra/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/cassandra (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/cassandra_1789261132/0000>)

E008

Error: YAML parse error on cert-manager/templates/cainjector/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/cert-manager (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/cert-manager_1789261145/0000>)

E009

Error: YAML parse error on clickhouse/templates/configd-configmap.yaml: error converting YAML to JSON: yaml: line 14: did not find expected key

- bitnami/clickhouse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/clickhouse_1789261201/0000>)

E010

Error: YAML parse error on cloudnative-pg/templates/operator/clusterrolebinding.yaml: error converting YAML to JSON: yaml: line 4: did not find expected comment or line break

- bitnami/cloudnative-pg (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/cloudnative-pg_1789261278/0000>)

E011

Error: YAML parse error on consul/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/consul (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/consul_1789261319/0000>)

E012

Error: YAML parse error on contour/templates/certgen/serviceaccount.yaml: error converting YAML to JSON: yaml: line 15: did not find expected key

- bitnami/contour (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/contour_1789261328/0000>)

E013

Error: YAML parse error on deepspeed/templates/client/client-dep-job.yaml: error converting YAML to JSON: yaml: line 31: did not find expected key

- bitnami/deepspeed (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/deepspeed_1789261342/0000>)

E014

Error: YAML parse error on discourse/templates/service.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/discourse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/discourse_1789261349/0000>)

E015

Error: YAML parse error on dremio/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/dremio (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/dremio_1789261357/0000>)

E016

Error: YAML parse error on ejbca/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/ejbca (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/ejbca_1789261434/0000>)

E017

Error: YAML parse error on elasticsearch/templates/coordinating/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/elasticsearch (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/elasticsearch_1789261468/0000>)

E018

Error: YAML parse error on envoy-gateway/templates/deployment.yaml: error converting YAML to JSON: yaml: line 37: did not find expected key

- bitnami/envoy-gateway (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/envoy-gateway_1789261488/0000>)

E019

Error: YAML parse error on etcd/templates/svc-headless.yaml: error converting YAML to JSON: yaml: line 14: did not find expected key

- bitnami/etcd (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/etcd_1789261495/0000>)

E020

Error: YAML parse error on external-dns/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/external-dns (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/external-dns_1789261550/0000>)

E021

Error: YAML parse error on flink/templates/taskmanager/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/flink (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/flink_1789261585/0000>)

E022

Error: YAML parse error on fluent-bit/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/fluent-bit (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/fluent-bit_1789261621/0000>)

E023

Error: YAML parse error on fluentd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/fluentd (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/fluentd_1789261647/0000>)

E024

Error: YAML parse error on flux/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/flux (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/flux_1789261654/0000>)

E025

Error: YAML parse error on gitea/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/gitea (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/gitea_1789261682/0000>)

E026

Error: YAML parse error on gitlab-runner/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/gitlab-runner (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/gitlab-runner_1789261710/0000>)

E027

Error: YAML parse error on grafana-k6-operator/templates/deployment.yaml: error converting YAML to JSON: yaml: line 85: mapping keys are not allowed in this context

- bitnami/grafana-k6-operator (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/grafana-k6-operator_1789261748/0000>)

E028

Error: YAML parse error on grafana-loki/templates/gateway/configmap-http.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/grafana-loki (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/grafana-loki_1789261775/0000>)

E029

Error: YAML parse error on grafana-operator/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/grafana-operator (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/grafana-operator_1789261806/0000>)

E030

Error: YAML parse error on grafana-tempo/templates/tempo-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/grafana-tempo (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/grafana-tempo_1789261832/0000>)

E031

Error: YAML parse error on grafana/templates/application.yaml: error converting YAML to JSON: yaml: line 138: mapping keys are not allowed in this context

- bitnami/grafana (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/grafana_1789261713/0000>)

E032

Error: YAML parse error on haproxy/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/haproxy (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/haproxy_1789261927/0000>)

E033

Error: YAML parse error on harbor/templates/core/core-dpl.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/harbor (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/harbor_1789261928/0000>)

E034

Error: YAML parse error on jaeger/templates/collector/configmap.yaml: error converting YAML to JSON: yaml: line 86: found unexpected end of stream

- bitnami/jaeger (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/jaeger_1789261953/0000>)

E035

Error: YAML parse error on janusgraph/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/janusgraph (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/janusgraph_1789261985/0000>)

E036

Error: YAML parse error on jenkins/templates/controller-svc.yaml: error converting YAML to JSON: yaml: line 13: mapping values are not allowed in this context

- bitnami/jenkins (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/jenkins_1789261998/0000>)

E037

Error: YAML parse error on kafka/templates/controller-eligible/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/kafka (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kafka_1789262019/0000>)

E038

Error: YAML parse error on kibana/templates/ingress.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/kibana (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kibana_1789262084/0000>)

E039

Error: YAML parse error on kong/templates/dep-ds.yaml: error converting YAML to JSON: yaml: line 58: block sequence entries are not allowed in this context

- bitnami/kong (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kong_1789262120/0000>)

E040

Error: YAML parse error on kube-arangodb/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/kube-arangodb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kube-arangodb_1789262121/0000>)

E041

Error: YAML parse error on kuberay/templates/apiserver/clusterrolebinding.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/kuberay (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kuberay_1789262165/0000>)

E042

Error: YAML parse error on kubernetes-event-exporter/templates/deployment.yaml: error converting YAML to JSON: yaml: line 27: did not find expected key

- bitnami/kubernetes-event-exporter (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kubernetes-event-exporter_1789262168/0000>)

E043

Error: YAML parse error on logstash/templates/sts.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/logstash (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/logstash_1789262184/0000>)

E044

Error: YAML parse error on matomo/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/matomo (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/matomo_1789262257/0000>)

E045

Error: YAML parse error on metallb/templates/controller/configmap.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/metallb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/metallb_1789262350/0000>)

E046

Error: YAML parse error on metrics-server/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/metrics-server (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/metrics-server_1789262363/0000>)

E047

Error: YAML parse error on mlflow/templates/run/dep-job.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/mlflow (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mlflow_1789262402/0000>)

E048

Error: YAML parse error on mongodb-sharded/templates/config-server/config-server-statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/mongodb-sharded (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mongodb-sharded_1789262509/0000>)

E049

Error: YAML parse error on mongodb/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/mongodb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mongodb_1789262443/0000>)

E050

Error: YAML parse error on moodle/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/moodle (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/moodle_1789262603/0000>)

E051

Error: YAML parse error on multus-cni/templates/daemonset.yaml: error converting YAML to JSON: yaml: line 73: did not find expected comment or line break

- bitnami/multus-cni (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/multus-cni_1789262612/0000>)

E052

Error: YAML parse error on mysql/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/mysql (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mysql_1789262639/0000>)

E053

Error: YAML parse error on nats/templates/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/nats (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/nats_1789262668/0000>)

E054

Error: YAML parse error on nessie/templates/networkpolicy.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- bitnami/nessie (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/nessie_1789262730/0000>)

E055

Error: YAML parse error on nginx/templates/context-includes-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/nginx (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/nginx_1789262745/0000>)

E056

Error: YAML parse error on nginx/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/nginx (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/nginx_1789262745/0000>)

E057

Error: YAML parse error on opensearch/templates/coordinating/statefulset.yaml: error converting YAML to JSON: yaml: line 184: mapping values are not allowed in this context

- bitnami/opensearch (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/opensearch_1789262840/0000>)

E058

Error: YAML parse error on parse/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/parse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/parse_1789262841/0000>)

E059

Error: YAML parse error on pinniped/templates/concierge/apiservice-identity.yaml: error converting YAML to JSON: yaml: line 23: found unexpected end of stream

- bitnami/pinniped (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/pinniped_1789262910/0000>)

E060

Error: YAML parse error on postgresql-ha/templates/pgpool/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/postgresql-ha (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/postgresql-ha_1789262929/0000>)

E061

Error: YAML parse error on postgresql/templates/primary/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/postgresql (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/postgresql_1789262926/0000>)

E062

Error: YAML parse error on prometheus/templates/alertmanager/networkpolicy.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/prometheus (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/prometheus_1789262960/0000>)

E063

Error: YAML parse error on prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/prometheus (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/prometheus_1789262960/0000>)

E064

Error: YAML parse error on rabbitmq-cluster-operator/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/rabbitmq-cluster-operator (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/rabbitmq-cluster-operator_1789263004/0000>)

E065

Error: YAML parse error on rabbitmq/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/rabbitmq (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/rabbitmq_1789262993/0000>)

E066

Error: YAML parse error on redis-cluster/templates/redis-statefulset.yaml: error converting YAML to JSON: yaml: line 177: block sequence entries are not allowed in this context

- bitnami/redis-cluster (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/redis-cluster_1789263038/0000>)

E067

Error: YAML parse error on redmine/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/redmine (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/redmine_1789263074/0000>)

E068

Error: YAML parse error on redmine/templates/svc.yaml: error converting YAML to JSON: yaml: line 14: block sequence entries are not allowed in this context

- bitnami/redmine (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/redmine_1789263074/0000>)

E069

Error: YAML parse error on seaweedfs/templates/filer/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/seaweedfs (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/seaweedfs_1789263116/0000>)

E070

Error: YAML parse error on solr/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/solr (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/solr_1789263147/0000>)

E071

Error: YAML parse error on sonarqube/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/sonarqube (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/sonarqube_1789263200/0000>)

E072

Error: YAML parse error on superset/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/superset (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/superset_1789263238/0000>)

E073

Error: YAML parse error on tensorflow-resnet/templates/service.yaml: error converting YAML to JSON: yaml: line 15: mapping values are not allowed in this context

- bitnami/tensorflow-resnet (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/tensorflow-resnet_1789263255/0000>)

E074

Error: YAML parse error on thanos/templates/storegateway/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/thanos (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/thanos_1789263263/0000>)

E075

Error: YAML parse error on tomcat/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/tomcat (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/tomcat_1789263266/0000>)

E076

Error: YAML parse error on valkey-cluster/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/valkey-cluster (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/valkey-cluster_1789263288/0000>)

E077

Error: YAML parse error on valkey/templates/replicas/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/valkey (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/valkey_1789263282/0000>)

E078

Error: YAML parse error on vault/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- bitnami/vault (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/vault_1789263307/0000>)

E079

Error: YAML parse error on victoriametrics/templates/vmagent/dep-ds.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/victoriametrics (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/victoriametrics_1789263322/0000>)

E080

Error: YAML parse error on wordpress/templates/httpd-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- bitnami/wordpress (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/wordpress_1789263373/0000>)

E081

Error: YAML parse error on wordpress/templates/svc.yaml: error converting YAML to JSON: yaml: line 13: mapping keys are not allowed in this context

- bitnami/wordpress (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/wordpress_1789263373/0000>)

E082

Error: YAML parse error on zookeeper/templates/statefulset.yaml: error converting YAML to JSON: yaml: line 181: block sequence entries are not allowed in this context

- bitnami/zookeeper (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/zookeeper_1789263392/0000>)

E083

Error: mlflow/templates/tracking/deployment.yaml:105:12
executing "mlflow/templates/tracking/deployment.yaml" at <include
"mlflow.v0.volumePermissionsInitContainer" .>:
error calling include:
mlflow/templates/_helpers.tpl:553:12
executing "mlflow.v0.volumePermissionsInitContainer" at <include>:
wrong number of args for include: want 2 got 1

- bitnami/mlflow (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mlflow_1789262402/0000>)

E084

Error: schema-registry/templates/http-route.yaml:7:13
executing "schema-registry/templates/http-route.yaml" at <\$route.enabled>:
nil pointer evaluating interface {}.enabled

- bitnami/schema-registry (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/schema-registry_1789263074/0000>)

E085

Error: scylladb/templates/networkpolicy.yaml:62:19
executing "scylladb/templates/networkpolicy.yaml" at <.containerPort>:
nil pointer evaluating interface {}.containerPort

- bitnami/scylladb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/scylladb_1789263109/0000>)

E086

Error: values don't meet the specifications of the schema(s) in the following chart(s):
mysql:
- at '/architecture': value must be one of 'standalone', 'replication'

- bitnami/ghost (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/ghost_1789261679/0000>)

E087

chart rendered no resources (use allow_empty explicitly)

- bitnami/kube-prometheus/charts/kube-prometheus-crds (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kube-prometheus-crds_1789262163/0000>)
- bitnami/kube-prometheus/charts/kube-prometheus-crds (robustness; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kube-prometheus-crds_1789262163/0000>)

E088

duplicate resource: ('rbac.authorization.k8s.io/v1', 'Role', None, 'hypothesis-clickhouse-operator')

- bitnami/clickhouse-operator (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/clickhouse-operator_1789261238/0000>)

E089

Source: airflow 25.1.0 / templates/NOTES.txt

execution error at (airflow/templates/NOTES.txt:129:3):
VALUES VALIDATION:

airflow: executors
You need to provide at least one value for the '.executor' parameter.

- bitnami/airflow (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/airflow_1789260968/0000>)

E090

Source: aspnet-core 8.0.0 / templates/NOTES.txt

execution error at (aspnet-core/templates/NOTES.txt:58:4):

VALUES VALIDATION:

aspnet-core: missing-extra-volume-mounts

You specified extra volumes but not mount points for them.

Please also set the extraVolumeMounts parameter.

- bitnami/aspnet-core (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/aspnet-core_1789261101/0000>)

E091

Source: cadvisor 0.1.14 / templates/daemonset.yaml

execution error at (cadvisor/templates/daemonset.yaml:155:25): ERROR: Preset key '' invalid. Allowed values are xlarge,2xlarge,nano,micro,small,medium,large

- bitnami/cadvisor (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/cadvisor_1789261127/0000>)

E092

Source: chainloop 4.0.76 / templates/controlplane/secret-jwt-cas-private-key.yaml

execution error at (chainloop/templates/controlplane/secret-jwt-cas-private-key.yaml:14:22):

Authentication Private Key "casJWTPrivateKey" required

- bitnami/chainloop (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/chainloop_1789261157/0000>)

E093

Source: grafana-alloy 1.0.8 / templates/NOTES.txt

execution error at (grafana-alloy/templates/NOTES.txt:71:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/grafana-alloy:1.10.2-debian-12-r0
- 00/bitnami/configmap-reload:0.15.0-debian-12-r12

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true.

Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- bitnami/grafana-alloy (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/grafana-alloy_1789261741/0000>)

E094

Source: influxdb 7.1.21 / templates/NOTES.txt

execution error at (influxdb/templates/NOTES.txt:146:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/influxdb:3.4.1-debian-12-r0
- 00/bitnami/os-shell:12-debian-12-r51
- 00/bitnami/kubectl:1.33.4-debian-12-r0

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true. Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- bitnami/influxdb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/influxdb_1789261931/0000>)

E095

Source: jupyterhub 10.0.6 / templates/proxy/deployment.yaml

execution error at (jupyterhub/templates/proxy/deployment.yaml:32:32): ERROR: Preset key '' invalid. Allowed values are medium,large,xlarge,2xlarge,nano,micro,small

- bitnami/jupyterhub (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/jupyterhub_1789262019/0000>)

E096

Source: kube-state-metrics 5.1.1 / templates/deployment.yaml

execution error at (kube-state-metrics/templates/deployment.yaml:205:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- bitnami/kube-state-metrics (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kube-state-metrics_1789262164/0000>)

E097

Source: mariadb-galera 16.0.2 / templates/statefulset.yaml

execution error at (mariadb-galera/templates/statefulset.yaml:78:25): ERROR: Preset key '' invalid. Allowed values are nano,micro,small,medium,large,xlarge,2xlarge

- bitnami/mariadb-galera (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mariadb-galera_1789262206/0000>)

E098

Source: mariadb 22.0.0 / templates/NOTES.txt

```
execution error at (mariadb/templates/NOTES.txt:74:4):
VALUES VALIDATION:
mariadb: architecture
    Invalid architecture selected. Valid values are "standalone" and
    "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/drupal (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789260948/runs/drupal_1789261399/0000>)
```

E099

Source: mariadb 23.0.1 / templates/NOTES.txt

```
execution error at (mariadb/templates/NOTES.txt:74:4):
VALUES VALIDATION:
mariadb: architecture
    Invalid architecture selected. Valid values are "standalone" and
    "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/mariadb (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789260948/runs/mariadb_1789262195/0000>)
- bitnami/mariadb (robustness; failed) (<bitnami-runs/bitnami-
charts_1789260948/runs/mariadb_1789262195/0000>)
```

E100

Source: memcached 7.9.7 / templates/NOTES.txt

```
execution error at (memcached/templates/NOTES.txt:46:4):
VALUES VALIDATION:
memcached: architecture
    Invalid architecture selected. Valid values are "standalone" and
    "high-availability". Please set a valid architecture (--set architecture="xxxx")

- bitnami/grafana-mimir (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789260948/runs/grafana-mimir_1789261802/0000>)
```

E101

Source: memcached 8.0.0 / templates/NOTES.txt

```
execution error at (memcached/templates/NOTES.txt:46:4):
VALUES VALIDATION:
memcached: architecture
    Invalid architecture selected. Valid values are "standalone" and
    "high-availability". Please set a valid architecture (--set architecture="xxxx")

- bitnami/memcached (known-inputs; failed) (<bitnami-runs/bitnami-
charts_1789260948/runs/memcached_1789262312/0000>)
```

E102

Source: odoo 28.2.11 / templates/deployment.yaml

execution error at (odoo/templates/deployment.yaml:270:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- bitnami/odoo (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/odoo_1789262798/0000>)

E103

Source: postgresql 17.1.2 / templates/NOTES.txt

execution error at (postgresql/templates/NOTES.txt:118:4):

VALUES VALIDATION:

postgresql: psp.create, rbac.create

RBAC should be enabled if PSP is enabled in order for PSP to work.

More info at <https://kubernetes.io/docs/concepts/policy/pod-security-policy/#authorizing-policies>

- bitnami/postgresql (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/postgresql_1789262926/0000>)

E104

Source: pytorch 5.0.0 / templates/NOTES.txt

execution error at (pytorch/templates/NOTES.txt:69:3):

VALUES VALIDATION:

pytorch: architecture

Invalid architecture selected. Valid values are "distributed" and "standalone". Please set a valid architecture (--set architecture="xxxx")

- bitnami/pytorch (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/pytorch_1789262979/0000>)

E105

Source: redis 22.0.4 / templates/NOTES.txt

execution error at (redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- bitnami/oauth2-proxy (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/oauth2-proxy_1789262793/0000>)

E106

Source: redis 23.1.1 / templates/NOTES.txt

execution error at (redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and

"replication". Please set a valid architecture (--set architecture="xxxx")

```
- bitnami/redis (known-inputs; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/redis_1789263022/0000>)  
- bitnami/redis (robustness; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/redis_1789263022/0000>)
```

E107

Source: sealed-secrets 2.5.20 / templates/deployment.yaml

execution error at (sealed-secrets/templates/deployment.yaml:172:25): ERROR: Preset key '' invalid.
Allowed values are nano,micro,small,medium,large,xlarge,2xlarge

```
- bitnami/sealed-secrets (known-inputs; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/sealed-secrets_1789263115/0000>)
```

E108

Source: whereabouts 1.2.20 / templates/daemonset.yaml

execution error at (whereabouts/templates/daemonset.yaml:164:25): ERROR: Preset key '' invalid.
Allowed values are nano,micro,small,medium,large,xlarge,2xlarge

```
- bitnami/whereabouts (known-inputs; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/whereabouts_1789263358/0000>)
```

E109

invalid rendered YAML: more indented follow up line than first in a block scalar
in "<unicode string>", line 474, column 15:
 set -o errexit
 ^ (line: 474)

```
- bitnami/zipkin (known-inputs; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/zipkin_1789263388/0000>)  
- bitnami/zipkin (robustness; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/zipkin_1789263388/0000>)
```

E110

level=INFO msg="warning: destination for kube-state-metrics.rbac.rules is a table. Ignoring non-
table value ([])"
Error: YAML parse error on kube-prometheus/templates/extra-list.yaml: error unmarshaling JSON: while
decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

```
- bitnami/kube-prometheus (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/kube-  
prometheus_1789262132/0000>)
```

E111

level=INFO msg="warning: destination for postgresql.tls.autoGenerated is a table. Ignoring non-table
value (false)"
Error: YAML parse error on keycloak/templates/statefulset.yaml: error converting YAML to JSON: yaml:
control characters are not allowed

```
- bitnami/keycloak (known-inputs; failed) (<bitnami-runs/bitnami-  
charts_1789260948/runs/keycloak_1789262075/0000>)
```

E112

resource has no metadata.name

- bitnami/jenkins (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/jenkins_1789261998/0000>)
- bitnami/keydb (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/keydb_1789262081/0000>)
- bitnami/mastodon (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/mastodon_1789262219/0000>)
- bitnami/neo4j (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/neo4j_1789262693/0000>)
- bitnami/phpmyadmin (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/phpmyadmin_1789262890/0000>)
- bitnami/spark (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/spark_1789263236/0000>)
- bitnami/wildfly (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/wildfly_1789263365/0000>)

E113

Source: cilium 3.1.10 / templates/agent/daemonset.yaml

template: cilium/templates/agent/daemonset.yaml:30:15: executing "cilium/templates/agent/daemonset.yaml" at <semverCompare "<1.30-0" (include "common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- bitnami/cilium (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/cilium_1789261173/0000>)

E114

Source: common 2.31.4 / templates/_capabilities.tpl

template: common/templates/_capabilities.tpl:131:32: executing "common.capabilities.psp.supported" at <semverCompare "<1.25-0" \$kubeVersion>: error calling semverCompare: invalid semantic version

- bitnami/node-exporter (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/node-exporter_1789262746/0000>)

E115

Source: concourse 5.1.47 / templates/worker/rolebinding.yaml

template: concourse/templates/worker/rolebinding.yaml:27:22: executing "concourse/templates/worker/rolebinding.yaml" at <semverCompare "<1.25-0" (include "common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- bitnami/concourse (known-inputs; failed) (<bitnami-runs/bitnami-charts_1789260948/runs/concourse_1789261279/0000>)

Charts

bitnami/airflow

Result: FAIL | Status: failed
Attempts: 145 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/airflow_1789260968/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 506 | Varied in render attempts: 3
Missing values: 6 | Undocumented template fields: 534
Unreferenced values: 280 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: E089 (#e089)

Reproducing values (known-inputs):

```
{  
  "executor": ""  
}
```

bitnami/apache

Result: FAIL | Status: failed
Attempts: 212 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/apache_1789260968/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 116 | Varied in render attempts: 30
Missing values: 2 | Undocumented template fields: 116
Unreferenced values: 41 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 115

Phase robustness: failed | Attempts: 97

Errors: E001 (#e001), E002 (#e002)

Reproducing values (known-inputs):

```
{  
  "nameOverride": "\u001f"  
}
```

Reproducing values (robustness):

```
{
```

```
"service": {
  "": [],
  "type": "\u001f"
}
```

bitnami/apisix

Result: FAIL | Status: failed
Attempts: 85 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/apisix_1789260968/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 369 | Varied in render attempts: 17
Missing values: 0 | Undocumented template fields: 37
Unreferenced values: 114 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 52

Phase robustness: time-limit | Attempts: 33

Errors: E003 (#e003)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/appsmith

Result: FAIL | Status: failed
Attempts: 136 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/appsmith_1789260968/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 229 | Varied in render attempts: 2
Missing values: 0 | Undocumented template fields: 240
Unreferenced values: 120 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 35

Phase robustness: passed | Attempts: 101

Errors: E004 (#e004)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/argo-cd

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/argo-cd_1789261025/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 631 | Varied in render attempts: 7
Missing values: 26 | Undocumented template fields: 647
Unreferenced values: 240 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: E005 (#e005)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/argo-workflows

Result: FAIL | Status: failed
Attempts: 131 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/argo-workflows_1789261054/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 176 | Varied in render attempts: 0
Missing values: 0 | Undocumented template fields: 184
Unreferenced values: 91 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 30

Phase robustness: passed | Attempts: 101

Errors: E006 (#e006)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/aspnet-core

Result: FAIL | Status: failed
Attempts: 206 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/aspnet-core_1789261101/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 111 | Varied in render attempts: 38
Missing values: 5 | Undocumented template fields: 116
Unreferenced values: 33 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 105

Phase robustness: passed | Attempts: 101

Errors: E090 (#e090)

Reproducing values (known-inputs):

```
{
  "extraVolumes": [
    null
  ]
}
```

bitnami/cadvisor

Result: FAIL | Status: failed
Attempts: 126 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/cadvisor_1789261127/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 98 | Varied in render attempts: 2
Missing values: 3 | Undocumented template fields: 102
Unreferenced values: 34 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 25

Phase robustness: passed | Attempts: 101

Errors: E091 (#e091)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```


bitnami/cassandra

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/cassandra_1789261132/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 131 | Varied in render attempts: 1
Missing values: 1 | Undocumented template fields: 137
Unreferenced values: 53 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: E007 (#e007)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/cert-manager

Result: FAIL | Status: failed
Attempts: 168 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/cert-manager_1789261145/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 186 | Varied in render attempts: 51
Missing values: 4 | Undocumented template fields: 195
Unreferenced values: 66 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 67

Phase robustness: passed | Attempts: 101

Errors: E008 (#e008)

Reproducing values (known-inputs):

```
{
  "leaderElection": {
    "namespace": "\u001f"
  }
}
```

bitnami/chainloop

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/chainloop_1789261157/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 331 | Varied in render attempts: 6
Missing values: 6 | Undocumented template fields: 346
Unreferenced values: 81 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: E092 (#e092)

Reproducing values (known-inputs):

```
{  
  "development": false  
}
```

bitnami/cilium

Result: FAIL | Status: failed
Attempts: 187 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/cilium_1789261173/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 456 | Varied in render attempts: 11
Missing values: 0 | Undocumented template fields: 478
Unreferenced values: 310 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 86

Phase robustness: passed | Attempts: 101

Errors: E113 (#e113)

Reproducing values (known-inputs):

```
{  
  "kubeVersion": ":"  
}
```

bitnami/clickhouse

Result: FAIL | Status: failed
Attempts: 181 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/clickhouse_1789261201/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 243 | Varied in render attempts: 24
Missing values: 0 | Undocumented template fields: 255
Unreferenced values: 84 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 80

Phase robustness: passed | Attempts: 101

Errors: E009 (#e009)

Reproducing values (known-inputs):

```
{
  "configdFiles": {
    "": null
  }
}
```

bitnami/clickhouse-operator

Result: FAIL | Status: failed
Attempts: 172 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/clickhouse-operator_1789261238/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 117 | Varied in render attempts: 10
Missing values: 0 | Undocumented template fields: 124
Unreferenced values: 56 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 71

Phase robustness: passed | Attempts: 101

Errors: E088 (#e088)

Reproducing values (known-inputs):

```
{
  "watchNamespaces": [
    null,
    null
  ]
}
```

bitnami/cloudnative-pg

Result: FAIL | Status: failed
Attempts: 152 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/cloudnative-pg_1789261278/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 227 | Varied in render attempts: 1
Missing values: 0 | Undocumented template fields: 235
Unreferenced values: 50 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: E010 (#e010)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ">"  
}
```

bitnami/common

Result: N/A | Status: skipped-library
Attempts: N/A | Remaining iterations: unknown
Coverage: not a standalone application
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/common_1789261278/0000

Filtering applied: False
Chart did not enter finite permutation testing

bitnami/concourse

Result: FAIL | Status: failed
Attempts: 158 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/concourse_1789261279/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 229 | Varied in render attempts: 1
Missing values: 5 | Undocumented template fields: 236
Unreferenced values: 76 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 57

Phase robustness: passed | Attempts: 101

Errors: E115 (#e115)

Reproducing values (known-inputs):

```
{  
  "kubeVersion": ":"  
}
```

bitnami/consul

Result: FAIL | Status: failed
Attempts: 140 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/consul_1789261319/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 123 | Varied in render attempts: 3
Missing values: 2 | Undocumented template fields: 129
Unreferenced values: 38 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: E011 (#e011)

Reproducing values (known-inputs):

```
{  
  "existingConfigmap": "\u001f"  
}
```

bitnami/contour

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/contour_1789261328/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 262 | Varied in render attempts: 3
Missing values: 3 | Undocumented template fields: 274
Unreferenced values: 141 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E012 (#e012)

Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": null  
  }  
}
```

}

bitnami/deepspeed

Result: FAIL | Status: failed
Attempts: 107 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/deepspeed_1789261342/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 145 | Varied in render attempts: 9
Missing values: 1 | Undocumented template fields: 13
Unreferenced values: 71 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 12

Phase robustness: time-limit | Attempts: 95

Errors: E013 (#e013)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/discourse

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/discourse_1789261349/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 129 | Varied in render attempts: 12
Missing values: 1 | Undocumented template fields: 136
Unreferenced values: 74 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: E014 (#e014)

Reproducing values (known-inputs):

```
{
  "service": {
    "annotations": {
      "": []
    }
  }
}
```

```
}  
}
```

bitnami/dremio

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/dremio_1789261357/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 304 | Varied in render attempts: 28
Missing values: 7 | Undocumented template fields: 326
Unreferenced values: 137 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: E015 (#e015)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```

bitnami/drupal

Result: FAIL | Status: failed
Attempts: 131 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/drupal_1789261399/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 149 | Varied in render attempts: 21
Missing values: 6 | Undocumented template fields: 143
Unreferenced values: 48 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 30

Phase robustness: passed | Attempts: 101

Errors: E098 (#e098)

Reproducing values (known-inputs):

```
{  
  "mariadb": {  
    "architecture": ""  
  }  
}
```

}

bitnami/ejbca

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/ejbca_1789261434/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 100 | Varied in render attempts: 4
Missing values: 4 | Undocumented template fields: 103
Unreferenced values: 52 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: E016 (#e016)

Reproducing values (known-inputs):

```
{  
  "ejbcaKeystoreExistingSecret": "\u001f"  
}
```

bitnami/elasticsearch

Result: FAIL | Status: failed
Attempts: 143 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/elasticsearch_1789261468/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 382 | Varied in render attempts: 5
Missing values: 0 | Undocumented template fields: 396
Unreferenced values: 180 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 42

Phase robustness: passed | Attempts: 101

Errors: E017 (#e017)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```


bitnami/envoy-gateway

Result: FAIL | Status: failed
Attempts: 156 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/envoy-gateway_1789261488/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 147 | Varied in render attempts: 9
Missing values: 0 | Undocumented template fields: 153
Unreferenced values: 55 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 55

Phase robustness: passed | Attempts: 101

Errors: E018 (#e018)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/etcd

Result: FAIL | Status: failed
Attempts: 108 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/etcd_1789261495/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 190 | Varied in render attempts: 26
Missing values: 1 | Undocumented template fields: 199
Unreferenced values: 58 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 62

Phase robustness: time-limit | Attempts: 46

Errors: E019 (#e019)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/external-dns

Result: FAIL | Status: failed
Attempts: 148 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/external-dns_1789261550/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 235 | Varied in render attempts: 9
Missing values: 10 | Undocumented template fields: 238
Unreferenced values: 58 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 47

Phase robustness: passed | Attempts: 101

Errors: E020 (#e020)

Reproducing values (known-inputs):

```
{  
  "interval": "\u001f"  
}
```

bitnami/flink

Result: FAIL | Status: failed
Attempts: 188 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/flink_1789261585/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 134 | Varied in render attempts: 35
Missing values: 0 | Undocumented template fields: 139
Unreferenced values: 53 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 87

Phase robustness: passed | Attempts: 101

Errors: E021 (#e021)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\b"  
}
```

bitnami/fluent-bit

Result: FAIL | Status: failed
Attempts: 217 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/fluent-bit_1789261621/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 121 | Varied in render attempts: 39
Missing values: 0 | Undocumented template fields: 126
Unreferenced values: 35 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 116

Phase robustness: passed | Attempts: 101

Errors: E022 (#e022)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/fluentd

Result: FAIL | Status: failed
Attempts: 128 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/fluentd_1789261647/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 208 | Varied in render attempts: 16
Missing values: 7 | Undocumented template fields: 217
Unreferenced values: 64 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 27

Phase robustness: passed | Attempts: 101

Errors: E023 (#e023)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/flux

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/flux_1789261654/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 543 | Varied in render attempts: 20
Missing values: 9 | Undocumented template fields: 565
Unreferenced values: 163 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E024 (#e024)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/ghost

Result: FAIL | Status: failed
Attempts: 152 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/ghost_1789261679/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 121 | Varied in render attempts: 25
Missing values: 4 | Undocumented template fields: 114
Unreferenced values: 43 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: E086 (#e086)

Reproducing values (known-inputs):

```
{
  "mysql": {
    "architecture": ""
  }
}
```

bitnami/gitea

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/gitea_1789261682/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 113 | Varied in render attempts: 5
Missing values: 0 | Undocumented template fields: 118
Unreferenced values: 40 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: E025 (#e025)

Reproducing values (known-inputs):

```
{  
  "smtpExistingSecret": "\u001f"  
}
```

bitnami/gitlab-runner

Result: FAIL | Status: failed
Attempts: 248 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/gitlab-runner_1789261710/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 142 | Varied in render attempts: 44
Missing values: 0 | Undocumented template fields: 145
Unreferenced values: 48 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 147

Phase robustness: passed | Attempts: 101

Errors: E026 (#e026)

Reproducing values (known-inputs):

```
{  
  "helperImage": {  
    "digest": "\u001f"  
  }  
}
```

bitnami/grafana

Result: FAIL | Status: failed
Attempts: 164 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana_1789261713/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 151 | Varied in render attempts: 15
Missing values: 5 | Undocumented template fields: 156
Unreferenced values: 52 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 63

Phase robustness: passed | Attempts: 101

Errors: E031 (#e031)

Reproducing values (known-inputs):

```
{
  "admin": {
    "existingSecret": "?"
  }
}
```

bitnami/grafana-alloy

Result: FAIL | Status: failed
Attempts: 368 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana-alloy_1789261741/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 132 | Varied in render attempts: 88
Missing values: 3 | Undocumented template fields: 138
Unreferenced values: 61 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 267

Phase robustness: passed | Attempts: 101

Errors: E093 (#e093)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

bitnami/grafana-k6-operator

Result: FAIL | Status: failed
Attempts: 173 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana-k6-operator_1789261748/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 91 | Varied in render attempts: 5
Missing values: 0 | Undocumented template fields: 95
Unreferenced values: 32 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 72

Phase robustness: passed | Attempts: 101

Errors: E027 (#e027)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "?"  
}
```

bitnami/grafana-loki

Result: FAIL | Status: failed
Attempts: 148 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana-loki_1789261775/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 671 | Varied in render attempts: 7
Missing values: 6 | Undocumented template fields: 696
Unreferenced values: 287 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 47

Phase robustness: passed | Attempts: 101

Errors: E028 (#e028)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/grafana-mimir

Result: FAIL | Status: failed
Attempts: 125 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana-mimir_1789261802/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 703 | Varied in render attempts: 1
Missing values: 6 | Undocumented template fields: 729
Unreferenced values: 335 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 24

Phase robustness: passed | Attempts: 101

Errors: E100 (#e100)

Reproducing values (known-inputs):

```
{
  "memcachedchunks": {
    "architecture": ""
  }
}
```

bitnami/grafana-operator

Result: FAIL | Status: failed
Attempts: 143 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana-operator_1789261806/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 120 | Varied in render attempts: 25
Missing values: 1 | Undocumented template fields: 127
Unreferenced values: 44 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 42

Phase robustness: passed | Attempts: 101

Errors: E029 (#e029)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```


bitnami/grafana-tempo

Result: FAIL | Status: failed
Attempts: 138 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/grafana-tempo_1789261832/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 469 | Varied in render attempts: 3
Missing values: 2 | Undocumented template fields: 489
Unreferenced values: 204 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 37

Phase robustness: passed | Attempts: 101

Errors: E030 (#e030)

Reproducing values (known-inputs):

```
{
  "tempo": {
    "configuration": "\u001f"
  }
}
```

bitnami/haproxy

Result: FAIL | Status: failed
Attempts: 192 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/haproxy_1789261927/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 87 | Varied in render attempts: 56
Missing values: 0 | Undocumented template fields: 91
Unreferenced values: 34 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 91

Phase robustness: passed | Attempts: 101

Errors: E032 (#e032)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/harbor

Result: FAIL | Status: failed
Attempts: 137 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/harbor_1789261928/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 554 | Varied in render attempts: 2
Missing values: 4 | Undocumented template fields: 586
Unreferenced values: 294 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: E033 (#e033)

Reproducing values (known-inputs):

```
{
  "existingSecret": "\u001f"
}
```

bitnami/influxdb

Result: FAIL | Status: failed
Attempts: 380 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/influxdb_1789261931/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 167 | Varied in render attempts: 119
Missing values: 0 | Undocumented template fields: 174
Unreferenced values: 51 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 279

Phase robustness: passed | Attempts: 101

Errors: E094 (#e094)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

bitnami/jaeger

Result: FAIL | Status: failed
Attempts: 220 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/jaeger_1789261953/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 155 | Varied in render attempts: 7
Missing values: 0 | Undocumented template fields: 160
Unreferenced values: 101 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 119

Phase robustness: passed | Attempts: 101

Errors: E034 (#e034)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/janusgraph

Result: FAIL | Status: failed
Attempts: 139 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/janusgraph_1789261985/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 125 | Varied in render attempts: 2
Missing values: 6 | Undocumented template fields: 134
Unreferenced values: 52 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 38

Phase robustness: passed | Attempts: 101

Errors: E035 (#e035)

Reproducing values (known-inputs):

```
{  
  "existingConfigmap": "\u001f"  
}
```

bitnami/jenkins

Result: FAIL | Status: failed
Attempts: 426 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/jenkins_1789261998/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 172 | Varied in render attempts: 15
Missing values: 0 | Undocumented template fields: 171
Unreferenced values: 43 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 118

Phase robustness: failed | Attempts: 308

Errors: E112 (#e112), E036 (#e036)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": ":"
  }
}
```

bitnami/jupyterhub

Result: FAIL | Status: failed
Attempts: 125 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/jupyterhub_1789262019/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 252 | Varied in render attempts: 1
Missing values: 4 | Undocumented template fields: 262
Unreferenced values: 102 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 24

Phase robustness: passed | Attempts: 101

Errors: E095 (#e095)

Reproducing values (known-inputs):

```
{
  "singleuser": {
    "resourcesPreset": ""
  }
}
```

bitnami/kafka

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kafka_1789262019/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 356 | Varied in render attempts: 2
Missing values: 3 | Undocumented template fields: 372
Unreferenced values: 154 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 40

Phase robustness: passed | Attempts: 101

Errors: E037 (#e037)

Reproducing values (known-inputs):

```
{
  "dnsPolicy": "\u001f"
}
```

bitnami/keycloak

Result: FAIL | Status: failed
Attempts: 214 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/keycloak_1789262075/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 232 | Varied in render attempts: 93
Missing values: 0 | Undocumented template fields: 239
Unreferenced values: 64 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 113

Phase robustness: passed | Attempts: 101

Errors: E111 (#e111)

Reproducing values (known-inputs):

```
{
  "dnsPolicy": "\u001f"
}
```

bitnami/keydb

Result: FAIL | Status: failed
Attempts: 127 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/keydb_1789262081/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 207 | Varied in render attempts: 4
Missing values: 3 | Undocumented template fields: 218
Unreferenced values: 119 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 26

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/kibana

Result: FAIL | Status: failed
Attempts: 254 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kibana_1789262084/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 139 | Varied in render attempts: 42
Missing values: 1 | Undocumented template fields: 144
Unreferenced values: 30 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 153

Phase robustness: passed | Attempts: 101

Errors: E038 (#e038)

Reproducing values (known-inputs):

```
{  
  "ingress": {  
    "enabled": true,  
    "hostname": "\u001f"  
  }  
}
```

bitnami/kong

Result: FAIL | Status: failed
Attempts: 140 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kong_1789262120/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 156 | Varied in render attempts: 1
Missing values: 9 | Undocumented template fields: 160
Unreferenced values: 84 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: E039 (#e039)

Reproducing values (known-inputs):

```
{  
  "terminationGracePeriodSeconds": "-"  
}
```

bitnami/kube-arangodb

Result: FAIL | Status: failed
Attempts: 163 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kube-arangodb_1789262121/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 153 | Varied in render attempts: 4
Missing values: 0 | Undocumented template fields: 158
Unreferenced values: 61 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 62

Phase robustness: passed | Attempts: 101

Errors: E040 (#e040)

Reproducing values (known-inputs):

```
{  
  "nameOverride": "\u001f"  
}
```

bitnami/kube-prometheus

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kube-prometheus_1789262132/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 691 | Varied in render attempts: 18
Missing values: 6 | Undocumented template fields: 711
Unreferenced values: 83 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E110 (#e110)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/kube-prometheus/charts/kube-prometheus-crds

Result: FAIL | Status: failed
Attempts: 2 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kube-prometheus-crds_1789262163/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 0 | Varied in render attempts: 0
Missing values: 0 | Undocumented template fields: 0
Unreferenced values: 1 (possibly unused; not proven)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 1

Phase robustness: failed | Attempts: 1

Errors: E087 (#e087)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```


bitnami/kube-state-metrics

Result: FAIL | Status: failed
Attempts: 118 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kube-state-metrics_1789262164/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 117 | Varied in render attempts: 2
Missing values: 1 | Undocumented template fields: 120
Unreferenced values: 32 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 17

Phase robustness: passed | Attempts: 101

Errors: E096 (#e096)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/kuberay

Result: FAIL | Status: failed
Attempts: 134 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kuberay_1789262165/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 283 | Varied in render attempts: 2
Missing values: 0 | Undocumented template fields: 295
Unreferenced values: 64 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: E041 (#e041)

Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": []  
  }  
}
```

bitnami/kubernetes-event-exporter

Result: FAIL | Status: failed
Attempts: 191 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/kubernetes-event-exporter_1789262168/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 82 | Varied in render attempts: 23
Missing values: 2 | Undocumented template fields: 87
Unreferenced values: 33 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 90

Phase robustness: passed | Attempts: 101

Errors: E042 (#e042)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/logstash

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/logstash_1789262184/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 110 | Varied in render attempts: 4
Missing values: 5 | Undocumented template fields: 119
Unreferenced values: 27 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 40

Phase robustness: passed | Attempts: 101

Errors: E043 (#e043)

Reproducing values (known-inputs):

```
{
  "existingConfiguration": "\u001f"
}
```

bitnami/mariadb

Result: FAIL | Status: failed
Attempts: 132 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mariadb_1789262195/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 242 | Varied in render attempts: 72
Missing values: 12 | Undocumented template fields: 22
Unreferenced values: 81 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 5

Phase robustness: failed | Attempts: 127

Errors: E099 (#e099)

Reproducing values (known-inputs):

```
{  
  "architecture": ""  
}
```

Reproducing values (robustness):

```
{  
  "": [],  
  "architecture": ""  
}
```

bitnami/mariadb-galera

Result: FAIL | Status: failed
Attempts: 128 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mariadb-galera_1789262206/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 139 | Varied in render attempts: 38
Missing values: 10 | Undocumented template fields: 127
Unreferenced values: 50 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 100

Phase robustness: time-limit | Attempts: 28

Errors: E097 (#e097)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

}

bitnami/mastodon

Result: FAIL | Status: failed
Attempts: 160 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mastodon_1789262219/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 284 | Varied in render attempts: 16
Missing values: 5 | Undocumented template fields: 300
Unreferenced values: 150 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 59

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{
  "serviceAccount": {
    "name": ""
  }
}
```

bitnami/matomo

Result: FAIL | Status: failed
Attempts: 134 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/matomo_1789262257/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 160 | Varied in render attempts: 3
Missing values: 0 | Undocumented template fields: 170
Unreferenced values: 53 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: E044 (#e044)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/memcached

Result: FAIL | Status: failed
Attempts: 146 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/memcached_1789262312/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 122 | Varied in render attempts: 27
Missing values: 1 | Undocumented template fields: 129
Unreferenced values: 46 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 45

Phase robustness: passed | Attempts: 101

Errors: E101 (#e101)

Reproducing values (known-inputs):

```
{  
  "architecture": ""  
}
```

bitnami/metallb

Result: FAIL | Status: failed
Attempts: 160 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/metallb_1789262350/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 166 | Varied in render attempts: 7
Missing values: 3 | Undocumented template fields: 174
Unreferenced values: 75 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 59

Phase robustness: passed | Attempts: 101

Errors: E045 (#e045)

Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": []  
  }  
}
```

bitnami/metrics-server

Result: FAIL | Status: failed
Attempts: 199 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/metrics-server_1789262363/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 72 | Varied in render attempts: 13
Missing values: 0 | Undocumented template fields: 75
Unreferenced values: 32 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 98

Phase robustness: passed | Attempts: 101

Errors: E046 (#e046)

Reproducing values (known-inputs):

```
{  
  "dnsPolicy": "\u001f"  
}
```

bitnami/milvus

Result: N/A | Status: time-limit
Attempts: 30 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/milvus_1789262386/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 601 | Varied in render attempts: 3
Missing values: 1 | Undocumented template fields: 32
Unreferenced values: 227 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: time-limit | Attempts: 23

Phase robustness: time-limit | Attempts: 7

bitnami/mlflow

Result: FAIL | Status: failed
Attempts: 251 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mlflow_1789262402/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 217 | Varied in render attempts: 20
Missing values: 3 | Undocumented template fields: 18
Unreferenced values: 110 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 120

Phase robustness: failed | Attempts: 131

Errors: E083 (#e083), E047 (#e047)

Reproducing values (known-inputs):

```
{
  "volumePermissions": {
    "enabled": true
  }
}
```

Reproducing values (robustness):

```
{
  "nameOverride": "\u001f",
  "": []
}
```

bitnami/mongodb

Result: FAIL | Status: failed

Attempts: 101 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mongodb_1789262443/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 348 | Varied in render attempts: 7

Missing values: 5 | Undocumented template fields: 348

Unreferenced values: 141 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 43

Phase robustness: time-limit | Attempts: 58

Errors: E049 (#e049)

Reproducing values (known-inputs):

```
{
  "configuration": "\u001f"
}
```

bitnami/mongodb-sharded

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mongodb-sharded_1789262509/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 280 | Varied in render attempts: 2
Missing values: 2 | Undocumented template fields: 306
Unreferenced values: 7 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: E048 (#e048)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/moodle

Result: FAIL | Status: failed
Attempts: 242 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/moodle_1789262603/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 140 | Varied in render attempts: 45
Missing values: 3 | Undocumented template fields: 147
Unreferenced values: 51 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 141

Phase robustness: passed | Attempts: 101

Errors: E050 (#e050)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/multus-cni

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/multus-cni_1789262612/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 51 | Varied in render attempts: 2
Missing values: 1 | Undocumented template fields: 54
Unreferenced values: 36 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: E051 (#e051)

Reproducing values (known-inputs):

```
{  
  "CNIMountPath": ">"  
}
```

bitnami/mysql

Result: FAIL | Status: failed

Attempts: 239 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/mysql_1789262639/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 235 | Varied in render attempts: 40

Missing values: 6 | Undocumented template fields: 226

Unreferenced values: 86 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 138

Phase robustness: passed | Attempts: 101

Errors: E052 (#e052)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```

bitnami/nats

Result: FAIL | Status: failed

Attempts: 327 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/nats_1789262668/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 129 | Varied in render attempts: 51

Missing values: 0 | Undocumented template fields: 135

Unreferenced values: 70 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 226

Phase robustness: passed | Attempts: 101

Errors: E053 (#e053)

Reproducing values (known-inputs):

```
{  
  "nameOverride": "\u001f"  
}
```

bitnami/neo4j

Result: FAIL | Status: failed

Attempts: 137 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/neo4j_1789262693/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 123 | Varied in render attempts: 9

Missing values: 0 | Undocumented template fields: 131

Unreferenced values: 32 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/nessie

Result: FAIL | Status: failed

Attempts: 184 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/nessie_1789262730/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 141 | Varied in render attempts: 29

Missing values: 1 | Undocumented template fields: 147

Unreferenced values: 59 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 83

Phase robustness: passed | Attempts: 101

Errors: E054 (#e054)

Reproducing values (known-inputs):

```
{
  "annotations": {
    "": []
  }
}
```

bitnami/nginx

Result: FAIL | Status: failed
Attempts: 325 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/nginx_1789262745/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 170 | Varied in render attempts: 108
Missing values: 2 | Undocumented template fields: 159
Unreferenced values: 58 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 84

Phase robustness: failed | Attempts: 241

Errors: E056 (#e056), E055 (#e055)

Reproducing values (known-inputs):

```
{
  "existingContextEventsConfigmaps": [
    "\u001f"
  ]
}
```

Reproducing values (robustness):

```
{
  "contextIncludes": {
    "events": "\u001f",
    "": []
  }
}
```

bitnami/node-exporter

Result: FAIL | Status: failed
Attempts: 240 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/node-exporter_1789262746/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 85 | Varied in render attempts: 23
Missing values: 1 | Undocumented template fields: 88
Unreferenced values: 35 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 139

Phase robustness: passed | Attempts: 101

Errors: E114 (#e114)

Reproducing values (known-inputs):

```
{  
  "kubeVersion": ":"  
}
```

bitnami/oauth2-proxy

Result: FAIL | Status: failed

Attempts: 130 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/oauth2-proxy_1789262793/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 103 | Varied in render attempts: 23

Missing values: 0 | Undocumented template fields: 106

Unreferenced values: 50 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 29

Phase robustness: passed | Attempts: 101

Errors: E105 (#e105)

Reproducing values (known-inputs):

```
{  
  "redis": {  
    "architecture": ""  
  }  
}
```

bitnami/odoo

Result: FAIL | Status: failed

Attempts: 128 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/odoo_1789262798/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 122 | Varied in render attempts: 12

Missing values: 4 | Undocumented template fields: 127

Unreferenced values: 42 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 27

Phase robustness: passed | Attempts: 101

Errors: E102 (#e102)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/opensearch

Result: FAIL | Status: failed

Attempts: 206 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/opensearch_1789262840/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 523 | Varied in render attempts: 17

Missing values: 17 | Undocumented template fields: 546

Unreferenced values: 217 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 105

Phase robustness: passed | Attempts: 101

Errors: E057 (#e057)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": ":"  
}
```

bitnami/parse

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/parse_1789262841/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 165 | Varied in render attempts: 21

Missing values: 0 | Undocumented template fields: 173

Unreferenced values: 61 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E058 (#e058)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/phpmyadmin

Result: FAIL | Status: failed
Attempts: 234 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/phpmyadmin_1789262890/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 120 | Varied in render attempts: 27
Missing values: 5 | Undocumented template fields: 124
Unreferenced values: 36 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 133

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{
  "serviceAccount": {
    "name": ""
  }
}
```

bitnami/pinniped

Result: FAIL | Status: failed
Attempts: 160 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/pinniped_1789262910/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 173 | Varied in render attempts: 1
Missing values: 0 | Undocumented template fields: 180
Unreferenced values: 56 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 59

Phase robustness: passed | Attempts: 101

Errors: E059 (#e059)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/postgresql

Result: FAIL | Status: failed
Attempts: 280 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/postgresql_1789262926/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 310 | Varied in render attempts: 21
Missing values: 7 | Undocumented template fields: 314
Unreferenced values: 106 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 15

Phase robustness: failed | Attempts: 265

Errors: E103 (#e103), E061 (#e061)

Reproducing values (known-inputs):

```
{
  "psp": {
    "create": true
  }
}
```

Reproducing values (robustness):

```
{
  "": [],
  "auth": {
    "database": "\u001f"
  }
}
```

bitnami/postgresql-ha

Result: FAIL | Status: failed
Attempts: 157 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/postgresql-ha_1789262929/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 371 | Varied in render attempts: 18
Missing values: 3 | Undocumented template fields: 386
Unreferenced values: 121 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 56

Phase robustness: passed | Attempts: 101

Errors: E060 (#e060)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/prometheus

Result: FAIL | Status: failed

Attempts: 345 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/prometheus_1789262960/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 230 | Varied in render attempts: 18

Missing values: 0 | Undocumented template fields: 10

Unreferenced values: 86 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 93

Phase robustness: failed | Attempts: 252

Errors: E062 (#e062), E063 (#e063)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "extraDeploy": [
    []
  ]
}
```

bitnami/pytorch

Result: FAIL | Status: failed

Attempts: 179 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/pytorch_1789262979/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 87 | Varied in render attempts: 17

Missing values: 8 | Undocumented template fields: 92

Unreferenced values: 38 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 78

Phase robustness: passed | Attempts: 101

Errors: E104 (#e104)

Reproducing values (known-inputs):

```
{  
  "architecture": ""  
}
```

bitnami/rabbitmq

Result: FAIL | Status: failed

Attempts: 185 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/rabbitmq_1789262993/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 215 | Varied in render attempts: 28

Missing values: 1 | Undocumented template fields: 213

Unreferenced values: 94 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 84

Phase robustness: passed | Attempts: 101

Errors: E065 (#e065)

Reproducing values (known-inputs):

```
{  
  "hostPorts": {  
    "amqp": "\u001f"  
  }  
}
```

bitnami/rabbitmq-cluster-operator

Result: FAIL | Status: failed

Attempts: 230 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/rabbitmq-cluster-operator_1789263004/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 206 | Varied in render attempts: 90

Missing values: 3 | Undocumented template fields: 212

Unreferenced values: 53 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 129

Phase robustness: passed | Attempts: 101

Errors: E064 (#e064)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/redis

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/redis_1789263022/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 350 | Varied in render attempts: 67

Missing values: 6 | Undocumented template fields: 29

Unreferenced values: 133 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 5

Phase robustness: failed | Attempts: 129

Errors: E106 (#e106)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

Reproducing values (robustness):

```
{
  "": [],
  "architecture": ""
}
```

bitnami/redis-cluster

Result: FAIL | Status: failed

Attempts: 148 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/redis-cluster_1789263038/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 175 | Varied in render attempts: 4

Missing values: 1 | Undocumented template fields: 184

Unreferenced values: 51 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 47

Phase robustness: passed | Attempts: 101

Errors: E066 (#e066)

Reproducing values (known-inputs):

```
{  
  "existingSecret": "-"  
}
```

bitnami/redmine

Result: FAIL | Status: failed
Attempts: 516 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/redmine_1789263074/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 157 | Varied in render attempts: 50
Missing values: 9 | Undocumented template fields: 153
Unreferenced values: 66 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 104

Phase robustness: failed | Attempts: 412

Errors: E067 (#e067), E068 (#e068)

Reproducing values (known-inputs):

```
{  
  "terminationGracePeriodSeconds": "\u001f"  
}
```

Reproducing values (robustness):

```
{  
  "": [],  
  "service": {  
    "type": "-"  
  }  
}
```

bitnami/schema-registry

Result: FAIL | Status: failed
Attempts: 171 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/schema-registry_1789263074/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 119 | Varied in render attempts: 35
Missing values: 5 | Undocumented template fields: 122
Unreferenced values: 35 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 70

Phase robustness: passed | Attempts: 101

Errors: E084 (#e084)

Reproducing values (known-inputs):

```
{
  "httpRoutes": [
    null
  ]
}
```

bitnami/scylladb

Result: FAIL | Status: failed
Attempts: 209 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/scylladb_1789263109/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 161 | Varied in render attempts: 79
Missing values: 0 | Undocumented template fields: 169
Unreferenced values: 82 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 108

Phase robustness: passed | Attempts: 101

Errors: E085 (#e085)

Reproducing values (known-inputs):

```
{
  "extraContainerPorts": [
    null
  ]
}
```

bitnami/sealed-secrets

Result: FAIL | Status: failed
Attempts: 164 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/sealed-secrets_1789263115/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 114 | Varied in render attempts: 4
Missing values: 0 | Undocumented template fields: 117
Unreferenced values: 33 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 63

Phase robustness: passed | Attempts: 101

Errors: E107 (#e107)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/seaweedfs

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/seaweedfs_1789263116/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 578 | Varied in render attempts: 3
Missing values: 6 | Undocumented template fields: 610
Unreferenced values: 250 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: E069 (#e069)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/solr

Result: FAIL | Status: failed
Attempts: 213 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/solr_1789263147/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 168 | Varied in render attempts: 71
Missing values: 1 | Undocumented template fields: 176
Unreferenced values: 66 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 112

Phase robustness: passed | Attempts: 101

Errors: E070 (#e070)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/sonarqube

Result: FAIL | Status: failed

Attempts: 129 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/sonarqube_1789263200/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 165 | Varied in render attempts: 8

Missing values: 0 | Undocumented template fields: 181

Unreferenced values: 55 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 28

Phase robustness: passed | Attempts: 101

Errors: E071 (#e071)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/spark

Result: FAIL | Status: failed

Attempts: 129 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/spark_1789263236/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 180 | Varied in render attempts: 1

Missing values: 0 | Undocumented template fields: 185

Unreferenced values: 57 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 28

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": "0"  
}
```

bitnami/superset

Result: FAIL | Status: failed

Attempts: 137 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/superset_1789263238/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 299 | Varied in render attempts: 6

Missing values: 1 | Undocumented template fields: 313

Unreferenced values: 161 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: E072 (#e072)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```

bitnami/tensorflow-resnet

Result: FAIL | Status: failed

Attempts: 215 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/tensorflow-resnet_1789263255/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 73 | Varied in render attempts: 30

Missing values: 4 | Undocumented template fields: 77

Unreferenced values: 30 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 114

Phase robustness: passed | Attempts: 101

Errors: E073 (#e073)

Reproducing values (known-inputs):

```
{
  "service": {
    "loadBalancerIP": ":"
  }
}
```

bitnami/thanos

Result: FAIL | Status: failed

Attempts: 155 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/thanos_1789263263/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 971 | Varied in render attempts: 36

Missing values: 62 | Undocumented template fields: 992

Unreferenced values: 242 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 54

Phase robustness: passed | Attempts: 101

Errors: E074 (#e074)

Reproducing values (known-inputs):

```
{
  "bucketCacheConfig": "\u001f"
}
```

bitnami/tomcat

Result: FAIL | Status: failed

Attempts: 144 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/tomcat_1789263266/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 80 | Varied in render attempts: 0

Missing values: 5 | Undocumented template fields: 82

Unreferenced values: 93 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 43

Phase robustness: passed | Attempts: 101

Errors: E075 (#e075)

Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/valkey

Result: FAIL | Status: failed

Attempts: 140 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/valkey_1789263282/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 311 | Varied in render attempts: 13

Missing values: 1 | Undocumented template fields: 314

Unreferenced values: 132 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: E077 (#e077)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/valkey-cluster

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/valkey-cluster_1789263288/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 168 | Varied in render attempts: 51

Missing values: 0 | Undocumented template fields: 177

Unreferenced values: 49 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: E076 (#e076)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```

```
]
}
```

bitnami/vault

Result: FAIL | Status: failed
Attempts: 168 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/vault_1789263307/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 259 | Varied in render attempts: 7
Missing values: 1 | Undocumented template fields: 273
Unreferenced values: 94 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 67

Phase robustness: passed | Attempts: 101

Errors: E078 (#e078)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/victoriametrics

Result: FAIL | Status: failed
Attempts: 174 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/victoriametrics_1789263322/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 591 | Varied in render attempts: 4
Missing values: 0 | Undocumented template fields: 617
Unreferenced values: 129 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 73

Phase robustness: passed | Attempts: 101

Errors: E079 (#e079)

Reproducing values (known-inputs):

```
{
  "loggerFormat": "\u001f"
}
```

bitnami/whereabouts

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/whereabouts_1789263358/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 48 | Varied in render attempts: 4
Missing values: 0 | Undocumented template fields: 51
Unreferenced values: 33 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: E108 (#e108)

Reproducing values (known-inputs):

```
{  
  "resourcesPreset": ""  
}
```

bitnami/wildfly

Result: FAIL | Status: failed
Attempts: 145 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/wildfly_1789263365/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 110 | Varied in render attempts: 2
Missing values: 6 | Undocumented template fields: 116
Unreferenced values: 36 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: E112 (#e112)

Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/wordpress

Result: FAIL | Status: failed
Attempts: 395 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/wordpress_1789263373/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 177 | Varied in render attempts: 41
Missing values: 5 | Undocumented template fields: 170
Unreferenced values: 84 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 122

Phase robustness: failed | Attempts: 273

Errors: E080 (#e080), E081 (#e081)

Reproducing values (known-inputs):

```
{
  "apacheConfiguration": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": "?"
  }
}
```

bitnami/zipkin

Result: FAIL | Status: failed
Attempts: 2 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/zipkin_1789263388/0000

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 135 | Varied in render attempts: 0
Missing values: 1 | Undocumented template fields: 140
Unreferenced values: 77 (unknown)
Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 1

Phase robustness: failed | Attempts: 1

Errors: E109 (#e109)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```

bitnami/zookeeper

Result: FAIL | Status: failed

Attempts: 131 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: bitnami-runs/bitnami-charts_1789260948/runs/zookeeper_1789263392/0000

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Identified input fields (lower bound): 166 | Varied in render attempts: 1

Missing values: 2 | Undocumented template fields: 173

Unreferenced values: 46 (unknown)

Field variation does not prove branch or output coverage.

Phase known-inputs: failed | Attempts: 30

Phase robustness: passed | Attempts: 101

Errors: E082 (#e082)

Reproducing values (known-inputs):

```
{  
  "dataLogDir": "-"  
}
```