



Completed all 115 discovered charts with --filter, four workers, and a five-minute test budget per chart. No scan-wide deadline was imposed.

Recorded 19,846 test attempts across the 115 primary chart records in 41.0 minutes of wall time, including dependency preparation. Attempts include baseline checks and counterexample shrinking; they are not a count of unique inputs or bugs.

The kube-prometheus worker also recursively tested its nested CRD chart. That additional result is retained in supplemental-recursive-results.json; the 115-chart totals use each chart's dedicated job once.

Findings: 112 failed; 1 skipped-library; 2 time-limit.

Known-input phase: 112 failed; 2 time-limit.

Deferred robustness phase: 13 failed; 95 passed; 6 time-limit.

Known fields receive up to 90% of each chart budget; deferred original-contract cases run afterward using the remainder. A phase can finish early after finding and shrinking a counterexample. Dynamic and schema-defined maps remain open; the generation preference does not change the original validation contract or prove deferred inputs irrelevant.

Failure diagnostics across both phases: 13 explicit chart validation rejection; 6 manifest processing; 11 other; inspect diagnostic; 76 rendered YAML; 15 template evaluation; 4 values transport. These categories are based on diagnostic text and are not confirmed root causes.

Failures are observed render/manifest-check failures, including deliberate chart validation rejections and manifest-processing limitations. They need triage before being classified as chart defects. Charts without a values schema use inferred generation, not an authoritative input specification. A passed sample or completed scan does not establish exhaustive coverage.

Checks: dependency build in isolated copies, Helm lint, Helm template with values-schema checks, and built-in manifest checks. External kubeconform/kubesecc validation was not configured for this run.

Source: third_party/bitnami-charts at 6a8cccf3c29a1faabf0c34c8276a09ed14f3c5b3. The source checkout is retained.

A post-run serializer correction keeps ordinary Unicode keys literal instead of unnecessarily escaping every character. The original production findings remain unchanged; the four values-transport diagnostics are not evidence of chart-template defects. See transport-triage.json for the isolated reproduction.

[Combined PDF](#) · [Aggregate data](#) · [Raw logs and provenance](#)

Directory: third_party/bitnami-charts

Started (Unix epoch): 1789251228

Elapsed: 2461.80 seconds

Charts discovered: 115

Scan status: completed

Discovery complete: True

Unstarted charts: 0

Results describe the tested sample; they do not prove chart correctness.

Baseline-only, skipped, blocked, and incomplete charts are not property-test passes.

Status counts

```
{
  "failed": 112,
  "skipped-library": 1,
  "time-limit": 2
}
```



Settings

```
{
  "max_examples": 100,
  "filter": true,
  "permutations": null,
  "chart_timeout_seconds": 300.0,
  "scan_timeout_seconds": null,
  "helm": "Helm 4.3.0",
  "seed": 0,
  "build_dependencies": true,
  "values": "values.yaml",
  "workers": 4,
  "max_examples_per_phase": 100,
  "known_input_budget_fraction": 0.9,
  "external_conformity": false
}
```

Errors

113 distinct diagnostics across 125 occurrences; 12 repeats grouped.
Matching diagnostics do not establish a shared root cause.

E001

Error: YAML parse error on apache/templates/svc.yaml: error converting YAML to JSON: yaml: line 13: mapping values are not allowed in this context

- [bitnami/apache \(robustness: failed\)](#)

E002

Error: YAML parse error on apisix/templates/control-plane/api-token-secret.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/apisix \(known-inputs: failed\)](#)

E003

Error: YAML parse error on appsmith/templates/backend/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/appsmith \(known-inputs: failed\)](#)

E004

Error: YAML parse error on argo-cd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/argo-cd \(known-inputs: failed\)](#)

E005

Error: YAML parse error on argo-workflows/templates/controller/deployment.yaml: error converting YAML to JSON: yaml: line 30: mapping values are not allowed in this context

- [bitnami/argo-workflows \(known-inputs: failed\)](#)

E006

Error: YAML parse error on cassandra/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/cassandra \(known-inputs: failed\)](#)



E007

Error: YAML parse error on cert-manager/templates/cainjector/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/cert-manager \(known-inputs; failed\)](#)

E008

Error: YAML parse error on clickhouse/templates/statefulset.yaml: error converting YAML to JSON: yaml: line 178: mapping values are not allowed in this context

- [bitnami/clickhouse \(known-inputs; failed\)](#)

E009

Error: YAML parse error on cloudnative-pg/templates/operator/clusterrolebinding.yaml: error converting YAML to JSON: yaml: line 4: did not find expected comment or line break

- [bitnami/cloudnative-pg \(known-inputs; failed\)](#)

E010

Error: YAML parse error on consul/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/consul \(known-inputs; failed\)](#)

E011

Error: YAML parse error on contour/templates/certgen/serviceaccount.yaml: error converting YAML to JSON: yaml: line 15: did not find expected key

- [bitnami/contour \(known-inputs; failed\)](#)

E012

Error: YAML parse error on deepspeed/templates/client/client-dep-job.yaml: error converting YAML to JSON: yaml: line 31: did not find expected key

- [bitnami/deepspeed \(known-inputs; failed\)](#)

E013

Error: YAML parse error on discourse/templates/service.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/discourse \(known-inputs; failed\)](#)

E014

Error: YAML parse error on dremio/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/dremio \(known-inputs; failed\)](#)

E015

Error: YAML parse error on drupal/templates/svc.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/drupal \(robustness; failed\)](#)

E016

Error: YAML parse error on ejbca/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/ejbca \(known-inputs; failed\)](#)



E017

Error: YAML parse error on elasticsearch/templates/coordinating/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/elasticsearch \(known-inputs; failed\)](#)

E018

Error: YAML parse error on envoy-gateway/templates/deployment.yaml: error converting YAML to JSON: yaml: line 37: did not find expected key

- [bitnami/envoy-gateway \(known-inputs; failed\)](#)

E019

Error: YAML parse error on external-dns/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/external-dns \(known-inputs; failed\)](#)

E020

Error: YAML parse error on flink/templates/jobmanager/deployment.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/flink \(known-inputs; failed\)](#)

E021

Error: YAML parse error on fluentd/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/fluentd \(known-inputs; failed\)](#)

E022

Error: YAML parse error on flux/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/flux \(known-inputs; failed\)](#)

E023

Error: YAML parse error on ghost/templates/svc.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/ghost \(known-inputs; failed\)](#)

E024

Error: YAML parse error on gitea/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/gitea \(known-inputs; failed\)](#)

E025

Error: YAML parse error on gitlab-runner/templates/cluster-role.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/gitlab-runner \(known-inputs; failed\)](#)

E026

Error: YAML parse error on grafana-alloy/templates/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/grafana-alloy \(known-inputs; failed\)](#)



E027

Error: YAML parse error on grafana-loki/templates/gateway/configmap-http.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/grafana-loki \(known-inputs; failed\)](#)

E028

Error: YAML parse error on grafana-operator/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/grafana-operator \(known-inputs; failed\)](#)

E029

Error: YAML parse error on grafana-tempo/templates/tempo-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/grafana-tempo \(known-inputs; failed\)](#)

E030

Error: YAML parse error on haproxy/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/haproxy \(known-inputs; failed\)](#)

E031

Error: YAML parse error on harbor/templates/core/core-dpl.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/harbor \(known-inputs; failed\)](#)

E032

Error: YAML parse error on influxdb/templates/pdb.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/influxdb \(known-inputs; failed\)](#)

E033

Error: YAML parse error on janusgraph/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/janusgraph \(known-inputs; failed\)](#)

E034

Error: YAML parse error on kafka/templates/controller-eligible/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/kafka \(known-inputs; failed\)](#)

E035

Error: YAML parse error on kube-arangodb/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/kube-arangodb \(known-inputs; failed\)](#)

E036

Error: YAML parse error on kuberay/templates/apiserver/clusterrolebinding.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go struct field .metadata.annotations. of type string

- [bitnami/kuberay \(known-inputs; failed\)](#)



E037

Error: YAML parse error on kubernetes-event-exporter/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/kubernetes-event-exporter \(known-inputs; failed\)](#)

E038

Error: YAML parse error on logstash/templates/sts.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/logstash \(known-inputs; failed\)](#)

E039

Error: YAML parse error on mariadb-galera/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/mariadb-galera \(known-inputs; failed\)](#)

E040

Error: YAML parse error on mastodon/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/mastodon \(known-inputs; failed\)](#)

E041

Error: YAML parse error on matomo/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/matomo \(known-inputs; failed\)](#)

E042

Error: YAML parse error on metrics-server/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/metrics-server \(known-inputs; failed\)](#)

E043

Error: YAML parse error on mlflow/templates/run/dep-job.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/mlflow \(robustness; failed\)](#)

E044

Error: YAML parse error on mlflow/templates/run/dep-job.yaml: error converting YAML to JSON: yaml: line 29: did not find expected key

- [bitnami/mlflow \(known-inputs; failed\)](#)

E045

Error: YAML parse error on mongodb-sharded/templates/config-server/config-server-statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/mongodb-sharded \(known-inputs; failed\)](#)

E046

Error: YAML parse error on mongodb/templates/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/mongodb \(known-inputs; failed\)](#)



E047

Error: YAML parse error on moodle/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/moodle \(known-inputs; failed\)](#)

E048

Error: YAML parse error on multus-cni/templates/daemonset.yaml: error converting YAML to JSON: yaml: line 73: did not find expected comment or line break

- [bitnami/multus-cni \(known-inputs; failed\)](#)

E049

Error: YAML parse error on mysql/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/mysql \(known-inputs; failed\)](#)

E050

Error: YAML parse error on nessie/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/nessie \(known-inputs; failed\)](#)

E051

Error: YAML parse error on nginx/templates/context-includes-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/nginx \(robustness; failed\)](#)

E052

Error: YAML parse error on nginx/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/nginx \(known-inputs; failed\)](#)

E053

Error: YAML parse error on node-exporter/templates/daemonset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/node-exporter \(known-inputs; failed\)](#)

E054

Error: YAML parse error on parse/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/parse \(known-inputs; failed\)](#)

E055

Error: YAML parse error on phpmyadmin/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/phpmyadmin \(known-inputs; failed\)](#)

E056

Error: YAML parse error on pinniped/templates/concierge/apiservice-identity.yaml: error converting YAML to JSON: yaml: line 23: found unexpected end of stream

- [bitnami/pinniped \(known-inputs; failed\)](#)



E057

Error: YAML parse error on prometheus/templates/alertmanager/networkpolicy.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/prometheus \(known-inputs; failed\)](#)

E058

Error: YAML parse error on prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/prometheus \(robustness; failed\)](#)

E059

Error: YAML parse error on rabbitmq/templates/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/rabbitmq \(robustness; failed\)](#)

E060

Error: YAML parse error on redmine/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/redmine \(known-inputs; failed\)](#)

E061

Error: YAML parse error on seaweedfs/templates/filer/statefulset.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/seaweedfs \(known-inputs; failed\)](#)

E062

Error: YAML parse error on solr/templates/statefulset.yaml: error converting YAML to JSON: yaml: line 180: did not find expected key

- [bitnami/solr \(known-inputs; failed\)](#)

E063

Error: YAML parse error on sonarqube/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/sonarqube \(known-inputs; failed\)](#)

E064

Error: YAML parse error on spark/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/spark \(known-inputs; failed\)](#)

E065

Error: YAML parse error on superset/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/superset \(known-inputs; failed\)](#)

E066

Error: YAML parse error on tensorflow-resnet/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/tensorflow-resnet \(known-inputs; failed\)](#)



E067

Error: YAML parse error on thanos/templates/storegateway/configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/thanos \(known-inputs; failed\)](#)

E068

Error: YAML parse error on tomcat/templates/deployment.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/tomcat \(known-inputs; failed\)](#)

E069

Error: YAML parse error on valkey-cluster/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/valkey-cluster \(known-inputs; failed\)](#)

E070

Error: YAML parse error on valkey/templates/replicas/application.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/valkey \(known-inputs; failed\)](#)

E071

Error: YAML parse error on vault/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/vault \(known-inputs; failed\)](#)

E072

Error: YAML parse error on victoriametrics/templates/vmagent/dep-ds.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/victoriametrics \(known-inputs; failed\)](#)

E073

Error: YAML parse error on wordpress/templates/httpd-configmap.yaml: error converting YAML to JSON: yaml: control characters are not allowed

- [bitnami/wordpress \(known-inputs; failed\)](#)

E074

Error: execution error at (airflow/templates/NOTES.txt:129:3):
VALUES VALIDATION:

airflow: executors

You need to provide at least one value for the '.executor' parameter.

- [bitnami/airflow \(known-inputs; failed\)](#)

E075

Error: execution error at (aspnet-core/templates/NOTES.txt:58:4):
VALUES VALIDATION:

aspnet-core: missing-extra-volume-mounts

You specified extra volumes but not mount points for them.
Please also set the extraVolumeMounts parameter.

- [bitnami/aspnet-core \(known-inputs; failed\)](#)



E076

Error: execution error at (cadvisor/templates/daemonset.yaml:155:25): ERROR: Preset key '' invalid. Allowed values are xlarge,2xlarge,nano,micro,small,medium,large

- [bitnami/cadvisor \(known-inputs; failed\)](#)

E077

Error: execution error at (chainloop/templates/controlplane/secret-jwt-cas-private-key.yaml:14:22): Authentication Private Key "casJWTPrivateKey" required

- [bitnami/chainloop \(known-inputs; failed\)](#)

E078

Error: execution error at (drupal/charts/mariadb/templates/NOTES.txt:74:4):

VALUES VALIDATION:

mariadb: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/drupal \(known-inputs; failed\)](#)

E079

Error: execution error at (fluent-bit/templates/NOTES.txt:30:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/fluent-bit:4.0.8-debian-12-r0

If you are sure you want to proceed with non-standard containers, you can skip container image verification by setting the global parameter 'global.security.allowInsecureImages' to true. Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- [bitnami/fluent-bit \(known-inputs; failed\)](#)

E080

Error: execution error at (grafana-mimir/charts/memcachedchunks/templates/NOTES.txt:46:4):

VALUES VALIDATION:

memcached: architecture

Invalid architecture selected. Valid values are "standalone" and "high-availability". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/grafana-mimir \(known-inputs; failed\)](#)

E081

Error: execution error at (jaeger/templates/collector/deployment.yaml:199:25): ERROR: Preset key '' invalid. Allowed values are xlarge,2xlarge,nano,micro,small,medium,large

- [bitnami/jaeger \(known-inputs; failed\)](#)

E082

Error: execution error at (jenkins/templates/NOTES.txt:54:4):

\u26a0 ERROR: Original containers have been substituted for unrecognized ones. Deploying this chart with non-standard containers is likely to cause degraded security and performance, broken chart features, and missing environment variables.

Unrecognized images:

- 00/bitnami/jenkins:2.516.2-debian-12-r0
- 00/bitnami/jenkins-agent:0.3327.0-debian-12-r1
- 00/bitnami/os-shell:12-debian-12-r51

If you are sure you want to proceed with non-standard containers, you can skip container image



verification by setting the global parameter 'global.security.allowInsecureImages' to true.
Further information can be obtained at <https://github.com/bitnami/charts/issues/30850>

- [bitnami/jenkins \(known-inputs; failed\)](#)

E083

Error: execution error at (jupyterhub/templates/proxy/deployment.yaml:32:32): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- [bitnami/jupyterhub \(known-inputs; failed\)](#)

E084

Error: execution error at (kube-state-metrics/templates/deployment.yaml:205:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- [bitnami/kube-state-metrics \(known-inputs; failed\)](#)

E085

Error: execution error at (mariadb/templates/NOTES.txt:74:4):

VALUES VALIDATION:

mariadb: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/mariadb \(known-inputs; failed\)](#)

- [bitnami/mariadb \(robustness; failed\)](#)

E086

Error: execution error at (memcached/templates/NOTES.txt:46:4):

VALUES VALIDATION:

memcached: architecture

Invalid architecture selected. Valid values are "standalone" and "high-availability". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/memcached \(known-inputs; failed\)](#)

E087

Error: execution error at (nats/templates/NOTES.txt:176:4):

VALUES VALIDATION:

nats: resourceType

Invalid resourceType selected. Valid values are "deployment" and "statefulset". Please set a valid mode (--set resourceType="xxxx")

- [bitnami/nats \(known-inputs; failed\)](#)

E088

Error: execution error at (oauth2-proxy/charts/redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/oauth2-proxy \(known-inputs; failed\)](#)

E089

Error: execution error at (odoo/templates/deployment.yaml:270:25): ERROR: Preset key '' invalid. Allowed values are large,xlarge,2xlarge,nano,micro,small,medium

- [bitnami/odoo \(known-inputs; failed\)](#)



E090

Error: execution error at (opensearch/templates/ingest/statefulset.yaml:90:12): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- [bitnami/opensearch \(known-inputs; failed\)](#)

E091

Error: execution error at (postgresql/templates/NOTES.txt:118:4):

VALUES VALIDATION:

postgresql: psp.create, rbac.create

RBAC should be enabled if PSP is enabled in order for PSP to work.

More info at <https://kubernetes.io/docs/concepts/policy/pod-security-policy/#authorizing-policies>

- [bitnami/postgresql \(known-inputs; failed\)](#)

E092

Error: execution error at (pytorch/templates/NOTES.txt:69:3):

VALUES VALIDATION:

pytorch: architecture

Invalid architecture selected. Valid values are "distributed" and "standalone". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/pytorch \(known-inputs; failed\)](#)

E093

Error: execution error at (redis/templates/NOTES.txt:202:4):

VALUES VALIDATION:

redis: architecture

Invalid architecture selected. Valid values are "standalone" and "replication". Please set a valid architecture (--set architecture="xxxx")

- [bitnami/redis \(known-inputs; failed\)](#)

- [bitnami/redis \(robustness; failed\)](#)

E094

Error: execution error at (sealed-secrets/templates/deployment.yaml:172:25): ERROR: Preset key '' invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- [bitnami/sealed-secrets \(known-inputs; failed\)](#)

E095

Error: execution error at (whereabouts/templates/daemonset.yaml:164:25): ERROR: Preset key ''

invalid. Allowed values are small,medium,large,xlarge,2xlarge,nano,micro

- [bitnami/whereabouts \(known-inputs; failed\)](#)

E096

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-aswf0y7m/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- [bitnami/jenkins \(robustness; failed\)](#)

E097

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-i22elfg5/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- [bitnami/redmine \(robustness; failed\)](#)



E098

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-if0kaa5a/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- [bitnami/ghost \(robustness; failed\)](#)

E099

Error: failed to parse /var/folders/dd/pd400p1j4vgf5gv6qp6zfx000000gn/T/hypothesis-helm-rtvkvk8/values.json: cannot unmarshal yaml document: error converting YAML to JSON: yaml: did not find expected ',', ' or '}'

- [bitnami/rabbitmq \(known-inputs; failed\)](#)

E100

Error: grafana/templates/application.yaml:225:72
executing "grafana/templates/application.yaml" at <.configMapName>:
nil pointer evaluating interface {}.configMapName

- [bitnami/grafana \(known-inputs; failed\)](#)

E101

Error: kibana/templates/ingress.yaml:33:64
executing "kibana/templates/ingress.yaml" at <.name>:
nil pointer evaluating interface {}.name

- [bitnami/kibana \(known-inputs; failed\)](#)

E102

Error: neo4j/templates/networkpolicy.yaml:47:19
executing "neo4j/templates/networkpolicy.yaml" at <.containerPort>:
nil pointer evaluating interface {}.containerPort

- [bitnami/neo4j \(known-inputs; failed\)](#)

E103

Error: schema-registry/templates/http-route.yaml:7:13
executing "schema-registry/templates/http-route.yaml" at <\$route.enabled>:
nil pointer evaluating interface {}.enabled

- [bitnami/schema-registry \(known-inputs; failed\)](#)

E104

Error: template: cilium/templates/agent/daemonset.yaml:30:15: executing
"cilium/templates/agent/daemonset.yaml" at <semverCompare "<1.30-0" (include
"common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- [bitnami/cilium \(known-inputs; failed\)](#)

E105

Error: template: concourse/templates/worker/rolebinding.yaml:27:22: executing
"concourse/templates/worker/rolebinding.yaml" at <semverCompare "<1.25-0" (include
"common.capabilities.kubeVersion" .)>: error calling semverCompare: invalid semantic version

- [bitnami/concourse \(known-inputs; failed\)](#)



E106

Error: template: metallb/templates/speaker/rbac.yaml:44:14: executing "metallb/templates/speaker/rbac.yaml" at <include "common.capabilities.psp.supported" .>: error calling include: template: metallb/charts/common/templates/_capabilities.tpl:131:32: executing "common.capabilities.psp.supported" at <semverCompare "<1.25-0" \$kubeVersion>: error calling semverCompare: invalid semantic version

- [bitnami/metallb \(known-inputs; failed\)](#)

E107

Error: template: rabbitmq-cluster-operator/templates/messaging-topology-operator/validating-webhook-configuration.yaml:14:13: executing "rabbitmq-cluster-operator/templates/messaging-topology-operator/validating-webhook-configuration.yaml" at <genSignedCert (include "rmqco.msgTopologyOperator.fullname" .) nil (list (printf "%s.%s.svc" (include "rmqco.msgTopologyOperator.webhook.fullname" .) (include "common.names.namespace" .)) (printf "%s.%s.svc.%s" (include "rmqco.msgTopologyOperator.webhook.fullname" .) (include "common.names.namespace" .) .Values.clusterDomain)) 365 \$ca>: error calling genSignedCert: error creating certificate: x509: "hypothesis-rabbitmq-messaging-topology-operator-webhook.default.svc.\u0080" cannot be encoded as an IA5String

- [bitnami/rabbitmq-cluster-operator \(known-inputs; failed\)](#)

E108

chart rendered no resources (use allow_empty explicitly)

- [bitnami/kube-prometheus/charts/kube-prometheus-crds \(known-inputs; failed\)](#)

- [bitnami/kube-prometheus/charts/kube-prometheus-crds \(robustness; failed\)](#)

E109

duplicate resource: ('rbac.authorization.k8s.io/v1', 'Role', None, 'hypothesis-clickhouse-operator')

- [bitnami/clickhouse-operator \(known-inputs; failed\)](#)

E110

invalid rendered YAML: more indented follow up line than first in a block scalar

in "<unicode string>", line 474, column 15:

set -o errexit

^ (line: 474)

- [bitnami/zipkin \(known-inputs; failed\)](#)

- [bitnami/zipkin \(robustness; failed\)](#)

E111

The test tool could not convert a YAML-tagged value to JSON. See this chart's reproducing values. This diagnostic alone does not establish a chart defect.

- [bitnami/apache \(known-inputs; failed\)](#)

- [bitnami/grafana-k6-operator \(known-inputs; failed\)](#)

- [bitnami/kong \(known-inputs; failed\)](#)

- [bitnami/redis-cluster \(known-inputs; failed\)](#)

- [bitnami/scylladb \(known-inputs; failed\)](#)

- [bitnami/zookeeper \(known-inputs; failed\)](#)

E112

level=INFO msg="warning: destination for kube-state-metrics.rbac.rules is a table. Ignoring non-table value ([])"

Error: YAML parse error on kube-prometheus/templates/extra-list.yaml: error unmarshaling JSON: while decoding JSON: json: cannot unmarshal array into Go value of type util.SimpleHead

- [bitnami/kube-prometheus \(known-inputs; failed\)](#)



E113

resource has no metadata.name

- [bitnami/keycloak \(known-inputs; failed\)](#)
- [bitnami/keydb \(known-inputs; failed\)](#)
- [bitnami/postgresql-ha \(known-inputs; failed\)](#)
- [bitnami/wildfly \(known-inputs; failed\)](#)

Charts

bitnami/airflow

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/airflow_1789251228/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: [E074](#)

Reproducing values (known-inputs):

```
{
  "executor": ""
}
```

bitnami/apache

Result: FAIL | Status: failed

Attempts: 411 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/apache_1789251228/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 119

Phase robustness: failed | Attempts: 292

Errors: [E111](#), [E001](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "="
}
```

Reproducing values (robustness):

```
{
  "": [],
  "service": {
    "type": ":"
  }
}
```



bitnami/apisix

Result: FAIL | Status: failed
Attempts: 83 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/apisix_1789251228/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 52
Phase robustness: time-limit | Attempts: 31
Errors: [E002](#)
Reproducing values (known-inputs):

```
{  
  "nameOverride": "\u001f"  
}
```

bitnami/appsmith

Result: FAIL | Status: failed
Attempts: 136 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/appsmith_1789251228/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 35
Phase robustness: passed | Attempts: 101
Errors: [E003](#)
Reproducing values (known-inputs):

```
{  
  "nameOverride": "\u001f"  
}
```

bitnami/argo-cd

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/argo-cd_1789251295/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 61
Phase robustness: passed | Attempts: 101
Errors: [E004](#)
Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```



bitnami/argo-workflows

Result: FAIL | Status: failed

Attempts: 130 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/argo-workflows_1789251302/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 29

Phase robustness: passed | Attempts: 101

Errors: [E005](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/aspnet-core

Result: FAIL | Status: failed

Attempts: 186 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/aspnet-core_1789251350/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 85

Phase robustness: passed | Attempts: 101

Errors: [E075](#)

Reproducing values (known-inputs):

```
{
  "extraVolumes": [
    null
  ]
}
```

bitnami/cadvisor

Result: FAIL | Status: failed

Attempts: 126 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/cadvisor_1789251373/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 25

Phase robustness: passed | Attempts: 101

Errors: [E076](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```



bitnami/cassandra

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/cassandra_1789251382/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 34
Phase robustness: passed | Attempts: 101
Errors: [E006](#)
Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/cert-manager

Result: FAIL | Status: failed
Attempts: 170 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/cert-manager_1789251391/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 69
Phase robustness: passed | Attempts: 101
Errors: [E007](#)
Reproducing values (known-inputs):

```
{  
  "leaderElection": {  
    "namespace": "\u001f"  
  }  
}
```

bitnami/chainloop

Result: FAIL | Status: failed
Attempts: 165 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/chainloop_1789251406/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 64
Phase robustness: passed | Attempts: 101
Errors: [E077](#)
Reproducing values (known-inputs):

```
{  
  "development": false  
}
```



bitnami/cilium

Result: FAIL | Status: failed
Attempts: 187 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/cilium_1789251449/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 86
Phase robustness: passed | Attempts: 101
Errors: [E104](#)
Reproducing values (known-inputs):

```
{  
  "kubeVersion": ":"  
}
```

bitnami/clickhouse

Result: FAIL | Status: failed
Attempts: 193 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/clickhouse_1789251452/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 92
Phase robustness: passed | Attempts: 101
Errors: [E008](#)
Reproducing values (known-inputs):

```
{  
  "startdbScriptsSecret": ":"  
}
```

bitnami/clickhouse-operator

Result: FAIL | Status: failed
Attempts: 157 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/clickhouse-operator_1789251497/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 56
Phase robustness: passed | Attempts: 101
Errors: [E109](#)
Reproducing values (known-inputs):

```
{  
  "watchNamespaces": [  
    null,  
    null  
  ]  
}
```



bitnami/cloudnative-pg

Result: FAIL | Status: failed

Attempts: 152 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/cloudnative-pg 1789251513/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: [E009](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ">"
}
```

bitnami/common

Result: N/A | Status: skipped-library

Attempts: N/A | Remaining iterations: unknown

Coverage: not a standalone application

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/common 1789251532/0000](#)

Filtering applied: False

Chart did not enter finite permutation testing

bitnami/concourse

Result: FAIL | Status: failed

Attempts: 158 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/concourse 1789251532/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 57

Phase robustness: passed | Attempts: 101

Errors: [E105](#)

Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```

bitnami/consul

Result: FAIL | Status: failed

Attempts: 140 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/consul 1789251533/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 39

Phase robustness: passed | Attempts: 101

Errors: [E010](#)

Reproducing values (known-inputs):

```
{
```



```
"existingConfigmap": "\u001f"
}
```

bitnami/contour

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/contour 1789251558/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E011](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/deepspeed

Result: FAIL | Status: failed
Attempts: 101 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/deepspeed 1789251584/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 12

Phase robustness: time-limit | Attempts: 89

Errors: [E012](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": null
  }
}
```

bitnami/discourse

Result: FAIL | Status: failed
Attempts: 162 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/discourse 1789251597/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 61

Phase robustness: passed | Attempts: 101

Errors: [E013](#)

Reproducing values (known-inputs):

```
{
  "service": {
    "annotations": {
```



```

    "": []
  }
}
}

```

bitnami/dremio

Result: FAIL | Status: failed
 Attempts: 133 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/dremio_1789251625/0000
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 32
 Phase robustness: passed | Attempts: 101
 Errors: [E014](#)
 Reproducing values (known-inputs):

```

{
  "extraDeploy": [
    []
  ]
}

```

bitnami/drupal

Result: FAIL | Status: failed
 Attempts: 252 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: bitnami-runs/bitnami-charts_1789251211/runs/drupal_1789251652/0000
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 29
 Phase robustness: failed | Attempts: 223
 Errors: [E078](#), [E015](#)
 Reproducing values (known-inputs):

```

{
  "mariadb": {
    "architecture": ""
  }
}

```

Reproducing values (robustness):

```

{
  "": [],
  "service": {
    "type": "\u001f"
  }
}

```



bitnami/ejbca

Result: FAIL | Status: failed
Attempts: 147 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/ejbca_1789251723/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 46
Phase robustness: passed | Attempts: 101
Errors: [E016](#)

Reproducing values (known-inputs):

```
{  
  "ejbcaKeystoreExistingSecret": "\u001f"  
}
```

bitnami/elasticsearch

Result: FAIL | Status: failed
Attempts: 180 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/elasticsearch_1789251725/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 79
Phase robustness: passed | Attempts: 101
Errors: [E017](#)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/envoy-gateway

Result: FAIL | Status: failed
Attempts: 157 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/envoy-gateway_1789251751/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 56
Phase robustness: passed | Attempts: 101
Errors: [E018](#)

Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": null  
  }  
}
```



bitnami/etcd

Result: N/A | Status: time-limit
Attempts: 105 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/etcd_1789251756/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: time-limit | Attempts: 95
Phase robustness: time-limit | Attempts: 10

bitnami/external-dns

Result: FAIL | Status: failed
Attempts: 148 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/external-dns_1789251819/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 47
Phase robustness: passed | Attempts: 101

Errors: [E019](#)

Reproducing values (known-inputs):

```
{
  "interval": "\u001f"
}
```

bitnami/flink

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/flink_1789251853/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 19
Phase robustness: passed | Attempts: 101

Errors: [E020](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": []
  }
}
```

bitnami/fluent-bit

Result: FAIL | Status: failed
Attempts: 245 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/fluent-bit_1789251880/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 144



Phase robustness: passed | Attempts: 101

Errors: [E079](#)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

bitnami/fluentd

Result: FAIL | Status: failed

Attempts: 129 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/fluentd_1789251891/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 28

Phase robustness: passed | Attempts: 101

Errors: [E021](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/flux

Result: FAIL | Status: failed

Attempts: 119 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/flux_1789251919/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 18

Phase robustness: passed | Attempts: 101

Errors: [E022](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/ghost

Result: FAIL | Status: failed

Attempts: 396 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/ghost_1789251929/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 154



Phase robustness: failed | Attempts: 242

Errors: [E023](#), [E098](#)

Reproducing values (known-inputs):

```
{
  "service": {
    "annotations": {
      "": []
    }
  }
}
```

Reproducing values (robustness):

```
{
  "": {
    "\u1e70\u033a\u033a\u0315o\u035e \u0337i\u0332\u032c\u0347\u032a\u0359n\u031d\u0317\u0355v\u031f
\u031c\u0318\u0326\u035fo\u0336\u0319\u0330\u0320k\u00e8\u035a\u032e\u033a\u032a\u0339\u0331\u0324 \
\u0316t\u031d\u0355\u0333\u0323\u033b\u032a\u035eh\u033c\u0353\u0332\u0326\u0333\u0318\u0332e\u0347\u
0323\u0330\u0326\u032c\u034e \u0322\u033c\u033b\u0331\u0318h\u035a\u034e\u0359\u031c\u0323\u0332\u03
45i\u0326\u0332\u0323\u0330\u0324v\u033b\u034de\u033a\u032d\u0333\u032a\u0330-
m\u0322i\u0345n\u0316\u033a\u031e\u0332\u032f\u0330d\u0335\u033c\u031f\u0359\u0329\u033c\u0318\u0333
\u031e\u0325\u0331\u0333\u032dr\u031b\u0317\u0318e\u0359p\u0360r\u033c\u031e\u033b\u032d\u0317e\u033
a\u0320\u0323\u035fs\u0318\u0347\u0333\u034d\u031d\u0349e\u0349\u0325\u032f\u031e\u0332\u035a\u032c\
\u035c\u01f9\u032c\u034e\u034e\u031f\u0316\u0347\u0324t\u034d\u032c\u0324\u0353\u033c\u032d\u0358\u03
45i\u032a\u0331n\u0360g\u0334\u0349 \u034f\u0349\u0345c\u032c\u031fh\u0361a\u032b\u033b\u032f\u0358o
\u032b\u031f\u0316\u034d\u0319\u031d\u0349s\u0317": null
  }
}
```

bitnami/gitea

Result: FAIL | Status: failed

Attempts: 147 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/gitea 1789251952/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 46

Phase robustness: passed | Attempts: 101

Errors: [E024](#)

Reproducing values (known-inputs):

```
{
  "smtpExistingSecret": "\u001f"
}
```

bitnami/gitlab-runner

Result: FAIL | Status: failed

Attempts: 213 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/gitlab-runner 1789251987/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 112

Phase robustness: passed | Attempts: 101



Errors: [E025](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/grafana

Result: FAIL | Status: failed

Attempts: 197 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana_1789252005/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 96

Phase robustness: passed | Attempts: 101

Errors: [E100](#)

Reproducing values (known-inputs):

```
{
  "dashboardsConfigMaps": [
    null
  ]
}
```

bitnami/grafana-alloy

Result: FAIL | Status: failed

Attempts: 239 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana-alloy_1789252023/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 138

Phase robustness: passed | Attempts: 101

Errors: [E026](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

bitnami/grafana-k6-operator

Result: FAIL | Status: failed

Attempts: 187 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana-k6-operator_1789252042/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 86

Phase robustness: passed | Attempts: 101

Errors: [E111](#)

Reproducing values (known-inputs):

```
{
```



```
"extraEnvVarsCM": "="
}
```

bitnami/grafana-loki

Result: FAIL | Status: failed
 Attempts: 149 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana-loki_1789252062/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 48
 Phase robustness: passed | Attempts: 101
 Errors: [E027](#)
 Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u001f"
}
```

bitnami/grafana-mimir

Result: FAIL | Status: failed
 Attempts: 125 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana-mimir_1789252066/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 24
 Phase robustness: passed | Attempts: 101
 Errors: [E080](#)
 Reproducing values (known-inputs):

```
{
  "memcachedchunks": {
    "architecture": ""
  }
}
```

bitnami/grafana-operator

Result: FAIL | Status: failed
 Attempts: 162 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana-operator_1789252073/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 61
 Phase robustness: passed | Attempts: 101
 Errors: [E028](#)
 Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```



bitnami/grafana-tempo

Result: FAIL | Status: failed

Attempts: 138 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/grafana-tempo_1789252105/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 37

Phase robustness: passed | Attempts: 101

Errors: [E029](#)

Reproducing values (known-inputs):

```
{
  "tempo": {
    "configuration": "\u001f"
  }
}
```

bitnami/haproxy

Result: FAIL | Status: failed

Attempts: 193 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/haproxy_1789252206/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 92

Phase robustness: passed | Attempts: 101

Errors: [E030](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/harbor

Result: FAIL | Status: failed

Attempts: 137 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/harbor_1789252208/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 36

Phase robustness: passed | Attempts: 101

Errors: [E031](#)

Reproducing values (known-inputs):

```
{
  "existingSecret": "\u001f"
}
```



bitnami/influxdb

Result: FAIL | Status: failed
Attempts: 344 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/influxdb_1789252221/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 243
Phase robustness: passed | Attempts: 101
Errors: [E032](#)
Reproducing values (known-inputs):

```
{
  "pdb": {
    "maxUnavailable": "\u001f"
  }
}
```

bitnami/jaeger

Result: FAIL | Status: failed
Attempts: 207 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/jaeger_1789252233/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 106
Phase robustness: passed | Attempts: 101
Errors: [E081](#)
Reproducing values (known-inputs):

```
{
  "collector": {
    "resourcesPreset": ""
  }
}
```

bitnami/janusgraph

Result: FAIL | Status: failed
Attempts: 139 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/janusgraph_1789252257/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 38
Phase robustness: passed | Attempts: 101
Errors: [E033](#)
Reproducing values (known-inputs):

```
{
  "existingConfigmap": "\u001f"
}
```



bitnami/jenkins

Result: FAIL | Status: failed
 Attempts: 405 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/jenkins_1789252283/0000](#)

Filtering applied: True
 Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 136

Phase robustness: failed | Attempts: 269

Errors: [E082](#), [E096](#)

Reproducing values (known-inputs):

```
{
  "global": {
    "imageRegistry": "00"
  }
}
```

Reproducing values (robustness):

```
{
  "": {
    "\u001e70\u0033a\u0033a\u003150\u0035e \u00337i\u0032\u0032c\u00347\u0032a\u00359n\u0031d\u00317\u00355v\u0031f
\u0031c\u00318\u00326\u0035fo\u00336\u00319\u00330\u00320k\u000e8\u0035a\u0032e\u0033a\u0032a\u00339\u00331\u00324 \
\u00316t\u0031d\u00355\u00333\u00323\u0033b\u0032a\u0035eh\u0033c\u00353\u0032\u00326\u00333\u00318\u00332e\u00347\u
00323\u00330\u00326\u0032c\u0034e \u00322\u0033c\u0033b\u00331\u00318h\u0035a\u0034e\u00359\u0031c\u00323\u00332\u003
45i\u00326\u00332\u00323\u00330\u00324v\u0033b\u0034de\u0033a\u0032d\u00333\u0032a\u00330-
m\u00322i\u00345n\u00316\u0033a\u0031e\u00332\u0032f\u00330d\u00335\u0033c\u0031f\u00359\u00329\u0033c\u00318\u00333
\u0031e\u00325\u00331\u00333\u0032dr\u0031b\u00317\u00318e\u00359p\u00360r\u0033c\u0031e\u0033b\u0032d\u00317e\u0033
a\u00320\u00323\u0035fs\u00318\u00347\u00333\u0034d\u0031d\u00349e\u00349\u00325\u0032f\u0031e\u00332\u0035a\u0032c\u
\u0035c\u001f9\u0032c\u0034e\u0034e\u0031f\u00316\u00347\u00324t\u0034d\u0032c\u00324\u00353\u0033c\u0032d\u00358\u003
45i\u0032a\u00331n\u00360g\u00334\u00349 \u0034f\u00349\u00345c\u0032c\u0031fh\u00361a\u0032b\u0033b\u0032f\u00358o
\u0032b\u0031f\u00316\u0034d\u00319\u0031d\u00349s\u00317": null
  }
}
```

bitnami/jupyterhub

Result: FAIL | Status: failed
 Attempts: 126 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/jupyterhub_1789252291/0000](#)

Filtering applied: True
 Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 25

Phase robustness: passed | Attempts: 101

Errors: [E083](#)

Reproducing values (known-inputs):

```
{
  "singleuser": {
    "resourcesPreset": ""
  }
}
```



bitnami/kafka

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kafka_1789252297/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 40
Phase robustness: passed | Attempts: 101
Errors: [E034](#)
Reproducing values (known-inputs):

```
{  
  "dnsPolicy": "\u001f"  
}
```

bitnami/keycloak

Result: FAIL | Status: failed
Attempts: 240 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/keycloak_1789252350/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 139
Phase robustness: passed | Attempts: 101
Errors: [E113](#)
Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/keydb

Result: FAIL | Status: failed
Attempts: 127 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/keydb_1789252362/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 26
Phase robustness: passed | Attempts: 101
Errors: [E113](#)
Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```



bitnami/kibana

Result: FAIL | Status: failed
Attempts: 317 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kibana_1789252366/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 216
Phase robustness: passed | Attempts: 101
Errors: [E101](#)
Reproducing values (known-inputs):

```
{
  "ingress": {
    "enabled": true,
    "extraHosts": [
      null
    ]
  }
}
```

bitnami/kong

Result: FAIL | Status: failed
Attempts: 142 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kong_1789252404/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 41
Phase robustness: passed | Attempts: 101
Errors: [E111](#)
Reproducing values (known-inputs):

```
{
  "terminationGracePeriodSeconds": "="
}
```

bitnami/kube-arangodb

Result: FAIL | Status: failed
Attempts: 163 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kube-arangodb_1789252412/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 62
Phase robustness: passed | Attempts: 101
Errors: [E035](#)
Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```



bitnami/kube-prometheus

Result: FAIL | Status: failed
Attempts: 119 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kube-prometheus_1789252419/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 18
Phase robustness: passed | Attempts: 101
Errors: [E112](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/kube-prometheus/charts/kube-prometheus-crds

Result: FAIL | Status: failed
Attempts: 2 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kube-prometheus-crds_1789252451/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 1
Phase robustness: failed | Attempts: 1
Errors: [E108](#)

Reproducing values (known-inputs):

```
{}
```

Reproducing values (robustness):

```
{}
```

bitnami/kube-state-metrics

Result: FAIL | Status: failed
Attempts: 118 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kube-state-metrics_1789252452/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 17
Phase robustness: passed | Attempts: 101
Errors: [E084](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```



bitnami/kuberay

Result: FAIL | Status: failed
Attempts: 132 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kuberay_1789252452/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 31
Phase robustness: passed | Attempts: 101
Errors: [E036](#)

Reproducing values (known-inputs):

```
{
  "commonAnnotations": {
    "": []
  }
}
```

bitnami/kubernetes-event-exporter

Result: FAIL | Status: failed
Attempts: 331 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/kubernetes-event-exporter_1789252461/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 230
Phase robustness: passed | Attempts: 101
Errors: [E037](#)

Reproducing values (known-inputs):

```
{
  "image": {
    "digest": "\u001f"
  }
}
```

bitnami/logstash

Result: FAIL | Status: failed
Attempts: 141 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/logstash_1789252473/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 40
Phase robustness: passed | Attempts: 101
Errors: [E038](#)

Reproducing values (known-inputs):

```
{
  "existingConfiguration": "\u001f"
}
```



bitnami/mariadb

Result: FAIL | Status: failed
Attempts: 127 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mariadb_1789252495/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 5
Phase robustness: failed | Attempts: 122
Errors: [E085](#)

Reproducing values (known-inputs):

```
{  
  "architecture": ""  
}
```

Reproducing values (robustness):

```
{  
  "": [],  
  "architecture": ""  
}
```

bitnami/mariadb-galera

Result: FAIL | Status: failed
Attempts: 90 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mariadb-galera_1789252506/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 68
Phase robustness: time-limit | Attempts: 22
Errors: [E039](#)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```

bitnami/mastodon

Result: FAIL | Status: failed
Attempts: 200 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mastodon_1789252506/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 99
Phase robustness: passed | Attempts: 101
Errors: [E040](#)

Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```



```
[ ]
]
```

bitnami/matomo

Result: FAIL | Status: failed
Attempts: 134 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/matomo_1789252549/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 33
Phase robustness: passed | Attempts: 101
Errors: [E041](#)
Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/memcached

Result: FAIL | Status: failed
Attempts: 161 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/memcached_1789252601/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 60
Phase robustness: passed | Attempts: 101
Errors: [E086](#)
Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

bitnami/metallb

Result: FAIL | Status: failed
Attempts: 225 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/metallb_1789252639/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 124
Phase robustness: passed | Attempts: 101
Errors: [E106](#)
Reproducing values (known-inputs):

```
{
  "kubeVersion": ":"
}
```



bitnami/metrics-server

Result: FAIL | Status: failed
Attempts: 248 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/metrics-server_1789252645/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 147
Phase robustness: passed | Attempts: 101
Errors: [E042](#)
Reproducing values (known-inputs):

```
{  
  "terminationGracePeriodSeconds": "\u001f"  
}
```

bitnami/milvus

Result: N/A | Status: time-limit
Attempts: 30 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/milvus_1789252691/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: time-limit | Attempts: 23
Phase robustness: time-limit | Attempts: 7

bitnami/mlflow

Result: FAIL | Status: failed
Attempts: 193 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mlflow_1789252697/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 66
Phase robustness: failed | Attempts: 127
Errors: [E044](#), [E043](#)
Reproducing values (known-inputs):

```
{  
  "commonAnnotations": {  
    "": null  
  }  
}
```

Reproducing values (robustness):

```
{  
  "nameOverride": "\u001f",  
  "": []  
}
```



bitnami/mongodb

Result: FAIL | Status: failed
Attempts: 87 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mongodb_1789252761/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 43
Phase robustness: time-limit | Attempts: 44
Errors: [E046](#)

Reproducing values (known-inputs):

```
{  
  "configuration": "\u001f"  
}
```

bitnami/mongodb-sharded

Result: FAIL | Status: failed
Attempts: 145 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mongodb-sharded_1789252809/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 44
Phase robustness: passed | Attempts: 101
Errors: [E045](#)

Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/moodle

Result: FAIL | Status: failed
Attempts: 184 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/moodle_1789252874/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 83
Phase robustness: passed | Attempts: 101
Errors: [E047](#)

Reproducing values (known-inputs):

```
{  
  "existingSecret": "\u001f"  
}
```



bitnami/multus-cni

Result: FAIL | Status: failed

Attempts: 135 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/multus-cni_1789252902/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 34

Phase robustness: passed | Attempts: 101

Errors: [E048](#)

Reproducing values (known-inputs):

```
{
  "CNIMountPath": ">"
}
```

bitnami/mysql

Result: FAIL | Status: failed

Attempts: 234 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/mysql_1789252935/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 133

Phase robustness: passed | Attempts: 101

Errors: [E049](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/nats

Result: FAIL | Status: failed

Attempts: 152 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/nats_1789252944/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 51

Phase robustness: passed | Attempts: 101

Errors: [E087](#)

Reproducing values (known-inputs):

```
{
  "resourceType": ""
}
```



bitnami/neo4j

Result: FAIL | Status: failed
Attempts: 188 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/neo4j_1789252975/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 87
Phase robustness: passed | Attempts: 101
Errors: [E102](#)

Reproducing values (known-inputs):

```
{
  "extraContainerPorts": [
    null
  ]
}
```

bitnami/nessie

Result: FAIL | Status: failed
Attempts: 252 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/nessie_1789252998/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 151
Phase robustness: passed | Attempts: 101
Errors: [E050](#)

Reproducing values (known-inputs):

```
{
  "existingConfigmap": "\u001f"
}
```

bitnami/nginx

Result: FAIL | Status: failed
Attempts: 325 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/nginx_1789253009/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 81
Phase robustness: failed | Attempts: 244
Errors: [E052](#), [E051](#)

Reproducing values (known-inputs):

```
{
  "existingContextEventsConfigmaps": [
    "\u001f"
  ]
}
```

Reproducing values (robustness):

```
{
```



```
"contextIncludes": {
  "events": "\u001f",
  "": []
}
}
```

bitnami/node-exporter

Result: FAIL | Status: failed
 Attempts: 190 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/node-exporter_1789253016/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 89
 Phase robustness: passed | Attempts: 101
 Errors: [E053](#)
 Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

bitnami/oauth2-proxy

Result: FAIL | Status: failed
 Attempts: 130 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/oauth2-proxy_1789253043/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 29
 Phase robustness: passed | Attempts: 101
 Errors: [E088](#)
 Reproducing values (known-inputs):

```
{
  "redis": {
    "architecture": ""
  }
}
```

bitnami/odoo

Result: FAIL | Status: failed
 Attempts: 128 | Remaining iterations: unknown
 Coverage: known inputs, then original-schema robustness sampling
 Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/odoo_1789253062/0000](#)
 Filtering applied: True
 Generation order only; original-schema cases run last, not removed
 Phase known-inputs: failed | Attempts: 27
 Phase robustness: passed | Attempts: 101
 Errors: [E089](#)
 Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```



```
}
```

bitnami/opensearch

Result: FAIL | Status: failed
Attempts: 183 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/opensearch_1789253064/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 82
Phase robustness: passed | Attempts: 101
Errors: [E090](#)
Reproducing values (known-inputs):

```
{
  "ingest": {
    "resourcesPreset": ""
  }
}
```

bitnami/parse

Result: FAIL | Status: failed
Attempts: 120 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/parse_1789253081/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 19
Phase robustness: passed | Attempts: 101
Errors: [E054](#)
Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/phpmyadmin

Result: FAIL | Status: failed
Attempts: 301 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/phpmyadmin_1789253091/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 200
Phase robustness: passed | Attempts: 101
Errors: [E055](#)
Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```



bitnami/pinniped

Result: FAIL | Status: failed
Attempts: 160 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/pinniped_1789253122/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 59
Phase robustness: passed | Attempts: 101
Errors: [E056](#)
Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```

bitnami/postgresql

Result: FAIL | Status: failed
Attempts: 116 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/postgresql_1789253136/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 15
Phase robustness: passed | Attempts: 101
Errors: [E091](#)
Reproducing values (known-inputs):

```
{  
  "psp": {  
    "create": true  
  }  
}
```

bitnami/postgresql-ha

Result: FAIL | Status: failed
Attempts: 156 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/postgresql-ha_1789253152/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 55
Phase robustness: passed | Attempts: 101
Errors: [E113](#)
Reproducing values (known-inputs):

```
{  
  "fullnameOverride": ""  
}
```



bitnami/prometheus

Result: FAIL | Status: failed

Attempts: 318 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/prometheus_1789253175/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 75

Phase robustness: failed | Attempts: 243

Errors: [E057](#), [E058](#)

Reproducing values (known-inputs):

```
{
  "nameOverride": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "extraDeploy": [
    []
  ]
}
```

bitnami/pytorch

Result: FAIL | Status: failed

Attempts: 143 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/pytorch_1789253187/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 42

Phase robustness: passed | Attempts: 101

Errors: [E092](#)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```

bitnami/rabbitmq

Result: FAIL | Status: failed

Attempts: 539 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/rabbitmq_1789253191/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 274

Phase robustness: failed | Attempts: 265

Errors: [E099](#), [E059](#)

Reproducing values (known-inputs):

```
{
  "args": [
```



```
{
  "\u001e70\u0033a\u0033a\u00315o\u0035e \u00337i\u00332\u0032c\u00347\u0032a\u00359n\u0031d\u00317\u00355v\u003
1f\u0031c\u00318\u00326\u0035fo\u00336\u00319\u00330\u00320k\u000e8\u0035a\u0032e\u0033a\u0032a\u00339\u00331\u00324
\u00316t\u0031d\u00355\u00333\u00323\u0033b\u0032a\u0035eh\u0033c\u00353\u00332\u00326\u00333\u00318\u00332e\u00347\
\u00323\u00330\u00326\u0032c\u0034e \u00322\u0033c\u0033b\u00331\u00318h\u0035a\u0034e\u00359\u0031c\u00323\u00332\u00
345i\u00326\u00332\u00323\u00330\u00324v\u0033b\u0034de\u0033a\u0032d\u00333\u0032a\u00330-
m\u00322i\u00345n\u00316\u0033a\u0031e\u00332\u0032f\u00330d\u00335\u0033c\u0031f\u00359\u00329\u0033c\u00318\u00333
\u0031e\u00325\u00331\u00333\u0032dr\u0031b\u00317\u00318e\u00359p\u00360r\u0033c\u0031e\u0033b\u0032d\u00317e\u0033
a\u00320\u00323\u0035fs\u00318\u00347\u00333\u0034d\u0031d\u00349e\u00349\u00325\u0032f\u0031e\u00332\u0035a\u0032c\
\u0035c\u001f9\u0032c\u0034e\u0034e\u0031f\u00316\u00347\u00324t\u0034d\u0032c\u00324\u00353\u0033c\u0032d\u00358\u003
45i\u0032a\u00331n\u00360g\u00334\u00349 \u0034f\u00349\u00345c\u0032c\u0031fh\u00361a\u0032b\u0033b\u0032f\u00358o
\u0032b\u0031f\u00316\u0034d\u00319\u0031d\u00349s\u00317": null
}
]
}
```

Reproducing values (robustness):

```
{
  "": [],
  "auth": {
    "username": "\u001f"
  }
}
```

bitnami/rabbitmq-cluster-operator

Result: FAIL | Status: failed

Attempts: 173 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/rabbitmq-cluser-operator 1789253208/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 72

Phase robustness: passed | Attempts: 101

Errors: [E107](#)

Reproducing values (known-inputs):

```
{
  "clusterDomain": "\u0080"
}
```

bitnami/redis

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/redis 1789253220/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 5

Phase robustness: failed | Attempts: 140

Errors: [E093](#)

Reproducing values (known-inputs):

```
{
  "architecture": ""
}
```



Reproducing values (robustness):

```
{
  "": [],
  "architecture": ""
}
```

bitnami/redis-cluster

Result: FAIL | Status: failed

Attempts: 150 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/redis-cluster 1789253276/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 49

Phase robustness: passed | Attempts: 101

Errors: [E111](#)

Reproducing values (known-inputs):

```
{
  "existingSecret": ""
}
```

bitnami/redmine

Result: FAIL | Status: failed

Attempts: 304 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts 1789251211/runs/redmine 1789253293/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 62

Phase robustness: failed | Attempts: 242

Errors: [E060](#), [E097](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```

Reproducing values (robustness):

```
{
  "": [],
  "\u001e70\u0033a\u0033a\u00315o\u0035e \u00337i\u00332\u0032c\u00347\u0032a\u00359n\u0031d\u00317\u00355v\u0031f\u0031c\u00318\u00326\u0035fo\u00336\u00319\u00330\u00320k\u0000e8\u0035a\u0032e\u0033a\u0032a\u00339\u00331\u00324 \u00316t\u0031d\u00355\u00333\u00323\u0033b\u0032a\u0035eh\u0033c\u00353\u0032\u00326\u00333\u00318\u00332e\u00347\u00323\u00330\u00326\u0032c\u0034e \u00322\u0033c\u0033b\u00331\u00318h\u0035a\u0034e\u00359\u0031c\u00323\u00332\u00345i\u00326\u00332\u00323\u00330\u00324v\u0033b\u0034de\u0033a\u0032d\u00333\u0032a\u00330-m\u00322i\u00345n\u00316\u0033a\u0031e\u00332\u0032f\u00330d\u00335\u0033c\u0031f\u00359\u00329\u0033c\u00318\u00333\u0031e\u00325\u00331\u00333\u0032dr\u0031b\u00317\u00318e\u00359p\u00360r\u0033c\u0031e\u0033b\u0032d\u00317e\u0033a\u00320\u00323\u0035fs\u00318\u00347\u00333\u0034d\u0031d\u00349e\u00349\u00325\u0032f\u0031e\u00332\u0035a\u0032c\u0035c\u0031f9\u0032c\u0034e\u0034e\u0031f\u00316\u00347\u00324t\u0034d\u0032c\u00324\u00353\u0033c\u0032d\u00358\u00345i\u0032a\u00331n\u00360g\u00334\u00349 \u0034f\u00349\u00345c\u0032c\u0031fh\u00361a\u0032b\u0033b\u0032f\u00358o\u0032b\u0031f\u00316\u0034d\u00319\u0031d\u00349s\u00317": null
}
```



bitnami/schema-registry

Result: FAIL | Status: failed

Attempts: 172 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/schema-registry_1789253309/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 71

Phase robustness: passed | Attempts: 101

Errors: [E103](#)

Reproducing values (known-inputs):

```
{
  "httpRoutes": [
    null
  ]
}
```

bitnami/scylladb

Result: FAIL | Status: failed

Attempts: 247 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/scylladb_1789253311/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 146

Phase robustness: passed | Attempts: 101

Errors: [E111](#)

Reproducing values (known-inputs):

```
{
  "initDBConfigMap": "="
}
```

bitnami/sealed-secrets

Result: FAIL | Status: failed

Attempts: 164 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/sealed-secrets_1789253315/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 63

Phase robustness: passed | Attempts: 101

Errors: [E094](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```



bitnami/seaweedfs

Result: FAIL | Status: failed
Attempts: 135 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/seaweedfs_1789253341/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 34
Phase robustness: passed | Attempts: 101
Errors: [E061](#)
Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```

bitnami/solr

Result: FAIL | Status: failed
Attempts: 166 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/solr_1789253352/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 65
Phase robustness: passed | Attempts: 101
Errors: [E062](#)
Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": ""  
}
```

bitnami/sonarqube

Result: FAIL | Status: failed
Attempts: 128 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/sonarqube_1789253377/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 27
Phase robustness: passed | Attempts: 101
Errors: [E063](#)
Reproducing values (known-inputs):

```
{  
  "extraDeploy": [  
    []  
  ]  
}
```



bitnami/spark

Result: FAIL | Status: failed
Attempts: 220 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/spark_1789253392/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 119
Phase robustness: passed | Attempts: 101
Errors: [E064](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/superset

Result: FAIL | Status: failed
Attempts: 137 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/superset_1789253412/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 36
Phase robustness: passed | Attempts: 101
Errors: [E065](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/tensorflow-resnet

Result: FAIL | Status: failed
Attempts: 179 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/tensorflow-resnet_1789253441/0000](#)

Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 78
Phase robustness: passed | Attempts: 101
Errors: [E066](#)

Reproducing values (known-inputs):

```
{
  "extraEnvVarsCM": "\u001f"
}
```



bitnami/thanos

Result: FAIL | Status: failed
Attempts: 132 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/thanos_1789253463/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 31
Phase robustness: passed | Attempts: 101
Errors: [E067](#)
Reproducing values (known-inputs):

```
{  
  "bucketCacheConfig": "\u001f"  
}
```

bitnami/tomcat

Result: FAIL | Status: failed
Attempts: 144 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/tomcat_1789253463/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 43
Phase robustness: passed | Attempts: 101
Errors: [E068](#)
Reproducing values (known-inputs):

```
{  
  "extraEnvVarsCM": "\u001f"  
}
```

bitnami/valkey

Result: FAIL | Status: failed
Attempts: 140 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/valkey_1789253482/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 39
Phase robustness: passed | Attempts: 101
Errors: [E070](#)
Reproducing values (known-inputs):

```
{  
  "clusterDomain": "\u001f"  
}
```



bitnami/valkey-cluster

Result: FAIL | Status: failed

Attempts: 134 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/valkey-cluster_1789253483/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 33

Phase robustness: passed | Attempts: 101

Errors: [E069](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/vault

Result: FAIL | Status: failed

Attempts: 167 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/vault_1789253486/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 66

Phase robustness: passed | Attempts: 101

Errors: [E071](#)

Reproducing values (known-inputs):

```
{
  "extraDeploy": [
    []
  ]
}
```

bitnami/victoriametrics

Result: FAIL | Status: failed

Attempts: 171 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/victoriametrics_1789253519/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 70

Phase robustness: passed | Attempts: 101

Errors: [E072](#)

Reproducing values (known-inputs):

```
{
  "loggerFormat": "\u001f"
}
```



bitnami/whereabouts

Result: FAIL | Status: failed

Attempts: 120 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/whereabouts_1789253539/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 19

Phase robustness: passed | Attempts: 101

Errors: [E095](#)

Reproducing values (known-inputs):

```
{
  "resourcesPreset": ""
}
```

bitnami/wildfly

Result: FAIL | Status: failed

Attempts: 145 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/wildfly_1789253553/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 44

Phase robustness: passed | Attempts: 101

Errors: [E113](#)

Reproducing values (known-inputs):

```
{
  "fullnameOverride": ""
}
```

bitnami/wordpress

Result: FAIL | Status: failed

Attempts: 213 | Remaining iterations: unknown

Coverage: known inputs, then original-schema robustness sampling

Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/wordpress_1789253554/0000](#)

Filtering applied: True

Generation order only; original-schema cases run last, not removed

Phase known-inputs: failed | Attempts: 112

Phase robustness: passed | Attempts: 101

Errors: [E073](#)

Reproducing values (known-inputs):

```
{
  "apacheConfiguration": "\u001f"
}
```



bitnami/zipkin

Result: FAIL | Status: failed
Attempts: 2 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/zipkin_1789253576/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 1
Phase robustness: failed | Attempts: 1
Errors: [E110](#)
Reproducing values (known-inputs):
{}
Reproducing values (robustness):
{}

bitnami/zookeeper

Result: FAIL | Status: failed
Attempts: 133 | Remaining iterations: unknown
Coverage: known inputs, then original-schema robustness sampling
Artifacts: [bitnami-runs/bitnami-charts_1789251211/runs/zookeeper_1789253580/0000](#)
Filtering applied: True
Generation order only; original-schema cases run last, not removed
Phase known-inputs: failed | Attempts: 32
Phase robustness: passed | Attempts: 101
Errors: [E111](#)
Reproducing values (known-inputs):
{
 "dataLogDir": ""
}