Assignment #8

Write an assembler codes to accept 10 characters from KBD and perform the following operations

- **Replace * character by + character**
- **- Display the result on the screen on position (10,4)**

```
ORG 100H

    MOV AH,0AH
    LEA DX,PARLST
    INT 21H

    MOV CX,12
    CLD
    LEA DI,PARLST

 L2:MOV AL,'*'
    SCASB
    JNZ L1
    MOV AL,'+'
    DEC DI
    STOSB
 L1:LOOP L2

    MOV AH,02H
    MOV BH,00
    MOV DH,10
    MOV DL,4
    INT 10H

    MOV AH,09H
    LEA DX,PARLST+2
    INT 21H


HLT

    PARLST DB 12,?,11 DUP ('')
```



ليث عمرو