SEGMENTS

ID	CARRIER	FROM	TO	CABLE	L mm	END A	END B
W32	R1-CASS + COLUMN	kit drop P3-KIT	soffit right end	nylon draw cord 3 mm	1870	tied at P3-KIT	tied at the soffit entry
W33	B4-CASS + CEILING	shelf feed pocket P6	soffit back face, top	nylon draw cord 3 mm	1680	tied at P6	tied at the ceiling cassette's front hole

FORMBOARD 1:5 (lengths to scale along the line; cords tied off at both ends)

MATERIAL FOR THIS HARNESS (its share of the parts list lines, counted from the segments above)

PART NO.	NAME	QTY
718044	ELECTRICAL - DRAW CORD - NYLON 3 MM	3.55 m

Bushings and edge-protected slots it passes: G-CEIL-B, G-CEIL-F, G-SOFFIT (Heyco 2836 / edge strip, parts list 718041, 718042).

NOTES
Segments, ends and lengths from the harness list (710000_P01_ELECTRICAL-HARNESS-LIST_SPEC.csv), same revision.
UNITS: mm. GENERAL TOLERANCE: harness segment lengths +20/-0 mm; positions taken from the route model +/-5 mm;
sheet-metal parts ISO 2768-m (their DXF or drawing rules). Status of every number: parts list and harness list.
Every harness segment is tested in the factory before it ships (D-87): continuity, polarity, no shorts, latch pull,
label with its ID. Cables clip to the cassette tray only (D-26). Supply side = receptacle (female contacts).
Bought parts are on HOLD: no order, no supplier contact. Generated by assembly_sheets.py from the model and parts data.

PROJECT	FocusPod v2 - Spaceship
TITLE	**ELECTRICAL - DRAW WIRE - CEILING ROUTE: ASSEMBLY**
DWG / PART NO.	710031 (assembly)
REV / STATUS	P01 / DRAFT - not for production
UNITS / SCALE	mm / formboard 1:5; tables not to scale
SHEET	1 of 1 (A2)
DATE / BY	2026-11-01 / ELECTRICAL Engineer
SOURCE	electrical_model.py, electrical_parts.py