

UHF demonstration application operation instructions

1. Inventory tag

1.1 Enter the EPC home page, click the save button or handle button, save all the labels in the disk, showing the EPC area tag (**group read tag: domestic module rate 140-160 / S, R2000 module rate 180-220 / S**).

Read			
ID	EPC	Times	RSSI
1	00110000	25	88
2	333333334444333332498765	25	85
3	000000000000000000000000	24	80
4	E200001B1919007323402B00	24	75
5	6666	2	63
Number: 5 Time: 00:00:04 (s) Speed: 39 (t/s)			
INVENTORY			
Read	R/W	Set	

2. Read and write labels

2.1 Select "Label ID" in the read and write interface for reading. The storage area is the user area by default, and other areas can also be selected.

R/W

Result: 13:14:22 Read Failed ErrorCode=FB

ID: E200001B1919007323402..

Bank: User

Ptr: 0

Len: 6

Access Pwd: 00000000

WriteData: E2034121EA12BCED32498765

ReadData: E200001B1919007323402B11

READ WRITE WRITEEPC

Read R/W Set

2.2 Write the labels of the user and EPC areas, select "Label ID" to write the new data, write the rules of the label (**write the label according to the ISO18000-6C protocol**),

1.3000-> 24 bits

2,800-> 20 bits

2000-> 16 bits

1,800-> 12 bits

1,000- -> 8 bits

0800-> 4 bits

2.The starting address starts from 1, the 0th bit is the check bit, the pc bit length is 16 (2 system),

and the first 5 bits of the length represent the length to write, 1 word (word) ==2 bytes, namely 4 bits.

3. Parameter Setting

3.1Set basic parameters and check parameters (basic parameters can set the frequency band, according to different frequency band antenna equipment, set different frequency band (**default US band**), power setting (**default 30 dbm**)).

Set

Result: 13:15:41 Read Success

Basic Parameter

Version:

Band: US band

MinFre: 902.75MHz

MaxFre: 927.25MHz

Power: 30

GET

SET

Inventory Parameter

Q: 4

Session: S0

TID Ptr: 0

TID Len: 0

MaxScanTime: 20*100ms

Interval: 20ms

GET

SET

OPEN LOW POWER MODE

CLOSE LOW POWER MODE

Temperature

Return Loss:

READ

READ

3.2 Inquiry parameter setting

Single-standard reading setting: Session=S0; Q value =4;

Multi-standard reading setting: Session=S2; Q value =10;

TID address =0, TID length =0, maximum query time =25 * 100ms, interval time =20ms (**corresponding parameters can be selected for pull-down**).

4. Export files

4.1 Click on the upper right corner to export the read data in the format of Excel. After exporting Excel, please find the excel _ Tags folder in the pda file management, and store the export Excel file here.



