

An Open-Source Physically Validated Optical Channel Framework for Quantum Key Distribution

First-Principles Field Propagation with Per-Component Literature Validation and Verified System-Level Composition

A. Mahmood *et al.*

July 20, 2026

Abstract

We present an open-source optical channel simulation framework for quantum key distribution (QKD) that is, to the best of our knowledge, the first to simultaneously provide (i) complex-envelope electric field propagation at the physical-layer level, (ii) independent per-component validation against published literature, (iii) verified system-level composition of those components, and (iv) full seeded reproducibility under an open-source licence. No existing QKD simulator — whether protocol-level, commercial optical, or QKD-specific — offers this combination: protocol simulators operate at the qubit abstraction level without field physics, while commercial optical simulators are closed-source and lack transparent per-component validation.

The field $\mathbf{E}(t) = [E_x(t), E_y(t)]^T$ is the single source of truth for both polarisation state and optical power ($\langle |E|^2 \rangle = P_{\text{opt}}$). Five components are independently validated: (i) a continuous-wave laser with Wiener phase noise and relaxation-oscillation RIN (Henry 1982, Coldren 2012), reproducing the correct power convention ($< 5 \times 10^{-4}\%$ error), phase diffusion, and RIN spectral shape; (ii) a Mach-Zehnder modulator with push-pull (zero chirp) and single-drive (linear chirp) configurations, finite extinction ratio, insertion loss, and crystal-cut-dependent modulation (Agrawal 2021, Koyama & Iga 1988); (iii) a four-impairment fibre channel — temperature- and bend-dependent birefringence via random-axis SU(2) rotation (Menyuk & Wai 1994, Wai & Menyuk 1996, Ulrich 1980), FFT-based chromatic dispersion (Agrawal 2021, $< 10^{-13}\%$ error), Maxwellian polarisation-mode dispersion (Razavi 2012, KS $p = 0.42$), and exponential attenuation (Keiser 2015, $< 10^{-13}\%$ error); and (iv) an avalanche photodiode with excess-noise-factor-corrected shot noise and Johnson-Nyquist thermal noise (Kasap 2013, Saleh & Teich 2019).

The system-level BB84 demonstration confirms that independently validated components compose correctly, producing physically sensible QBER under combined CD, PMD, birefringence, and attenuation across sweeps of distance, pulse width, temperature, and bend radius. The framework is fully reproducible (seeded RNG, version-controlled, 48 unit tests passing) and available at <https://github.com/azaan-mahmood/opto>.

1 Introduction

1.1 Motivation

Quantum key distribution (QKD) promises information-theoretically secure communication by exploiting the principles of quantum mechanics. As QKD transitions from laboratory demonstrations to deployed networks, simulation plays a critical role in

system design, performance prediction, and security analysis. The optical channel between Alice and Bob is not a passive conduit; it actively shapes the quantum state through chromatic dispersion, polarisation-mode dispersion, birefringence, and attenuation, all of which interact with the laser source and modulator to determine the quantum bit error rate (QBER) and achievable secret key rate.

Physical-layer modelling matters because QKD security proofs assume specific noise characteristics. Environmental perturbations — temperature fluctuations altering fibre birefringence, mechanical stress inducing polarisation drift, and bend-induced phase shifts — can degrade performance in ways that abstract depolarisation models cannot capture. A simulator that replaces the optical channel with a parametrised loss and depolarisation model may produce correct QBER under nominal conditions but will fail to predict performance under realistic environmental stress.

Existing QKD simulators fall into two camps, and neither provides the combination required for defensible physical-layer QKD simulation. *Abstract qubit simulators* such as NetSquid [1], SimulaQron [3], and QuTIP [4] represent channels as depolarising maps with parametrised loss and click probabilities. There is no field, no wavelength, no phase noise, and no birefringence between Alice and Bob. *Commercial optical simulators* such as OptiSystem [11], VPItransmissionMaker [13], and Synopsys OptSim [14] solve the nonlinear Schrödinger equation for the complex envelope, but they are closed-source, proprietary, and — critically — do not provide transparent, independently verifiable per-component validation against published literature. No existing simulator in either camp simultaneously provides first-principles optical field modelling, per-component validation, verified system-level composition, and open-source reproducibility.

Reproducibility concerns compound the problem. Simulation studies in QKD frequently report results without publishing seeded code, version information, or validation against independent references. This makes it difficult to distinguish genuine physical insights from implementation artifacts. A literature-traceable framework, where every equation cites a specific source and every component is independently verified, provides the foundation for reproducible and credible QKD research.

1.2 Related Work

The landscape of quantum network simulation can be broadly divided into three categories: protocol-level simulators, commercial optical system simulators, and QKD-specific simulation tools. Each category addresses different aspects of the quantum communication stack, and none provides the combination of physical-layer optical modelling, component-wise literature validation, and open-source reproducibility that we target here.

1.2.1 Protocol-Level Quantum Network Simulators

Several open-source simulators have been developed to study quantum networking protocols, entanglement distribution, and quantum internet architectures. NetSquid [1] (QuTech, TU Delft) is a discrete-event simulator with a modular component library for modelling quantum memories, channels, and processing nodes. It provides physically realistic building blocks and supports density-matrix and stabiliser-state representations, but its physical-layer models use abstract depolarisation and loss parameters rather than first-principles optical field propagation [2]. SimulaQron [3] (QuTech) is a distributed simulator designed for quantum internet application development, providing a Classical-Quantum Combiner (CQC) interface between simulated quantum processors. It delegates the underlying quantum simulation to pluggable backends (e.g., QuTIP) and does not model optical-layer impairments. SeQUeNCe [5] (Argonne

National Laboratory) is a discrete-event simulator with five modules (hardware, entanglement management, resource management, network management, application) and a quantum manager that tracks entangled states across the network. While it models quantum channels and memories, its channel model is limited to depolarisation and loss without chromatic dispersion, PMD, or birefringence. QuISP [6] (SFC/WIDE Project) targets large-scale quantum internet simulation on the OMNeT++ framework, supporting first-, second-, and third-generation quantum repeater protocols with up to 100 networks of 100 nodes each. Its physical layer operates on error bases rather than optical fields. QuNetSim [7] (Technical University of Munich) is a lightweight Python framework for network-layer protocol development, offering built-in teleportation, superdense coding, and EPR generation over multi-hop topologies, but it explicitly does not model quantum physics accurately and is intended as an educational tool. SQUANCH [8] (AT&T Research) is a Python library for distributed quantum simulation using an agent-based model with multiprocessed NumPy backends, but it lacks a discrete-event engine and native noise modelling.

1.2.2 Commercial Optical System Simulators

Commercial photonic design tools provide detailed optical-layer modelling but are closed-source, expensive, and — critically — do not provide transparent, independently verifiable per-component validation against published literature. OptiSystem [11] (Optiwave Systems) is a comprehensive photonic design suite with over 600 components covering transmitters, fibres, amplifiers, and receivers. It supports QKD simulation through specialised components (single-photon lasers, single-photon detectors) and has been used to model BB84 over fibre and free-space channels [15]. However, its models are proprietary with no independent validation of the internal physics. Lumerical [12] (Ansys) provides device-level photonic simulation through its MODE, FDTD, and INTERCONNECT solvers, targeting waveguide design, photonic integrated circuits, and component-level characterisation. While physically rigorous at the device level, it does not provide system-level optical channel simulation for QKD. VPItransmissionMaker [13] (VPIphotonics) is an optical system simulator with 700+ validated component modules and sophisticated fibre models including Kerr nonlinearity, Raman scattering, and stochastic PMD. It offers a QKD toolkit add-on for discrete-variable and continuous-variable QKD scenarios, but the core platform is proprietary and its fibre models, while detailed, have not been independently validated against published literature on a per-component basis. Synopsys OptSim [14] (Synopsys) is an award-winning fibre-optic system simulator with time-domain and frequency-domain split-step engines, supporting coherent and direct-detection systems. It interfaces with MATLAB and SPICE for co-simulation, but like other commercial tools, its internal models are not independently verifiable.

1.2.3 QKD-Specific Simulators

QKDNetSim [9] (NS-3 module) focuses on QKD network management, key relay, and post-processing emulation using ETSI standardised interfaces. It implements a full Key Management System but delegates the quantum channel to simplified models or external tools such as Qiskit, and does not model optical-layer impairments. QKDSim-HT [10] (built on NetSquid) adds realistic polarisation-based DV-QKD physical-layer models including depolarisation, dephasing, detector efficiency, dark counts, and dead times, with multi-hop key relay and adaptive routing. While more physically detailed than abstract qubit simulators, its optical channel model remains phenomenological (parameterised loss and depolarisation) rather than derived from first-principles Maxwell equations.

1.2.4 Comparison and Gap Analysis

Table 1 compares the capabilities of existing tools along the dimensions most relevant to physically accurate QKD simulation. No existing tool provides all of the following simultaneously: (a) complex-envelope optical field propagation, (b) chromatic dispersion via FFT-based transfer functions, (c) Maxwellian PMD, (d) temperature- and bend-dependent birefringence, (e) per-component validation against published literature, (f) open-source availability with reproducible validation, and (g) a system-level demonstration that independently validated components compose correctly under combined impairments.

Table 1: Comparison of quantum network and optical system simulators. “Physical layer” refers to first-principles optical field modelling; “CD/PMD/Biref” indicates whether fibre impairments are modelled from physics rather than phenomenological parameters; “Per-component validation” indicates independent verification against published literature for each component.

Simulator	Open source	Physical layer	CD/PMD/Biref	Per-comp. validation	Complex-envelope
NetSquid [1]	No [†]	Partial*	No	No	No
SimulaQron [3]	Yes	No	No	No	No
SeQUeNCe [5]	Yes	Partial*	No	No	No
QuISP [6]	Yes	Partial*	No	No	No
QuNetSim [7]	Yes	No	No	No	No
SQUANCH [8]	Yes	No	No	No	No
QKDNetSim [9]	Yes	No	No	No	No
OptiSystem [11]	No	Yes [‡]	Partial	No	No
VPIphotonics [13]	No	Yes [‡]	Yes	No	No
OptSim [14]	No	Yes [‡]	Partial	No	No
This work	Yes	Yes	Yes	Yes	Yes

[†] Open API, closed source. * Abstract depolarisation/loss models. [‡] Sinusoid-carrier level, proprietary.

The gap is clear: protocol-level simulators sacrifice optical-layer fidelity for scalability and protocol flexibility, while commercial optical simulators provide detailed physics but are closed-source, expensive, and lack independent per-component validation. Neither category — nor the QKD-specific simulators surveyed in Section 1.2.3 — provides all of the following in a single framework: first-principles complex-envelope optical field modelling, per-component literature validation, verified system-level composition, and full open-source reproducibility. Our framework targets exactly this intersection.

1.3 Contributions

Our primary contribution is a framework that simultaneously achieves four capabilities absent from existing QKD simulators:

- **First-principles complex-envelope field propagation** — the electric field $\mathbf{E}(t)$ is the single source of truth for power and polarisation, enabling physically correct modelling of CD, PMD, birefringence, and their interactions, in contrast to the abstract qubit-level models used by protocol simulators.
- **Per-component literature validation** — every equation cites a specific numbered reference (34 sources), and each of the five components is independently verified against published theory, in contrast to commercial simulators whose internal physics is not transparently verifiable.

- **Verified system-level composition** — a five-panel BB84 demonstration confirms that independently validated components compose correctly under combined impairments, producing physically sensible QBER across sweeps of distance, pulse width, temperature, and bend radius.
- **Full open-source reproducibility** — seeded RNG (default 42), version-controlled codebase, 48 passing unit tests, and an automated validation pipeline (`run_all.py`) producing seed-tagged outputs.

The specific component models are:

- CWLaser with Wiener phase noise (Henry 1982) and relaxation-oscillation RIN (Coldren 2012)
- MZM with push-pull (zero chirp) and single-drive (linear chirp) configurations (Koyama & Iga 1988)
- Random-axis birefringence model with diffusive polarisation scrambling (Menyuk & Wai 1994, Wai & Menyuk 1996) and temperature/bend modulation (Ulrich 1980, Smith 1980, Shibata 1986)
- FFT-based CD (Agrawal 2021), Maxwellian PMD (Razavi 2012), and exponential attenuation (Keiser 2015)
- APD with excess-noise-factor-corrected shot noise (Kasap 2013)

2 Physical-Layer Model

2.1 Field Convention

The complex-envelope electric field $E(t) = [E_x(t), E_y(t)]^T$ is the single source of truth for both polarisation and optical power:

$$\langle |E|^2 \rangle = \frac{1}{N} \sum_{i=1}^N (|E_x(t_i)|^2 + |E_y(t_i)|^2) = P_{\text{opt}} \quad [\text{W}] \quad (1)$$

The field is calibrated once at the laser output so that $\langle |E|^2 \rangle$ equals the specified laser power in Watts. All downstream components (modulator, fibre, detector) derive power from the field via Eq. 1 — no separate power tracking variables.

2.2 CW Laser

The continuous-wave laser model follows Henry [16] for phase noise and Coldren [17] for relative intensity noise (RIN).

2.2.1 Power

The laser output power in Watts is derived from the power in dBm:

$$P = 10^{(P_{\text{dBm}}/10)} \times 10^{-3} \quad (2)$$

2.2.2 Phase Noise (Wiener Process)

The phase diffusion coefficient D_ϕ is related to the laser linewidth $\Delta\nu$ (Henry [16] Eq. 18):

$$D_\phi = 2\pi\Delta\nu \quad (3)$$

Phase increments are Gaussian:

$$\Delta\phi(t_i) \sim \mathcal{N}(0, D_\phi \Delta t) \quad (4)$$

and the cumulative phase $\phi(t) = \sum_i \Delta\phi(t_i)$ follows a Wiener process.

2.2.3 Relative Intensity Noise

The RIN power spectral density follows the linearised rate-equation result (Coldren [17] Eq. 5.3.38):

$$S_{\text{RIN}}(f) = \text{RIN}_0 \frac{\gamma^2 + (2\pi f)^2}{|(2\pi f_{\text{RO}})^2 - (2\pi f)^2 + j\gamma(2\pi f)|^2} \quad (5)$$

where f_{RO} is the relaxation oscillation frequency (default 5 GHz), γ is the damping rate (default 1.88×10^{10} rad/s), and RIN_0 is the DC RIN density (default -130 dB/Hz). The RIN is generated in the frequency domain: white noise is shaped by $\sqrt{S_{\text{RIN}}(f)}$ via rFFT, then transformed back to the time domain and applied as amplitude fluctuations to the field.

The FFT length is chosen as the next power of two above N and is internally decimated when the optical sampling rate (~ 200 THz) exceeds the Nyquist rate of the RIN bandwidth (~ 50 GHz) by more than $10^3\times$, maintaining numerical efficiency without aliasing the relaxation-oscillation peak at 5 GHz.

2.2.4 Polarisation

The polarisation state is defined by the azimuth ψ and ellipticity χ angles (Yariv [18] Ch. 6):

$$E_{\text{pol}} = \begin{pmatrix} \cos \chi \cos \psi - j \sin \chi \sin \psi \\ \cos \chi \sin \psi + j \sin \chi \cos \psi \end{pmatrix} \quad (6)$$

The complete field sample is:

$$E(t) = \sqrt{P(1 + r(t))} e^{j\phi(t)} E_{\text{pol}} \quad (7)$$

where $r(t)$ is the RIN amplitude fluctuation.

2.3 Mach-Zehnder Modulator

The MZM model follows Agrawal [20] §4.2 for the transfer function, Koyama and Iga [21] for the chirp analysis, and Weis and Gaylord [22] for the Pockels coefficients.

2.3.1 Push-Pull Configuration

Both arms are modulated with opposite voltages. No residual frequency chirp because the common-mode phase cancels:

$$E_{\text{out}} = \sqrt{\text{IL}} E_{\text{in}} \cos\left(\frac{\pi(V + V_{\text{bias}})}{2V_\pi}\right) \quad (8)$$

2.3.2 Single-Drive Configuration

Only one arm is modulated; the other is a passive reference. Residual frequency chirp appears:

$$E_{\text{out}} = \sqrt{\text{IL}} E_{\text{in}} e^{j\pi(V + V_{\text{bias}})/(2V_\pi)} \cos\left(\frac{\pi(V + V_{\text{bias}})}{2V_\pi}\right) \quad (9)$$

2.3.3 Extinction Ratio and Insertion Loss

The extinction ratio is modelled via Y-branch splitting imbalance. For a specified ER in dB:

$$\delta = 10^{-\text{ER}/20}, \quad r = 0.5(1 + \delta) \quad (10)$$

The null transmission power is $P_{\text{null}} = \delta^2 \cdot P_{\text{in}}$.

Insertion loss is a separate power-scaling factor:

$$\text{IL}_{\text{lin}} = 10^{-\text{IL}_{\text{dB}}/10} \quad (11)$$

2.3.4 Crystal Cut

The crystal cut (X or Y) determines which transverse field component is modulated. X-cut modulates the E_y component; Y-cut modulates the E_x component. The orthogonal component passes through unchanged. This is physically correct for LiNbO_3 modulators where the RF field is aligned to either the extraordinary or ordinary axis [22].

2.4 Fibre Channel

The fibre channel applies four impairments sequentially to the complex-envelope field: birefringence, chromatic dispersion, polarisation-mode dispersion, and attenuation.

2.4.1 Birefringence

Birefringence is modelled by a multi-section random-axis Jones matrix on the Poincaré sphere (Menyuk & Wai [35], Wai & Menyuk [36]). The fibre is divided into N sections of equal length Δz (default 100 m). Each section has its own independent random birefringence axis $\mathbf{n}$ and a deterministic phase retardation $\Delta\beta \cdot \Delta z = 2\pi|\Delta n|\Delta z/\lambda$, where Δn is the total birefringence. The Jones matrix of each section is an $\text{SU}(2)$ rotation:

$$J_k = \cos \frac{\Delta\beta \cdot \Delta z}{2} I - j \sin \frac{\Delta\beta \cdot \Delta z}{2} (\mathbf{n}_k \cdot \boldsymbol{\sigma}) \quad (12)$$

where $\boldsymbol{\sigma} = (\sigma_x, \sigma_y, \sigma_z)$ are the Pauli matrices and $\mathbf{n}_k$ is a uniformly random unit vector on the Poincaré sphere. The total Jones matrix is the ordered product $J_{\text{total}} = J_N \cdots J_2 J_1$, which naturally produces diffusive polarisation evolution without a phenomenological characteristic length.

The birefringence Δn has three contributions:

$$\Delta n = \Delta n_0 + \Delta n_T(T) + \Delta n_{\text{bend}}(R) + \Delta n_{\text{stoch}} \quad (13)$$

$$\Delta n_T = T_{\text{coeff}}(T - T_0), \quad T_{\text{coeff}} = -5 \times 10^{-7} / ^\circ\text{C} \quad (14)$$

$$\Delta n_{\text{bend}} = 0.135 \left(\frac{r_{\text{clad}}}{R} \right)^2 \quad (\text{Ulrich [27], Smith [28], Shibata [29]}) \quad (15)$$

$$\Delta n_{\text{stoch}} \sim \mathcal{N}(0, 0.1 \Delta n_0) \quad (16)$$

with $\Delta n_0 = 5.0 \times 10^{-8}$ (Agrawal [20] §4.1: $L_B \approx 10\text{--}100$ m for standard SMF-28), $T_0 = 25^\circ\text{C}$, $r_{\text{clad}} = 62.5 \mu\text{m}$ (SMF-28 cladding radius), and R the bend radius in metres. The stochastic term Δn_{stoch} is drawn once per fibre call and prevents unphysical cancellation when temperature-induced birefringence approaches $-\Delta n_0$; $|\Delta n|$ is clamped to a minimum of 5×10^{-10} as a safety net below the residual floor. This baseline birefringence corresponds to a beat length $L_B = \lambda/\Delta n_0 \approx 31$ m at 1550 nm, consistent with

standard SMF-28 fibre. With a section length of 100 m, each section produces a deterministic phase retardation $\Delta\beta \cdot \Delta z = 2\pi \Delta n \Delta z / \lambda$ whose effective $SO(3)$ rotation (on the Poincaré sphere) is approximately 2.8 rad, giving diffusive polarisation scrambling over kilometre-scale distances.

Each call to the fibre model draws N new random axes $\{\mathbf{n}_k\}$, so different bits experience different polarisation transformations — this models the temporal variation of birefringence axes over the timescale of a QBER measurement (seconds to minutes). Without active polarisation compensation, the QBER approaches 50% for fibres much longer than ~ 100 km, consistent with the behaviour of field-deployed QKD systems that require continuous polarisation tracking.

The multi-section model is physically correct for short fibres ($L < 2$ km) where the detailed polarisation evolution is resolved. However, the ordered product of many random $SU(2)$ rotations converges to a uniform (Haar) distribution on the Poincaré sphere within approximately 1 km regardless of the birefringence strength — once the number of sections exceeds a few hundred, the net rotation is uniformly distributed and the output polarisation is fully scrambled. This makes the multi-section model unsuitable for long-haul BB84 simulation: the QBER would saturate at $\sim 50\%$ within the first kilometre, showing no distance-dependent structure beyond that point.

For long-haul BB84 simulation ($L \geq 2$ km) we therefore replace the ordered product with a single $SU(2)$ rotation whose angle follows the phenomenological $\sqrt{L}$ law (Menyuk & Wai 1994):

$$\theta = \min\left(\pi, \frac{\pi}{2} \sqrt{\frac{L}{L_{\text{char}}}}\right), \quad L_{\text{char}} = L_0 \left(\frac{\Delta n_0}{|\Delta n|}\right)^2 \quad (17)$$

with $L_0 = 75$ km, $\Delta n_0 = 0.87 \times 10^{-5}$, and the same temperature coefficient ($-5 \times 10^{-7}/^\circ\text{C}$) and bend model as the multi-section model. The rotation angle θ grows from 0 at $L \ll L_{\text{char}}$ to π at $L \gg L_{\text{char}}$, producing a gradual distance-dependent QBER that matches the qualitative behaviour of long-haul BB84 links without resolving the sub-km polarisation structure.

The dispatch between the two models is automatic: the function `propagate()` selects the multi-section model for $L < 2000$ m and the phenomenological model for $L \geq 2000$ m, and the user may override this choice via the `model` parameter ('sectional', 'phenomenological', or 'auto').

2.4.2 Chromatic Dispersion

Chromatic dispersion is applied via an FFT-based transfer function (Agrawal [20] Eq. 2.4.11):

$$H(\omega) = \exp(-j \beta_2 \omega^2 L/2), \quad \beta_2 = -\frac{D \lambda^2}{2\pi c} \quad (18)$$

The dispersion parameter $D_{\text{total}} = D_{\text{material}} + D_{\text{waveguide}} = 17.0 - 3.0 = 14.0$ ps/(nm·km) at 1550 nm [24, 25]. $H(\omega)$ is applied identically to both E_x and E_y (CD is isotropic in standard SMF).

2.4.3 Polarisation-Mode Dispersion

PMD is modelled with a Maxwellian-distributed differential group delay (Razavi [26] Fig. 2.11):

$$\Delta\tau \sim \text{Maxwellian}\left(\sigma = \frac{\text{PMD}_{\text{coeff}}\sqrt{L}}{\sqrt{3}}\right) \quad (19)$$

The frequency-domain Jones matrix is:

$$J_{\text{pmd}}(\omega) = \begin{pmatrix} e^{-j\omega\Delta\tau/2} & 0 \\ 0 & e^{+j\omega\Delta\tau/2} \end{pmatrix} \quad \text{or swapped (50:50 fast/slow axis)} \quad (20)$$

Default $\text{PMD}_{\text{coeff}} = 0.1 \text{ ps}/\sqrt{\text{km}}$ (Corning SMF-28 Ultra specification).

2.4.4 Attenuation

Attenuation follows the exponential loss law (Keiser [23] Eq. 3.6):

$$\frac{P_{\text{out}}}{P_{\text{in}}} = 10^{-\alpha L/10}, \quad E_{\text{out}} = E_{\text{in}} \sqrt{10^{-\alpha L/10}} \quad (21)$$

with $\alpha = 0.182 \text{ dB/km}$ at 1550 nm (Corning SMF-28 Ultra).

2.4.5 Impairment Control

The four impairments are applied sequentially by the function `propagate()` in the order: birefringence $\rightarrow$ CD $\rightarrow$ PMD $\rightarrow$ attenuation. Each impairment can be independently enabled or disabled via keyword arguments: `birefringence` (default True), `cd` (default None, aliased to the legacy dispersion flag), `pmd` (default None, also aliased to dispersion), and `attenuation` (default True). A call to `propagate(L, E, birefringence=False, attenuation=False)` applies no impairments, returning the field unchanged; `propagate(L, E, birefringence=False)` applies attenuation only; and `propagate(L, E, cd=True, dt=1e-12)` applies birefringence, CD, and attenuation without PMD.

2.5 Avalanche Photodiode

The APD model follows Kasap [30] Ch. 4 and Saleh and Teich [31] Ch. 17.

2.5.1 Responsivity

The responsivity is (Kasap [30] Eq. 4.19):

$$R = \frac{\eta e \lambda}{h c} \quad (22)$$

where η is the quantum efficiency, e the elementary charge, h Planck's constant, and c the speed of light.

2.5.2 Signal Current

The signal current after avalanche gain M is (Kasap [30] Eq. 4.23):

$$I_{\text{sig}} = M R P \quad (23)$$

2.5.3 Noise

The RMS noise current includes three contributions (Kasap [30] Eqs. 4.42–4.46):

$$i_{\text{dark}}^2 = 2eI_{\text{dark}}B \quad (24)$$

$$i_{\text{shot}}^2 = 2eI_{\text{sig}}B \quad (25)$$

$$i_{\text{thermal}}^2 = \frac{4k_B T B}{R_L} \quad (26)$$

The excess noise factor F applies only to the shot-noise terms (Kasap [30] Eq. 4.45):

$$i_{\text{total}}^2 = F(i_{\text{dark}}^2 + i_{\text{shot}}^2) + i_{\text{thermal}}^2 \quad (27)$$

where F is the excess noise factor, k_B Boltzmann's constant, T the temperature, B the bandwidth, and R_L the load resistance. The factor is correctly applied only to the shot-noise components (which are amplified by the gain stage), not to the thermal noise (which is added after amplification).

2.5.4 Photon Detection

Photon detection follows a Poisson process (Saleh and Teich [31] Eq. 17.1-10):

$$\bar{n} = \frac{P}{h\nu} \cdot t \cdot \eta \quad (28)$$

where t is the exposure time and $\nu = c/\lambda$ the optical frequency.

3 Validation Results

All validations use seeded RNG (-seed 42), produce seed-tagged PNG and CSV outputs, and are run via `run_all.py` in isolated subprocesses.

3.1 CW Laser Validation

3.1.1 Power Calibration

Table 2: CW laser validation summary.

Parameter	Value
Power calibration	max error = 4.82e-04 %
Phase diffusion coeff	$D_\phi = 6.28\text{e}+08 \text{ rad}^2/\text{s}$
Phase increments	Gaussian, std = 2.51e-02 rad
RIN resonance	$f_{\text{RO}} = 5 \text{ GHz}$, damping = 1.88e10 rad/s
Polarization	Unit norm, linear/circular verified

Figure 1A shows the power calibration. The measured $\langle |E|^2 \rangle$ from `sample_field()` reproduces the theory $P = 10^{(P_{\text{dBm}}/10)} \times 10^{-3} \text{ W}$ across -20 to $+10 \text{ dBm}$ with a maximum error of $4.8 \times 10^{-4}\%$.

Figure 1B shows the phase diffusion. The cumulative sum of squared phase increments $\sum \Delta\phi^2$ tracks the theoretical line $D_\phi t$ where $D_\phi = 2\pi\Delta\nu = 6.28 \times 10^8 \text{ rad}^2/\text{s}$ for $\Delta\nu = 100 \text{ MHz}$. Figure 1C confirms the phase increments are Gaussian with standard deviation $\sqrt{D_\phi \Delta t}$, consistent with the Wiener process model [16].

Figure 1D shows the RIN PSD (Coldren [17] Eq. 5.3.38). The relaxation oscillation peak at 5 GHz and the low-frequency plateau are reproduced. The damping rate $\gamma = 1.88 \times 10^{10} \text{ rad/s}$ sets the resonance width.

Figure 1E validates the polarisation Jones vector. For linear polarisation ($\chi = 0$), $|E_x| = \cos \psi$, $|E_y| = \sin \psi$, and $\sqrt{|E_x|^2 + |E_y|^2} = 1$ across all azimuth angles $\psi \in [0, \pi]$.




Figure 1: CW laser validation. A: Power calibration ($\langle |E|^2 \rangle$ vs P_{dBm}). B: Phase diffusion (cumulative squared phase increments $\sum \Delta\phi^2$ vs $D_\phi t$). C: Phase increment PDF (Gaussian fit). D: RIN spectral density with relaxation-oscillation peak at 5 GHz (Coldren Eq. 5.3.38). E: Polarisation Jones vector ($|E_x|$, $|E_y|$, norm).

Table 3: MZM validation summary.

Parameter	Value
Transfer function	$\cos^2(\pi V / (2 V_{\pi}))$ verified
Peak ($V=0$)	$P_{out} = 1.0$
Quadrature ($V=V_{\pi}/2$)	$P_{out} = 0.5$
Null ($V=V_{\pi}$)	$P_{out} = 0$
Chirp (push-pull)	Zero (ideal)
Chirp (single-drive)	$\phi = \pi V / (2 V_{\pi})$ verified
ER degradation	10 dB ER: null depth = 0.100
Insertion loss	Scales as $10^{(-IL/10)}$
Crystal cut	X-cut modulates E_y ; Y-cut modulates E_x

3.2 MZM Validation

Figure 2A validates the transfer function. Both push-pull and single-drive configurations reproduce the $\cos^2(\pi V / 2 V_{\pi})$ characteristic (Agrawal [20] §4.2). At $V = 0$, the output power is P_{in} (peak). At $V = V_{\pi}/2$, the output is $0.5 P_{in}$ (quadrature). At $V = V_{\pi}$, the output is zero (null).




Figure 2: MZM validation. A: Transfer function – $\cos^2(\pi V/2V_\pi)$ verified for push-pull and single-drive. B: Phase response (chirp) – push-pull has zero chirp; single-drive has linear chirp $\phi = \pi V/2V_\pi$. C: Extinction ratio effect (ideal, 20 dB, 10 dB). D: Insertion loss scaling as $10^{-IL/10}$. E: Crystal cut – X-cut modulates E_y ; Y-cut modulates E_x .

Figure 2B shows the chirp phase response. The push-pull configuration produces zero chirp (flat phase at 0 rad, ideal for high-speed modulation). The single-drive configuration produces a linear chirp $\phi = \pi V/2V_\pi$ (Koyama and Iga [21]), verified against the analytic theory to within numerical precision after masking the null crossing where the phase is undefined.

Figure 2C demonstrates the extinction ratio effect. The null transmission power scales as $10^{-ER/10}$, with $ER = 10$ dB giving $P_{\text{null}} \approx 0.1$.

Figure 2D validates the insertion loss. The output power scales as $10^{-IL_{\text{dB}}/10}$ across 0–6 dB insertion loss.

Figure 2E confirms the crystal cut selection. X-cut modulates the E_y component while E_x passes unchanged. Y-cut modulates E_x while E_y passes unchanged, consistent with the LiNbO_3 Pockels coefficients [22].

3.3 Chromatic Dispersion Validation

Figure 3 validates the FFT-based chromatic dispersion model. A 30 ps Gaussian pulse is propagated through `propagate()` at distances $z/L_D = 0.0, 0.5, 1.0, 2.0$, where $L_D = T_0^2/|\beta_2| = 50.40$ km is the dispersion length. The measured RMS width $\sigma(z)$ reproduces the analytic formula (Agrawal [20] Eq. 3.2.6):




Figure 3: Chromatic dispersion validation. Gaussian pulse broadening at $z/L_D = \{0.0, 0.5, 1.0, 2.0\}$ compared with the analytic formula $\sigma(z) = \sigma_0 \sqrt{1 + (z/L_D)^2}$ (Agrawal Eq. 3.2.6). Error: $< 10^{-13}\%$ at all points.

Table 4: Chromatic dispersion validation summary.

Parameter	Value
D_total	14.0 ps/(nm*km)
D_material	17.0 ps/(nm*km)
D_waveguide	-3.0 ps/(nm*km)
beta2	-1.786e-26 s ² /m
Dispersion length L_D	50.40 km
Max error	3.012676e-14 %
Gaussian broadening	Matches analytic: all $< 0.001\%$

$$\sigma(z) = \sigma_0 \sqrt{1 + (z/L_D)^2}, \quad \sigma_0 = \frac{T_0}{\sqrt{2}} \quad (29)$$

with an error of $< 10^{-13}\%$ at all points. The FFT-based implementation agrees with the analytic formula within floating-point precision, which is expected because the Fourier transform of a Gaussian is Gaussian, and the quadratic phase factor $H(\omega)$ in Eq. 18 is the analytic continuation of the propagation operator.

3.4 PMD Validation

Figure 4 validates the PMD model against Razavi [26] Fig. 2.11. The DGD is recorded directly from `propagate()` across 10,000 fibre realisations at 100 km with $\text{PMD}_{\text{coeff}} = 0.1 \text{ ps}/\sqrt{\text{km}}$.

The Kolmogorov-Smirnov test confirms the Maxwellian distribution ($p = 0.42$, well above the 0.05 threshold). The mean DGD error is 0.3% and the RMS DGD error is 0.3%. The R^2 of the DGD vs $\sqrt{L}$ fit is 0.999987.




Figure 4: PMD validation. Histogram of 10,000 fibre realisations at 100 km with Maxwellian PDF overlay (Razavi Fig. 2.11). KS test $p = 0.42$ confirms Maxwellian distribution.

Table 5: PMD validation summary.

Parameter	Value	Expected
Mean DGD (ps)	29.212	29.135
RMS DGD (ps)	31.730	31.623
KS D-stat	0.00876	< 0.05 typical
KS p-value	0.4249	> 0.05 (not rejected)
PMD coeff (ps/sqrt(km))	3.1565	3.1623
DGD sqrt(L) R2	0.999987	~ 1.0

3.5 Attenuation Validation

Table 6: Attenuation validation summary.

L (km)	P_meas (a.u.)	P_theory (a.u.)	Error (%)
0	5.00901828e-01	5.00901828e-01	0.000000e+00
20	2.16646968e-01	2.16646968e-01	0.000000e+00
50	6.16243876e-02	6.16243876e-02	2.251996e-14
100	7.58145595e-03	7.58145595e-03	0.000000e+00
150	9.32722850e-04	9.32722850e-04	2.324811e-14
200	1.14749979e-04	1.14749979e-04	1.181048e-14

Figure 5 validates the attenuation model (Keiser [23] Eq. 3.6). The measured $P_{\text{out}}/P_{\text{in}}$ reproduces $10^{-\alpha L/10}$ across 0–200 km with an error of $< 10^{-13}\%$. The fitted attenuation coefficient is $\alpha = 0.182$ dB/km with $R^2 > 0.999999$, consistent with the analytical nature of the validation.

Fiber Attenuation - Validation vs Keiser [1] Eq 3.6




Figure 5: Attenuation validation. Power vs distance for SMF-28 at 1550 nm ($\alpha = 0.182$ dB/km). Error: $< 10^{-13}\%$ across 0–200 km.

3.6 Birefringence Validation

Table 7: Birefringence validation summary (13 self-consistency checks).

Test	Model	Result
Power conservation	Sectional	err $< 1e-12$
Temperature sensitivity	Sectional	PASS
Wavelength sensitivity	Sectional	PASS
Seed randomness	Sectional	PASS
Poincaré scrambling	Sectional (1.5 km)	std > 0.05
Power conservation	Phenomenological	err $< 1e-12$
Temperature sensitivity	Phenomenological	PASS
Wavelength sensitivity	Phenomenological	PASS
Seed randomness	Phenomenological	PASS
Poincaré scrambling	Phenomenological (100 km)	std > 0.05
Zero-length identity	Both	PASS
Auto-dispatch threshold enabled=False bypass	SECTIONAL_LIMIT = 2000 m	PASS
	Both	PASS

Figure 6 validates the dual birefringence model (sectional for $L < 2$ km, phenomenological for $L \geq 2$ km; see §3.3.1). Panel A shows the multi-section random-axis model (Menyuk [35], Wai [36]) on a short scale (0–1.5 km), where the ordered product of independent SU(2) rotations produces a diffusive random walk on the Poincaré sphere. Panel B shows the phenomenological model on a long scale (0–200 km); the single SU(2) rotation angle $\theta = \min(\pi, \frac{\pi}{2}\sqrt{L/L_{\text{char}}})$ produces a gradual depolarisation that matches the qualitative behaviour of long-haul BB84 links.

Panel C shows the temperature sensitivity (phenomenological model, 50 km). The rotation angle θ reaches a minimum when $\Delta n \approx 0$ at $\sim 40^\circ\text{C}$, but because the plot shows the output power $|E_x|^2$ rather than θ itself, the curve appears as an inverted V (Λ shape): at the null temperature, $\theta \approx 0$ and the input polarisation is preserved ($|E_x|^2 \approx 1$); away from the null, θ grows and the polarisation scrambles ($|E_x|^2 \rightarrow 0.5$). The direct plot of θ vs T would be V-shaped, with the minimum at the same temperature.

Panel D confirms the bend birefringence law (Ulrich [27] Eq. 1): $\Delta n_{\text{bend}} = 0.135 (r_{\text{clad}}/R)^2$;

Fiber Birefringence — Dual-Model Validation (Sectional + Phenomenological)
(Menyuk & Wai 1994; Wai & Menyuk 1996; Ulrich 1980; Agrawal 2021)




Figure 6: Birefringence validation (dual-model: sectional and phenomenological). A: Sectional model — mean output $|E_x|^2$ vs fibre length (0–1.5 km), showing the multi-section random walk that gradually scrambles the polarisation from $|E_x|^2 = 1$ toward 0.5. B: Phenomenological model — mean output $|E_x|^2$ vs fibre length (0–200 km), showing the gradual $\sqrt{L}$ -dependent rotation that produces a distance-dependent QBER for long-haul BB84. C: Phenomenological model — mean output $|E_x|^2$ vs temperature at 50 km; the curve is inverted (peak at $\sim 40^\circ\text{C}$) because $|E_x|^2$ is plotted rather than the rotation angle θ itself, which would show a V-shaped minimum at the null. D: Phenomenological model — mean output $|E_x|^2$ vs bend radius at 50 km (Ulrich [27]). E: Beat length $L_B = \lambda/\Delta n_0$ vs wavelength (Agrawal Eq. 4.1.2) for the sectional model’s $\Delta n_0 = 5 \times 10^{-8}$. F: Deterministic Δn components showing temperature dependence and bend contributions.

tight bends below 10 mm produce strong scrambling at 50 km. Panel E shows the beat length $L_B = \lambda/\Delta n_0$ across the 800–1700 nm window ($L_B \approx 31$ m at 1550 nm, consistent with SMF-28). Panel F displays the deterministic Δn components: the linear temperature dependence and the asymptotic bend contributions at several bend radii. All 13 self-consistency checks pass, including power conservation (unitary Jones matrix, $< 10^{-12}$ error), seed-dependent randomness, zero-length identity, auto-dispatch routing, and the enabled=False bypass.

3.7 APD Validation

Figure 8A validates the responsivity. The measured R across 800–1700 nm reproduces $\eta e\lambda/hc$ at all wavelengths. At 1550 nm, $R = 1124$ mA/W for $\eta = 0.9$.

Figure 8B confirms the signal current $I_{\text{sig}} = MRP$ (Kasap [30] Eq. 4.23) across 10^{-9} to 10^{-3} W with $M = 10$.

Figure 8C validates the RMS noise current vs bandwidth. The total noise matches the quadrature sum of shot noise $\sqrt{F \cdot 2eIB}$ and thermal noise $\sqrt{4k_BTB/R_L}$ (Kasap [30] Eqs. 4.42–4.46). The excess noise factor $F = 10$ is correctly applied only to the shot-noise terms.

**Convergence of Multi-Section Model to Uniform SU(2) on Poincare Sphere
(500 realisations per distance, input $E_x=1, E_y=0$)**




Figure 7: Convergence of the multi-section model to uniform SU(2) on the Poincaré sphere (500 realisations per distance, input $E_x = 1$, $E_y = 0$, $\Delta n_0 = 5 \times 10^{-8}$). At $L = 0.01$ km the points cluster near the input state $(S_1, S_2, S_3) = (1, 0, 0)$; by $L = 1$ km the distribution is nearly uniform ($|\langle \mathbf{S} \rangle| = 0.02$), and further propagation does not change the statistics. The QBER under this model therefore saturates at $\sim 50\%$ within the first kilometre, motivating the phenomenological model for long-haul BB84.

Table 8: APD validation summary.

Parameter	Value
Responsivity	$R = 1124.253$ mA/W at 1550 nm
Signal current	$I = M * R * P$ linear verified
Shot noise	propto $\sqrt{B}$ and propto $\sqrt{P}$ verified
Thermal noise	$\sqrt{4 * k_B * T * B / R_L}$ verified
Photon detection	Poisson process, $\eta = 0.9$
Excess noise	$F = 10$ applied to shot terms

Figure 8D shows the thermal noise floor at zero signal current, matching the Johnson-Nyquist formula $\sqrt{4k_B T B / R_L}$.

Figure 8E validates photon detection. The measured photon counts follow $\bar{n} = P t \eta / h \nu$ with Poisson statistics (Saleh and Teich [31] Eq. 17.1-10).




Figure 8: APD validation. A: Responsivity vs wavelength ($R = \eta e \lambda / hc$, Kasap Eq. 4.19). B: Signal current ($I_{sig} = MRP$, Kasap Eq. 4.23). C: RMS noise vs bandwidth (shot + thermal, Kasap Eqs. 4.42-4.46). D: Thermal noise floor ($\sqrt{4k_B T B / R_L}$, Johnson-Nyquist). E: Photon detection ($\bar{n} = P t \eta / h \nu$, Saleh and Teich Eq. 17.1-10).

4 System-Level Demonstration

To demonstrate that the independently validated components compose correctly, we simulate BB84 QKD with MZM-carved Gaussian pulses under combined impairments (CWLaser $\rightarrow$ MZM $\rightarrow$ fibre with CD, PMD, birefringence, and attenuation $\rightarrow$ APD). The demonstration uses 3000 bits per measurement point with seeded RNG (seed 42) for reproducibility. The effective bit rate is 250 MHz (4 ns window per bit), well within the range of demonstrated high-speed BB84 systems [38, 39]. Five panels (Fig. 9) explore the parameter space of the optical channel over 0-1000 km of fibre.

Panel A: QBER vs distance. The QBER traces a three-regime curve across 0-1000 km. Regime 1 (0-80 km): the product of random-section rotations along the fibre has not yet accumulated enough net rotation to flip the bit decision, and the QBER is 0%. Regime 2 (80-200 km): the cumulative rotation grows through the diffusive range (Menyuk [35], Wai [36]), the birefringence-dominated regime where the bit decision flips on a majority of random axes, driving the QBER to a peak of 68% at 200 km. Regime 3 (200-1000 km): the polarisation is fully scrambled (antipodal map on the Poincaré sphere); the two detector outputs approach equal power, and the detection falls back to random guessing; beyond 500 km the 182 dB path loss (Keiser [23])




Figure 9: System-level BB84 demonstration. A: QBER vs fibre distance (30 ps pulses, 250 MHz effective bit rate) from 0 to 1000 km, showing the diffusive rise from 0% to 68%, followed by roll-off to the dark-count floor near 48%. B: QBER vs pulse width at 75 km — shorter pulses experience stronger CD and PMD. C: QBER vs temperature at 75 km showing the V-shaped response as $\Delta n(T)$ crosses zero. D: QBER vs PMD coefficient at 75 km. E: QBER vs bend radius at 75 km — tight bends ($R < 10$ mm) produce strong bend birefringence that scrambles the polarisation.

Table 9: System-level combined impairment scenarios at 100 km. Values shown for the corrected phenomenological birefringence model (Menyuk [35], Wai [36]) with the old symmetric-diagonal model values in parentheses for comparison.

Scenario	QBER (new)	QBER (old)
No Impairments	41.9%	0.0%
Attenuation Only	42.5%	42.7%
CD Only	42.0%	45.2%
PMD Only	44.5%	43.0%
CD + PMD	44.5%	43.0%
CD + PMD + Bend ($R=1\text{cm}$)	70.6%	70.1%
CD + PMD + Attenuation + Bend	69.9%	—
<i>Attenuation dominance at long range:</i>		
Attenuation Only @ 500 km	50.6%	—
Attenuation Only @ 1000 km	50.0%	—

Eq. 3.6) attenuates the signal below the APD noise floor, yielding QBER fluctuations around 48%, consistent with the dark-count limit. This three-regime shape is consistent with experimental QBER-vs-distance measurements [37, 38], which show the same qualitative transition from signal-dominated to noise-dominated detection. The attenuation-only curve closely tracks the all-impairments curve for 30 ps pulses, confirming that CD and PMD are negligible at this pulse width.

Panel B: QBER vs pulse width. At the critical distance 75 km, the QBER decreases from 25.5% at 5 ps to 2.5% at 30 ps and beyond. Narrow pulses ($\sigma < 10$ ps RMS, where $\sigma = T_0/\sqrt{2}$ for a Gaussian pulse) have a wider optical bandwidth, making them susceptible to CD-induced intersymbol interference ($z/L_D \approx 65$ at 75 km for a 5 ps pulse) and PMD walk-off. For $\sigma \geq 30$ ps, the pulse bandwidth is sufficiently narrow that CD and PMD are negligible, and the residual QBER is entirely due to birefringence at the 75 km operating point.

Panel C: QBER vs temperature. The QBER at 75 km exhibits a broad minimum around 40°C, where the temperature-induced birefringence crosses zero ($\Delta n(T \approx 42^\circ\text{C}) \approx 0$). At this point the phenomenological rotation angle $\theta \approx 0$, the polarisation is minimally disturbed, and the QBER drops to a few percent. Away from the null, $|\Delta n|$ grows, the rotation $\theta \propto 1/\sqrt{|\Delta n|}$ increases, and the QBER rises. The temperature coefficient $T_{\text{coeff}} = -5 \times 10^{-7}/^\circ\text{C}$ (phenomenological model) gives a fractional sensitivity of $\sim 5.7\%$, consistent with the multi-section model's 6% change per $^\circ\text{C}$.

Panel D: QBER vs PMD coefficient. The QBER at 75 km increases linearly with the PMD coefficient from 0.6% at 0 ps/ $\sqrt{\text{km}}$ to 4.4% at 0.3 ps/ $\sqrt{\text{km}}$, consistent with the expected PMD penalty for a 30 ps pulse.

Panel E: QBER vs bend radius. Tight bends ($R < 10$ mm) produce strong bend-induced birefringence $\Delta n_{\text{bend}} \propto (r_{\text{clad}}/R)^2$, scrambling the polarisation fully (QBER $\approx 70\%$). As the bend radius increases beyond 20 mm, the bend contribution becomes negligible compared to Δn_0 , and the QBER returns to the distance-dependent baseline (19% at 75 km with a 50 mm bend).

Combined impairment scenarios (Table 9). The system-level QBER at 100 km for each impairment combination is shown in Table 9, with the old symmetric-diagonal birefringence model values in parentheses for comparison. Under the corrected phenomenological model (Menyuk [35], Wai [36]), the birefringence alone produces 41.9% QBER ($\theta = \sqrt{100/75} \cdot \pi/2 \approx 1.81$ rad at 100 km), whereas the old symmetric-diagonal model happened to give 0% at exactly 100 km due to its deterministic modulo- 2π oscillation — at a different length it would produce 100%. The corrected model yields a smooth, physically consistent QBER that varies continuously with distance.

The CD-only, PMD-only, and CD+PMD scenarios all cluster around 42–45% QBER, confirming that the narrow-band 30 ps pulse is insensitive to CD and PMD at this distance; the birefringence dominates the error rate. Attenuation alone at 100 km adds less than 1% to the baseline birefringence QBER (42.5% vs 41.9%). The tight bend ($R = 1$ cm) drives the QBER to 70% in all bend-inclusive scenarios, including CD+PMD+Attenuation+Bend, consistent with the bend-induced birefringence dominating the net rotation angle.

At 500 km and beyond, the 91–182 dB path loss (Keiser [23] Eq. 3.6) attenuates the signal below the APD noise floor, and the QBER saturates at 50% (random guessing

— Table 9 bottom rows). This confirms the literature expectation that attenuation overtakes all other impairments at sufficiently long distances.

The five panels together confirm that the independently validated components compose correctly and produce physically sensible behaviour across the full parameter space. The smooth QBER curves, the diffusive transition with distance, the V-shaped temperature response, and the bend-radius dependence are all consistent with the underlying physical models validated in Section 4.

5 Discussion

5.1 Summary of Validation Results

Table 10: Summary of all component validations.

Component	Reference	Metric	Result
CW Laser (power)	Henry, Coldren	$ P_{\text{meas}} - P_{\text{theory}} /P_{\text{theory}}$	$< 5 \times 10^{-4}\%$
CW Laser (phase)	Henry Eq. 18	$\sum \Delta\phi^2$ vs $D_\phi t$	Matches
CW Laser (RIN)	Coldren Eq. 5.3.38	PSD shape	Peak at 5 GHz, roll-off
MZM (transfer)	Agrawal §4.2	$\cos^2(\pi V/2V_\pi)$	Verified
MZM (chirp)	Koyama and Iga	$\phi_{\text{pp}} = 0, \phi_{\text{sd}} = \pi V/2V_\pi$	Verified
CD	Agrawal Eq. 2.4.11	$\sigma(z)/\sigma_0$	$< 10^{-13}\%$
PMD	Razavi Fig. 2.11	KS test vs Maxwellian	$p = 0.42$
Attenuation	Keiser Eq. 3.6	$P(L)/P(0)$	$< 10^{-13}\%$
Birefringence	Menyuk & Wai, Ulrich Eq. 1	Rotation vs $L, \Delta n(T, R)$	PASS
APD (R)	Kasap Eq. 4.19	$R = \eta e\lambda/hc$	Verified
APD (noise)	Kasap Eq. 4.45	F on shot terms only	Verified

5.2 Parameter Sensitivity

The default fibre parameters are within published specifications for Corning SMF-28 Ultra. The attenuation coefficient $\alpha = 0.182$ dB/km is within the SMF-28e range (0.19–0.22 dB/km) and slightly above the Ultra max spec (0.18 dB/km) — a conservative choice. The residual birefringence $\Delta n_0 = 5.0 \times 10^{-8}$ corresponds to a beat length $L_B \approx 31$ m, consistent with standard SMF-28 fibre (Agrawal [20] §4.1).

5.3 Reproducibility

All simulations are reproducible:

- Seeded RNG (--seed N, default 42) pinned at session start
- All validation scripts produce seed-tagged CSV + PNG outputs
- run_all.py executes all validations in subprocesses (isolates module-level side effects)
- 48 unit tests (pytest) with automated seed pinning in conf_test.py
- Version-controlled repository with tagged commits

5.4 Limitations

The current model has several limitations that represent opportunities for future work:

1. **Section length vs. beat length ratio:** The multi-section model uses 100 m sections with $\Delta n_0 = 5 \times 10^{-8}$ ($L_B \approx 31$ m), giving a section-to-beat-length ratio of $\Delta z/L_B \approx 3.2$. Each section therefore produces an effective $SO(3)$ rotation of ~ 2.8 rad (well above a small-angle approximation), and the ordered product of ~ 100 sections scrambles the polarisation fully over 10 km. A model with shorter sections ($\Delta z \ll L_B$) would resolve the true diffusive random walk at higher computational cost; the current ratio provides a practical compromise for system-level QKD simulation.
2. **No polarisation-dependent loss (PDL):** Real fibres and in-line components have PDL that interacts with PMD.
3. **No Kerr nonlinearity:** At powers > 0 dBm and distances > 50 km, self-phase modulation and four-wave mixing become relevant. The current model is valid for typical QKD powers (-20 to 0 dBm).
4. **Single-segment PMD:** The PMD vector is drawn once per `propagate()` call. A multi-segment model would allow frequency correlation and second-order PMD.
5. **CW Laser phase noise is pure Wiener:** No $1/f$ phase noise component. Henry [16] describes only white frequency noise; adding $1/f$ noise would increase the linewidth at short timescales.
6. **Fixed dispersion parameters:** The model currently uses a single D value; a full Sellmeier model would allow wavelength-dependent dispersion over broad bandwidths.
7. **No temperature-dependent attenuation:** The attenuation coefficient varies slightly with temperature in deployed fibres.

6 Conclusion

We have presented an open-source, physically validated optical channel framework for QKD simulation. Five active components – CW laser, Mach-Zehnder modulator, fibre channel (birefringence, CD, PMD, attenuation), and avalanche photodiode – are independently validated against published literature. The primary contribution is the validation methodology: every equation cites a specific numbered reference, and every component is verified independently, providing a level of traceability absent from existing quantum network and optical system simulators.

The system-level BB84 demonstration confirms that the independently validated components compose correctly, producing physically sensible QBER under combined CD+PMD. This demonstration serves as evidence of correct composition rather than as a standalone QKD contribution; the framework’s value lies in enabling defensible studies of environmental sensitivity and physical-layer security that existing QKD simulators cannot support.

The framework is available under an open-source licence at <https://github.com/azaan-mahmood/optical-channel>.

References

- [1] T. Coopmans *et al.*, “NetSquid, a discrete-event simulation platform for quantum networks,” *arXiv:2012.15635*, 2020.
- [2] T. Coopmans, R. Knegjens, A. Dahlberg, D. Maier, L. Nijsten, J. de Oliveira Filho, M. Skotiniotis, J. Cals, and W. Kozłowski, “NetSquid, a NETwork Simulator for QUantum Information using Discrete events,” *Commun. Phys.*, vol. 4, no. 1, p. 164, 2021.

- [3] A. Dahlberg *et al.*, “SimulaQron – a simulator for developing quantum internet software,” *npj Quantum Inf.*, vol. 2, 16025, 2016.
- [4] J. R. Johansson, P. D. Nation, and F. Nori, “QuTIP 2: A Python framework for the dynamics of open quantum systems,” *Comput. Phys. Commun.*, vol. 184, no. 4, pp. 1234–1240, 2013.
- [5] X. Wu, A. Kolar, J. Chung, D. Jin, T. Zhong, R. Kettimuthu, and M. Suchara, “Se-QUeNCe: a customizable discrete-event simulator of quantum networks,” *Quantum Sci. Technol.*, vol. 6, no. 4, 045027, 2021.
- [6] R. Satoh *et al.*, “QuISP: a quantum internet simulation package,” *arXiv:2112.07093*, 2022.
- [7] S. DiAdamo, J. Nötzel, B. Zanger, and M. M. Beşe, “QuNetSim: a software framework for quantum networks,” *IEEE Trans. Quantum Eng.*, vol. 2, pp. 1–12, 2021.
- [8] B. Bartlett, “A distributed simulation framework for quantum networks and channels,” *arXiv:1808.07047*, 2018.
- [9] M. Mehic *et al.*, “A quantum key distribution network simulation module,” *IEEE Access*, vol. 8, pp. 212869–212883, 2020.
- [10] J. Park *et al.*, “QKDSim-HT: a NetSquid-based layered simulator for realistic quantum key distribution networks,” *IEEE Internet Things J.*, 2025.
- [11] Optiwave Systems Inc., “OptiSystem—optical communication system design software,” <https://optiwave.com/optisystem/>, 2024.
- [12] Ansys Inc., “Ansys Lumerical—photonic component and circuit simulation,” <https://www.ansys.com/products/optics>, 2024.
- [13] VPIphotonics GmbH, “VPItransmissionMaker optical systems,” <https://www.vpiphotonics.com/>, 2024.
- [14] Synopsys Inc., “Synopsys OptSim—photonic system design and simulation,” <https://synopsys.com/photonic-solutions.html>, 2024.
- [15] A. Buhari, Z. A. Zukarnain, S. K. Subramaniam, H. Zainuddin, and S. Saharudin, “An efficient modeling and simulation of quantum key distribution protocols using OptiSystem,” in *Proc. IEEE ISIEA*, 2012, pp. 84–89.
- [16] C. H. Henry, “Theory of the linewidth of semiconductor lasers,” *IEEE J. Quantum Electron.*, vol. QE-18, no. 2, pp. 259–264, 1982.
- [17] L. A. Coldren, S. W. Corzine, and M. L. Mashanovitch, *Diode Lasers and Photonic Integrated Circuits*, 2nd ed., Wiley, 2012.
- [18] A. Yariv, *Optical Electronics*, 4th ed., Saunders, 1991.
- [19] G. P. Agrawal, *Fiber-Optic Communication Systems*, 4th ed., Wiley, 2010.
- [20] G. P. Agrawal, *Fiber-Optic Communication Systems*, 5th ed., Wiley, 2021.
- [21] M. Koyama and K. Iga, “Frequency chirping in external modulators,” *J. Lightwave Technol.*, vol. 6, no. 1, pp. 87–93, 1988.
- [22] R. S. Weis and T. K. Gaylord, “Lithium Niobate: Summary of Physical Properties and Crystal Structure,” *Appl. Phys. A*, vol. 37, pp. 191–203, 1985.

- [23] G. Keiser, *Optical Fiber Communications*, 5th ed., McGraw-Hill, 2015.
- [24] R. Hui and M. O’Sullivan, *Fiber-Optic Measurement Techniques*, Academic Press, 2009.
- [25] D. B. Keck *et al.*, “Waveguide dispersion in single-mode fibers,” *IEEE J. Quantum Electron.*, vol. QE-21, no. 6, 1985.
- [26] B. Razavi, *Design of Integrated Circuits for Optical Communications*, 2nd ed., Wiley, 2012.
- [27] R. Ulrich *et al.*, “Bending-induced birefringence in single-mode fibers,” *Opt. Lett.*, vol. 5, no. 6, pp. 273–275, 1980.
- [28] A. M. Smith, “Birefringence induced by bends and twists in single-mode optical fiber,” *Appl. Opt.*, vol. 19, no. 15, 1980.
- [29] N. Shibata *et al.*, “Birefringence and polarization mode dispersion in a coil of a single-mode fiber,” *J. Opt. Soc. Am. A*, vol. 3, no. 11, 1986.
- [30] S. O. Kasap, *Optoelectronics and Photonics*, 2nd ed., Pearson, 2013.
- [31] B. E. A. Saleh and M. C. Teich, *Fundamentals of Photonics*, 3rd ed., Wiley, 2019.
- [32] Corning Inc., “SMF-28 Ultra Optical Fiber Product Information,” PI-1470-AEN, 2020.
- [33] M. Karlsson, “Probability density functions of the differential group delay in optical fiber communication systems,” *J. Lightwave Technol.*, vol. 19, no. 3, 2001.
- [34] A. L. Schawlow and C. H. Townes, “Infrared and Optical Masers,” *Phys. Rev.*, vol. 112, no. 6, pp. 1940–1949, 1958.
- [35] C. R. Menyuk and P. K. A. Wai, “Polarization evolution and dispersion in fibers with randomly varying birefringence,” *J. Opt. Soc. Am. B*, vol. 11, no. 7, pp. 1288–1300, 1994.
- [36] P. K. A. Wai and C. R. Menyuk, “Polarization mode dispersion, decorrelation, and diffusion in optical fibers with randomly varying birefringence,” *J. Lightwave Technol.*, vol. 14, no. 2, pp. 148–157, 1996.
- [37] C. Gobby, Z. L. Yuan, and A. J. Shields, “Quantum key distribution over 122 km of standard telecom fiber,” *Appl. Phys. Lett.*, vol. 84, no. 19, pp. 3762–3764, 2004. (Experimental QBER vs distance, 0–122 km.)
- [38] H. Takesue *et al.*, “Quantum key distribution over a 40-dB channel loss using superconducting single-photon detectors,” *Nature Photonics*, vol. 1, pp. 343–348, 2007. (1.6 GHz clock BB84 over 200 km.)
- [39] A. R. Dixon *et al.*, “Continuous operation of high bit rate quantum key distribution,” *Appl. Phys. Lett.*, vol. 93, 131107, 2008. (GHz-clock QKD, long-duration stability.)