

PREMIUM INTERACTIVE KIT

The Complete Outage-Ready Homeowner's Kit

Interactive tools to plan, prepare, and maintain your backup power system.

Live Wattage Calculator

Interactive Checklist

Maintenance Schedule

Emergency Card

Generator Capacity Calculator

Toggle the appliances you want to power. The calculator shows your total load vs your generator's capacity in real time.

My generator rated watts:

7500

watts

Your Load	350 W
Refrigerator	150 W ☐
Well Pump (1/2 HP)	1,000 W ☐
Central AC (3-ton)	3,500 W ☐
Window AC Unit	1,200 W ☐
Sump Pump	800 W ☐
Lights (10 LEDs)	100 W ☒
Phone / Router / TV	250 W ☒
Space Heater	1,500 W ☐
Microwave	1,000 W ☐
Electric Water Heater	4,500 W ☐

Capacity Used



5%

Stay under 80%. If your generator is 7,500W, keep your load under 6,000W. Gives headroom for starting surges.



72-Hour Storm Prep Checklist

Tap each item as you complete it. Your progress saves automatically.

Progress: 0 / 19

FUEL

- ☐ Fill generator tank completely
- ☐ Have 5-10 extra gallons in approved containers
- ☐ Add fuel stabilizer if gas is 30+ days old
- ☐ Store fuel away from house and generator

GENERATOR

- ☐ Check oil level, add if low
- ☐ Start it up for 10 minutes. Confirm clean and steady
- ☐ Inspect power cord. No cuts, exposed wire, or melted prongs
- ☐ Check inlet box cover closes and latches

INSIDE THE HOUSE

- ☐ Test CO detectors. Replace batteries if needed
- ☐ Know which breakers to turn on first
- ☐ Charge all phones, laptops, battery packs to 100%
- ☐ Fill bathtubs with water (if on well pump)
- ☐ Have flashlights accessible

WHEN POWER GOES OUT

- ☐ Turn OFF the main breaker
- ☐ Roll generator outside, 20+ feet from house

- ☐ Connect power cord from generator to inlet
- ☐ Start generator, let stabilize 30 seconds
- ☐ Engage interlock. Turn ON generator breaker
- ☐ Turn on circuits one at a time, heaviest first



Maintenance Schedule

Your generator cost \$800 to \$2,000. 30 minutes a quarter protects that investment.

Task	Monthly	Quarterly	Annual
Run 15-20 min	●		
Check oil level	●		
Change oil		●	
Clean/replace air filter		●	
Check spark plug		●	
Add fuel stabilizer		●	
Inspect power cord		●	
Inspect inlet box			●
Test interlock			●
Replace spark plug			●

#1 failure cause: stale fuel. Run it 15 minutes monthly. That alone prevents most problems.



Emergency Contact Card

Fill this in and bookmark this page, or print it and tape to your breaker panel.

EMERGENCY POWER CARD

Backup Power Pro

(864) 863-7800

Duke Energy (Upstate SC)

1-800-769-3766

Laurens Electric Co-op

1-800-942-3141

Blue Ridge Electric

1-800-240-3400

GENERATOR Brand & model

SERIAL # Serial number

INLET AMP ☒ 30A ☐ 50A

MY CRITICAL BREAKERS

BREAKER # e.g. Fridge

BREAKER # e.g. Well pump

BREAKER # e.g. Lights

BREAKER # e.g. HVAC

BREAKER # e.g. Kitchen

BREAKER # e.g. Garage