Table 35. Current consumption of peripherals (continued)

<table>
<tr><th>Peripheral</th><th>Bus</th><th>Consumption in µA/MHz</th></tr>
<tr><td>SPI1</td><td rowspan="9">APB</td><td>3.18</td></tr>
<tr><td>SPI1 independent clock domain</td><td>1.44</td></tr>
<tr><td>USART1</td><td>2.22</td></tr>
<tr><td>USART1 independent clock domain</td><td>5.77</td></tr>
<tr><td>TIM14</td><td>1.42</td></tr>
<tr><td>TIM16</td><td>2.54</td></tr>
<tr><td>TIM17</td><td>2.45</td></tr>
<tr><td>ADC1</td><td>1.92</td></tr>
<tr><td>ADC1 independent clock domain</td><td>0.12</td></tr>
<tr><td colspan="2">All peripherals</td><td>43.56</td></tr>
</table>

5.3.6 Wake-up time from low-power modes

The wake-up times given in *Table 36* are the latency between the event and the execution of the first user instruction.

Table 36. Low-power mode wake-up times[1]

<table>
<tr><th>Symbol</th><th>Parameter</th><th colspan="2">Conditions</th><th>Typ</th><th>Max</th><th>Unit</th></tr>
<tr><td rowspan="2">$t_{WUSLEEP}$</td><td rowspan="2">Wake-up time from Sleep to Run mode</td><td rowspan="2">HCLK = HSI48/4 = 12 MHz</td><td>Transiting to Run-mode execution in flash memory powered during Sleep mode</td><td>10</td><td>12</td><td>CPU clock cycles</td></tr>
<tr><td>Transiting to Run-mode execution in flash memory not powered during Sleep mode</td><td>4.75</td><td>5.02</td><td>µs</td></tr>
<tr><td rowspan="3">$t_{WULPSTOP}$</td><td rowspan="3">Wake-up time from Stop mode</td><td rowspan="3">Clock after wake-up is HCLK = HSI48/4 = 12 MHz</td><td>Transiting to Run-mode execution in flash memory powered during Stop mode</td><td>2.7</td><td>3.1</td><td rowspan="5">µs</td></tr>
<tr><td>Transiting to Run-mode execution in flash memory not powered during Stop mode</td><td>5.9</td><td>6.4</td></tr>
<tr><td>Transiting to Run-mode execution in SRAM</td><td>2.5</td><td>2.9</td></tr>
<tr><td>t_{WUSTBY}</td><td>Wake-up time from Standby mode</td><td>Clock after wake-up is HCLK = HSI48/4 = 12 MHz</td><td>Transiting to Run mode</td><td>23</td><td>35</td></tr>
<tr><td>t_{WUSHDN}</td><td>Wake-up time from Shutdown mode</td><td>Clock after wake-up is HCLK = HSI48/4 = 12 MHz</td><td>Transiting to Run mode</td><td>385</td><td>466</td></tr>
</table>

1. Evaluated by characterization – Not tested in production.