

Table 12. Pin assignment and description (continued)

Pin Number					Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
WLCSP15	TSSOP20	UFQFPN28	LQFP32 UFQFPN32	LQFP48 UFQFPN48						
-	-	-	17	21	PB2	I/O	FT_a	-	USART1_RX, MCO2, SPI2_MISO, EVENTOUT	ADC_IN19
-	-	-	-	22	PB10	I/O	FT_fa	-	TIM2_CH3, SPI2_SCK, I2C2_SCL	ADC_IN20
-	-	-	-	23	PB11	I/O	FT_fa	-	SPI2_MOSI, TIM2_CH4, I2C2_SDA	ADC_IN21
-	-	-	-	24	PB12	I/O	FT_a	-	SPI2_NSS, TIM1_BKIN2, TIM1_BKIN, EVENTOUT	ADC_IN22
-	-	-	-	25	PB13	I/O	FT_f	-	SPI2_SCK, TIM1_CH1N, I2C2_SCL, EVENTOUT	-
-	-	-	-	26	PB14	I/O	FT_f	-	SPI2_MISO, TIM1_CH2N, I2C2_SDA, EVENTOUT	-
-	-	-	-	27	PB15	I/O	FT	-	SPI2_MOSI, TIM1_CH3N, EVENTOUT	RTC_REFIN
K1	15	16	18	28	PA8	I/O	FT_a	-	MCO, USART2_TX, TIM1_CH1, SPI2_NSS, SPI2_MISO, EVENTOUT, SPI1_NSS/ I2S1_WS, TIM1_CH2N, TIM1_CH3N, TIM3_CH3, TIM3_CH4, TIM14_CH1, USART1_RX, MCO2	ADC_IN8
-	-	-	19	29	PA9	I/O	FT_f	(2)	MCO, USART1_TX, TIM1_CH2, TIM3_ETR, SPI2_MISO, I2C1_SCL, EVENTOUT, I2C2_SCL	-
-	-	17	20	30	PC6	I/O	FT	-	TIM3_CH1, TIM2_CH3	-
-	-	-	-	31	PC7	I/O	FT	-	TIM3_CH2, TIM2_CH4	-
-	-	-	21	32	PA10	I/O	FT_f	(2)	SPI2_MOSI, USART1_RX, TIM1_CH3, MCO2, TIM17_BKIN, I2C1_SDA, EVENTOUT, I2C2_SDA	-
F1	16	18	22	33	PA11 [PA9]	I/O	FT_fa	(2)	SPI1_MISO/I2S1_MCK, USART1_CTS/ USART1_NSS, TIM1_CH4, TIM1_BKIN2, I2C2_SCL	ADC_IN11
H1	17	19	23	34	PA12 [PA10]	I/O	FT_fa	(2)	SPI1_MOSI/I2S1_SD, USART1_RTS/ USART1_DE/USART1_CK, TIM1_ETR, I2S_CKIN, I2C2_SDA	ADC_IN12
D1	18	20	24	35	PA13	I/O	FT_a	(3)	SWDIO, IR_OUT, TIM3_ETR, USART2_RX, EVENTOUT	ADC_IN13
E2	19	21	25	36	PA14- BOOT0	I/O	FT_a	(3)	SWCLK, USART2_TX, EVENTOUT, SPI1_NSS/I2S1_WS, USART2_RX, TIM1_CH1, MCO2, USART1_RTS/ USART1_DE/USART1_CK	ADC_IN14, BOOT0
E2	19	22	26	37	PA15	I/O	FT	-	SPI1_NSS/I2S1_WS, USART2_RX, TIM1_CH1, MCO2, USART1_RTS/ USART1_DE/USART1_CK, TIM2_ETR/ TIM2_CH1, EVENTOUT	-
-	-	-	-	38	PD0	I/O	FT	-	EVENTOUT, TIM16_CH1, SPI2_NSS	-
-	-	-	-	39	PD1	I/O	FT	-	EVENTOUT, TIM17_CH1, SPI2_SCK	-