

Table 30. Typical current consumption in Run depending on code executed

Symbol	Parameter	Conditions			Typ	Unit	Typ	Unit
		General ⁽¹⁾	Code	Fetch from ⁽²⁾	25 °C		25 °C	
I _{DD} (Run)	Supply current in Run mode	f _{HCLK} = f _{HSE_bypass} = 48 MHz	Reduced code ⁽³⁾	Flash memory	3.65	mA	76.0	μA/MHz
			Coremark		3.30		68.8	
			Dhrystone		3.35		69.8	
			Fibonacci		2.50		52.1	
			WhileLoop		1.80		37.5	
			Reduced code ⁽³⁾	SRAM	2.95		61.5	
			Coremark		2.75		57.3	
			Dhrystone		2.75		57.3	
			Fibonacci		2.95		61.5	
			WhileLoop		2.20		45.8	
		f _{HCLK} = f _{HSE_bypass} = 16 MHz	Reduced code ⁽³⁾	Flash memory	1.30		81.3	μA/MHz
			Coremark		1.20		75.0	
			Dhrystone		1.20		75.0	
			Fibonacci		0.865		54.1	
			WhileLoop		0.645		40.3	
			Reduced code ⁽³⁾	SRAM	1.050		65.6	
			Coremark		0.975		60.9	
			Dhrystone		0.965		60.3	
			Fibonacci		1.05		65.6	
			WhileLoop		0.795		49.7	
		f _{HCLK} = f _{HSE_bypass} = 2 MHz	Reduced code ⁽³⁾	Flash memory	0.235		117.5	μA/MHz
			Coremark		0.215		107.5	
			Dhrystone		0.220		110.0	
			Fibonacci		0.180		90.0	
			WhileLoop		0.150		75.0	
			Reduced code ⁽³⁾	SRAM	0.200		100.0	
			Coremark		0.190		95.0	
			Dhrystone		0.190		95.0	
			Fibonacci		0.200		100.0	
			WhileLoop		0.170		85.0	