

Table 12. Pin assignment and description (continued)

Pin Number ⁽¹⁾							Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
WLCSP19 GP	TSSOP20 GP/N	UFQFPN28 GP/N	LQFP32, UFQFPN32 GP/N	LQFP48, UFQFPN48 GP/N	LQFP64 GP/N	UFPGA64 N						
-	-	-	17	21	29	H7	PB2	I/O	FT_a	-	USART1_RX, MCO2, SPI2_MISO, EVENTOUT	ADC_IN19
-	-	-	-	22	30	G6	PB10	I/O	FT_fa	-	TIM2_CH3, SPI2_SCK, I2C2_SCL	ADC_IN20
-	-	-	-	23	31	H8	PB11	I/O	FT_fa	-	SPI2_MOSI, TIM2_CH4, I2C2_SDA	ADC_IN21
-	-	-	-	24	32	G7	PB12	I/O	FT_a	-	SPI2_NSS, TIM1_BKIN2, TIM1_BKIN, EVENTOUT	ADC_IN22
-	-	-	-	25	33	G8	PB13	I/O	FT_sfa	-	SPI2_SCK, TIM1_CH1N, I2C2_SCL, EVENTOUT	-
-	-	-	-	26	34	F6	PB14	I/O	FT_s	-	SPI2_MISO, TIM1_CH2N, I2C2_SDA, EVENTOUT	-
-	-	-	-	27	35	F7	PB15	I/O	FT_s	-	SPI2_MOSI, TIM1_CH3N, EVENTOUT	RTC_REFI N
F1	15/ 14	16	18	28	36	F8	PA8	I/O	FT_sa	-	MCO, USART2_TX, TIM1_CH1, SPI2_NSS, CRS_SYNC, SPI2_MISO, EVENTOUT, SPI1_NSS/I2S1_WS, TIM1_CH2N, TIM1_CH3N, TIM3_CH3, TIM3_CH4, TIM14_CH1, USART1_RX, MCO2	ADC_IN8
-	-	-	19	29	37	E6	PA9	I/O	FT_sf	(3)	MCO, USART1_TX, TIM1_CH2, TIM3_ETR, SPI2_MISO, I2C1_SCL, EVENTOUT, I2C2_SCL	-
-	-	17/-	20/-	30/-	38	E7	PC6	I/O	FT_s	-	TIM3_CH1, TIM2_CH3	-
-	-	-	-	31/-	39	E5	PC7	I/O	FT_s	-	TIM3_CH2, TIM2_CH4	-
-	-	-	-	-	40/-	-	PD8	I/O	FT_s	-	SPI1_SCK/I2S1_CK	-
-	-	-	-	-	41/-	-	PD9	I/O	FT_s	-	SPI1_NSS/I2S1_WS, TIM1_BKIN2	-
-	-	-	-	-30	-40	E8	VSS	S	-	-	-	-
-	-15	-17	-20	-31	-41	D8	VDDIO2	S	-	(4)	-	-
-	-	-	21	32	42	D6	PA10	I/O	FT_sf	(3)	SPI2_MOSI, USART1_RX, TIM1_CH3, MCO2, TIM17_BKIN, I2C1_SDA, EVENTOUT, I2C2_SDA	-
D1	16	18	22	33	43	C8	PA11 [PA9]	I/O	FT_usf	(3)	SPI1_MISO/I2S1_MCK, USART1_CTS/USART1_NSS, TIM1_CH4, TIM1_BKIN2, I2C2_SCL	USB_DM
B1	17	19	23	34	44	B8	PA12 [PA10]	I/O	FT_usf	(3)	SPI1_MOSI/I2S1_SD, USART1_RTS/USART1_DE/USART1_CK, TIM1_ETR, I2S_CKIN, I2C2_SDA	USB_DP
C2	18	20	24	35	45	D7	PA13	I/O	FT_sa	(5)	SWDIO, IR_OUT, USB_NOE, TIM3_ETR, USART2_RX, EVENTOUT	ADC_IN13
A2	19	21	25	36	46	C7	PA14- BOOT0	I/O	FT_sa	(5)	SWCLK, USART2_TX, EVENTOUT, SPI1_NSS/I2S1_WS, USART2_RX, TIM1_CH1, MCO2, USART1_RTS/USART1_DE/USART1_CK	ADC_IN14, BOOT0
A2	19	22	26	37	47	C6	PA15	I/O	FT_s	-	SPI1_NSS/I2S1_WS, USART2_RX, TIM1_CH1, MCO2, USART1_RTS/USART1_DE/USART1_CK, TIM2_ETR/TIM2_CH1, USB_NOE, EVENTOUT	-
-	-	-	-	-	48	A8	PC8	I/O	FT_s	-	TIM3_CH3, TIM1_CH1	-
-	-	-	-	-	49	B7	PC9	I/O	FT_s	-	TIM3_CH4, TIM1_CH2, I2S_CKIN, USB_NOE	-
-	-	-	-	38	50	A7	PD0	I/O	FT_s	-	EVENTOUT, TIM16_CH1, SPI2_NSS	-
-	-	-	-	39	51	B6	PD1	I/O	FT_s	-	EVENTOUT, TIM17_CH1, SPI2_SCK	-