

Table 30. Typical current consumption in Run depending on code executed

Symbol	Parameter	Conditions			Typ	Unit	Typ	Unit
		General ⁽¹⁾	Code	Fetch from ⁽²⁾	25 °C		25 °C	
$I_{DD(Run)}$	Supply current in Run mode	$f_{HCLK} = f_{HSE_bypass} = 48 \text{ MHz}$	Reduced code	Flash memory	4.00	mA	83.3	$\mu\text{A/MHz}$
			Coremark		3.70		77.1	
			Dhrystone		3.80		79.2	
			Fibonacci		3.00		62.5	
			WhileLoop		1.90		39.6	
			Reduced code	SRAM	3.10		64.6	
			Coremark		3.00		62.5	
			Dhrystone		2.95		61.5	
			Fibonacci		3.20		66.7	
			WhileLoop		2.30		47.9	
		$f_{HCLK} = f_{HSE_bypass} = 16 \text{ MHz}$	Reduced code	Flash memory	1.50		93.8	
			Coremark		1.35		84.4	
			Dhrystone		1.40		87.5	
			Fibonacci		1.050		65.6	
			WhileLoop		0.685		42.8	
			Reduced code	SRAM	1.100		68.8	
			Coremark		1.050		65.6	
			Dhrystone		1.050		65.6	
			Fibonacci		1.10		68.8	
			WhileLoop		0.815		50.9	
		$f_{HCLK} = f_{HSE_bypass} = 2 \text{ MHz}$	Reduced code	Flash memory	0.265		132.5	
			Coremark		0.245		122.5	
			Dhrystone		0.245		122.5	
			Fibonacci		0.205		102.5	
			WhileLoop		0.160		80.0	
			Reduced code	SRAM	0.210		105.0	
			Coremark		0.205		102.5	
			Dhrystone		0.205		102.5	
			Fibonacci		0.215		107.5	
			WhileLoop		0.175		87.5	