

Table 11. Terms and symbols used in the pin assignment table

Column	Symbol	Definition
Pin name	Terminal name corresponds to its by-default function at reset, unless otherwise specified in parenthesis under the pin name.	
Pin type	S	Supply pin
	I	Input only pin
	I/O	Input / output pin
I/O structure	FT	5 V tolerant I/O
	RST	Reset pin with embedded weak pull-up resistor
	Options for FT I/Os	
	_f	I/O, Fm+ capable
	_a	I/O, with analog switch function
Note	Upon reset, all I/Os are set as analog inputs, unless otherwise specified.	
Pin functions	Alternate functions	Functions selected through GPIOx_AFR registers
	Additional functions	Functions directly selected/enabled through peripheral registers

Table 12. Pin assignment and description

Pin number							Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	WLCSP24	UFQFPN28	LQFP32 UFQFPN32	LQFP48 UFQFPN48	LQFP64	UFBGA64						
-	-	-	-	-	1	A1	PC11	I/O	FT	-	USART3_RX, USART4_RX, TIM1_CH4	-
-	-	-	-	-	2	B2	PC12	I/O	FT	-	TIM14_CH1	-
-	-	-	-	1	3	C2	PC13	I/O	FT	-	TIM1_ETR, TIM1_BKIN	RTC_TS, RTC_OUT1, WKUP2
2	A7	1	2	2	4	C1	PC14- OSCX_IN(PC14)	I/O	FT_f	-	USART1_TX, TIM1_ETR, TIM1_BKIN2, USART3_TX, IR_OUT, USART2_RTS/USART2_DE/USART2_CK, TIM17_CH1, TIM3_CH2, SPI2_NSS, FDCAN1_TX, I2C1_SDA, EVENTOUT	OSCX_IN
3	B6	2	3	3	5	B1	PC15- OSCX_OUT(PC15)	I/O	FT	-	OSC32_EN, OSC_EN, TIM1_ETR, TIM3_CH3, TIM15_BKIN	OSCX_OUT