

Table 12. Pin assignment and description (continued)

Pin number							Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	WLCSP24	UFQFPN28	LQFP32 UFQFPN32	LQFP48 UFQFPN48	LQFP64	UFBGA64						
13	F4	12	13	17	23	F4	PA6	I/O	FT_fa	-	SPI1_MISO/I2S1_MCK, TIM3_CH1, TIM1_BKIN, USART3_CTS/USART3_NSS, TIM16_CH1, I2C2_SDA	ADC_IN6
14	G3	13	14	18	24	E4	PA7	I/O	FT_fa	-	SPI1_MOSI/I2S1_SD, TIM3_CH2, TIM1_CH1N, TIM14_CH1, TIM17_CH1, I2C2_SCL	ADC_IN7
-	-	-	-	-	25	H5	PC4	I/O	FT_a	-	USART3_TX, USART1_TX, TIM2_ETR/TIM2_CH1, FDCAN1_RX	ADC_IN11
-	-	-	-	-	26	H6	PC5	I/O	FT_a	-	USART3_RX, USART1_RX, TIM2_CH2, FDCAN1_TX	ADC_IN12, WKUP5
15	E3	14	15	19	27	F5	PB0	I/O	FT_a	-	SPI1_NSS/I2S1_WS, TIM3_CH3, TIM1_CH2N, FDCAN1_RX, USART3_RX	ADC_IN17
15	C1	15	16	20	28	G5	PB1	I/O	FT_a	-	TIM14_CH1, TIM3_CH4, TIM1_CH3N, FDCAN1_TX, USART3_RTS/USART3_DE/USART3_CK, TIM1_CH2N, EVENTOUT	ADC_IN18
15	G1	-	17	21	29	H7	PB2	I/O	FT_a	-	USART1_RX, MCO2, SPI2_MISO, USART3_TX, EVENTOUT	ADC_IN19
-	-	-	-	22	30	G6	PB10	I/O	FT_fa	-	TIM2_CH3, USART3_TX, SPI2_SCK, I2C2_SCL	ADC_IN20
-	-	-	-	23	31	H8	PB11	I/O	FT_fa	-	SPI2_MOSI, TIM2_CH4, USART3_RX, I2C2_SDA	ADC_IN21
-	-	-	-	24	32	G7	PB12	I/O	FT_a	-	SPI2_NSS, TIM1_BKIN2, TIM1_BKIN, FDCAN1_RX, TIM15_BKIN, EVENTOUT	ADC_IN22
-	-	-	-	25	33	G8	PB13	I/O	FT_fa	-	SPI2_SCK, TIM1_CH1N, FDCAN1_TX, USART3_CTS/USART3_NSS, TIM15_CH1N, I2C2_SCL, EVENTOUT	-
-	-	-	-	26	34	F6	PB14	I/O	FT_fa	-	SPI2_MISO, TIM1_CH2N, USART3_RTS/USART3_DE/USART3_CK, TIM15_CH1, I2C2_SDA, EVENTOUT	-
-	-	-	-	27	35	F7	PB15	I/O	FT	-	SPI2_MOSI, TIM1_CH3N, TIM15_CH1N, TIM15_CH2, EVENTOUT	RTC_REFIN
15	G1	16	18	28	36	F8	PA8	I/O	FT_a	-	MCO, USART2_TX, TIM1_CH1, SPI2_NSS, SPI2_MISO, EVENTOUT, SPI1_NSS/I2S1_WS, TIM1_CH2N, TIM1_CH3N, TIM3_CH3, TIM3_CH4, TIM14_CH1, USART1_RX, MCO2	ADC_IN8
-	-	-	19	29	37	E6	PA9	I/O	FT_f	(2)	MCO, USART1_TX, TIM1_CH2, TIM3_ETR, SPI2_MISO, TIM15_BKIN, I2C1_SCL, EVENTOUT, I2C2_SCL	-
-	-	17	20	30	38	E7	PC6	I/O	FT	-	TIM3_CH1, TIM2_CH3	-
-	-	-	-	31	39	E5	PC7	I/O	FT	-	TIM3_CH2, TIM2_CH4	-