

Table 12. Pin assignment and description (continued)

Pin number							Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	WLCSP24	UFQFPN28	LQFP32 UFQFPN32	LQFP48 UFQFPN48	LQFP64	UFPGA64						
-	-	-	-	-	40	E8	PD8	I/O	FT	-	SPI1_SCK/I2S1_CK, USART3_TX	-
-	-	-	-	-	41	D8	PD9	I/O	FT	-	SPI1_NSS/I2S1_WS, TIM1_BKIN2, USART3_RX	-
-	-	-	21	32	42	D6	PA10	I/O	FT_f	(2)	SPI2_MOSI, USART1_RX, TIM1_CH3, MCO2, TIM17_BKIN, I2C1_SDA, EVENTOUT, I2C2_SDA	-
16	F2	18	22	33	43	C8	PA11 [PA9]	I/O	FT_f	(2)	SPI1_MISO/I2S1_MCK, USART1_CTS/USART1_NSS, TIM1_CH4, FDCAN1_RX, TIM1_BKIN2, I2C2_SCL	-
17	E1	19	23	34	44	B8	PA12 [PA10]	I/O	FT_f	(2)	SPI1_MOSI/I2S1_SD, USART1_RTS/USART1_DE/USART1_CK, TIM1_ETR, FDCAN1_TX, I2S_CKIN, I2C2_SDA	-
18	C3	20	24	35	45	D7	PA13	I/O	FT_a	(3)	SWDIO, IR_OUT, TIM3_ETR, USART2_RX, EVENTOUT	ADC_IN13
19	B2	21	25	36	46	C7	PA14-BOOT0	I/O	FT_a	(3)	SWCLK, USART2_TX, EVENTOUT, SPI1_NSS/I2S1_WS, USART2_RX, TIM1_CH1, MCO2, USART1_RTS/USART1_DE/USART1_CK	ADC_IN14, BOOT0
19	A1	22	26	37	47	C6	PA15	I/O	FT	-	SPI1_NSS/I2S1_WS, USART2_RX, TIM1_CH1, MCO2, USART1_RTS/USART1_DE/USART1_CK, TIM2_CH1/TIM2_ETR, USART4_RTS/USART4_DE/USART4_CK, EVENTOUT, USART3_RTS/USART3_DE/USART3_CK	-
-	-	-	-	-	48	A8	PC8	I/O	FT	-	TIM3_CH3, TIM1_CH1	-
-	-	-	-	-	49	B7	PC9	I/O	FT	-	TIM3_CH4, TIM1_CH2, I2S_CKIN	-
-	-	-	-	38	50	A7	PD0	I/O	FT	-	EVENTOUT, TIM16_CH1, SPI2_NSS, FDCAN1_RX	-
-	-	-	-	39	51	B6	PD1	I/O	FT	-	EVENTOUT, TIM17_CH1, SPI2_SCK, FDCAN1_TX	-
-	-	-	-	40	52	A6	PD2	I/O	FT	-	USART3_RTS/USART3_DE/USART3_CK, TIM3_ETR, TIM1_CH1N	-
-	-	-	-	41	53	D5	PD3	I/O	FT	-	USART2_CTS/USART2_NSS, TIM1_CH2N, SPI2_MISO	-
-	-	-	-	-	54	C5	PD4	I/O	FT	-	SPI2_MOSI, USART2_RTS/USART2_DE/USART2_CK, TIM1_CH3N	-
-	-	-	-	-	55	B5	PD5	I/O	FT	-	SPI1_MISO/I2S1_MCK, USART2_TX, TIM1_BKIN	-
-	-	-	-	-	56	A5	PD6	I/O	FT	-	SPI1_MOSI/I2S1_SD, USART2_RX	-