

Table 30. Typical current consumption in Run depending on code executed

Symbol	Parameter	Conditions			Typ	Unit	Typ	Unit
		General ⁽¹⁾	Code	Fetch from ⁽²⁾	25 °C		25 °C	
$I_{DD(Run)}$	Supply current in Run mode	$f_{HCLK} = f_{HSE_bypass} = 48 \text{ MHz}$	Reduced code	Flash memory	3.95	mA	82.3	$\mu\text{A/MHz}$
			Coremark		3.60		75.0	
			Dhrystone		3.65		76.0	
			Fibonacci		2.90		60.4	
			WhileLoop		1.95		40.6	
			Reduced code	SRAM	3.15		65.6	
			Coremark		2.90		60.4	
			Dhrystone		2.95		61.5	
			Fibonacci		3.10		64.6	
			WhileLoop		2.30		47.9	
		$f_{HCLK} = f_{HSE_bypass} = 16 \text{ MHz}$	Reduced code	Flash memory	1.45		90.6	
			Coremark		1.30		81.3	
			Dhrystone		1.30		81.3	
			Fibonacci		1.000		62.5	
			WhileLoop		0.700		43.8	
			Reduced code	SRAM	1.100		68.8	
			Coremark		1.050		65.6	
			Dhrystone		1.050		65.6	
			Fibonacci		1.10		68.8	
			WhileLoop		0.830		51.9	
		$f_{HCLK} = f_{HSE_bypass} = 2 \text{ MHz}$	Reduced code	Flash memory	0.255		127.5	
			Coremark		0.235		117.5	
			Dhrystone		0.235		117.5	
			Fibonacci		0.200		100.0	
			WhileLoop		0.160		80.0	
			Reduced code	SRAM	0.215		107.5	
			Coremark		0.205		102.5	
			Dhrystone		0.205		102.5	
			Fibonacci		0.210		105.0	
			WhileLoop		0.180		90.0	