

Table 11. STM32C53xxx pin/ball definition

| Pin number |          |          |          |        |        |          |        | Pin name<br>(function<br>after reset) | Pin type | I/O structure | Notes  | Alternate functions                                                                                                                       | Additional<br>functions                    |
|------------|----------|----------|----------|--------|--------|----------|--------|---------------------------------------|----------|---------------|--------|-------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------|
| TSSOP20    | UFQFPN20 | UFQFPN24 | UFQFPN32 | LQFP32 | LQFP48 | UFQFPN48 | LQFP64 |                                       |          |               |        |                                                                                                                                           |                                            |
| -          | -        | -        | -        | -      | 1      | 1        | 1      | PE2                                   | I/O      | FT            | -      | TRACECLK, LPTIM1_IN2,<br>EVENTOUT                                                                                                         | -                                          |
| -          | -        | -        | -        | -      | 2      | 2        | 2      | PC13                                  | I/O      | FT_t          | (1)(2) | FDCAN1_TX, EVENTOUT                                                                                                                       | TAMP_IN1,<br>RTC_OUT1/<br>RTC_TS, WKUP4    |
| -          | -        | -        | 2        | 2      | 3      | 3        | 3      | PC14-OSC32_IN<br>(OSC32_IN)           | I/O      | FT            | (1)    | TIM12_CH1, FDCAN1_RX,<br>EVENTOUT                                                                                                         | OSC32_IN                                   |
| -          | -        | -        | -        | -      | 4      | 4        | 4      | PC15-<br>OSC32_OUT<br>(OSC32_OUT)     | I/O      | FT            | (1)    | TIM12_CH2, EVENTOUT                                                                                                                       | OSC32_OUT                                  |
| 4          | 2        | 1        | 2        | 2      | 5      | 5        | 5      | PH0-OSC_IN<br>(PH0)                   | I/O      | FT_f          | -      | I2C1_SDA, EVENTOUT                                                                                                                        | OSC_IN                                     |
| 3          | 1        | 2        | 3        | 3      | 6      | 6        | 6      | PH1-OSC_OUT<br>(PH1)                  | I/O      | FT_f          | -      | I2C1_SCL, EVENTOUT                                                                                                                        | OSC_OUT                                    |
| 2          | 20       | 3        | 4        | 4      | 7      | 7        | 7      | NRST                                  | I/O      | RST           | -      | -                                                                                                                                         | -                                          |
| -          | -        | -        | -        | -      | -      | -        | 8      | PC0                                   | I/O      | FT_a          | -      | SPI2_RDY, EVENTOUT                                                                                                                        | ADC1_IN8,<br>COMP2_INP                     |
| -          | -        | -        | -        | -      | -      | -        | 9      | PC1                                   | I/O      | FT_a          | -      | TRACED0, SPI2_MOSI/<br>I2S2_SDO, EVENTOUT                                                                                                 | ADC1_IN9,<br>COMP2_INM,<br>TAMP_IN2        |
| -          | -        | -        | -        | -      | -      | -        | 10     | PC2                                   | I/O      | FT_a          | -      | PWR_CSLEEP, SPI2_MISO/<br>I2S2_SDI, EVENTOUT                                                                                              | ADC1_IN10                                  |
| -          | -        | -        | -        | -      | -      | -        | 11     | PC3                                   | I/O      | FT_a          | -      | PWR_CSTOP, LPUART1_TX,<br>SPI2_MOSI/I2S2_SDO,<br>EVENTOUT                                                                                 | ADC1_IN11                                  |
| 5          | 3        | -        | -        | -      | 8      | 8        | 12     | VREF-                                 | S        | -             | -      | -                                                                                                                                         | -                                          |
| 6          | 4        | 4        | 5        | 5      | 9      | 9        | 13     | VREF+                                 | S        | -             | -      | -                                                                                                                                         | -                                          |
| -          | -        | 5        | 6        | 6      | 10     | 10       | 14     | PA0                                   | I/O      | FT_a          | -      | TIM2_CH1, TIM8_ETR,<br>TIM15_BKIN, SPI2_RDY,<br>SPI1_RDY, USART2_CTS/<br>USART2_NSS, UART4_TX,<br>SPI2_NSS/I2S2_WS,<br>TIM2_ETR, EVENTOUT | ADC1_IN0,<br>COMP1_INP,<br>TAMP_IN2, WKUP1 |

