

Pin number								Pin name (function after reset)	Pin type	I/O structure	Notes	Alternate functions	Additional functions
TSSOP20	UFQFPN20	UFQFPN24	UFQFPN32	LQFP32	LQFP48	UFQFPN48	LQFP64						
14	12	14	18	18	28	28	36	PB15	I/O	TT	-	RTC_REFIN, TIM1_CH3N, TIM12_CH2, TIM8_CH3N, USART1_RX, SPI2_MOSI/ I2S2_SDO, SPI1_MOSI/ I2S1_SDO, UART4_CTS, UART5_RX, EVENTOUT	COMP2_INP, OPAMP1_VINP2
-	-	-	-	-	-	-	37	PC6	I/O	FT	-	TIM12_CH1, TIM8_CH1, I2S2_MCK, EVENTOUT	-
-	-	-	-	-	-	-	38	PC7	I/O	FT	-	TIM8_CH2, I2S1_MCK, EVENTOUT	-
-	-	-	-	-	-	-	39	PC8	I/O	FT	-	TRACED1, TIM8_CH3, UART5_RTS, EVENTOUT	-
-	-	-	-	-	-	-	40	PC9	I/O	FT_f	-	MCO2, TIM12_CH2, TIM8_CH4, AUDIOCLK, UART5_CTS, I2C1_SDA, EVENTOUT	-
-	-	-	19	19	29	29	41	PA8	I/O	FT_f	-	MCO1, TIM1_CH1, I3C1_SDA, TIM8_BKIN2, TIM15_CH2, SPI1_RDY, SPI2_MOSI/ I2S2_SDO, USART1_CK, I2C1_SCL, USB_SOF, TIM2_CH4, EVENTOUT	-
-	-	-	20	20	30	30	42	PA9	I/O	FT	-	MCO2, TIM1_CH2, I3C1_SCL, LPUART1_TX, TIM15_CH1N, SPI2_SCK/I2S2_CK, USART1_TX, I2C1_SMBA, TIM8_CH2N, EVENTOUT	-
-	-	-	-	-	31	31	43	PA10	I/O	FT	-	TIM1_CH3, LPUART1_RX, USART1_RX, FDCAN2_TX, EVENTOUT	-
14	12	15	21	21	32	32	44	PA11	I/O	FT_fu	-	TIM1_CH4, LPUART1_CTS, USART2_TX, SPI2_NSS/ I2S2_WS, UART4_RX, USART1_CTS/USART1_NSS, I2C1_SCL, FDCAN1_RX, EVENTOUT	USB_DM

